SERVICE MANUAL RG-3 CHASSIS

MODEL	COMMANDER	DEST.	CHASSIS NO.	MODEL	COMMANDER	DEST.	CHASSIS NO.
KP-ES43HK1	RM-961	HK	SCC-P45B-A	KP-ES53HK1	RM-961	HK	SCC-P45C-A
KP-ES43ME1	RM-961	ME	SCC-P46B-A	KP-ES53ME1	RM-961	ME	SCC-P46C-A
KP-ES43MN1	RM-961	GE	SCC-P44D-A	KP-ES53MN1	RM-961	GE	SCC-P44B-A
KP-ES43SN1	RM-961	AUS	SCC-P47B-A	KP-ES53SN1	RM-961	AUS	SCC-P47C-A
KP-ES48HK1	RM-961	HK	SCC-P45A-A	KP-ES61HK1	RM-961	HK	SCC-P45D-A
KP-ES48ME1	RM-961	ME	SCC-P46A-A	KP-ES61ME1	RM-961	ME	SCC-P46D-A
KP-ES48MN1	RM-961	GE	SCC-P44A-A	KP-ES61MN1	RM-961	GE	SCC-P44C-A
KP-ES48SN1	RM-961	AUS	SCC-P47A-A	KP-ES61SN1	RM-961	AUS	SCC-P47D-A

RM-961

KP-ES43HK1/ME1/MN1/SN1

KP-ES53HK1/ME1/MN1/SN1

KP-ES48HK1/ME1/MN1/SN1

KP-ES61HK1/ME1/MN1/SN1

* Please file according to model size. ...☐

| 43 | 48 | 53 | 61 |

PROJECTION TV
SONY®

KP-ES43HK1/ME1/MN1/SN1, ES48HK1/ME1/MN1/SN1, ES53HK1/ME1/MN1/SN1, ES61HK1/ME1/MN1/SN1 RM-961

SPECIFICATIONS

	KP-ES61MN1/ KP-ES61HK1/ KP-ES61ME1/ KP-ES61SN1	KP-ES53MN1/ KP-ES53HK1/ KP-ES53ME1/ KP-ES53SN1	KP-ES48MN1/ KP-ES48HK1/ KP-ES48ME1/ KP-ES48SN1	KP-ES43MN1/ KP-ES43HK1/ KP-ES43ME1/ KP-ES43SN1
Projection system	3 picture tubes, 3 lenses, horizontal inline system			
Picture tube	7 inch high-brightnes monochorome tubes (6.3 raster size), with optical coupling and liquidcooling system			
Projection lenses	High performance, large-diameter highbrid lens F1.0			
Screen size	61 inches	53 inches	48 inches	43 inches
Television system	B/G, I, D/K, M			
Color system	PAL, PAL 60, SECAM, NTSC4.43, NTSC3.58			
Stereo/Bilingual system	NICAM Stereo/Bilingual B/G, I; A2 Stereo/Bilingual (German) B/G			
Channel coverage B/G	VHF : E2 to E12 / UHF : E21 to E69 / CATV : S01 to S03, S1 to S41			
I	UHF : B21 to B68 / CATV : S01 to S03, S1 to S41			
D/K	VHF : C1 to C12, R1 to R12 / UHF : C13 to C57, R21 to R60 / CATV : S01 to S03, S1 to S41, Z1 to Z39			
M	VHF : A2 to A13 / UHF : A14 to A79 / CATV : A-8 to A-2, A to W+4, W+6 to W+84			
⊓ (Antenna)	75-ohm external terminal			
Audio output (Speaker)	13W + 13W, (10% distortion)			
Number of terminal (Video)	Input: 4 Output: 1	Phono jacks; 1 Vp-p, 75 ohms		
♪ (Audio)	Input: 4 Output: 1	Phono jacks; 500 mVrms		
(S Video)	Input: 2	Y: 1 Vp-p, 75 ohms, unbalanced, sync negative C: 0.286 Vp-p, 75 ohms		
(Component Video)	Input: 1	Phono jacks Y: 1 Vp-p, 75 ohms, sync negative C_B/B-Y: 0.7 Vp-p, 75 ohms C_R/R-Y: 0.7 Vp-p, 75 ohms Audio: 500 mVrms		
↦	Output: 1	Phono jack; 500 mVrms		
∩ (Headphones)	Output: 1	Stereo minijack		
Dimensions (w/h/d, mm)	1372 × 1542 × 661.5	1218 × 1423 × 623	1091 × 1336 × 580	966 × 1078 × 532
Mass (kg)	90	76	68	61

Power requirements 110 V – 240 V (For KP-ES61MN1/KP-ES53MN1/KP-ES48MN1/KP-ES43MN1/ KP-ES61ME1/KP-ES53ME1/KP-ES48ME1/KP-ES43ME1)
220 V – 240 V (For KP-ES61HK1/KP-ES53HK1/KP-ES48HK1/KP-ES43HK1/ KP-ES61SN1/KP-ES53SN1/KP-ES48SN1/KP-ES43SN1)

Power consumption (W) 270 W (For KP-ES61MN1/KP-ES53MN1/KP-ES48MN1/KP-ES43MN1/ KP-ES61ME1/KP-ES53ME1/KP-ES48ME1/KP-ES43ME1)
255 W (For KP-ES61HK1/KP-ES53HK1/KP-ES48HK1/KP-ES43HK1/ KP-ES61SN1/KP-ES53SN1/KP-ES48SN1/KP-ES43SN1)

Design and specifications are subject to change without notice.

CAUTION
SHORT CIRCUIT THE ANODE OF HTE PICTURE TUBE AND THE ANODE CAP TO THE METAL CHASSIS, CRT SHIELD, OR CARBON PAINTED ON THE CRT, AFTER REMOVING THE ANODE.

SAFETY-RELATED COMPONENT WARNING!!
COMPONENTS IDENTIFIED BY SHADING AND MARK ⚠ ON THE SCHEMATIC DIAGRAMS, EXPLODED VIEWS AND IN THE PARTS LIST ARE CRITICAL TO SAFE OPERATION. REPLACE THESE COMPONENTS WITH SONY PARTS WHOSE PART NUMBERS APPEAR AS SHOWN IN THIS MANUAL OR IN SUPPLEMENTS PUBLISHED BY SONY.

TABLE OF CONTENTS

KP-ES43HK1/ME1/MN1/SN1, ES48HK1/ME1/MN1/SN1, ES53HK1/ME1/MN1/SN1, ES61HK1/ME1/MN1/SN1 RM-961

SECTION 1
SELF DIAGNOSIS FUNCTION

The unit in this manual contain a self-diagnostic function. If an error occurs, the STANDBY/TIMER lamp will automatically begin to flash.

The number of times the lamp flashes translates to a probable source of the problem. A definition of the STANDBY/TIMER lamp flash indicators is listed in the instruction manual for the user's knowledge and reference. If an error symptom cannot be reproduced, the remote commander can be used to review the failure occurrence data stored in memory to reveal past problems and how often these problems occur.

1-1. DIAGNOSTIC TEST INDICATORS

When an errors occurs, the STANDBY/TIMER lamp will flash a set number of times to indicate the possible cause of the problem. If there is more than one error, the lamp will identify the first of the problem areas.

Result for all of the following diagnostic items are displayed on screen. No error has occurred if the screen displays a "0".

Diagnostic Item Description	No. of times STANDBY/TIMER lamp flashes	Self-diagnostic display/ Diagnostic result	Probable Cause Location	Detected Symptoms
• Power does not turn on	Does not light	————	• Power cord is not plugged in. • Fuse (F6001) is burned out. (G, G1 board)	• Power does not come on. • No power is supplied to the PJ. • AC power supply is faulty.
• +B overcurrent (OCP)	2 times	002:000 or 002:001 ~ 255	• H. OUT Q5104 is shorted. • H. LIN Q5105 is shorted. (D board)	• Power does not come on. • Load on power line is shorted.
• +B overvoltage (OVP)	3 times	003:000 or 003:001 ~ 255	• IC6002 faulty. • 10.5 V is not supplied. (G, G1 board)	• Power does not come on.
• Vertical deflection failure	4 times	004:000 or 004:001 ~ 255	• V. OUT IC5302 faulty. • R5340 open • R5341 open (D board)	• Vertical deflection pulse is stopped. • Vertical size is too small. • Vertical deflection stopped.
• White balance failure (no PICTURE)	5 times	005:000 or 005:001 ~ 255	• G2 is improperly adjusted. (Note 1) • CRT problem. • Video OUT IC7101 (CR board), IC7201 (CG board), IC7301 (CB board) are faulty. • IC8306 (J1 board) and IC4301 (E board) are faulty. • No connection E board to CR board.	• No raster is generated. • CRT cathode current detection reference pulse output is small.
• High Voltage failure	6 times	006:000 or 006:001 ~ 255	• IC6301 (G, G1 bard) faulty.	• +135 V is too high.
• Audio Protection	7 times	007:000 or 007:001 ~ 255	• Power supply fails. • IC1101 (A1 board) faulty.	• There is picture but speaker does not release sound.
• Micro reset	————	101:000 or 101:001 ~ 255	• Discharge CRT (CR, CG, CB boards) • Static discharge • External noise	• Power is shut down shortly, after this return back to normal. • Detect Micro latch up.

Note 1 : Refer to screen (G2) adjustment in section 4-2 of this manual.

1-2. DISPLAY OF STANDBY/TIMER LIGHT FLASH COUNT

2 times

3 times

Lamp ON
0.3 sec.

Lamp OFF
3 sec.

Lamp OFF
0.3 sec.

4 times

5 times

6 times

7 times

STANDBY/TIMER
lamp

Diagnostic Item	Flash Count *
+B overcurrent	2 times
+B overvoltage	3 times
V deflection stop	4 times
White balance failure	5 times
High voltage protector	6 times
Audio Protection	7 times

* One flash count is not used for self-diagnostic.

1-3. STOPPING THE STANDBY/TIMER FLASH

Turn off the power switch on the TV main unit or unplug the power cord from the outlet to stop the STANDBY/TIMER lamp from flashing.

1-4. SELF-DIAGNOSTIC SCREEN DISPLAY

For errors with symptoms such as "power sometimes shuts off" or "screen sometimes goes out" that cannot be confirmed, it is possible to bring up past occurrences of failure for confirmation on the screen:

[To Bring Up Screen Test]

In standby mode, press buttons on the remote commander sequentially in rapid succession as shown below:

i+	➡	⑤	➡	◿ –	➡	I/⏻

(ON SCREEN
  DISPLAY)   (DIGIT 5)   * (VOLUME –)   (POWER)

* : Note that this differs from entering the service mode (volume +)

Self-Diagnosis screen display

SELF DIAGNOSTIC

002:000 ⟵——— Numeral "0" means that no fault has been detected.
003:000
004:000
005:001 ⟵——— Numeral "1" means a fault has been detected.
006:002 ⟵——— Numeral "2" means two faults have been detected.

007:000
101:000

1-5. HANDLING OF SELF-DIAGNOSTIC SCREEN DISPLAY

Since the diagnostic results displayed on the screen are not automatically cleared, always check the self-diagnostic screen during repairs. When you have completed the repairs, clear the result display to "0".

Unless the result display is cleared to "0", the self-diagnostic function will not be able to detect subsequent faults after completion of the repairs.

[Clearing the result display]

To clear the result display to "0", press button on the remote commander sequentially as shown below when the diagnostic screen is being displayed.

Press "⑧" button   ➡   Press "⓪" button
(It will indicate "CLEAR" on the screen.)   (The "CLEAR" display change to red color.)

[Quitting Self-diagnostic screen]

To quit the entire self-diagnostic screen, turn off the power switch on the remote commander or the main unit.

1-6. SELF-DIAGNOSTIC CIRCUIT

+B overcurrent (OCP)	Occurs when an overcurrent on the +B (135 V) line is detected by Q6303. If Q6303 go to ON, the voltage to pin 3 of IC002 go to UP. The unit will automatically turn off.
+B overvoltage (OVP)	Occurs when an overvoltage on the +B (135 V) line is detected by D6318. If D6318 go to ON, then voltage to pin 6 of IC002 go to UP. The unit will automatically turn off.
Vertical deflection failure	Occurs when an absence of the vertical deflection pulse is detected by Q5302, Q5303, and D5303. Shut down the power supply.
White balance failure	If the RGB levels do not balance or become low level within 5 seconds. This error will be detected by IC4301. TV will stay on, but there will be no picture.
High voltage protector of Horizontal Deflection	Occurs when an overvoltage of horizontal pulse is detected by D5115 and IC5201. If the voltage of pin 1 of IC5201 goes to High, the voltage to pin 20 of IC4301 go to UP. The unit will automatically turn off.
Audio Protector	If the Audio out lines become DC.This error will be detected by Q1202, Q1204 and Q1203. The unit will automatically turn off.

The operating instructions mentioned here are partial abstracts from the Operating Instruction Manual. The page numbers of the Operating Instruction Manual remain as in the manual.

SECTION 2
GENERAL

Using Your New Projection TV

Getting Started

Step 1

Connect the antenna

If you wish to connect a VCR, see the "Connecting a VCR" diagram below.

or

Antenna cable (not supplied)

IEC connector (not supplied)

Antenna cable (not supplied)

Rear of projection TV

: Signal flow

CAUTION
Do not connect the power cord until all other connections are complete; otherwise, a minimal current leakage through the antenna and/or other terminals to the ground could occur.

Connecting a VCR

To play a video tape, press ⊖ (see page 14).

To ⊤ (antenna)

Antenna cable (not supplied)

Rear of projection TV

To antenna output   VCR

To ⊷ (S video input)

S video cable (not supplied)

To S video output

VIDEO IN / VIDEO OUT / AUDIO VIDEO

To video and audio outputs

Y / Cᴮ/B-Y / Cᴿ/R-Y / 30W MAX 16 / L / R

: Signal flow

Audio/Video cable (not supplied)

To ⊖ 1, 2 or 3 (video input)
⊙ (yellow)
♪-L (MONO) (white)
♪-R (red)   continued

Getting Started (continued)

Notes
- If you connect a monaural VCR, connect the yellow plug to ⊙ (the yellow jack) and the black plug to ♪-L (MONO) (the white jack).
- If you connect a VCR to the ⊤ (antenna) terminal, preset the signal output from the VCR to the program number 0 on the projection TV.
- When both the ⊷ (S video input) and ⊖ 1 (video input) are connected, the ⊷ (S video input) is automatically selected. Ϭ view the video input to ⊖ 1 (video input), disconnect the S video cable.

Step 2

Insert the batteries into the remote

Notes
- Do not use old batteries or different types of batteries together.
- To operate some of the functions of your projection TV, you may have to open the remote control cover.

Step 3

Preset the channels automatically

KP-ES61/53/48

Inside the lower right side panel

1

2

AUTO PROGRAM
PR : 01
TV SYS : AUTO
VHF LOW

KP-ES43

Inside the lower panel

Notes
- To stop the automatic channel presetting, press MENU twice.
- If your projection TV has preset an unwanted channel or cannot preset a particular channel, then preset your projection TV manually (see page 44).
- To open the lower panel of your projection TV, push on it, then it will open.

KP-ES61/53/48   KP-ES43

Step 4

Adjusting the convergence automatically

KP-ES61/53/48   Inside the lower right side panel

KP-ES43   Inside the lower panel

Note
- Adjust convergence about 20 – 30 minutes after the projection TV is first turned on.
  The Digital Quick Focus feature allows you to adjust the convergence automatically.

Connecting optional components

You can connect optional audio/video components, such as a VCR, multi disc player, camcorder, video game, or stereo system. To watch and operate the connected equipment, see pages 14 and 28.

Connecting a camcorder/video game equipment using the ⊖ (video input) jacks

KP-ES61/53/48
Rear of projection TV

Video game equipment   Inside the lower left side panel

To S video output   To ⊖ (S video input)
S video cable (not supplied)

or

Camcorder

Audio/Video cable (not supplied)
To video and audio outputs   To ⊖ 4 (video input)

⇨ : Signal flow

KP-ES43
Rear of projection TV

Video game equipment   Inside the lower panel

To S video output   To ⊖ (S video input)
S video cable (not supplied)

or

Camcorder

Audio/Video cable (not supplied)
To video and audio outputs   To ⊖ 4 (video input)

⇨ : Signal flow

Notes
- When connecting video game equipment, display the "FEATURE" menu and select "ON" for "GAME MODE" to adjust the picture setting that is suitable for video games (see page 39).
- You can also connect video equipment to the ⊖ 1, 2, or 3 (video input) jacks at the rear of your projection TV.
- When both the ⊖ (S video input) and ⊖ 4 (video input) are connected, the ⊖ (S video input) is automatically selected. To view the video input to ⊖ 4 (video input), disconnect the S video cable.

Connecting audio/video equipment using the $\ominus$ (monitor output) jacks

Rear of projection TV

Antenna cable (not supplied)

or

Audio system

To antenna output   VCR

To video and audio inputs

To audio inputs

(yellow)

♪-L (MONO) (white)

♪-R (red)

To $\ominus$ (monitor output)

Audio/Video cable (not supplied)

Audio cable (not supplied)

: Signal flow

Notes
- If you select "DVD" on your TV screen, no signal will be output at the $\ominus$ (monitor output) jacks (see page 14).
- When connecting the audio cable to the $\ominus$, you can adjust the volume with $\angle +/-$.

Connecting a DVD player to $\boxminus$ (component video input)

1 Using an audio cable, connect R and L under $\boxminus$ (component video input) on your projection TV to the LINE OUT, AUDIO R and L output connectors on your DVD player.
2 Using a component video cable, connect Y, C_B/B-Y, and C_R/R-Y under $\boxminus$ (component video input) on your projection TV to the COMPONENT VIDEO OUT Y, C_B, and C_R output connectors on your DVD player.
3 Press $\ominus$ on the remote or the projection TV until "DVD" appears on the screen.

Component video cable (not supplied)   To $\boxminus$ (component video input)

Rear of projection TV

To component video output

To audio output

Audio cable (not supplied)

To ♪ -L (white)

♪ -R (red)

DVD player

: Signal flow

Notes
- Some DVD player terminals may be labeled differently:

Connect	To (on the DVD player)
Y (green)	Y
C_B/B-Y (blue)	C_b, B-Y or P_B
C_R/R-Y (red)	C_r, R-Y or P_R

- When connecting to $\boxminus$ (component video input) on your projection TV, you must connect Y, C_B, and C_R to receive the video signals, and at least connect L and R to receive analog audio signals.

— 11 —

Connecting a DVD player to ⊖ (video input)

Connect ⊖ 1, 2, or 3 (video input) ♪/⊙ (audio/video) connectors on your projection TV to LINE OUT on your DVD player.

Notes
- Since the high quality pictures on a DVD disc contain a lot of information, picture noise may appear. In this case, adjust the sharpness ("SHARP") under "PERSONAL ADJUST" in the "PICTURE MODE" menu (see page 34).
- Connect your DVD player directly to your projection TV. Connecting the DVD player through other video equipment will cause unwanted picture noise.

Connecting an amplifier with Dolby* Pro Logic decoder to ⊳⊲ ← C– (center speaker input)

Connect the speaker terminals on your amplifier to ⊳⊲ ← C– on your projection TV.

Note
- When making connection to ⊳⊲ ← C– on your projection TV set "SPEAKER: CENTER IN" in the "A/V CONTROL" menu. (see page 33)

* Manufactured under license from Dolby Laboratories Licensing Corporation.
DOLBY, the double-D symbol ▢▢ and "PRO LOGIC" are trademarks of Dolby Laboratories Licensing Corporation.

Installing the projection TV

For the best picture quality, install the projection TV within the areas below.

Optimum viewing area (Horizontal)

KP-ES43

KP-ES61/53/48

Optimum viewing area (Vertical)

KP-ES43

KP-ES61/53/48

Using Your New Projection TV

Watching the TV

This section explains various functions and operations used while watching the TV. Most operations can be done using the remote.

KP-ES61/53/48

Ⅼ indicator

KP-ES43

Ⅼ indicator

I/⏻

Number buttons

PROGR +/-

1 Press ① to turn on the projection TV.

When the projection TV is in standby mode (the ⏻ indicator on the projection TV is lit red), press I/⏻ on the remote.

2 Press PROGR +/- or the number buttons to select the TV channel.

For double digit numbers, press -/-, then the number (e.g., for 25, press -/-, then 2 and 5).

Note
• When you turn on the projection TV, either the program number or video mode is displayed for approximately 40 seconds. The ECO MODE (🗲ᴇᴄᴏ) icon will also appear if "ECO MODE " in the "FEATURE" menu is set "ON" (see page 39).

To select a TV program quickly

(1) Press and hold PROGR +/−.
(2) Release PROGR +/− when the desired program number appears.

Note
• When you select a TV program quickly, the picture may be disrupted. This does not indicate a malfunction.

Using Your New Projection TV | 13

---

14 | Using Your New Projection TV

Watching the TV (continued)

KP-ES61/53/48   **KP-ES43**

Ⅼ indicator

Ⅼ indicator

JUMP

MENU

ENTER

◿ +/-

Additional tasks

To	Press
Turn off temporarily	I/⏻. The ⏻ indicator on the projection TV lights up red.
Turn off completely	① on the projection TV.
Adjust the volume	◿ +/−.
Mute the sound	◻️✕.
Watch the video input (VCR, camcorder, etc.)	⊡ (or ⊡ on the projection TV) to select "VIDEO 1", "VIDEO 2", "VIDEO 3", "VIDEO 4" or "DVD". To return to the TV screen, press ☐ (or ⊡ on the projection TV).
Jump back to the previous channel	JUMP.
Display the on-screen information*	⊞.

* Some picture/sound settings, and either the program number or video mode are displayed. The on-screen display for the picture/sound settings disappears after about 3 seconds.

Using the Remote Control Button Joystick (⊕)

You can select the menu item on the screen by moving ⊕ up, down, left or right (see page 32).

To confirm a selected item, press ⊕. You can also press ENTER on the remote to confirm a selected item.

To move

To confirm

Changing the menu language

You can change the menu language as well as the on-screen language. For details on how to use the menu, see "Introducing the menu system" on page 30.

1 Press MENU.

```
⊃A/V CONTROL
DRC-MF: DRC1250
PICTURE MODE: DYNAMIC
SOUND MODE: DYNAMIC
SPEAKER:MAIN
```

2 Move ⊕ up or down to select 🔧, then press ⊕.

```
⊃SET UP
LANGUAGE:ENGLISH
CHILD LOCK:PR01 OFF
FAVORITE CH
INTELLIGENT VOL:OFF
```

3 Make sure "LANGUAGE" is selected then press ⊕.

```
⊃SET UP
LANGUAGE: ENGLISH
CHILD LOCK 中文
FAVORITE C عربي
INTELLIGEN
```

4 Move ⊕ up or down to select the desired language (e.g.,"中文"), then press ⊕.

The selected menu language appears.

```
⊃设定
语言/LANGUAGE: 中文
童锁:PR01 关
常用频道
智能音量控制: 关
```

To return to the normal screen

Press MENU.

Watching the TV (continued)

Setting the Wake Up timer

1 Press ⏰ until the desired period of time appears.

The Wake Up timer starts immediately after you have set it.

```
WAKE UP TIMER:10M
After 10 minutes

WAKE UP TIMER:OFF ← WAKE UP TIMER:12H00M
No Wake Up Timer        After 12 hours
```

2 Select the TV channel or video mode you want to wake up to.

3 Press I/⏻, or set the Sleep timer if you want the projection TV to turn off automatically.

The ⏰ indicator on the projection TV lights up orange.

To cancel the Wake Up timer

Press ⏰ until "WAKE UP TIMER: OFF" appears, or turn the projection TV off.

Note
- If no buttons or controls are pressed for more than two hours after the projection TV is turned on using the Wake Up timer, the projection TV automatically goes into standby mode. To resume watching the TV, press any button or control on the projection TV or the remote.

Setting the Sleep timer

Press ⏰ until the desired period of time appears.

The Sleep timer starts immediately after you have set it.

```
SLEEP TIMER:30M → SLEEP TIMER:60M
After 30 minutes      After 60 minutes

SLEEP TIMER:OFF ← SLEEP TIMER:90M
No Sleep Timer         After 90 minutes
```

To cancel the Sleep timer

Press ⏰ until "SLEEP TIMER: OFF" appears, or turn the projection TV off.

– 14 –

Selecting the picture and sound modes

→ SOUND MODE

→ PIC MODE

You can select picture and sound modes and adjust the setting to your preference in the "PERSONAL" option.

Selecting the picture mode

Press PIC MODE repeatedly until the desired picture mode is selected.

DYNAMIC → STANDARD
↑   ↓
PERSONAL ← HI-FINE

Select	To
"DYNAMIC"	receive high contrast pictures.
"STANDARD"	receive normal pictures.
"HI-FINE"	receive higher resolution pictures with mild contrast.
"PERSONAL"	receive the last adjusted picture setting from the "ADJUST" option in the "A/V CONTROL" menu (see page 34).

Selecting the sound mode

Press SOUND MODE repeatedly until the desired sound mode is selected.

♪DYNAMIC → ♪DRAMA
↑   ↓
♪PERSONAL ← ♪SOFT

Select	To
"DYNAMIC"	listen to dynamic and clear sound that emphasizes both the low and high tones.
"DRAMA"	listen to sound that emphasizes voice and high tones.
"SOFT"	receive soft sound.
"PERSONAL"	receive the last adjusted sound setting from the "ADJUST" option in the "A/V CONTROL" menu (see page 34).

Tip
• You can also set the picture and sound modes using the menu (see "Changing the "A/V CONTROL" setting" on page 33).

Viewing higher quality pictures
— "DRC-MF"

→ DRC-MF

The Digital Reality Creation-Multi Function (DRC-MF) feature allows you to enjoy higher quality pictures on your projection TV. You can select "DRC1250" to watch super real (higher resolution) pictures, or "DRC100" to reduce flicker if necessary.

Press DRC-MF repeatedly until you receive the desired picture quality.

DRC-MF: DRC1250 → DRC-MF: DRC100

Select	To
"DRC1250"	select higher resolution pictures.
"DRC100"	reduce flicker on the screen.

Tip
• When the broadcast signal is weak, you may see some dots or noise on the TV screen. To reduce this interference, display the "A/V CONTROL" menu and select "ADJUST" in "PICTURE MODE", then adjust "SHARP" to reduce the sharpness (see page 34).

Note
• The DRC-MF mode is not selectable when using the "PROGRAM INDEX" or "FAVORITE CH" feature, or when the "GAME MODE", Picture-In-Picture ("PIP"), or "TWIN" mode is turned "ON".

The DRC-MF logo ( ) and "DRC-MF" are trademarks of Sony Corporation.

Viewing your favorite channels
— "FAVORITE CH"

You can display seven favorite channels for quick and easy selection.

The last seven channels selected with the number buttons are displayed in "AUTO" mode. You can set up your own favorite channels in "MANUAL" mode under the "FAVORITE CH" menu (see "Changing the favorite channel setting" on page 42).

FAVORITE

ENTER

Selecting a favorite channel

1 Press FAVORITE.

FAVORITE

FAVORITE CH

2 Move ⊕ up, down, left or right to select the desired channel (e.g. PR 8), then press ⊕.

FAVORITE CH

3 Press ⊕ again.

8

Note
• When you use your projection TV for the first time, seven preset channels appear.

Watching two programs at the same time
— "PIP", "TWIN"

With the Picture-in-Picture (PIP) or TWIN pictures features, you can display a different TV program or video within or beside the main picture.

**PIP PROGR +/
PIP PROGR –**

Displaying the PIP screen

Press ⊡.

12

Displaying TWIN pictures

Press ⊡.

♪ 10   12

To return to the normal screen

Press ⊡ (when in the PIP screen) or ⊡ (when in the TWIN picture screen).

Tip
• You can also display the PIP screen or TWIN pictures using the menu (see "Changing the MULTI PICTURE setting" on page 36).

Additional PIP/TWIN pictures tasks

To	Press/Move
change a TV program in the PIP screen or in the right TWIN picture	Press PIP PROGR + or PIP PROGR –. For a video input, press ⏺.
swap pictures between the main and PIP screens	Press ⏺.
freeze the PIP screen	Press ⏺. To unfreeze the screen, press the button again.
change the position of the PIP screen	Press ⏺.
swap the right and left pictures of the TWIN pictures	Press ⏺.
change the screen size of the TWIN pictures	Move ⏺ left to increase the left screen size. Move ⏺ right to increase the right screen size.

Notes
- The ⏺ button does not function in the TWIN pictures mode.
- When you display a video input on the PIP screen at a faster/slower speed, the picture may be disrupted depending on the VCR type.
- If you display different color systems on the main screen and the PIP screen, the size of the PIP screen may be different and the PIP picture may be disrupted. This does not indicate a malfunction of the projection TV.
- In the TWIN picture screen, you can only operate and hear the sound of the main left screen (♪ appears on the screen).
- When the ⏺ button is pressed, the TV screen flickers or goes blank for about one second before the TWIN pictures appear. This does not indicate a malfunction of the projection TV.

Displaying multiple programs
— "PROGRAM INDEX"

PROGR INDEX

PROGR +/–

The PROGRAM INDEX feature displays all of the preset TV programs on twelve or seven sub screens for direct selection.

Press PROGR INDEX.

The first twelve preset programs appear one by one, clockwise from the upper left corner.

Sub screens
Main screen

When the number of the preset TV programs is less than eight, the first seven preset programs appear one by one, clockwise from the upper right corner.

Main screen
Sub screens

Tip
- When you press the PROGR INDEX button in the TWIN pictures mode, the left picture appears as the main screen of the PROGRAM INDEX mode.

To view the next or the previous twelve preset programs

This works only when the number of the preset TV programs is more than twelve.

Press PROGR +/– on the remote or the projection TV.

To select the desired program directly from the sub screens

1 Move ⊕ up, down, left or right to move the frame to the screen of the program you want to watch.

2 Press ⊕.

3 Press ⊕ again.

Tip
• Pressing the number buttons directly displays the program.

To return to the normal screen

Press PROGR INDEX again, or:

1 Select "PROGRAM INDEX" from the "MULTI PICTURE" menu.
2 Press ⊕.

Tip
• You can also display multiple programs using the menu (see "Changing the MULTI PICTURE setting" on page 36).

Note
• When displaying multiple programs, only the sound of the main screen is heard.

Enjoying stereo or bilingual programs

You can enjoy stereo sound or bilingual programs of NICAM and A2 (German) stereo systems.

A/B ⊕

Press A/B repeatedly until you receive the sound you want.

The on-screen display changes to show the selected sound and the ⊙ indicator on the projection TV lights up red.

A/B ⊕ ➡ NICAM

When receiving a NICAM program

Broadcasting	On-screen display (Selected sound)		
NICAM stereo	**NICAM** (Stereo sound)		**MONO** (Regular sound)
NICAM bilingual	**NICAM MAIN** (Main sound)	**NICAM SUB** (Sub sound)	**MONO** (Regular sound)
NICAM monaural	**NICAM MAIN** (Main sound)		**MONO** (Regular sound)

When receiving an A2 (German) program

Broadcasting	On-screen display (Selected sound)
A2 (German) stereo	**MONO** (Regular sound) → **STEREO** (Stereo sound)
A2 (German) bilingual	**MAIN** (Main sound) → **SUB** (Sub sound)

Receiving area for NICAM and A2 (German) programs

System	Receiving area
NICAM	Hong Kong, Singapore, New Zealand, Malaysia, Thailand, etc.
A2 (German)	Australia, Malaysia, Thailand, etc.

Notes
- If the signal is very weak, the sound becomes monaural automatically.
- If the stereo sound is noisy when receiving a NICAM program, select "MONO". The sound becomes monaural, but the noise is reduced.
- Before receiving a NICAM stereo program in China, please check the NICAM broadcast condition at your area. When receiving a NICAM stereo program, the receiving conditions might vary depending on area. In addition, different strength of the NICAM broadcast signal might affect the receiving quality.

If the sound is distorted or noisy when receiving a monaural program through the ⊤⊤ (antenna) terminal

Press A/B repeatedly until "MONO" appears on the screen.

To cancel the monaural sound setting, press A/B again until "AUTO" appears on the screen.

MONO → **AUTO**

Notes
- The "MONO" or "AUTO" setting is memorized for each program position.
- You cannot receive a stereo broadcast signal when the projection TV is in the "MONO" setting. Normally, set the projection TV to "AUTO".

Viewing Teletext

Some TV stations broadcast an information service called Teletext which allows you to receive various information, such as stock market reports and news.

A/B ⊕

■■■■ (red, green, yellow, blue)

Displaying Teletext

1 Select a TV channel that carries the Teletext broadcast you want to watch.

2 Press ▤ to display the text.

A Teletext page (normally the index page) is displayed. If there is no Teletext broadcast, "100?" is displayed at the top left corner of the screen after approximately 10 seconds.

To turn off Teletext

Press ◯.

Additional Teletext tasks

To	Do this
display a Teletext page on the TV picture	Press ▤. Each time you press ▤ , the screen changes as follows: Teletext → Teletext and TV → TV.
check the contents of a Teletext service	Press ▤. An overview of the Teletext contents, including page numbers, appears on the screen.
select a Teletext page	Press the number buttons to enter the three-digit page number of the desired Teletext page.* If you make a mistake, reenter the correct page number. To access the next or previous page, press PROGR +/–.
hold (pause) a Teletext page (stop the page from scrolling)	Press ⊕ to display the symbol "⊡" at the top left corner of the screen. To resume normal Teletext viewing, press ⊕ or ▤.
reveal concealed information (e.g., an answer to a quiz)	Press ?. To conceal the information, press the button again.
enlarge the Teletext display	Press ⊕. Each time you press ⊕, the Teletext display changes as follows: Enlarge upper half → Enlarge lower half → Normal size.
stand by for a Teletext page while watching a TV program	1 Enter the Teletext page number that you want to refer to, then press ⊗. 2 When the page number is displayed, press ▤ to show the text.

* You can also select a Teletext page of any page number that appears in the colored column at the bottom of the screen using the corresponding color-coded button on the remote.

Using FASTEXT

This feature allows you to quickly access a Teletext page that uses FASTEXT. When a FASTEXT program is broadcast, colored menus appear at the bottom of the screen. The color of each menu corresponds to the color-coded buttons on the remote (red ▭ , green ▭ , yellow ▭ , and blue ▭).

To access a FASTEXT menu

Press the color-coded button on the remote corresponding to the menu you want. The menu page appears on the screen after a few seconds.

Operating optional components

You can use the supplied remote to operate Sony video equipment such as Beta, 8 mm, VHS or DVD.

VIDEO I/⏻
Video equipment operation buttons

MENU

VTR

Setting up the remote to work with other connected equipment

Switch VTR to select the desired equipment type (see the chart below).

For example, to operate a Sony 8 mm VCR:

VTR 1 2 3 DVD

To control	Select
DVD	DVD
VTR1 (Beta)	1
VTR2 (8 mm)	2
VTR3 (VHS)	3

Notes
• If your video equipment is furnished with a COMMAND MODE selector, set this selector to the same position as the VTR switch.
• If the equipment does not have a certain function, the corresponding button on the remote will not operate.

— 20 —

Operating a VCR using the remote

To	Press
turn on/off	VIDEO ∣/⏻
record	▶ while pressing ●.
play	▶
stop	■
fast forward (▶▶)	▶▶∣
rewind the tape (◀◀)	∣◀◀
pause	∥ Press again to resume normal playback.
search the picture forward (▶▶) or backward (◀◀)	▶▶∣ or ∣◀◀ during playback. Release to resume normal playback.

Operating a DVD player using the remote

To	Press
turn on/off	VIDEO ∣/⏻
play	▶
stop	■
pause	∥ Press again to resume normal playback.
step through different tracks of an audio disc	▶▶∣ to step forward or ∣◀◀ to step backward.
display the title menu	TITLE
display the menu	MENU while holding down ●.
select the menu item	Move ◉ up, down, left or right while holding down ●.

Adjusting Your Setup (MENU)

Introducing the menu system

The MENU button lets you open a menu and change the settings of your projection
TV. The following is an overview of the menu system.

Level 1	Level 2	Level 3/Function
"A/V CONTROL" 	"DRC-MF"	Select the "DRC-MF" mode: "DRC1250" → "DRC100"
	"PICTURE MODE"	Select the picture mode: "DYNAMIC" → "STANDARD" → "HI-FINE" → "PERSONAL" → "ADJUST"
	"ADJUST"	Adjust the "PERSONAL" option: "PICTURE" → "COLOR" → "BRIGHT" → "HUE" → "SHARP"
	"SOUND MODE"	Select the sound mode: "DYNAMIC" → "DRAMA" → "SOFT" → "PERSONAL" → "ADJUST"
	"ADJUST"	Adjust the "PERSONAL" option: "BASS" → "TREBLE" → "BALANCE"
	"SPEAKER"	Select the "SPEAKER" mode: "MAIN" → "CENTER IN"
"MULTI PICTURE"	"PIP"	Activate or deactivate the PIP feature.
	"PIP POSITION"	Change the position of the sub screen.
	"SWAP"	Swap the pictures between the main and sub screens.
	"TWIN"	Display a TV program or video beside the main screen.
	"PROGRAM INDEX"	Display all the preset TV programs at the same time.
"FEATURE"	"WIDE MODE"	Activate or deactivate WIDE MODE feature.
	"ECO MODE"	Activate or deactivate ECO MODE feature.
	"GAME MODE"	Activate or deactivate GAME MODE feature.

– 21 –

Level 1	Level 2	Level 3/Function
"SET UP"	"LANGUAGE"	Change the menu language: "ENGLISH" → "中文" (Chinese) → "عربي" (Arabic)
	"CHILD LOCK"	Lock out specific channels.
	"FAVORITE CH"	Set favorite channels.
	"INTELLIGENT VOL"	Adjust the volume automatically.
"CH PRESET"	"AUTO PROGRAM"	Preset channels automatically.
	"MANUAL PROGRAM"	Preset channels manually.
	"SKIP"	Skip unwanted or unused program numbers.
	"TV SYS"	Select the TV system: "B/G" → "I" → "D/K" → " M"
	"COL SYS"	Select the color system: "AUTO" →" PAL" → "SECAM" → "NTSC3.58" → "NTSC4.43"

Introducing the menu system (continued)

How to use the menu

Press MENU to display the menu.

Move the button joystick ( ) up, down, left or right to select the desired item.

Press the button joystick ( ) to confirm the selection and/or go to the next level. You can also press ENTER on the remote to do this.

or

Other menu operations

To	Press/Move
Adjust the setting value	Move up, down, left or right.
Move to the next/previous menu level	Move left or right.
Cancel the menu	Press MENU.

Tips
- If you want to exit from Menu level 2 to Menu level 1, move up or down until the return icon (⌐) is highlighted, then press or ENTER.
- The MENU, ENTER, and ∠ +/– buttons on the projection TV can also be used for the operations above.
- The ♦ + and ♦ – buttons on the projection TV can also be used instead of moving the button joystick ( ) up or down.

Note
- If more than 60 seconds elapse between entries, the menu screen automatically disappears.

Changing the "A/V CONTROL" setting

The "A/V CONTROL" menu allows you to adjust the picture and sound settings.

1 Press MENU.

```
⊃A/V  CONTROL
DRC-MF: DRC1250
PICTURE MODE: DYNAMIC
SOUND MODE: DYNAMIC
SPEAKER:MAIN
```

2 Move ⊕ up or down to select, then press ⊕.

```
⊃A/V  CONTROL
DRC-MF: DRC1250
PICTURE MODE: DYNAMIC
SOUND MODE: DYNAMIC
SPEAKER:MAIN
```

3 Move ⊕ up or down to select either "DRC-MF", "PICTURE MODE", "SOUND MODE", or "SPEAKER", then press ⊕.

```
⊃A/V  CONTROL
DRC-MF :          DRC1250
PICTURE MODE   DRC100
SOUND MODE
SPEAKER:MAIN
```

4 Move ⊕ up or down to select the desired option, then press ⊕.

For	Select
"DRC-MF"	either "DRC1250" or "DRC100".
"PICTURE MODE"	either "DYNAMIC", "STANDARD", "HI-FINE", "PERSONAL"*, or "ADJUST".
"SOUND MODE"	either "DYNAMIC", "DRAMA", "SOFT", "PERSONAL"*, or "ADJUST".
"SPEAKER"	either "MAIN" or "CENTER IN".

* When the "PERSONAL" mode is selected, the last adjusted picture/sound settings from the "ADJUST" option are received (see page 34).

Tip
• For details on the options under the "DRC-MF", "PICTURE MODE"/ "SOUND MODE", and "SPEAKER" modes, see pages 18, 17 and 35 respectively.

To return to the normal screen

Press MENU.

Changing the "A/V CONTROL" setting (continued)

Adjusting the "ADJUST" options under "PICTURE MODE"

1 Move ⊕ up or down to select the desired item (e.g., "COLOR"), then press ⊕.

COLOR ‖‖‖‖‖‖‖‖‖‖‖‖···· 80

2 Adjust the value according to the following table, then press ⊕.

For	Move ⊕ down or left to	Move ⊕ up or right to
"PICTURE"	decrease picture contrast	increase picture contrast
"COLOR"	decrease color intensity	increase color intensity
"BRIGHT"	darken the picture	brighten the picture
"HUE"*	increase red picture tones	increase green picture tones
"SHARP"	soften the picture	sharpen the picture

* You can adjust "HUE" for the NTSC color system only.

3 Repeat the above steps to adjust other items.

The adjusted settings will be received when you select "PERSONAL".

Adjusting the "ADJUST" options under "SOUND MODE"

1 Move ⊕ up or down to select the desired item (e.g., "BALANCE"), then press ⊕.

BALANCE ‖‖‖‖‖‖‖‖‖‖‖‖‖00

2 Adjust the value according to the following table, then press ⊕.

For	Move ⊕
"BASS"	down or left to decrease the bass, up or right to increase the bass.
"TREBLE"	down or left to decrease the treble, up or right to increase the treble.
"BALANCE"	down or left to increase the left speaker's volume, up or right to increase the right speaker's volume.

3 Repeat the above steps to adjust other items.

The adjusted settings will be received when you select "PERSONAL".

Setting the "SPEAKER" options

1 In the "SPEAKER" menu, move ⊕ up or down to select the desired option (see table below).

⊃A/V CONTROL
DRC-MF : DRC   MAIN
PICTURE MODE   CENTER IN
SOUND MODE
SPEAKER

Select	To
"MAIN"	listen to the sound from a projection TV.
"CENTER IN"	use the projection TV speakers as center speakers.

2 Press ⊕ to confirm the selected option.

Tip
• For details on the menu system and how to use the menu, refer to "Introducing the menu system" on page 30.

Changing the "MULTI PICTURE" setting

The "MULTI PICTURE" menu allows you to use the Picture-in-Picture (PIP), TWIN pictures, or PROGRAM INDEX features.

MENU

PROGR INDEX

1 Press MENU.

MENU

⊃A/V CONTROL
DRC-MF: DRC1250
PICTURE MODE: DYNAMIC
SOUND MODE: DYNAMIC
SPEAKER: MAIN

2 Move ⊕ up or down to select ▦, then press ⊕.

⊃MULTI PICTURE
PIP:OFF
PIP POSITION : ▭
SWAP
TWIN:OFF
PROGRAM INDEX

– 24 –

3 Move ⊕ up or down to select the desired option (see the table below), then press ⊕.

Select	To
"PIP"	display the PIP screen within the main picture. Move ◉ up or down to select "ON", then press ◉. To cancel, press ◻ or select "OFF", then press ◉.
"PIP POSITION"	change the position of the PIP screen. Move ◉ up or down to select the desired position, then press ◉.
"SWAP"	swap the main and PIP screens, or right and left pictures of the TWIN pictures.
"TWIN"	display a different TV program or video beside the main picture. Move ◉ up or down to select "ON", then press ◉. To cancel, press ◻ or select "OFF", then press ◉.
"PROGRAM INDEX"	view multiple programs on the sub-screens. To cancel, press PROGR INDEX.

To return to the normal screen

Press MENU.

Tip
• For details on the menu system and how to use the menu, see "Introducing the menu system" on page 30.

Changing the "FEATURE" setting

The "FEATURE" menu allows you to change the size of the picture on the screen when receiving wide mode (16:9) picture signals. You can also adjust the picture setting that is suitable for viewing video games, and reduce the power consumption of your projection TV.

1 Press MENU.

```
▷A/V  CONTROL
DRC-MF: DRC1250
PICTURE MODE: DYNAMIC
SOUND MODE: DYNAMIC
SPEAKER: MAIN
```

2 Move ⊕ up or down to select 🗔, then press ⊕.

```
▷FEATURE
WIDE MODE: OFF
ECO MODE: OFF
GAME MODE: OFF
```

– 25 –

3 Move ⊕ up or down to select the desired option (see the table below), then press ⊕.

Select	To
"WIDE MODE"	change the size of the picture when receiving wide-mode (16:9) picture signal. Move ⊕ up or down to select "ON", then press ⊕. To restore the normal picture size, select "OFF" then press ⊕.
"ECO MODE"	reduce power consumption of your projection TV to save energy. Move ⊕ up or down to select "ON", then press ⊕. To cancel, select "OFF", then press ⊕.
"GAME MODE"	adjust the picture setting that is suitable to view video games. Move ⊕ up or down to select "ON", then press ⊕. To cancel, select "OFF", then press ⊕.

Notes
- When you turn on "ECO MODE", the picture may become dimmer. Turning "ECO MODE" off will restore the picture to its original setting.
- "WIDE MODE" is available only when you have selected DRC1250 (NTSC mode) in the "A/V CONTROL" menu with video input or DVD input.
- "WIDE MODE" and "GAME MODE" is available only when receiving signals through the ⊖ (video input), ⊕ (S video input), or ⊕ (component video input) jacks at the front and rear of your projection TV.
- If "ECO MODE" is on, the ECO MODE ( ) icon will appear at the bottom right corner of the screen when you turn on the projection TV or when you press ⊕ on the remote. (See pages 13 and 14)

To return to the normal screen

Press MENU.

Tip
- For details on the menu system and how to use the menu, see "Introducing the menu system" on page 30.

— 26 —

Changing the "SET UP" setting

The "SET UP" menu allows you to: change the menu language, block channels, adjust the picture position, program your favorite channels, and adjust the volume automatically.

Number buttons

MENU

ENTER

1 Press MENU.

```
⊐A/V CONTROL
DRC-MF: DRC1250
PICTURE MODE: DYNAMIC
SOUND MODE: DYNAMIC
SPEAKER: MAIN
```

2 Move ⊕ up or down to select 🖥, then press ⊕.

```
⊐SET UP
LANGUAGE: ENGLISH
CHILD LOCK: PR01 OFF
FAVORITE CH
INTELLIGENT VOL: OFF
```

3 Move ⊕ up or down to select the desired option, then press ⊕.

Select	To
"LANGUAGE"	change the menu language (see page 15).
"CHILD LOCK"	block channels (see page 41).
"FAVORITE CH"	select your favorite channels (see pages 19 and 42).
"INTELLIGENT VOL"	adjust the volume of all TV programs automatically. Move ⊕ up or down to select "ON", then press ⊕. To cancel, select "OFF", then press ⊕.

To return to the normal screen

Press MENU.

Blocking channels ("CHILD LOCK")

1 After selecting "CHILD LOCK", either move ⊕ up or down, or press the number buttons (or PROGR +/–) to select the desired channel (e.g. PR 06), then press ⊕.

or

```
⇒SET UP
LANGUAGE:E
CHILD LOCK  PR 06
FAVORITE C
INTELLIGEN  ON
            OFF
```

2 Move ⊕ up or down to select "ON", then press ⊕.
To unlock the channel, select "OFF".

The lock symbol (🔒) appears on the screen when "ON" is selected.

If a locked channel is selected, the lock symbol appears on the screen.

```
⇒SET UP
LANGUAGE:ENGLISH
CHILD LOCK :PR06 ON
FAVORITE CH
INTELLIGENT VOL:OFF
```

🔒 6

3 Repeat steps 1 and 2 to lock other channels.

To return to the normal screen

Press MENU.

Note
• If you preset a locked channel, that channel will be unlocked automatically (see page 43).

Changing the "SET UP" setting (continued)

Changing the favorite channel setting

1 After selecting "FAVORITE CH", make sure "MODE" is selected, then press ⊕.

```
⇒FAVORITE CH
MODE:       AUTO
1.PR01      MANUAL
2.PR02
3.PR06
4.PR08
```

2 Move ⊕ up or down to select "MANUAL", then press ⊕.

```
⇒FAVORITE CH
MODE:MANUAL
1.PR01      5.PR09
2.PR02      6.PR11
3.PR06      7.PR13
4.PR08
```

3 Move ⊕ up or down to select the program you want to change, then press ⊕.

```
⇒FAVORITE CH
MODE:MANUAL
1.PR01      5.PR09
2.PR02      6.PR11
3.PR06      7.PR13
4.PR08
```

4 Move ⊕ up or down to change the number, then press ⊕.

```
⇒FAVORITE CH
MODE:MANUAL
1.PR01      5.PR09
2.PR02      6.PR11
3.PR05      7.PR13
4.PR08
```

5 Repeat steps 3 and 4 to set other channels.

To return to the normal screen

Press MENU.

Note
• If you press the PROGR +/– buttons or number buttons in step 4 above, the projection TV will display the channel immediately.

– 27 –

Changing the "CH PRESET" setting

The "CH PRESET" menu allows you to adjust the setup of your projection TV. For example, you can manually tune in a channel with a weak signal that fails to be tuned in by automatic presetting.

MENU

ENTER

PRESET

1 Press MENU.

```
⊃A/V CONTROL
DRC•MF: DRC1250
PICTURE MODE: DYNAMIC
SOUND MODE: DYNAMIC
SPEAKER: MAIN
```

2 Move ⊕ up or down to select 📺, then press ⊕.

```
⊃CH PRESET
AUTO PROGRAM
MANUAL PROGRAM
SKIP:PR02 OFF
TV SYS:B/G
COL SYS:AUTO
```

3 Move ⊕ up or down to select the desired option, then press ⊕.

Select	To
"AUTO PROGRAM"	preset channels automatically.
"MANUAL PROGRAM"	preset channels manually. See "Presetting channels manually" on page 44.
"SKIP"	skip unwanted or unused channels. 1 Either move ⊕ up or down, or press the number buttons (or PROGR +/–) until the unused or unwanted channel number appears, then press ⊕. 2 Select "ON", then press ⊕. 3 To disable other channels, repeat steps 1 and 2. To restore the skipped channel, select "OFF" in step 2.
"TV SYS"	select the TV system.
"COL SYS"	select the color system. Normally, set this to "AUTO".

To return to the normal screen
Press MENU.

Tip
• For details on the menu system and how to use the menu, refer to "Introducing the menu system" on page 30.

– 28 –

Presetting channels manually

1 After selecting "MANUAL PROGRAM", select the program number to which you want to preset a channel.
(1) Make sure "PR" is selected, then press ⊕.

```
⊃MANUAL PROGRAM
PR: 06
TV SYS:B/G
SENS:HIGH
VHF LOW ▓▓▓▓▓▓▓
FINE:AUTO
```

(2) Move ⊕ up or down until the program number you want to preset (e.g., program number "10") appears on the menu, then press ⊕.

```
⊃MANUAL PROGRAM
PR: 10
TV SYS:B/G
SENS:HIGH
VHF LOW ▓▓▓▓▓▓▓
FINE:AUTO
```

Tips
• You can also select the "MANUAL PROGRAM" menu directly by pressing the PRESET button on the remote.
• You can also select the program number with the PROGR +/– or number buttons.

2 Select the desired channel.
(1) Move ⊕ up or down to select either "VHF LOW", "VHF HIGH", or "UHF", then press ⊕.

```
⊃MANUAL PROGRAM
PR: 10
TV SYS:B/G
SENS:HIGH
VHF LOW ▓▓▓▓▓▓▓
FINE:AUTO
```

(2) Move ⊕ up or down until the desired channel's broadcast appears on the TV screen, then press ⊕.

```
⊃MANUAL PROGRAM
PR: 10
TV SYS:B/G
SENS:HIGH
VHF LOW ▓▓▓▓▓▓▓
FINE:AUTO
```

3 If the sound of the desired channel is abnormal, select the appropriate TV system.
(1) Move ⊕ up or down to select "TV SYS", then press ⊕.

```
⊃MANUAL PROGRAM
PR: 10      B/G
TV SYS:     I
SENS:HIG  D/K
VHF LOW ▓▓▓▓  M
FINE:AUTO
```

(2) Move ⊕ up or down until the sound becomes normal, then press ⊕.

```
⊃MANUAL PROGRAM
PR: 10
TV SYS:I
SENS:HIGH
VHF LOW ▓▓▓▓▓▓▓
FINE:AUTO
```

4 If you are not satisfied with the picture and sound quality, you may be able to improve them by using the "FINE" tuning feature.

(1) Move ⊕ up or down to select "FINE", then press ⊕.

```
⊐MANUAL  PROGRAM  ⬅↩
PR: 10          AUTO
TV SYS: I       MANUAL
↯SENS:HIG
VHF LOW ▒▒▒▒
↯FINE:
```

(2) Move ⊕ up or down to select "MANUAL", then press ⊕.

```
⊐MANUAL  PROGRAM  ⬅↩
PR: 10          AUTO
TV SYS: I       MANUAL
↯SENS:HIG       ▬ ⊞
VHF LOW ▒▒▒▒
↯FINE:
```

(3) Move ⊕ either up, down, left or right until the picture and sound quality are optimal, then press ⊕. The + or – icon on the menu flashes while tuning.

```
⊐MANUAL  PROGRAM  ⬅↩
PR: 10
TV SYS: I
↯SENS:HIGH
VHF  LOW ▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒
↯FINE:MANUAL
```

5 If the TV signal is too strong and the picture is distorted, you can adjust the TV reception sensitivity.

(1) Move ⊕ up or down to select "↯SENS", then press ⊕.

```
⊐MANUAL  PROGRAM  ⬅↩
PR: 10          HIGH
TV SYS: I       LOW
↯SENS:
VHF  LOW
↯FINE:MANUAL
```

(2) Move ⊕ up or down to select "LOW", then press ⊕.

```
⊐MANUAL  PROGRAM  ⬅↩
PR: 10
TV SYS: I
↯SENS:LOW
VHF  LOW ▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒
↯FINE:MANUAL
```

To return to the normal screen

Press MENU.

Notes
• The TV system ("TV SYS") and the TV reception sensitivity ("↯SENS") settings are memorized for each program number.
• If you preset a locked channel, that channel will be unlocked automatically (see page 41).

Troubleshooting

If you have any problem while viewing your TV, please check the following troubleshooting guide. If the problem persists, contact your Sony dealer.

Symptom	Possible cause	Solutions	Page
Snowy picture	• The connection is loose or the cable is damaged.	• Check the antenna cable and connection on the projection TV, VCR and at the wall.	5
Noisy sound	• Channel presetting is inappropriate or incomplete.	• Press the PRESET button to display the "MANUAL PROGRAM" menu and preset the channel again.	44
	• The antenna type is inappropriate.	• Check the antenna type (VHF/UHF). Contact a Sony dealer for advice.	–
	• The antenna direction needs adjustment.	• Adjust the antenna direction. Contact a Sony dealer for advice.	–
	• Signal transmission is low.	• Try using a booster.	–
Distorted picture	• Broadcast signals are too strong.	• Press the PRESET button to display the "MANUAL PROGRAM" menu. Then, select "↯ SENS: LOW".	45
Noisy sound		• Turn off or disconnect the booster if it is in use.	–
Good picture	• The TV system setting is inappropriate.	• If the sound of all the channels are noisy, display the "CH PRESET" menu and select "AUTO PROGRAM" to preset the channels again.	43
Noisy sound		• If the sound of some channels is noisy, select the channel, then display the "CH PRESET" menu and select the appropriate TV system ("TV SYS").	44
No picture	• The power cord, antenna or VCR is not connected.	• Check the power cord, antenna and the VCR connections.	5
No sound	• The projection TV is not turned on.	• Press I/⏻ on the remote.	13
		• Press ① on the TV to turn off the projection TV for about five seconds, then turn it on again.	14

Symptom	Possible cause	Solutions	Page
Good picture **No sound** 	• The volume level is too low.	• Press ⊿ + to increase the volume level.	14
	• The sound is muted.	• Press ⊠ to cancel the muting.	14
	• The broadcast signal has a transmission problem.	• Press A/B until a better sound is heard.	24
	• The "SPEAKER" setting in the "AV CONTROL" menu is inappropriate.	• When connecting to ⌷ ← C– (center speaker input) on your projection TV to use the projection TV speakers as center speakers, set SPEAKER: CENTER IN, or set SPEAKER: MAIN to listen to the sound from a projection TV.	35
Dotted lines or stripes 	• There is local interference from cars, neon signs, hair dryers, power generators, etc.	• Do not use a hair dryer or other equipment near the projection TV.	–
		• Adjust the antenna direction for minimum interference. Contact a Sony dealer for advice.	–
Double images or "ghosts" 	• Broadcast signals are reflected by nearby mountains or buildings.	• Use a highly directional antenna.	–
		• Use the fine tuning ("FINE") function.	45
	• The antenna direction needs adjustment.	• Adjust the antenna direction. Contact a Sony dealer for advice.	–
	• Use of a booster is inappropriate.	• Turn off or disconnect the booster if it is in use.	–
No color 	• The color level setting is too low.	• Display the "A/V CONTROL" menu and select "ADJUST" of "PICTURE MODE", then adjust the "COLOR" level.	34
	• The color system setting is inappropriate.	• Display the "CH PRESET" menu and check the color system ("COL SYS") setting (usually set this to "AUTO").	43
	• The antenna direction needs adjustment.	• Adjust the antenna direction. Contact a Sony dealer for advice.	–
Abnormal color patches 	• The magnetic disturbance from external speakers or other equipment, or the direction of the earth's magnetic field may affect the projection TV.	• Locate external speakers or other equipment away from the projection TV. Do not move the projection TV while the projection TV is turned on. Press ① on the projection TV to turn off the TV for about five minutes, then turn it on again.	–

– 30 –

Additional Information

Troubleshooting (continued)

Symptom	Possible cause	Solutions	Page
Projection TV cannot receive stereo broadcast signal.	• The stereo reception setting is inappropriate.	• Press A/B until "AUTO" appears on the screen.	24
Stereo broadcast sound switches on and off or is distorted. **or** **The sound switches between stereo and monaural frequently.**	• The connection is loose or the cable is damaged.	• Check the antenna cable and connection on the projection TV, VCR and on the wall.	5
	• The antenna direction needs adjustment.	• Adjust the antenna direction. Contact a Sony dealer for advice.	–
	• The broadcast signal has a transmission problem.	• Press A/B until a better sound is heard.	24
"100?" appears at the top of the screen after approximately 10 seconds and there is no Teletext display.	• The channel carries no Teletext broadcast.	—	26
Teletext display is incomplete (snowy picture or double images).	• Connection is loose or the cable is damaged.	• Check the antenna cable and connection on the projection TV, VCR, and at the wall.	5
	• The antenna direction is inappropriate.	• Adjust the antenna direction. Contact a Sony dealer for advice.	–
	• Signal transmission is too low.	• Try using a booster.	–
		• Use the fine tuning ("FINE") function.	45
Lines moving across the TV screen.	• There is interference from external sources, e.g., heavy machineries, nearby broadcast station.	• Use the fine tuning ("FINE") function.	45
Cannot play shooting games.	• Some shooting games which involve pointing a light beam at the projection TV screen with an electronic gun or rifle cannot be used with your TV. For detail, see the instruction manual supplied with the video game software.	—	–

Symptom	Possible cause	Solutions	Page
TV cabinet creaks.	• Changes in room temperature sometimes make the TV cabinet expand or contract, causing a noise. This does not indicate a malfunction.	—	–
Static discharge is felt when touching the TV cabinet.	• This is the same static discharge that is felt when touching metal door handles or car doors especially when the air is dry, for example in winter. This does not indicate a malfunction.	—	–

Self-diagnosis function

Your projection TV is equipped with a self-diagnosis function. If there is a problem with your projection TV, the ⏻ (standby) indicator flashes red. The number of times the ⏻ indicator flashes indicates the possible causes.

KP-ES61/53/48   KP-ES43

⏻ indicator

1 Check that the ⏻ indicator flashes red a number of times between 3-second intervals.

2 Count the number of times the ⏻ indicator flashes.

3 Press ① (main power) to turn off your projection TV.

4 Inform your nearest Sony service center about the number of times the ⏻ indicator flashed.

Be sure to note the model name and serial number located on the rear of your projection TV.

Identifying parts and controls

Front and inside the lower panels

KP-ES61/53/48   Front panel   KP-ES43   Front panel

Inside the lower panel   Inside the lower panel

Left side   Right side

Button	Function	Page
Front panel		
①	Turn off completely or turn on the projection TV.	13
PROGR +/–	Select program number.	13
⊿ +/–	Adjust volume.	14
⊖	Select TV or video input.	14
Inside the lower panel		
MENU	Display the menu.	32
ENTER	Confirm selected items.	32
⊞	Adjust convergence.	7
▶▶❘	Preset channel automatically.	6
♠+/♣–	Select menu item.	32
⌒	Headphone jack	–

— 31 —

Remote control

The names/symbols of buttons on the remote are indicated in different colors to represent the available functions.

Label color	Button function
White	For general TV operations
Green	For Teletext operations
Yellow	For PIP operations

Button	Function	Page
I / ⏻	Turn off temporarily or turn on the projection TV.	13
PROGR +/−	Select program number.	13
0 − 9, -/--	Input numbers.	13
ⓘ⊕	Display on-screen information.	14
⊠✕	Mute the sound.	14
▢	Display the TV program.	14
⊸	Select TV or video input.	14
⊿ +/−	Adjust volume.	14
JUMP	Jump to previous channel.	14
Timer operations		
⏲	Set projection TV to turn on automatically.	16
⏲	Set projection TV to turn off automatically.	16
SOUND MODE	Select sound mode.	17
PIC MODE	Select picture mode.	17
DRC-MF	Select DRC-MF mode.	18
Favorite Channel operations		
FAVORITE	Display favorite channels.	19
◉	Select desired channel.	19
PIP and Twin picture operations		
▣	Display the PIP screen.	20
▤	Display TWIN pictures.	20
◉	Adjust Twin picture size.	21
PIP PROGR +/ PIP PROGR −	Change program in PIP/ Twin picture.	21
▣	Select video input for PIP/ Twin picture.	21
▨	Swap main and PIP/Twin picture.	21
▣	Freeze PIP screen.	21
▣	Adjust position of PIP screen.	21

continued

Identifying parts and controls (continued)

Button	Function	Page
Program Index operations		
PROGR INDEX	Display all preset TV programs.	22
PROGR +/−	View next/previous 12 TV programs.	22
◉	Select desired channel.	23
Stereo/bilingual operations		
A/B	Select stereo/bilingual mode.	24
Teletext operations		
▤	Display Teletext broadcast.	26
▤	Display Teletext service contents.	27
⊕	Stop Teletext page from scrolling.	27
⑦	Reveal concealed information.	27
⊕	Enlarge the Teletext display.	27
⊗	Show TV screen while waiting for Teletext page.	27
0 - 9	Input Teletext page number.	27
PROGR +/−	Display the next or previous page.	27
▨ (red, green, yellow, blue)	Access a FASTEXT menu.	27
Optional components operations		
VTR	Set up the remote.	28
VIDEO I/⏻	Power.	29
TITLE	Display the title menu.	29
▶	Play.	29
▶▶I	Fast forward/Search forward.	29
I◀◀	Rewind/Search backward.	29
●	Record.	29
■	Stop.	29
II	Pause.	29
Menu operations		
MENU	Display the menu.	32
◉	Select, adjust and confirm selected items.	32
ENTER	Confirm selected items.	32
PRESET	Display "MANUAL PROGRAM" menu.	44

SECTION 3
DISASSEMBLY

3-1. REAR BOARD REMOVAL

• **KP-ES43**

② Rear board

① Eight screws
(Hexagon head)

• **KP-ES53**

② Rear board

① Thirteen screws
(Hexagon head)

• **KP-ES48**

② Rear board

① Thirteen screws
(Hexagon head)

• **KP-ES61**

② Rear board

① Twelve screws
(Hexagon head)

3-2. MAIN BRACKET BLOCK REMOVAL

• **KP-ES43**

② Net work
④ Woofer block assembly
③ Four screws (4 x 16)
① Two screws (Hexagon head)
① Open the printed circuit board holder.
⑥ Main bracket block

3-3. SERVICE POSITION

• **KP-ES43/ES48/ES53/ES61**

Main bracket block

• **KP-ES48/ES53/ES61**

① Light shield block
② Two screws (Hexagon head)
⑥ Main bracket block

3-4. CONTROL PANEL BLOCK AND RESISTOR ASSEMBLY (FOCUS PACK) REMOVAL

• KP-ES43

⑦ Control panel
   block

⑥ Three screws
   (Hexagon head)

⑤ Front cover (L)

④ Four screws
   (Hexagon head)

⑨ Resistor assembly
   (Focus pack)

⑧ Screw
   (+BVTP 4 x 16)

① Speaker grille
   assembly

③ Front cover (R)

② Four screws
   (Hexagon head)

• KP-ES48/ES53/ES61

⑤ Control panel
   block

④ Two screws
   (Hexagon head)

③ Front board

② Nine screws
   (Hexagon head)

① Speaker grille
   assembly

⑦ Resistor assembly
   (Focus pack)

⑥ Screws
   (+BVTP 4 x 16)

— 35 —

3-5. BEZNET BLOCK REMOVAL

• **KP-ES43**

① Eleven screws
(+BVTP 4 x 16)

③ Mirror cover block

⑤ Beznet block

② Four screws
(Hexagon head)

④ Four screws
(Hexagon head)

• **KP-ES48/ES53/ES61**

① Ten screws (KP-ES48)
Eleven screws (KP-ES53)
Thirteen screws (KP-ES61)

⑤ Beznet block

③ Mirror cover
block

② Four screws (KP-ES48)
Six screws (KP-ES53/ES61)
(Hexagon head)

④ Four screws
(Hexagon head)

3-6. CHASSIS BLOCK REMOVAL
(1) MAIN BRACKET REMOVAL
• KP-ES43/ES48/ES53/ES61

① Two screws
  (Hexagon head)

③ Set the main
  bracket.

② Pull the main bracket, and
  remove each connectors
  on main bracket.

※ Pay particular attention to the wires of each Printed circuit
  boards when puling out the main bracket.

(2) CHASSIS BLOCK REMOVAL
• KP-ES43/ES48/ES53/ES61

① Four screws
  (Hexagon head)

② Pull out the
  chassis block.

① Two screws
  (Hexagon head)

※ Pull out the chassis block by gripping the handles as shown in
  the diagram.
  At this time, pay particular attention to the components
  removed in (1).

3-7. TERMINAL BOARD REMOVAL

③ RF cable

④ Terminal board

① Five screws
(+BVTP 3 x 12)

② Two screws
(+BVTP 4 x 16)

3-8. BD, DS, D BOARDS REMOVAL

① Screw
(+BVTP 3 x 12)

② BD holder

③ Claw

⑤ DS board

④ BD board

⑥ Screw
(+BVTP 3 x 12)

⑧ D board

⑥ Screw
(+BVTP 3 x 12)

⑦ Three claws

3-9. G, G1 BOARD REMOVAL

① Four claws

② G board
(KP-ES43HK1/SN1, ES48HK1/SN1,
ES53HK1/SN1, ES61HK1/SN1)
G1 Board
(KP-ES43ME1/MN1, ES48ME1/MN1,
ES53ME1/MN1, ES61ME1/MN1)

3-10. J1, B3, E, M1 BOARDS REMOVAL

⑦ Four screws
(+BVTP 3 x 12)

⑥ E board

⑤ Claw

④ M1 board

⑧ Shied case

③ Claw

⑩ B3 board

⑨ Claw

② J1 board

① Claw

3-11. A1 BOARD REMOVAL

① Screw
(+BVTP 3 x 12)

③ A1 board

② Two claws

3-12. HIGH-VOLTAGE
CABLE REMOVAL
AND INSTALLATION

(1) Removal

① Rubber cap

② HV cable
turn 90°

(2) Installation

② Rubber cap

① HV cable

Hook

Gutter

3-13. PICTURE TUBE REMOVAL

Removing the arrow-marked screw is strictly inhibited.
If removed, it may cause liquid spill

① Four screws
(+BVTP 4 x 16)

② Lens

⑥ Four screws
(+BVTP 4 x 16)

⑦ Picture
tube

⑤ Deflection
yoke

④ Neck
assembly

③ CR board

SECTION 4
SET-UP ADJUSTMENTS

4-1. SCREEN VOLTAGE ADJUSTMENT (ROUGH ALIGNMENT)

1. Receive the Monoscope signal.
2. Set 50% BRIGHTNESS and minimum PICTURE.
3. Turn the red VR on the focus pack all the way to the left and then gradually turn it to the right until the point where you can see the retrace line.
4. Next gradually turn it to the left to the position where the retrace line disappears.

Fig. 4-1

4-2. SCREEN (G2) ADJUSTMENT

1. Turn on the power of the set.
2. Select VIDEO1 mode without signals.
3. Supply DC 175 ±0.5 V from external power supply to TP7103 (KR), TP7203 (KG) or TP7303 (KB) of CR board, CG board and CB board.
3. Adjust red, green and blue screen voltage to until retrace line disappears with screen VR on the focus pack.

4-3. FOCUS ROUGH ADJUSTMENT

1. Loose the lens screw.
2. Set in the service mode. (Refer to SECTION 6.)
3. Place the caps on the red and blue lens so that only the green color is shown.
4. Press "①" or "④" button on the commander and select "PJE", press "⑥" three times on the Commander to display the test signal (crosshatch) on the screen.

Test signal

Fig. 4-2

5. Rotate the green lens and align to obtain the best lens focus at the center area.
6. Rotate the green focus VR on the focus pack and align to obtain the best electrical focus in the top right corner.
7. Perform the same alignment for red and blue lenses and electric focus.
8. Fix lens screw.

Scanning line visible.

Lens

Minimize both A and B.

Fig. 4-3   **Fig. 4-4**

4-4. DEFLECTION YOKE TILT ADJUSTMENT

1. Receive the Monoscope signal.
2. Place the caps on the red and blue lens so that only the green color.
3. Loosen the deflection yoke setscrew and align the tilt of the Deflection yoke so that the bars at the center of the monoscope pattern are horizontal.
4. After aligning the deflection yoke, fasten it securely to the funnel-shaped portion (neck) of the CRT.
5. The tilt of the deflection yoke for red and blue is aligned the same as was done for green.

4-pole magnet

2-pole magnet   Deflection yoke

Neck Assy   Anode cap

Make sure deflection yoke is touching CRT closely.

Fig. 4-5

4-5. 2-POLE MAGNET ADJUSTMENT

1. Receive the Dot signal.
2. Place the caps on the red and blue lens so that only the green color is shown.
3. Turn the green focus VR on the focus pack to the right and set to over focus to enlarge the spot.
4. Now align the 2-Pole Magnet so that the enlarged spot is in the center of the just focus spot.
   (center of the dot doesn't move)
5. Align the green focus VR and set for just (precise) focus.
6. Perform the same alignment for red and blue.

Use the center dot

Fig. 4-6

4-6. 4-POLE MAGNET ADJUSTMENT

1. Receive the Dot signal.
2. Place the caps on the red and blue lens so that only the green color is shown.
3. Turn the green focus VR on the focus pack to the left and set to under focus to enlarge the spot.
4. Now align the 4-Pole Magnet so that the enlarged spot becomes a perfect circle.
5. Perform the same alignment for red and blue.

Use the center dot

NG   OK   NG

Fig. 4-7

4-7. GREEN, RED AND BLUE FOCUS ADJUSTMENT

4-7-1. Green, Red and Blue Lens Focus Adjustment

1. Receive the Monoscope signal.
2. Place the caps on the red and blue lens so that only the green color is shown.
3. Rotate the green lens and adjust to obtain the best lens focus at the center area.
4. Fix lens screw.
5. Repeat above process for red and blue.

Adjust Point

Fig. 4-8

4-7-2. Green, Red and Blue Electrical Focus Adjustment

1. Receive the Monoscope signal.
2. Place the caps on the red and blue lens so that only the green color is shown.
3. Rotate the green focus VR on the focus pack and adjust to obtain the best electrical focus in the adjust point.
4. Repeat above process for red and blue.
5. Repeat adjustment items 4-3. FOCUS ROUGH ADJUSTMENT, 4-5. 2-POLE MAGNET ADJUSTMENT, 4-6. 4-POLE MAGNET ADJUSTMENT and 4-7. GREEN, RED AND BLUE FOCUS ADJUSTMENT, and adjust to obtain the best focus.

Adjust Point of Blue

Adjust Point of Green and Red

Fig. 4-9

SECTION 5
SAFETY RELATED ADJUSTMENT

When replacing the following components marked with ⚟ on the schematic diagram, always check hold-down voltage and if necessary re-adjust.

Part Replaced (⚟)
R9901

Part Replaced (⚟)	
D Board	C5117, C5123, C5127, C5143, D5115, D5204, Q5104, R5136, R5138, R5140, R9901, T5102, T5104, T5103 (FBT)
G Board	C6024, C6032, D6020

5-1. HV HOLD-DOWN ADJUSTMENT

1. Connect HV static voltmeter to HV Block.
2. Mount a resistor (R9901 : 43 kΩ, 1/4 W, METAL FILM) at CN5003.
3. Remove CN5002 and connect External Power Supply to CN5002 ① pin (+135 V) and ② pin (GND).
4. Turn on the set.

Fig. 5-1

Remove the cap off from the unused terminal and connect a HV static voltmeter there.

Fig. 5-2

D BOARD   – CONDUCTOR SIDE –

Fig. 5-3

CN5003

Fig. 5-4

5. Receive the Dot signal and set PICTURE/BRIGHTNESS to minimum.
6. Slowly up the supply voltage from 0 V to 135 V until hold-down circuit works (picture disappear).
7. Read the HV static voltmeter of peak HV voltage.
   Spec : 33.7 ~ 35.3 kV
8. If Hold-down voltage is less than 33.7 kV then replace R9901 of 43 kΩ with that of 39 kΩ, and check if the voltage is within the spec.
9. If hold-down voltage is over than 35.3 kV then replace R9901 of 43 kΩ with that of 47 kΩ, and check if the voltage is within the spec.

SECTION 6
ELECTRICAL ADJUSTMENTS

6-1. ADJUSTMENTS WITH COMMANDER

Service adjustment to this model can performed with the supplied remote commander RM-961

(open the cover)

MUTE
Write data to NVM

ON SCREEN DISPLAY
Copy PAL data to NTSC

PIP

TWIN

PROGR INDEX

TV STANDBY

DRC-MF (blue)

SWAP

Change the PICTUER MODE

Adjustment item up

Adjustment item down

User control goes to the standard state

Read data from NVM

VOLUME +

Copy data to all mode

Data up

Data down

Initialize data (Not stored)

MENU

JOYSTICK
Up : Category up
Down : Category down
Push : Enter

SONY
TV

RM-961

6-1-1. How to Select Each Mode

The adjustment requires the following modes:

	50 Hz (PAL)	60 Hz (NTSC)	WIDE 60 Hz (NTSC)
DRC1250	○	○	○
DRC100	○	○	✕
PIP	○	○	○
TWIN	○	○	✕
INDEX	○	○	✕

1. Selection of Mode Between 50 Hz and 60 Hz

50 Hz   : Enter the PAL signal.
60 Hz   : Enter the NTSC signal.
WIDE 60 Hz : Enter the NTSC signal with video input

2. Selection of DRC Mode

1) Press "DRC-MF (blue)" button on the commander, repeatedly until displays the mode that you want to select on the screen.

Note : The DRC-MF mode is not selectable when using the "PROGRAM INDEX" or "FAVORITE CH" feature, or when the "GAME MODE", "PIP", or "TWIN" mode is turned "ON".

3. Selection of WIDE mode

The WIDE mode is selected only when the DRC1250 of NTSC signal with video input mode is active.

1) Enter the NTSC signal with video input.
2) Press "DRC-MF (blue)" button on the commander to select "DRC1250".
3) Press "MENU" button on the commander and move "⊕" up or down to enter the "FEATURE" ➔ "WIDE MODE".
4) Move "⊕" up or down to select "ON" or "OFF", and push "⊕ (ENTER)" button.
5) Press "MENU" button to return to normal screen.

4. Selection of PIP mode

1) Open the remote control cover, press "(PIP)" button on the commander.
2) Press "(PIP)" button again to return to normal screen.

5. Selection of TWIN mode

1) Press "(TWIN)" button on the commander.
2) Press "(TWIN)" button again to return to normal screen.

6. Selection of INDEX mode

1) Press "PROGR INDEX" button on the commander.
2) Press "PROGR INDEX" button again to return to normal screen.

6-1-2. How to Enter Service Mode

1. Turn on the main power switch to place this set in standby mode. (LED will light in red.)
2. Press the buttons on the commander as follows, and enter service mode.

| i + | ➡ | ⑤ | ➡ | ◿ + | ➡ | I/⏻ | ➡ | Enter the "Service mode" |

(ON SCREEN DISPLAY)　(DIGIT 5)　(VOLUME +)　(TV STANDBY)

6-1-3. Method of Cancellation from Service Mode

1. Set the standby mode (Press "I/⏻ (TV STANDBY)" button on the commander), then press "I/⏻ (TV STANDBY)" button again, hereupon it becomes TV mode.

6-1-4. How to Adjustments

1. Set in the service mode, the following screen will appear.

Category Name　　Item Name　　Mode　　50 : PAL, SECAM
　　　　Item No.　　　Data　　　　　　60 : NTSC

```
GEO 00   VSZ  2B SERVICE 50
0 025Q  1.4M  00 FF    0001
```

Suffix No.　　　　Total Power On time (Hours)

Software Version

2. Press "①" or "④" button on the commander to select the adjustment item.
3. Press "③" or "⑥" button on the commander to change the adjustment data.
4. Move "⊕" up or down to select the adjustment category.

   When move "⊕" up (category up), service mode changes in the order as shown below.

GEO	JGL	MSP	2CM	OPM
DAC	YCT	LTI	DSP	OPB
WHB	SYC	MID	TXT	
SAJ	AP	3CM	PJE*	

* : When it moves from PJE to other categrys, repeat ① or ④ button and press it.

6-1-5. How to Write the Data

1. Set in the service mode.
2. Press "①" or "④" button on the commander, select the adjustment item, and press "③" or "⑥" button to change the data.
3. Press "⊠ (MUTE)" button on the commander and it will indicate "WRITE" on the screen.
4. Press "⓪" button on the commander to write into memory. (The "WRITE" display will be changed to red color while executing, and back to "SERVICE".)

Commander Function (Except PJE mode)

Button	Mode	Description
⊠ + ⓪	WRITE	Writes data to NVM.
⑦ + ⓪	READ	Reads data from NVM.
⑧ + ⓪	NORMAL	All user control goes to the standard.
⑤ + ⓪	INITIAL	Service data initialization. Not stored. (Be sure not to use usually)
② + ⓪	COPY	Copies and writes data of DRC1250 (50Hz) mode to all other modes.
⑮ + ⓪	WRT5060	Copies data of 50 Hz (PAL) mode to 60 Hz (NTSC) mode.

Note : Before changing to other modes, press "⊠ (MUTE)" + "⓪" buttons on the commander to write the data. (Omission of this operation causes the data to be returned to the data before adjustment.)

: Confirm the adjustment mode before writing data for data values because to vary in each adjustment mode.

: The adjustment item that there are no relations in the adjustment is not to change data values because all items are written in each adjustment mode.

6-1-6. Memory Write Confirmation Method

1. After adjustment, pull put the plug from AC outlet, and then plug into AC outlet again.
2. Turn the power switch ON and set in service mode.
3. Call the adjustment items again to confirm adjustments were made.

6-2. SERVICE LIST

Note

- Common : The data value of each mode commonness. Others are set up by each mode.
- [▨] : Shaded items are fixed data.
- [ ] : Though data value is indicated on the screen, it is not used.
- Standard data listed on the Adjustment Item Table are reference values, therefore it may be different for each model and for each mode.
- Note for Different Data :

  Those are the standard data values written on the microprocessor. Therefore, the data values of the modes and stored respectively in the memory.

  In case of a device replacement, adjustment by rewriting the data value is necessary for some items.

OPTION NOTE

Category : **OPM**

Item : **COM**   Comb Operation Selection   00 = automatic operation (depends on color system status)
01 = no comb operation
02 = forced 2D-comb operation
03 = forced 3D-comb operation

Item : **TSY**   TV System Selection for Auto TV System   00 = B/G,   01 = I,   10 = D/K,   11 = M

Item : **SSO**   Speed CH Search Selection   00 = normal,   01 = 4 times,   10 = 6 times,   11 = 8 times

Item : **TRP**   MPEG/JPEG Noise Reduction

Bit	bit7	bit6	bit5	bit4	bit3	bit2	bit1	bit0
Input	–	–	TV	Video 1	Video 2	Video 3	Video 4	DVD

Category : **OPB**

OP1	bit7	bit6	bit5	bit4	bit3	bit2	bit1	bit0
Item	TOP	NICAM	HDEV	(reserved)	–	DVD Input	AV Input	
Data	1	1	1	0	0	1	1	1

AV Input   00 = no AV Input   01 = 1 AV Input

10 = 3 AV Input   11 = 4 AV Input

OP2	bit7	bit6	bit5	bit4	bit3	bit2	bit1	bit0
Item	C-Text	Korean Stereo	Korean Mode	A-TVsys	US ST	SSV Mode	OSD Language	
Data	0	0	0	1	0	0	1	1

C-Text	Text Decoder Selection	0 = original,	1 = chinese
Korean Stereo*	Korean Stereo	0 = disabled,	1 = enabled
Video NTSC 3.58*	Video Color System	0 = Multi System,	1 = Single System
A-TVsys	Auto TV System in Auto Program	0 = disabled,	1 = enabled
US ST*	USA Stereo	0 = disabled,	1 = enabled
SSV Model	SSV-production Model	0 = original,	1 = disable PIP/TWIN/Digital
OSD Language	00 = English only,	01 = English & Chinese,	
	10 = English & Arabic/Korean*	11 = English, Chinese & Arabic/Korean*	

* : APPLICABLE FOR NTSC MODELS ONLY

V : WIDE (V-Compressed) mode

Category	No.	Name	Function	Data Range	DRC 1250	PIP	INDEX	TWIN	DRC 100	DRC 1250	DRC 1250 V	PIP	PIP V	INDEX	TWIN	DRC 100	ECO ON	ECO OFF	ECO ON V	ECO OFF V	Device Name
					50Hz (PAL)					60Hz (NTSC)							ECO Mode				
GEO	00	VSZ	V SIZE	00 ~ 3F	1F	1F	1F	1F	1F	1F	1F	1F	1F	1F	1F	1F					CXA2100AQ
	01	VPS	V POSITION	00 ~ 3F	23	23	1F	1F	23	1F	1F	1F	1F	1F	1F	1F					
	02	VLN	V LINEARITY	00 ~ 0F	07	07			07	07	07	07	07			07					
	03	SCO	S CORRECTION	00 ~ 0F	07	07			07	07	07	07	07			07					
	04	HSZ	H SIZE	00 ~ 3F	33	33	33	33	33	33	33	33	33	33	33	33					
	05	HPS	H POSITION	00 ~ 3F	37	37	37	37	37	37	37	37	37	37	37	37					
	06	DVH	H POSITION OFFSET FOR DVD	00 ~ 0F	09					07											
	07	PAP	PIN AMP	00 ~ 3F	22	22			22	22	22	22	22			22					
	08	UPN	UPPER CORNER PIN	00 ~ 3F	22	22	22	22	22	22	22	22	22	22	22	22					
	09	LPN	LOWER CORNER PIN	00 ~ 3F	22	22	22	22	22	22	22	22	22	22	22	22					
	0A	TRZ	TRAPEZIUM	00 ~ 0F	06	06	06	06	06	06	06	06	06	06	06	06					
	0B	AGL	AFC ANGLE	00 ~ 0F	07	07			07	07	07	07	07			07					
	0C	BOW	AFC BOW	00 ~ 0F	07	07			07	07	07	07	07			07					
	0D	LBL	LEFT H BLANKING	00 ~ 3F	34	34	34	34	34	34	34	34	34	34	34	34					
	0E	RBL	RIGHT H BLANKING	00 ~ 3F	1F	1F	1F	1F	1F	1F	1F	1F	1F	1F	1F	1F					
	0F	MPN	MIDDLE PIN DISTORTION COMPENSATION	00 ~ 03	00					00	00										
	10	UVL	UPPER V LINEARITY	00 ~ 0F	00					00											
	11	LVL	LOWER V LINEARITY	00 ~ 0F	00					00											
	12	HCP	HORIZONTAL HIGH VOLTAGE COMPENSATION	00 ~ 03	01					01	01										
	13	VCP	VERTICAL HIGH VOLTAGE COMPENSATION	00 ~ 03	00					00	00										
	14	VAS	V ASPECT	00 ~ 3F	2F	2F	2F	2F	2F	2F	2C	2F	2C	2F	2F	2F					
	15	VSC	V SCROLL	00 ~ 3F	1F	1F	1F	1F	1F	22	22	22	22	22	22	22					
	16	USC	UNDER-SCAN MODE ON/OFF	00, 01	00					00	01										
	17	VBW	V BLANKING WIDTH CONTROL	00 ~ 03	00	00			00	00	03	00	03			00					
	18	AT1	AKB REFERENCE TIMING	00 ~ 03	00	00			00	00	00	00	00			00					
	19	CPY	COPY THE GEO DATA TO ALL 50/60Hz NVM AREA	00, 01																	
DAC	00	HCT	H CENTER	00 ~ FF																	MB88141
	01	HLN	H LINEARITY	00 ~ 3F																	
	02	MDP	MIDDLE PIN	00 ~ 3F																	
	03	CCP	LOWER CORNER PIN	00 ~ 3F																	
	04	HTR	HORIZONTAL TRAPEZIUM	00 ~ 3F																	
	05	DF	DF ON/OFF SWITCH	00, 01																	
	06	DPH	DF PHASE	00 ~ 3F																	
	07	QPH	QP PHASE	00 ~ 3F																	
	08	QAC	QP AMPLITUDE	00 ~ 3F																	
	09	QDC	QP DC LEVEL	00 ~ 3F																	
	0A	QDV	QP V MODULATION	00 ~ 3F																	
	0B	QAV	QP AMPLITUDE MODULATION	00 ~ 3F																	
	0C	ABC	ABL D/A CONTROL	00 ~ FF													00	00	7E	7E	
	0D	CPY	COPY THE DAC DATA TO ALL 50/60Hz NVM AREA	00, 01							00										

KP-ES43HK1/ME1/MN1/SN1, ES48HK1/ME1/MN1/SN1, ES53HK1/ME1/MN1/SN1, ES61HK1/ME1/MN1/SN1   RM-961

Category	Item		Function	Data Range	Standerd Data	Device Name
	No.	Name			Common	
WHB	00	CBO	DC OFFSET CANCELLER FOR CB1	00 ~ 0F	0A	CXA2100AQ
	01	CRO	DC OFFSET CANCELLER FOR CR1	00 ~ 0F	0A	
	02	SBR	SUB BRIGHTNESS CONTROL	00 ~ 3F	25	
	03	RDR	R DRIVE	00 ~ 3F	29	
	04	GDR	G DRIVE	00 ~ 3F	29	
	05	BDR	B DRIVE	00 ~ 3F	29	
	06	RCT	R CUTOFF	00 ~ 3F	29	
	07	GCT	G CUTOFF	00 ~ 3F	1A	
	08	BCT	B CUTOFF	00 ~ 3F	29	
	09	SBO	SUB BRIGHTNESS OFFSET	00 ~ 3F	1F	
	0A	RDO	R DRIVE OFFSET	00 ~ 3F	1F	
	0B	GDO	G DRIVE OFFSET	00 ~ 3F	1F	
	0C	BDO	B DRIVE OFFSET	00 ~ 3F	1F	
	0D	RCO	R CUTOFF OFFSET	00 ~ 3F	1F	
	0E	GCO	G CUTOFF OFFSET	00 ~ 3F	1F	
	0F	BCO	B CUTOFF OFFSET	00 ~ 3F	1F	

Category	No.	Name	Function	Data Range	Common	50Hz (PAL) TV	50Hz (PAL) Video	50Hz (PAL) DVD	60Hz (NTSC) TV	60Hz (NTSC) Video	60Hz (NTSC) DVD	Twin	Index	Dynamic	Standard	Hi-Fine	Personal	ECO ON	ECO OFF	ECO ON V	ECO OFF V	Device Name
SAJ	00	PIC	PICTURE CONTROL	00 ~ 3F										3F	2C	1C						CXA2100AQ
	01	BRT	BRIGHTNESS CONTROL	00 ~ 3F										21	1F	1B						
	02	COL	COLOR CONTROL	00 ~ 3F										27	1F	1F						
	03	HUE	HUE CONTROL	00 ~ 3F										1F	1F	1F						
	04	SHP	SHARPNESS CONTROL	00 ~ 3F										22	1F	1D						
	05	VML	VM LEVEL	00 ~ 03										03	03	02	03					
	06	DYC	DYNAMIC COLOR ON/OFF	00, 01										01	01	00	01					
	07	CTM	COLOR TEMPERATURE FOR DYNAMIC COLOR	00, 01										00	00	00	00					
	08	CAX	COLOR MATRIX SPECIFICATION	00 ~ 03			02			00												
	09	GMA	GAMMA CORRECTION	00 ~ 03										03	03	03	03					
	0A	DCT	DC TRANSMISSION CONTROL	00 ~ 03										01	00	00	00					
	0B	DPL	AUTO PEDESTAL LEVEL CONTROL	00 ~ 03										02	01	00	01					
	0C	ABM	ABL MODE CONTROL	00 ~ 03										01	00	00	00					
	0D	ABT	ABL CURRENT DETECTION Vth CONTROL	00 ~ 03														02	00	02	00	
	0E	CLO	COLOR OFFSET	00 ~ 0F		07	07		0C	0C												
	0F	CLW	COLOR STEP WIDTH TO THE CHANGE OF S/N	00 ~ 07	01																	
	10	HUO	HUE OFFSET	00 ~ 0F		08	08		09	09												
	11	SHO	SHARPNESS OFFSET	00 ~ 1F		0F	0F	0F	0C	0F	0F											
	12	SHW	SHARPNESS STEP WIDTH TO THE CHANGE OF S/N	00 ~ 07	01																	
	13	PIO	PICTURE OFFSET FOR TWIN/INDEX	00 ~ 07								07	07									
	14	BRO	BRIGHTNESS OFFSET	00 ~ 0F														07	07	07	07	
JGL	00	PON	RGB AND AKB REFERENCE PULSE OUTPUT ON/OFF	00, 01	01																	CXA2100AQ
	01	RGB	RGB OUTPUT SELECTION	00 ~ 07	07																	
	02	AGG	AGING MODE SELECTION	00 ~ 03	00																	
	03	DPS	Y/C DELAY LINE PASS MODE SWITCH	00, 01	00																	
	04	BBT	RGB BOTTOM LIMITTER CONTROL	00 ~ 03	03																	
	05	LML	RGB AMPLITUDE LIMITTER CONTROL	00 ~ 03	00																	
	06	PAB	DC LEVEL FOR PEAK ABL	00 ~ 0F	0F																	
	07	SCO	SUB PICTURE CONTROL	00 ~ 0F	07																	
	08	LV2	RGB LEVEL FOR RGB2	00 ~ 0F	06																	
	09	SF0	SHARPNESS CIRCUIT F0	00, 01		01	01	01	01	01	01											
	0A	PRO	PRE/OVER-SHOOT RATIO CONTROL	00 ~ 03		00	03	03	03	03	03											
	0B	LTI	LUMINANCE TRANSIENT IMPROVEMENT	00 ~ 03										02	02	00	02					
	0C	CTI	CHROMINANCE TRANSIENT IMPROVEMENT	00 ~ 03										01	01	00	01					

Category	No.	Name	Function	Data Range	Common	2D Comb	3D Comb	S-Input	others	TV 50Hz (PAL)	TV 60Hz (NTSC)	Video 50Hz (PAL)	Video 60Hz (NTSC)	DVD 50Hz (PAL)	DVD 60Hz (NTSC)	Device Name
YCT	00	TNT	TINT ADJUSTMENT FOR NTSC	00 ~ 3F							24		1F			CXA2123Q
	01	PNG	PAL/NTSC GATE WIDTH	00, 01	01											
	02	PNI	PAL/NTSC SENSITIVITY SW	00, 01	00											
	03	SCL	SUB COLOR CONTROL	00 ~ 0F						07	07	07	07			
	04	SCT	SUB CONTRAST CONTROL	00 ~ 0F						08	07	08	07			
	05	SF0	SHARPNESS CENTER FREQUENCY CHANGING	00 ~ 03	02											
	06	SEQ	SHARPNESS EQUALIZER CHARACTERISTIC	00 ~ 03	03											
	07	SHG	SHARPNESS GAIN CONTROL	00 ~ 0F						05	06	05	06	05	05	
	08	YOL	Y-OUTPUT LEVEL CONTROL	00 ~ 3F	1F											
	09	BSP	BLACK STRETCH START POINT CHANGING	00 ~ 03	00											
	0A	COL	CB/CR OUTPUT LEVEL CONTROL	00 ~ 3F	1A											
	0B	DCR	DC RESTORATION RATIO ADJUSTMENT	00 ~ 03	00											
	0C	BF0	BPF/TQF F0 ADJUSTMENT	00 ~ 03	01											
	0D	BFQ	BPF/TQF Q ADJUSTMENT	00 ~ 03	02											
	0E	FSW	BPF/TQF SWITCH	00, 01	01											
	0F	SDT	SECAM DOUBLE TRAP SWITCH	00, 01	01											
	10	LPF	Y/CB/CR LPF SWITCH	00, 01	01											
	11	YDL	Y-DL TIME ADJUSTMENT	00 ~ 0F		06	05	05	03							
	12	CMT	CB/CR OUTPUT MUTE SWITCH	00, 01	00											
	13	BO1	CB OFFSET ADJUSTMENT (MAIN ROUTE)	00 ~ 0F	07											
	14	RO1	CR OFFSET ADJUSTMENT	00 ~ 0F	07											
	15	CDF	V COUNT DOWN FREQUENCY SWITCH	00 ~ 07	00											
	16	CDM	V COUNT DOWN JUDGE SWITCH	00 ~ 03	00											
	17	AFC	AFC SENSITIVITY SWITCH	00 ~ 03										00	00	
	18	MVM	MACROVISION MASK + AFC MASK	00, 01	00											
	19	SRY	SECAM R-Y BLACK ADJUSTMENT	00 ~ 0F	07											
	1A	SBY	SECAM B-Y BLACK ADJUSTMENT	00 ~ 0F	01											
	1B	BEL	SECAM BELL/HPF SWITCHING	00 ~ 03	02											
	1C	BLF	BELL F0 ADJUSTMENT	00, 01	00											
	1D	SVI	SECAM V-ID SWITCH	00, 01	00											
	1E	SGP	SECAM GATE POSITION ADJUSTMENT	00 ~ 03	00											
	1F	SID	SECAM SENSITIVITY SWITCH	00, 01	01											
	20	SIH	SECAM INHIBITION SWITCH	00, 01	00											
	21	STP	Y BLACK LEVEL SETUP FOR PAL PLUS	00, 01	00											
	22	HVC	H-VCO TEMPERATURE CHARACTER CANCELLING	00 ~ 03	02											
	23	3NR	3D NR OPERATION ON/OFF	00, 01	01											
	24	BW6	3D NR FOR 60Hz NON-BURST SIGNAL ON/OFF	00, 01	01											
	25	WSH	SHARPNESS GAIN STEP FOR NOISE REDUCTION	00 ~ 03	00											
	26	WCO	CB/CR OUTPUT LEVEL STEP FOR NOISE REDUCTION	00 ~ 03	00											

Category	Item No.	Item Name	Function	Data Range	Standerd Data Common	S-Input	Col Mode SECAM	Col Mode NTSC	Col Mode PAL	TV 50Hz (PAL)	TV 60Hz (NTSC)	Video 50Hz (PAL)	Video 60Hz (NTSC)	DVD	Device Name
SYC	00	TNT	TINT ADJUSTMENT FOR NTSC	00 ~ 3F						21	20				CXA2123Q
	01	PNG	PAL/NTSC GATE WIDTH	00, 01		01									
	02	PNI	PAL/NTSC SENSITIVITY SW	00, 01	00										
	03	SCL	SUB COLOR CONTROL	00 ~ 0F						06	06	07	07		
	04	SCT	SUB CONTRAST CONTROL	00 ~ 0F						08	07	08	07		
	05	SF0	SHARPNESS CENTER FREQUENCY CHANGING	00 ~ 03	02										
	06	SEQ	SHARPNESS EQUALIZER CHARACTERISTIC	00 ~ 03	03										
	07	SHG	SHARPNESS GAIN CONTROL	00 ~ 0F	07										
	08	YOL	Y-OUTPUT LEVEL CONTROL	00 ~ 3F	1F										
	09	BSP	BLACK STRETCH START POINT CHANGING	00 ~ 03	00										
	0A	COL	CB/CR OUTPUT LEVEL CONTROL	00 ~ 3F	1A										
	0B	DCR	DC RESTORATION RATIO ADJUSTMENT	00 ~ 03	00										
	0C	BF0	BPF/TQF F0 ADJUSTMENT	00 ~ 03	01										
	0D	BFQ	BPF/TQF Q ADJUSTMENT	00 ~ 03	02										
	0E	FSW	BPF/TQF SWITCH	00, 01	01										
	0F	SDT	SECAM DOUBLE TRAP SWITCH	00, 01	01										
	10	LPF	Y/CB/CR LPF SWITCH	00, 01	01										
	11	YDL	Y-DL TIME ADJUSTMENT	00 ~ 0F		05	03	02	03						
	12	NCM	1-H ADDITION SWITCH	00, 01	01										
	13	CMT	CB/CR OUTPUT MUTE SWITCH	00, 01	00										
	14	BO1	CB OFFSET ADJUSTMENT (MAIN ROUTE)	00 ~ 0F	07										
	15	RO1	CR OFFSET ADJUSTMENT	00 ~ 0F	07										
	16	CDF	V COUNT DOWN FREQUENCY SWITCH	00 ~ 07	00										
	17	CDM	V COUNT DOWN JUDGE SWITCH	00 ~ 03	00							00		00	
	18	AFC	AFC SENSITIVITY SWITCH	00 ~ 03											
	19	MVM	MACROVISION MASK + AFC MASK	00, 01	00										
	1A	SRY	SECAM R-Y BLACK ADJUSTMENT	00 ~ 0F	07										
	1B	SBY	SECAM B-Y BLACK ADJUSTMENT	00 ~ 0F	01										
	1C	BEL	SECAM BELL/HPF SWITCHING	00 ~ 03	02										
	1D	BLF	BELL F0 ADJUSTMENT	00, 01	00										
	1E	SVI	SECAM V-ID SWITCH	00, 01	00										
	1F	SGP	SECAM GATE POSITION ADJUSTMENT	00 ~ 03	00										
	20	SID	SECAM SENSITIVITY SWITCH	00, 01	01										
	21	SIH	SECAM INHIBITION SWITCH	00, 01	00										
	22	STP	Y BLACK LEVEL SETUP FOR PAL PLUS	00, 01	00										
	23	HVC	H-VCO TEMPERATURE CHARACTER CANCELLING	00 ~ 03	02										

Category	Item No.	Item Name	Function	Data Range	Standerd Data Common	Sur VDD	Sur VDP	Sur TRS	Sur SIM	Sur OFF	Dynamic	Drama	Soft	Device Name
AP	00	BAS	BASS CONTROL	00 ~ 0F							0B	0A	07	TDA7315
	01	TRE	TREBLE CONTROL	00 ~ 0F							0A	09	07	
	02	LDN	LOUDNESS ON/OFF	00, 01	01									

Sur : Surround mode
VDD : Virtual Dolby Digital
VDP : Virtual Dolby Prologic
TRS : Tru Surround
SIM : Simulated

Category	Item No.	Item Name	Function	Data Range	Standerd Data Common	Device Name
MSP	00	WST	W/G STEREO THRESHOLD	00 ~ FF	15	MSP3415D
	01	WBT	W/G BILINGUAL THRESHOLD	00 ~ FF	EA	
	02	WLL	W/G MONAURAL THRESHOLD	00 ~ FF	05	
	03	WAC	W/G AGREEMENT COUNT	00 ~ 0F	01	
	04	WDL	W/G SEARCH DELAY	00 ~ FF	30	
	05	NDL	NICAM SEARCH DELAY	00 ~ FF	20	
	06	SDL	STEREO STATUS READ DELAY	00 ~ FF	10	
	07	AGC	AGC SWITCH AUTO/CONSTANT	00, 01	01	
	08	REL	AGC GAIN AT CONSTANT MODE	00 ~ 3F	28	
	09	CRM	CARRIER MUTING ON/OFF	00, 01	00	
	0A	ACO	AUDIO CLOCK OUT ON/OFF	00, 01	01	
	0B	FP	FM PRESCALE FOR NON-M SYSTEM	00 ~ 7F	1B	
	0C	FPM	FM PRESCALE FOR M SYSTEM	00 ~ 7F	32	
	0D	FH	FM PRESCALE FOR HDEV	00 ~ 7F	2D	
	0E	FHM	FM PRESCALE FOR HDEV AND M	00 ~ 7F	65	
	0F	WGP	W/G PRESCALE	00 ~ 7F	2A	
	10	NIP	NICAM PRESCALE	00 ~ 7F	6D	
	11	ERR	AUTO FM SWITCH THRESHOLD	00 ~ FF	50	
	12	VOL	LOUD SPEAKER GAIN 0700h to 07FFh	00 ~ FF	6D	

Category	Item No.	Item Name	Function	Data Range	Common	Twin	TV	Video	Dynamic	Standard	Hi-Fine	Personal	Device Name
LTI	00	LDH	HISTOGRAM SEGMENT SELECTION	00, 01	01								TDA9178
	01	CFS	CONTOUR FILTER SELECTION	00, 01	01								
	02	WLB	LETTERBOX WINDOW SWITCH	00, 01	00								
	03	VDC	VIDEO DEPENDENT CORING	00, 01					01	01	01	01	
	04	DEM	DEMONSTRATION MODE	00, 01	00								
	05	CDP	LUMINANCE DELAY	00 ~ 07	04								
	06	OSP	OVERRULE SMART PEAKING	00, 01	00								
	07	WPO	WHITE POINT STRETCH OFF	00, 01	00								
	08	DSK	SKIN TONE SWITCH	00, 01					00	00	00	00	
	09	ASK	SKIN TONE ANGLE SELECTION	00, 01	00								
	0A	WSK	SKIN TONE WIDTH SELECTION	00, 01	00								
	0B	SSK	SKIN TONE SIZE SELECTION	00, 01	00								
	0C	DGR	GREEN ENHANCEMENT SWITCH	00, 01		00			∗	01	00	01	
	0D	DGT	THRESHOLD OF GREEN ENHANCEMENT SWITCH	00 ~ 07	07								
	0E	GGR	GREEN ENHANCEMENT GAIN	00, 01	00								
	0F	WGR	GREEN ENHANCEMENT WIDTH	00, 01	00								
	10	SGR	GREEN ENHANCEMENT SIZE	00, 01	00								
	11	DBL	BLUE STRETCH SWITCH	00, 01	00								
	12	GBL	BLUE STRETCH GAIN SELECTION	00, 01	00								
	13	SBL	BLUE STRETCH SIZE SELECTION	00, 01	00								
	14	CDS	COLOR DEPENDENT SHARPNESS	00, 01					01	01	01	01	
	15	CST	THRESHOLD OF COLOR DEPENDENT SHARPNESS	00 ~ 07	07								
	16	CTI	COLOR TRANSIENT IMPROVEMENT	00, 01					00	00	00	00	
	17	BON	BLACK OFFSET COMPENSATION	00, 01					00	00	00	00	
	18	BTD	ADAPTIVE BLACK STRETCH	00 ~ 3F					00	00	00	00	
	19	NLD	NON-LINEARITY AMPLIFIER	00 ~ 3F		00			13	13	05	13	
	1A	NLW	STEP WIDTH OF NON-LINEARITY AMPLIFIER	00 ~ 07	07								
	1B	VGD	VARIABLE GAMMA	00 ~ 3F		1F			15	15	1A	15	
	1C	VGW	STEP WIDTH OF VARIABLE GAMMA	00 ~ 07	00								
	1D	PKD	PEAKING AMPLITUDE	00 ~ 3F					32	32	1D	32	
	1E	PKW	STEP WIDTH OF PEAKING AMPLITUDE	00 ~ 0F	08								
	1F	SPD	STEEPNESS CORRECTION	00 ~ 3F					00	00	00	00	
	20	CRD	CORING LEVEL	00 ~ 3F					14	0D	05	14	
	21	CRW	STEP WIDTH OF CORING LEVEL	00 ~ 0F	09								
	22	CRO	CORING LEVEL OFFSET FOR VIDEO MODE	00 ~ 0F	05								
	23	LWD	LINE WIDTH CORRECTION	00 ~ 3F	1F								
	24	SNM	S/N MODE UNDER UNRELIABLE S/N CONDITION	00 ~ 07	00								
	25	SNC	S/N RATIO AVERAGE COUNTER	00 ~ 0F			03	03					
	26	FMC	FEATURE MODE MATCHING COUNTER	00 ~ 0F	02								

∗ Mark Data Value GE/HK/ME model: 01
AUS model: 00

Category	No.	Name	Function	Data Range	DRC1250	PIP	TWIN	INDEX	DRC100	DRC1250	PIP	TWIN	INDEX	DRC100	Device Name
					50 Hz (PAL)					60 Hz (NTSC)					
MID	00	HPH	HORIZONTAL ACTIVE DISPLAY AREA PHASE	00 ~ FF	3E	3E	7B	78	3E	49	49	6F	6C	49	MB94918
	01	VPH	VERTICAL ACTIVE DISPLAY AREA PHASE	00 ~ 3F	15	15	20	1A	0C	25	25	2E	2D	13	
	02	HSZ	HORIZONTAL ACTIVE DISPLAY AREA SIZE	00 ~ FF	7F	7F	7F	7F	7F	7F	7F	7F	7F	7F	
	03	VSZ	VERTICAL ACTIVE DISPLAY AREA SIZE	00 ~ FF	7F	7F	7F	7F	7F	7F	7F	7F	7F	7F	
	04	HPW	DISPLAY H-SYNC PULSE WIDTH	00 ~ 3F	3F	3F	3F	3F	3F	3F	3F	3F	3F	3F	
	05	VPW	DISPLAY V-SYNC PULSE WIDTH	00 ~ 07	03	03	03	03	03	03	03	03	03	03	
	06	YDL	DISPLAY OUTPUT Y/C DELAY CORRECTION	00 ~ 3F	00	00	00	00	00	00	00	00	00	00	
	07	MHP	MAIN PICTURE HORIZONTAL POSITION (SINGLE & PIP)	00 ~ FF	7F	7F			7F	7F	7F			7F	
	08	MVP	MAIN PICTURE VERTICAL POSITION (SINGLE & PIP)	00 ~ FF	7F	7F			7F	7F	7F			7F	
	09	MHS	MAIN PICTURE HORIZONTAL SIZE (SINGLE & PIP)	00 ~ FF	7F	7F			7F	7F	7F			7F	
	0A	MVS	MAIN PICTURE VERTICAL SIZE (SINGLE & PIP)	00 ~ FF	7F	7F			7F	7F	7F			7F	
	0B	PHP	PIP SUB PICTURE HORIZONTAL POSITION	00 ~ FF		6B					53				
	0C	PVP	PIP SUB PICTURE VERTICAL POSITION	00 ~ FF		5E					57				
	0D	PHS	PIP SUB PICTURE HORIZONTAL SIZE	00 ~ FF		7F					7F				
	0E	PVS	PIP SUB PICTURE VERTICAL SIZE	00 ~ FF		7F					7F				
	0F	PHO	PIP SUB PICTURE HORIZONTAL POSITION OFFSET	00 ~ FF		76					68				
	10	PVO	PIP SUB PICTURE VERTICAL POSITION OFFSET	00 ~ FF		6E					6B				
	11	TMP	TWIN MAIN PICTURE HORIZONTAL POSITION	00 ~ 03			01								
	12	TSP	TWIN SUB PICTURE HORIZONTAL POSITION	00 ~ FF			00								
	13	TVP	TWIN MAIN & SUB PICTURE VERTICAL POSITION	00 ~ FF											
	14	THS	TWIN MAIN & SUB PICTURE HORIZONTAL SIZE	00 ~ FF											
	15	TVS	TWIN MAIN & SUB PICTURE VERTICAL SIZE	00 ~ FF											
	16	THO	TWIN MAIN & SUB PICTURE HORIZONTAL POSITION OFFSET	00 ~ FF											
	17	TVO	TWIN MAIN & SUB PICTURE VERTICAL POSITION OFFSET	00 ~ FF											
	18	XHS	INDEX SUB PICTURE HORIZONTAL SIZE	00 ~ FF											
	19	XVS	INDEX SUB PICTURE VERTICAL SIZE	00 ~ FF											
	1A	XHG	INDEX HORIZONTAL GAP WIDTH BETWEEN PICTURES	00 ~ FF											
	1B	XVG	INDEX VERTICAL GAP WIDTH BETWEEN PICTURES	00 ~ FF											
	1C	XHP	INDEX 1st SUB PICTURE HORIZONTAL POSITION	00 ~ FF											
	1D	XVP	INDEX 1st SUB PICTURE VERTICAL POSITION	00 ~ FF											
	1E	DHP	DRC HORIZONTAL ACTIVE AREA POSITION	00 ~ FF	7F		7F		7F	7F		7F		7F	
	1F	DHS	DRC HORIZONTAL ACTIVE AREA PIXEL SIZE	00 ~ FF	7F		7F		7F	7F		7F		7F	
	20	DVP	DRC VERTICAL ACTIVE ARE LINE POSITION	00 ~ 3F	1A		3F		1A	1A		39		1A	
	21	DVS	DRC VERTICAL ACTIVE AREA LINE SIZE	00 ~ FF	7F		7F		7F	7F		7F		7F	
	22	VHP	VDO HORIZONTAL ACTIVE AREA POSITION	00 ~ FF			7F					7F			
	23	VHS	VDO HORIZONTAL ACTIVE AREA PIXEL SIZE	00 ~ FF			7F					7F			
	24	VEP	VDO VERTICAL ACTIVE AREA EVEN POSITION	00 ~ 3F			1E					1B			
	25	VVS	VDO VERTICAL ACTIVE AREA LINE SIZE	00 ~ FF			7F					7F			
	26	VOP	VDO VERTICAL ACTIVE AREA ODD POSITION	00 ~ 03			00					00			
	27	CLT	VDO CLAMP PULSE OUTPUT TIMING	00 ~ FF			7F					7F			
	28	CLW	VDO CLAMP PULSE WIDTH	00 ~ 07			04					04			
	29	VYD	VDO ANALOG INPUT Y/C DELAY CORRECTION	00 ~ 3F			00					00			
	2A	VCR	VDO CHROMA SIGNAL ORDER	00, 01			01					01			
	2B	VDI	VDO DIGITAL ANGLE INPUT SELECTION	00 ~ 03			01					01			

Category	Item No.	Item Name	Function	Data Range	Common	TV	Video	NR Mode 0	NR Mode 1	NR Mode 2	NR Mode 3	Dynamic	Standard	Hi-Fine	Parsonal	Device Name
3CM	00	FRZ	EXTERNAL MEMORY TEST BIT	00, 01	00											μPD64082
	01	NRM	NOISE REDUCTION OPERATION MODE	00 ~ 03	00											
	02	YCO	Y/C SINGLE OUTPUT SELECTION	00 ~ 0F	0D											
	03	SYC	SYSTEM CLOCK SELECTION	00 ~ 03	01											
	04	STD	STANDARD/NON-STANDARD OPERATION SELECTION	00 ~ 03	00											
	05	MSS	INTER-FRAME/INTER-LINE OPERATION SELECTION	00 ~ 03	00											
	06	KIL	KILLER/NON-KILLER OPERATION SELECTION	00 ~ 03	03											
	07	EAD	EXTERNAL Y-ADC SWITCH	00, 01	00											
	08	ECS	EXTERNAL C-SYNC INPUT SELECTION	00 ~ 03	01											
	09	CPP	ADC INPUT LEVEL & CLUMP PULSE WIDTH SELECTION	00 ~ 03	02											
	0A	PWR	ADC INPUT WIDTH SWITCH	00, 01	00											
	0B	HDP	HORIZONTAL PHASE ADJUSTMENT	00 ~ 07	05											
	0C	CDL	C-SIGNAL DELAY ADJUSTMENT	00 ~ 07	04											
	0D	DYC	DY DETECTION CORING LEVEL ADJUSTMENT	00 ~ 0F				02	02	02	04					
	0E	DYG	DY DETECTION GAIN ADJUSTMENT	00 ~ 0F				0A	0A	0A	0A					
	0F	DCC	DC DETECTION CORING LEVEL ADJUSTMENT	00 ~ 0F				05	03	03	05					
	10	DCG	DC DETECTION GAIN ADJUSTMENT	00 ~ 0F				05	0A	0A	05					
	11	YNR	YNR NON-LINEAR FILTER SETUP	00 ~ 0F	01											
	12	CNR	CNR NON-LINEAR FILTER SETUP	00 ~ 0F	01											
	13	WSC	NOISE DETECTION CORING ADJUSTMENT	00 ~ 03	01											
	14	VTH	HYSTERESIS SELECTION FOR H-SYNC NON-STANDARD	00 ~ 03		01	01									
	15	VTR	SENSITIVITY SELECTION FOR H-SYNC NON-STANDARD	00 ~ 03		01	01									
	16	LDR	SENSITIVITY SELECTION FOR FRAME-SYNC NON-STANDARD	00 ~ 03		02	01									
	17	VAP	GAIN ADJUSTMENT FOR VERTICAL SHAPE CORRECTION	00 ~ 07								03	02	00	02	
	18	VAI	VANISHING ADJUSTMENT FOR VERTICAL SHAPE CORRECTION	00 ~ 1F								0C	06	00	06	
	19	TST	TEST BIT	00, 01	00											
	1A	YPF	CENTER FREQUENCY SELECTION FOR Y-PEAKING BPF	00 ~ 03								03	03	03	03	
	1B	YPG	GAIN ADJUSTMENT FOR Y-PEAKING BPF	00 ~ 0F								08	08	08	08	
	1C	VSE	LINE COMB FILTER SETUP	00 ~ 0F	0A											
	1D	CCN	C-SIGNAL SPLIT FILTER SWITCH	00, 01	00											
	1E	COS	C-SIGNAL DELAY SWITCH AT NOISE REDUCTION	00, 01	00											
	1F	SDC	DC DETECTION SENSITIVITY SWITCH	00, 01	00											

Category	No.	Name	Function	Data Range	Common	TV	Video	NR Mode 0	NR Mode 1	NR Mode 2	NR Mode 3	Dynamic	Standard	Hi-Fine	Parsonal	Device Name
3CM	20	SDY	DY DETECTION LOWER-LEVEL SENSITIVITY SWITCH	00, 01	01											µPD64082
	21	D2G	D2 GAIN SELECTION	00 ~ 07	04											
	22	YHC	Y-SIGNAL HIGHER-LEVEL CORING SELECTION	00 ~ 03								00	00	00	00	
	23	YHG	Y-SIGNAL HIGHER-LEVEL GAIN SWITCH	00, 01								00	00	00	00	
	24	SHT	NON-STANDARD DETECTION & H/V COUNTER TEST BITS	00 ~ 0F	00											
	25	CLK	CLOCK TEST BITS	00 ~ 0F	08											
	26	PLL	PLL FILTER SETUP	00 ~ 0F	0D											
	27	KRF	KILLER DETECTION REFERENCE ADJUSTMENT	00 ~ 0F	03											
	28	HSL	H-SYNC SLICE LEVEL ADJUSTMENT	00 ~ 0F	0C											
	29	VSL	V-SYNC SLICE LEVEL ADJUSTMENT	00 ~ 0F	08											
	2A	BPS	INTERNAL BURST GATE START POSITION ADJUSTMENT	00 ~ 0F	04											
	2B	BPW	INTERNAL BURST GATE WIDTH ADJUSTMENT	00 ~ 0F	0A											
	2C	ADC	ADC CLOCK DELAY SELECTION	00 ~ 03	03											
	2D	APD	ADC POWER-DOWN SWITCH	00, 01	01											
	2E	NSD	NON-STANDARD DETECTION TEST BIT	00, 01	01											
	2F	SPD	MEMORY POWER-DOWN SWITCH	00 ~ 03	02											
	30	CNT	CNR TEST BIT	00, 01	00											
2CM	00	APA	2D COMB APACON ON/OFF	00, 01												CXA2069Q

Category	Item No.	Item Name	Function	Data Range	Standerd Data Common	Sur VDD	Sur VDP	Sur TRS	Sur SIM	Sur OFF	Dynamic	Drama	Soft	Device Name
DSP	00	DUL	DIR UNLOCK DETECTION MODE	00 ~ 03										
	01	DIM	DIGITAL INPUT MODE	00 ~ 03										
	02	TFM	TruSurround FRONT MINUS	00 ~ 7F										
	03	TFP	TruSurround FRONT PLUS	00 ~ 7F										
	04	TCE	TruSurround CENTER	00 ~ 7F										
	05	TS1	TruSurround SURROUND #1	00 ~ FF										
	06	TS2	TruSurround SURROUND #2	00 ~ 7F										
	07	TSP	TruSurround SURROUND PLUS	00 ~ 7F										
	08	TSM	TruSurround SURROUND MINUS	00 ~ 7F										
	09	LFE	LOW FREQUENCY EFFECT	00 ~ 7F										
	0A	BHL	BBE EFFECT 1 FOR BBE HIGH	00 ~ 7F										
	0B	BHH	BBE EFFECT 2 FOR BBE HIGH	00 ~ 7F										
	0C	BLL	BBE EFFECT 1 FOR BBE LOW	00 ~ 7F										
	0D	BLH	BBE EFFECT 2 FOR BBE LOW	00 ~ 7F										
	0E	DLR	DELAY SELECTION AT DSP RESET (100msec to 1500msec)	00 ~ 07										
	0F	BBE	BBE SELECTION	00 ~ 03										

Sur : Surround mode
VDD : Virtual Dolby Digital
VDP : Virtual Dolby Prologic
TRS : Tru Surround
SIM : Simulated

Category	Item No.	Item Name	Function	Data Range	Standard Data Common	50 Hz (PAL)	60 Hz (NTSC)	Device Name
TXT	00	TXH	TELETEXT HORIZONTAL POSITION	00 ~ FF	61			SAA5261
	01	TXV	TELETEXT VERTICAL POSITION	00 ~ 3F	0E			

Category : PJE   ▭ : Fixed data

Item Number	Adjustment Item	Data Range	Standard Data					Name/Description
			DRC1250 (PAL)	DRC100 (PAL)	DRC1250 (NTSC)	DRC100 (NTSC)	DRC1250 VC (NTSC)	
00	FDIS	00,01	00					SELECT REGI DATA DISPLAY OF FINE ADJ
01	OSDH	01 ~ 255	32	32	32	32	32	PJED SERVICE MENU H POSITION
02	OSDV	01 ~ 255	75	55	75	55	65	PJED SERVICE MENU V POSITION
03	FVST	00 ~ 255	54	33	54	33	54	LINE NUMBER OF FINE ADJUST START
04	V1ST	00 ~ 255	00	00	00	00	00	V1 START DATA
05	V1CU	00 ~ 255	25	50	29	58	29	V1 COUNT UP DATA
06	COHP	00 ~ 255	00	00	00	00	00	H-PHASE OF ROUGH ADJ
07	FIHP	00 ~ 255	203	203	203	203	203	H-PHASE OF FINE ADJ
08	TPHP	00 ~ 255	51	51	51	51	51	H-PHASE OF TEST PATTERN
09	DFHP	00 ~ 255	00	00	00	00	00	H-PHASE OF DYNAMIC FOCUS
10	DFHG	−128 ~ 127	−80	−80	−80	−80	−80	H-2 GAIN OF DYNAMIC FOCUS
11	DFVG	−128 ~ 127	−30	−30	−30	−30	−30	V-2 GAIN OF DYNAMIC FOCUS
12	PWM1	00 ~ 255	00					PWM1
13	PWM2	00 ~ 255	29					H-PHASE OF AUTO REGI TEST PATTERN
14	HBLD	00 ~ 255	00					H-PHASE OF RETURNED BLUE V LINE
15	HBLW	00 ~ 63	00					PULSE WIDTH OF RETURNED BLUE V LINE
16	BLKP	00 ~ 255	44					START BLANK PULSE
17	COGV	−128 ~ 127	(*1)					GREEN V CENT OFFSET DATA OF AUTO REGI
18	CORV	−128 ~ 127	(*1)					RED V CENT OFFSET DATA OF AUTO REGI
19	COBV	−128 ~ 127	(*1)					BLUE V CENT OFFSET DATA OF AUTO REGI
20	COGH	−128 ~ 127	(*1)					GREEN H CENT OFFSET DATA OF AUTO REGI
21	CORH	−128 ~ 127	(*1)					RED H CENT OFFSET DATA OF AUTO REGI
22	COBH	−128 ~ 127	(*1)					BULE H CENT OFFSET DATA OF AUTO REGI
23	SOGV	−128 ~ 127	(*1)					GREEN V SKEW OFFSET DATA OF AUTO REGI
24	SORV	−128 ~ 127	(*1)					RED V SKEW OFFSET DATA OF AUTO REGI
25	SOBV	−128 ~ 127	(*1)					BLUE V SKEW OFFSET DATA OF AUTO REGI
26	SOGH	−128 ~ 127	(*1)					GREEN H SKEW OFFSET DATA OF AUTO REGI
27	SORH	−128 ~ 127	(*1)					RED H SKEW OFFSET DATA OF AUTO REGI
28	SOBH	−128 ~ 127	(*1)					BLUE H SKEW OFFSET DATA OF AUTO REGI
29	ERR	FIXED	00					AUTO REGI ERROR CODE
30	ADTM	00 ~ 255	144					TIMING TO GET A/D DATA OF AUTO REGI
31 *2	VUP	01 ~ 255	03	03	01	01	01	AUTO REGI PATTERN UPPER V POSITION
32 *2	VMID	01 ~ 255	135	130	115	110	115	AUTO REGI PATTERN MIDDLE V POSITION
33 *2	VLOW	01 ~ 255	260	255	225	212	225	AUTO REGI PATTERN LOWER V POSITION
34 *2	HPR	01 ~ 510	03	03	01	01	03	AUTO REGI PATTERN H POSITION
35	SFTF	00,01	00					SHIFT ENABLE 00 : DISABLE 01 : ENABLE
36	SFTE	00,01	00					SHIFT FAST 00 : NORMAL 01 : QUICK
37	ACTL	00 ~ 255	00					LOWER BYTE OF COUNTER VALUE
38	ACTH	00 ~ 255	00					HIGHER BYTE OF COUNTER VALUE
GRN	CENT	−512 ~ 511	000/000					GREEN H/V CENT (H CENT *3)
	SKEW	−512 ~ 511	000/000					GREEN H/V SKEW (H SKEW *3)
	SIZE	−512 ~ 511	000/−200					GREEN H/V SIZE (H/V SIZE *3)
	LIN	−512 ~ 511	xxxx/xxxx					GREEN H/V LIN
	KEY	−512 ~ 511	xxxx/xxxx					GREEN H/V KEY
	PIN	−512 ~ 511	xxxx/270					GREEN H/V PIN
BLU	CENT	−512 ~ 511	000/000					BLUE H/V CENT
	SKEW	−512 ~ 511	000/000					BLUE H/V SKEW
	SIZE	−512 ~ 511	000/−200					BLUE H/V SIZE
	LIN	−512 ~ 511	−150/xxxx					BLUE H/V LIN
	KEY	−512 ~ 511	xxxx/−70					BLUE H/V KEY
	PIN	−512 ~ 511	xxxx/270					BLUE H/V PIN
RED	CENT	−512 ~ 511	000/000					RED H/V CENT
	SKEW	−512 ~ 511	000/000					RED H/V SKEW
	SIZE	−512 ~ 511	000/−200					RED H/V SIZE
	LIN	−512 ~ 511	150/xxxx					RED H/V LIN
	KEY	−512 ~ 511	xxxx/−70					RED H/V KEY
	PIN	−512 ~ 511	xxxx/270					RED H/V PIN

VC : WIDE (V-Compressed) MODE
*1 : Set correctly by the automatic registration adjustment.
*2 : It can be adjust if automatic registration adjustment doesn't work.
*3 : It can be adjust Green a little.
xxxx : Cannot change.

Category	Item No.	Item Name	Function	Data Range	Standard Data Common	Standard Data 50 Hz (PAL)	Standard Data 60 Hz (NTSC)	Device Name
OPM	00	OSH	OSD H POSITION	00~3F	0F			CXP750096
	01	FW1	OSD ODD/EVEN FIELD WINDOW SETUP #1	00~3F	00			OPTION-MISC
	02	FW2	OSD ODD/EVEN FIELD WINDOW SETUP #2	00~3F	03			
	03	OHO	OSD H POSITION OFFSET FOR INDEX	00~0F	07			
	04	IL1	INDEX SUB-SCREEN OSD 1st LINE VERTICAL POSITION	00~3F		22	20	
	05	IVO	INDEX SUB-SCREEN OSD VERTICAL OFFSET	00~3F		2B	20	
	06	COM	COMB OPERATION SELECTION	00~03	00			
	07	APC	APC SWITCH	00,01	01			
	08	TSY	TV SYSTEM SELECTION UNDER SEARCHING WITH AUTO TV SYSTEM	00~03	00			
	09	MUT	NO SIGNAL MUTE	00,01	00			
	0A	AFM	AUTO FM SWITCH	00,01	01			
	0B	TVO	V-ANGLE CORRECTION TO PICTURE ROTATION	00~07	03			
	0C	DBL	DISABLE BLUEBACK FUNCTION	00,01	01			
	0D	SSO	SPEED CH SEARCH SELECTION	00~03	01			
	0E	TRP	MPEG/JPEG NOISE REDUCTION FOR EACH INPUT	00~3F	00			
	0F	SCH	CH SELECTION FOR SHIPPING CONDITION	00~7F				
	10	SCA	CABLE/AIR SELECTION FOR SHIPPING CONDITION	00,01	00			
	11	DMG	DISABLE MENU-OPERATION GUIDE	00,01	00			
	12	VSN	ENABLE NOISE REDUCTION IN VIDEO MODE	00,01	00			
OPB	00	OP1	OPTIONAL BITS 1 (SEE THE SPECIFIED SHEET)	00~FF	E7			OPTION-BITS
	01	OP2	OPTIONAL BITS 2 (SEE THE SPECIFIED SHEET)	00~FF	13			

6-3. Picture Quality Adjustment

6-3-1. Preparation

1. Set in the service mode.
2. Set respective items as follows.

Adjustment Condition

DRC-MF   : DRC1250
PICTURE MODE : HI-FINE
TWIN MODE   : ON
ECO MODE   : OFF
WIDE MODE   : OFF

Category	Item		Data
SAJ	00	PIC	3F
	06	DYC	00
	0E	CLO	06
	10	HUO	07
	13	PIO	00
JGL	04	BBT	00
	05	LML	03

3. Connect the oscilloscope probe to the following point on the E board.

Measurement Point

E Board CN4500 :
   ① pin R100 → VR
   ⑤ pin B100 → VB

Note : After the adjustment 6-3. Picture Quality Adjustment, these adjustment parameters must be recovered to the original condition.

Original Condition

DRC-MF   : DRC1250
PICTURE MODE : HI-FINE
TWIN MODE   : ON
ECO MODE   : OFF
WIDE MODE   : OFF

Category	Item		Data			
			50 TV	50 VIDEO	60 TV	60 VIDEO
SAJ	00	PIC	1F			
	06	DYC	00			
	0E	CLO	0C	0C	0C	0C
	10	HUO	08	08	09	09
	13	PIO	07			
JGL	04	BBT	03			
	05	LML	00			

6-3-2. NTSC Video Input

1. Enter the NTSC video color bar (White & color 75%) signal.
2. Enter the service mode, and set respective items as follows.
3. Measure waveform, and each item is adjusted to become the following figure.
4. Press "↩ (SWAP)" button on the commander, when the left screen and the right screen are changed.
5. After adjustment finished, press "◁ (MUTE)" + "◎" button to write the data to the NVM.

(i) SUB CONTRAST

Condition :

Category	Item		Data
SAJ	00	PIC	3F
	02	COL	00
	13	PIO	00
JGL	01	RGB	04

Adjusting Parameter :
  LEFT screen   : YCT   08 YOL
  RIGHT screen : SYC   08 YOL

VR1 − VR2 = 1.85 ± 0.07 Vp-p

(ii) SUB HUE/SUB COL

Condition :

Category	Item		Data
SAJ	02	COL	1F
	10	HUO	07
JGL	01	RGB	07

Adjusting Parameter :
  LEFT screen   : YCT   0A COL
                                 00 TNT
  RIGHT screen : SYC   0A COL
                                 00 TNT

VB1 = VB4 ± 70 mV
VB2 = VB3 ± 70 mV

6-3-3. NTSC RF Input

1. Enter the NTSC RF color bar (White & color 75%) signal.
2. Adjust with the same manner as 6-3-2. NTSC Video Input.

(i) SUB CONTRAST

Condition :

Category	Item		Data
SAJ	00	PIC	3F
	02	COL	00
JGL	01	RGB	04

Adjusting Parameter :

    LEFT screen   : YCT   04 SCT
    RIGHT screen : SYC   04 SCT

$$VR1 - VR2 = 1.85 \pm 0.07 \text{ Vp-p}$$

(ii) SUB HUE/SUB COL

Condition :

Category	Item		Data
SAJ	02	COL	1F
	10	HUO	07
JGL	01	RGB	07

Adjusting Parameter :

    LEFT screen   : YCT   03 SCL
                            00 TNT
    RIGHT screen : SYC   03 SCL
                            00 TNT

VB1 = VB4 ± 70 mV
VB2 = VB3 ± 70 mV

6-3-4. PAL Video Input

1. Enter the PAL video color bar (White & color 75%) signal.
2. Adjust with the same manner as 6-3-2. NTSC Video Input.

(i) SUB CONTRAST

Condition :

Category	Item		Data
SAJ	00	PIC	3F
	02	COL	00
JGL	01	RGB	04

Adjusting Parameter :

    LEFT screen   : YCT   04 SCT
    RIGHT screen : SYC   00 SCT

$$VR1 - VR2 = 1.85 \pm 0.07 \text{ Vp-p}$$

(ii) SUB HUE/SUB COL

Condition :

Category	Item		Data
SAJ	02	COL	1
JGL	01	RGB	07

Adjusting Parameter :

    LEFT screen   : YCT   03 SCL
    RIGHT screen : SYC   03 SCL

VB1 = VB3 = VB4 ± 70 mV
VB2 = VB3 ± 70 mV

6-3-5. PAL RF Input

1. Enter the PAL RF color bar (White & color 75%) signal.
2. Adjust with the same manner as 6-3-2. NTSC Video Input.

(i) SUB CONTRAST

Condition :

Category	Item		Data
SAJ	00	PIC	3F
	02	COL	00
JGL	01	RGB	04

Adjusting Parameter :

    LEFT screen   : YCT   04 SCT

    RIGHT screen : SYC   04 SCT

$$VR1 - VR2 = 1.85 \pm 0.07\ Vp\text{-}p$$

(ii) SUB HUE/SUB COL

Condition :

Category	Item		Data
SAJ	02	COL	1F
JGL	01	RGB	07

Adjusting Parameter :

    LEFT screen   : YCT   03 SCL

    RIGHT screen : SYC   03 SCL

$$VB1 = VB3 = VB4 \pm 70\ mV$$
$$VB2 = VB3 \pm 70\ mV$$

6-4. Color Offset (53, 61 inch model only)

6-4-1. 50 Hz (PAL) TV Mode

1) Enter the PAL RF signal.
2) Enter the service mode, and write the following data to the NVM.

Category	Item		Data	
			53 inch	61 inch
SAJ	0E	CLO	0A	0B

6-4-2. 50 Hz (PAL) Video Mode

1) Enter the PAL video signal.
2) Enter the service mode, and write the following data to the NVM.

Category	Item		Data	
			53 inch	61 inch
SAJ	0E	CLO	09	0A

6-4-3. 60 Hz (NTSC) TV Mode

1) Enter the NTSC RF signal.
2) Enter the service mode, and write the following data to the NVM.

Category	Item		Data	
			53 inch	61 inch
SAJ	0E	CLO	0A	0B

6-4-4. 60 Hz (NTSC) Video Mode

1) Enter the NTSC video signal.
2) Enter the service mode, and write the following data to the NVM.

Category	Item		Data	
			53 inch	61 inch
SAJ	0E	CLO	0A	0B

6-5. REGISTRATION ADJUSTMENT

It is adjusted by REGISTRATION ADJUSTMENT respectively in the following 5 modes.
- DRC1250 (50 Hz) mode
- DRC100 (50 Hz) mode
- DRC1250 (60 Hz) mode
- DRC100 (60 Hz) mode
- DRC1250 (60 Hz) WIDE mode

6-5-1. Setup for Adjustment
1. Marking

1) At the 4 insides of the screen, locate the middle. Use a tape measure to identify the middle.

× : midlle

2. Data Setting

1) Set in the DRC1250 (50 Hz) mode.
2) Set in the Service mode, and select the category "PJE".
3) Press "⑦" + "⓪" button on the commander to read the data from NVM. Then all the default data are restored.
4) Change it to other 4 modes, and set the data with the respectively same process.

Note : When you replaced printed circuit boards or devices or CRTs, and when correction is drastically necessary, press "⑤" +"⓪" (PJE INITIAL) button to initialize the data in the PJE mode.
Press "◁× (MUTE)" + "⓪" buttons on the commander to write the data.
: Be sure to set up the data in the PJE mode. All data initialize it when this operation is done by other categories.

6-5-2. Method of Main Deflection Adjustment

1. Place the caps on the red and blue lenses so that only the green color is displayed.
2. Enter the signal.
3. Set in the Service mode, and select the category "GEO".
4. Adjust "01 VPS" and "05 HPS" so that the picture is displayed in the center of screen.

01 VPS

05 HPS

5. Adjust "00 VSZ" and "04 HSZ" so that the picture size is within the specification.

00 VSZ

04 HSZ

6. Adjust the following items so as to attain the optimum picture.

02 VLN

03 SCO

07 PAP

08 UPN

09 LPN

0A TRZ

6-5-3. Operation Method for Projector Engine (PJE) Mode

MUTE 🕸
Write data to NVM

Copy data to all mode

Adjustment item up

Adjustment item down

Read data from NVM

ON SCREEN DISPLAY ⊞
Copy PAL data to NTSC

Color change

Internal test signal

Initialize data (Not stored)

Mode select (Fine or Rough)

JOYSTICK ⊕
Up : Data up (V)
Left : Data up (H)
Down : Data down (V)
Right : Data down (H)
Push : Enter

RM-961

1. Functions of Keys on Commander

- ①   : Changes adjustment item. (item No. moves up)
          : Marker moves clockwise from center to outside. (in fine adjustment mode)
- ④   : Changes adjustment item. (item No. moves down)
          : Marker moves counterclockwise from outside to center. (in fine adjustment mode)
- ⊕   : Changes data value. (up, down, or to the left or right)
- (move) : Marker moves up, down, or to the left or right. (in fine adjustment mode)
- ③   : Changes adjustment color. (except item No. 00~38) GRN → BLU → RED
- ⑥   : Displays or changes internal test signals.
          : crosshatch + external signal → dot + external signal → crosshatch only → dot only → off
- ⑨   : Switches adjustment mode. rough adjustment mode → fine adjustment mode
- ⊕   : Switches marker moving method.
- (push)   (in fine adjustment mode)

Commander Function (PJE mode)

Button	Mode	Description
🕸 + ⓪	WRITE	Writes data to NVM.
⑦ + ⓪	READ	Reads data from NVM.
⑤ + ⓪	*PJE INITIAL	Service data initialization. Not stored. (Be sure not to use usually)
② + ⓪	*PJE COPY	Copies and writes data of DRC1250 (50Hz) mode to all other modes.
⊞ + ⓪	*PJE WRT5060	Copies data of 50 Hz (PAL) mode to 60 Hz (NTSC) mode.

* : only data in the PJE mode.

joystick key → ① and ④ buttons

2. Operation Method for Rough Adjustment

1) Set in the Service mode, and select the category "PJE".
2) Press "①" or "④" button on the commander to select the item, and move "⊕" up, down, or to the left or right to

Item No.   Data

| PJE | 00 | 00 |
| FDIS | | |

Adjustment Item

change the data.
3) Select item "GRN CENT". When BLU or RED is displayed, press "③" button on the commander to change the adjustment color in the order of GRN → BLU → RED.
4) In the GRN, BLU, or RED mode, move "⊕" up or down to change the data in vertical direction, or move "⊕" to the

Color   Data (H)   Data (V)

| GRN CENT | 000 | 000 |

Adjustment Item

left or right to change the data in horizontal direction.
5) When it moves from PJE to other categories, repeat "①" or "④" button and press it.

– 64 –

3. Operation Method for Fine Adjustment (in GRN, BLU, or RED Mode)

1) Set in the Service mode, and select the category "PJE".
2) Select item "FDIS" so that the data at each position can be displayed in the fine adjustment mode, and set the data to "01".
3) Press "⑨" button on the commander, and the fine adjustment mode will be active where a green marker appears in the center of screen (in the case of GRN mode).
4) Push "⊕ (ENTER)" button, and the marker color will be switched between green (GRN mode) and white alternately.
5) Use "①" or "④" button on the commander, or the joystick to move the marker to the position to be adjusted, where fine adjustment can be made.

• When marker color is white.
  (in this case, fine adjustment is disabled)

Operating the joystick can move the marker
up, down, or to the left or right freely.

• When marker color is green. (GRN mode)

① : moves the marker clockwise from center to outside.
④ : moves the marker counterclockwise from outside to center.

• Fine adjustment can be made on the basis of marker position using joystick key.

Movement when joystick key is moved up.

Movement when joystic key is moved to the right.

CROSSHATCH   CROSSHATCH

6) Press "⑨" button on the commander to return to the rough adjustment mode.

6-5-4. Method of Projector Engine Adjustment (Sub Deflection Adjustment)

Adjustment   ○ : Yes   − : No

Adjustment Item	Adjustment Type		
	GRN	RED	BLU
	H / V	H / V	H / V
CENT	○ / ○	○ / ○	○ / ○
SKEW	○ / ○	○ / ○	○ / ○
SIZE	○ / ○	○ / ○	○ / ○
LIN	− / −	○ / −	○ / −
KEY	− / −	− / ○	− / ○
PIN	− / ○	− / ○	− / ○

1. Green Adjustment

1) Place the caps on the red and blue lenses so that only the green color is displayed.
2) Enter the signal.
3) Set in the Service mode, and select the category "PJE".
4) Press "⑥" button on the commander to display internal test signal (crosshatch).
5) Select "GRN CENT", and adjust so that the picture coincide in the center of screen.

• GRN CENT (horizontally/vertically)

Move the joystick to the right.

Move the joystick to the left.

Move the joystick up.

Move the joystick down.

6) Select "GRN SKEW", and correct the tilt of horizontal lines and vertical lines.

• GRN SKEW (horizontally/vertically)

Move the joystick to the right.

Move the joystick to the left.

Move the joystick up.

Move the joystick down.

7) Select "GRN SIZE", and adjust so that each distance from center to left end and to right end is equal. Adjust so that each distance from center to top and to bottom is equal.

• GRN SIZE (horizontally/vertically)

Move the joystick to the right.

Move the joystick to the left.

Move the joystick up.

Move the joystick down.

8) Select "GRN PIN", and adjust so that upper and lower horizontal lines on the screen become straight.

• GRN PIN (vertically)

Move the joystick up.

Move the joystick down.

9) Press "⑨" button on the commander to enter the fine adjustment mode.

10) Make fine adjustment so that horizontal lines and vertical lines become straight.

11) Press "⑨" button on the commander to return to the rough adjustment mode.

2. Blue Adjustment

1) Place a cap on the red lens so that green and blue colors are displayed.

2) Press "③" button on the commander to select BLU mode.

3) Adjust the following items so that blue lines overlap with green lines.

• BLU CENT (horizontally/vertically)
• BLU SKEW (horizontally/vertically)
• BLU SIZE (horizontally/vertically)
• BLU LIN (horizontally)
Adjust so that each space at the right end and at the left end of screen is equal.

Move the joystick to the right.

Move the joystick to the left.

• BLU KEY (vertically)
Adjust so that upper and lower horizontal lines on the screen become parallel.

Move the joystick up.

Move the joystick down.

• BLU PIN (vertically)

4) Press "⑨" button on the commander to enter the fine adjustment mode.

5) Make fine adjustment so that horizontal lines and vertical lines overlap with green lines.

6) Press "⑨" button on the commander to return to the rough adjustment mode.

3. Red Adjustment

1) Place a cap on the blue lens so that green and red colors are displayed.

2) Press "③" button on the commander to select RED mode.

3) Hereinafter, use same manner as that of blue adjustment to adjust so that the red lines overlap with green lines.

6-5-5. Deflection Adjustment
1. DRC1250 50 Hz (PAL) Mode

1) Enter the PAL SPCB signal, and set the DRC1250.
2) Set in the service mode, and write the following data to NVM.

Condition :

Category	Item		Data
GEO	0B	AGL	07
	0C	BOW	07
	15	VSC	1F
MID	00	HPH	3E
	01	VPH	15

3) Adjust the main deflection. (Refer to 6-5-2.)

SPEC   Overscan Spec. = 7.5%

Input Signal	H SIZE	V SIZE
PAL SPCB	16.6 ± 0.1 sq.	12.5 ± 0.1 sq.

4) After the Main Deflection Adjustment finished, press "⊠ (MUTE)"+"⓪" buttons on the commander to write the data to the NVM.
5) Select the category "GEO" and the item "19 CPY", and set the data to "01".
   Press "⊠ (MUTE)"+"⓪" buttons to copy GEO data to other 50 Hz modes

6) Adjust the sub deflection (Projector Engine Adjustment). (Refer to 6-5-3.)
7) After the Projector Engine Adjustment finished, press "⊠ (MUTE)"+"⓪" buttons on the commander to write the data to the NVM.
8) Press "②"+"⓪" buttons to copy PJE data to all other modes in the PJE mode.

2. DRC100 50 Hz (PAL) Mode

1) Enter the PAL SPCB signal, and set the DRC100.
2) Set in the service mode, and write the following data to NVM.

Condition :

Category	Item		Data
GEO	0B	AGL	07
	0C	BOW	07
	15	VSC	1F
MID	00	HPH	3E
	01	VPH	0C

3) Adjust the main deflection. (Refer to 6-5-2.)

SPEC   Overscan Spec. = 7.5%

Input Signal	H SIZE	V SIZE
PAL SPCB	16.6 ± 0.1 sq.	12.5 ± 0.1 sq.

4) After the Main Deflection Adjustment finished, press "⊠ (MUTE)"+"⓪" buttons on the commander to write the data to the NVM.
5) Adjust the sub deflection (Projector Engine Adjustment). (Refer to 6-5-3.)
6) After the Projector Engine Adjustment finished, press "⊠ (MUTE)"+"⓪" buttons on the commander to write the data to the NVM.

3. PIP 50 Hz (PAL) Mode

1) Enter the PAL SPCB signal, and set in the service mode.

2) Open the remote control cover, press "⬚ (PIP)" button on the commander to set the PIP mode.

3) Confirm and set the following data.

Condition :

Category	Item		Data
GEO	00	VSZ	
	01	VPS	
	02	VLN	
	03	SCO	
	04	HSZ	Same as DRC1250 50 Hz (PAL) mode
	05	HPS	
	07	PAP	
	08	UPN	
	09	LPN	
	0A	TRZ	
	0B	AGL	07
	0C	BOW	07
	15	VSC	1F
MID	00	HPH	3E
	01	VPH	15

4) Press "⧠ (MUTE)"+"⓪" buttons on the commander to write the data to the NVM.

4. TWIN 50 Hz (PAL) Mode

1) Enter the PAL SPCB signal, and set in the service mode.

2) Press "❙ (TWIN)" button on the commander to set the TWIN mode.

3) Confirm and set the following data.

Condition :

Category	Item		Data
GEO	00	VSZ	
	01	VPS	
	02	VLN	
	03	SCO	
	04	HSZ	Same as DRC1250 50 Hz (PAL) mode
	05	HPS	
	07	PAP	
	08	UPN	
	09	LPN	
	0A	TRZ	
	0B	AGL	07
	0C	BOW	07
	15	VSC	1F
MID	00	HPH	7B
	01	VPH	20
	11	TMP	01
	12	TSP	00

4) Select the category "GEO" and the item "05 HPS", and adjust the horizontal position.

H1 – H2 = ± 0.1 sq.

5) Press "⧠ (MUTE)"+"⓪" buttons on the commander to write the data to the NVM.

– 68 –

5. INDEX 50 Hz (PAL) Mode

1) Enter the PAL SPCB signal, and set in the service mode.

2) Press "PROGR INDEX" button on the commander to set the INDEX mode.

3) Confirm and set the following data.

Condition :

Category	Item		Data
GEO	00	VSZ	
	01	VPS	
	02	VLN	
	03	SCO	
	04	HSZ	Same as DRC1250 50 Hz (PAL) mode
	05	HPS	
	07	PAP	
	08	UPN	
	09	LPN	
	0A	TRZ	
	0B	AGL	07
	0C	BOW	07
	15	VSC	1F
MID	00	HPH	78
	01	VPH	1A

4) Select the category "GEO" and the item "05 HPS" to adjust the horizontal position, and select the item "01 VPS" to adjust the vertical position.

H1   V1 – V2 = ± 0.1 sq.   H2
       H1 – H2 = ± 0.1 sq.

5) Press "⊠ (MUTE)"+"◎" buttons on the commander to write the data to the NVM.

6. DRC1250 60 Hz (NTSC) Mode

1) Enter the NTSC monoscope signal, and set the DRC1250.

2) Set in the service mode, and write the following data to NVM.

Condition :

Category	Item		Data
GEO	0B	AGL	07
	0C	BOW	07
	15	VSC	22
MID	00	HPH	49
	01	VPH	25

3) Adjust the main deflection. (Refer to 6-5-2.)

SPEC   Overscan Spec. = 7.5%

Input Signal	H SIZE	V SIZE
NTSC monoscope	15.7 ± 0.1 sq.	11.8 ± 0.1 sq.

4) After the Main Deflection Adjustment finished, press "⊠ (MUTE)"+"◎" buttons on the commander to write the data to the NVM.

5) Select the category "GEO" and the item "19 CPY", and set the data to "01".
Press "⊠ (MUTE)"+"◎" buttons to copy GEO data to other 60 Hz modes

6) Adjust the sub deflection (Projector Engine Adjustment). (Refer to 6-5-3.)

7) After the Projector Engine Adjustment finished, press "⊠ (MUTE)"+"◎" buttons on the commander to write the data to the NVM.

7. DRC100 60 Hz (NTSC) Mode

1) Enter the NTSC monoscope signal, and set the DRC100.
2) Set in the service mode, and write the following data to NVM.

Condition :

Category	Item		Data
GEO	0B	AGL	07
	0C	BOW	07
	15	VSC	22
MID	00	HPH	49
	01	VPH	13

3) Adjust the main deflection. (Refer to 6-5-2.)

SPEC   Overscan Spec. = 7.5%

Input Signal	H SIZE	V SIZE
NTSC monoscope	15.7 ± 0.1 sq.	11.8 ± 0.1 sq.

4) After the Main Deflection Adjustment finished, press "◁ (MUTE)"+"⓪" buttons on the commander to write the data to the NVM.
5) Adjust the sub deflection (Projector Engine Adjustment). (Refer to 6-5-3.)
6) After the Projector Engine Adjustment finished, press "◁ (MUTE)"+"⓪" buttons on the commander to write the data to the NVM.

8. PIP 60 Hz (NTSC) Mode

1) Enter the NTSC monoscope signal, and set in the service mode.
2) Open the remote control cover, press "⬛ (PIP)" button on the commander to set the PIP mode.
3) Confirm and set the following data.

Condition :

Category	Item		Data
GEO	00	VSZ	
	01	VPS	
	02	VLN	
	03	SCO	
	04	HSZ	Same as DRC1250 60 Hz (NTSC) mode
	05	HPS	
	07	PAP	
	08	UPN	
	09	LPN	
	0A	TRZ	
	0B	AGL	07
	0C	BOW	07
	15	VSC	22
MID	00	HPH	49
	01	VPH	25

4) Press "◁ (MUTE)"+"⓪" buttons on the commander to write the data to the NVM.

– 70 –

9. TWIN 60 Hz (NTSC) Mode

1) Enter the NTSC monoscope signal, and set in the service mode.

2) Press " ▌ (TWIN)" button on the commander to set the TWIN mode.

3) Confirm and set the following data.

Condition :

Category	Item		Data
GEO	00	VSZ	
	01	VPS	
	02	VLN	
	03	SCO	
	04	HSZ	Same as DRC1250 60 Hz (NTSC) mode
	05	HPS	
	07	PAP	
	08	UPN	
	09	LPN	
	0A	TRZ	
	0B	AGL	07
	0C	BOW	07
	15	VSC	22
MID	00	HPH	6F
	01	VPH	2E
	11	TMP	01
	12	TSP	00

4) Select the category "GEO" and the item "05 HPS", and adjust the horizontal position.

H1 – H2 = ± 0.1 sq.

5) Press " ⊠ (MUTE)"+"◎" buttons on the commander to write the data to the NVM.

10. INDEX 60 Hz (NTSC) Mode

1) Enter the NTSC monoscope signal, and set in the service mode.

2) Press "PROGR INDEX" button on the commander to set the INDEX mode.

3) Confirm and set the following data.

Condition :

Category	Item		Data
GEO	00	VSZ	
	01	VPS	
	02	VLN	
	03	SCO	
	04	HSZ	Same as DRC1250 60 Hz (NTSC) mode
	05	HPS	
	07	PAP	
	08	UPN	
	09	LPN	
	0A	TRZ	
	0B	AGL	07
	0C	BOW	07
	15	VSC	22
MID	00	HPH	6C
	01	VPH	2D

4) Select the category "GEO" and the item "05 HPS" to adjust the horizontal position, and select the item "01 VPS" to adjust the vertical position.

V1 – V2 = ± 0.1 sq.
H1 – H2 = ± 0.1 sq.

5) Press " ⊠ (MUTE)"+"◎" buttons on the commander to write the data to the NVM.

11. DRC1250 WIDE 60 Hz (NTSC) Mode

1) Enter the NTSC monoscope signal and set the DRC1250.
2) Press "MENU" button on the commander and move "⊕" up or down to enter the "FEATURE" ➜ "WIDE MODE".
3) Select "WIDE MODE : ON", and push "⊕ (ENTER)" button.
4) Press "MENU" button to return to service mode screen.
5) Set in the service mode and write the following data to NVM.

Condition :

Category	Item		Data
GEO	0B	AGL	07
	0C	BOW	07
	14	VAS	2C
	15	VSC	22
	16	USC	01
	17	VBW	03

3) Adjust the main deflection. (Refer to 6-5-2.)

SPEC

Input Signal	H SIZE
NTSC monoscope	15.7 ± 0.1 sq.

V1

$V1 - V2 = \pm 0.1$ sq.

V2

4) After the Main Deflection Adjustment finished, press "◁╳ (MUTE)"+"◎" buttons on the commander to write the data to the NVM.
5) Adjust the sub deflection (Projector Engine Adjustment). (Refer to 6-5-3.)
6) After the Projector Engine Adjustment finished, press "◁╳ (MUTE)"+"◎" buttons on the commander to write the data to the NVM.

12. PIP WIDE 60 Hz (NTSC) Mode

1) Enter the NTSC monoscope signal and set in the service mode.
2) Set the WIDE mode and open the remote control cover, press "▢ (PIP)" button on the commander to set the PIP mode.
3) Confirm and write the following data.

Condition :

Category	Item		Data
GEO	00	VSZ	
	01	VPS	
	02	VLN	
	03	SCO	Same as
	04	HSZ	DRC1250
	05	HPS	WIDE 60 Hz
	07	PAP	(NTSC) mode
	08	UPN	
	09	LPN	
	0A	TRZ	
	0B	AGL	07
	0C	BOW	07
	14	VAS	2C
	15	VSC	22
	17	VBW	03

4) Press "◁╳ (MUTE)"+"◎" buttons on the commander to write the data to the NVM.

Note : Incase of replacing CRTs, adjust the set-up adjustments (items 4-1 to 4-7) and the registration adjustment (item 6-5).
In case of replacing two or three CRTs at the same time, replace and adjust one by one.

6-6. AUTO CONVERGENCE SETTING

This adjustment must be performed after the registration adjust-
ment was made or after readjustment was made by any reason.

1. Darken the periphery of this set.
2. Enter the PAL SPCB signal, and set the DRC100 mode.
3. Set in the service mode, and select the category "PJE" and
   the item "PWM2".
4. Adjust "PWM2" so that the marker line is on monoscope
   center line.

5. Press "◁╳ (MUTE)"+"⓪" buttons on the commander to
   write the data to the NVM.
6. Press " ⊡ (AUTO CONVERGENCE)" button on the front
   panel of the set.
   (The offset value is now automatically stored.)
7. Check that no error message appears.
   If an error message appears, recheck. (Refer to 6-8.)
8. In the same manner, select DRC100 mode respectively, and
   press the " ⊡ (AUTO CONVERGENCE)" button.
9. Enter the NTSC monoscope signal, and perform the same
   steps in the DRC1250, DRC100 and DRC1250 WIDE
   modes respectively.

6-7. WHITE BALANCE ADJUSTMENT

1. Enter the monoscope signal.
2. Set in the service mode.
3. Press "MENU" button on the commander to select "A/V
   CONTROL" ➜ "PICTURE MODE" ➜ "ADJUST".

Adjustment Condition
  PICTURE MODE : PERSONAL
  PICTURE   : 0%
  BRIGHT   : 50%

If the noise of DCF (Digital Comb Filter) has an effecting
white balance adjustment, change service data as follows
while the adjustment.
  OPM 06 COM : 00 → 01
(This time, beginning inspection also should be done under
some condition.)

Adjusting Parameter

Category	Item	
WHB	02	SBR
	03	RDR
	05	BDR
	06	RCT
	08	BCT

4. Adjust "02 SBR" so that 10 IRE section barely grows.
3. Enter the all-white pattern signal.
6. Adjust "06 RCT" and "08 BCT" so as to attain the optimum
   white balance.
7. Adjust "02 SBR" so that 100 IRE section barely grows.
8. Adjust "03 RDR" and "05 BDR" so as to attain the optimum
   white balance.
9. Repeatedly adjust the white balance for the minimum and
   maximum picture setting.
10. Enter the monoscope signal, and select "SAJ 00 PIC", and
    set the data to "00".
11. Adjust "02 SBR" so that the border between 0 IRE and 10
    IRE becomes distinct.

6-8. AUTO CONVERGENCE ERROR CODE LIST

If an error code is displayed after the set has been fully adjusted, correctly, plese check the following items : position, tilt and sizing. If either of these adjustments are off, even slightli, the auto registration pattern will not hit the four sensors properly. This occurs when the internal generator patterns is being flashed on the screen for the sensor to read. Therefore, auto registration (called auto convergence) cannot operate properly causing an error code to be displayed. In order for this function to operate properly, correct position, tilt and size must be adjusted properly.

ERROR CODE LIST

ERROR CODE	DESCRIPTION	NOTE	
00	No Error		
10	Sensor Input Level Low	* Check wiring, beam position, sensor.	0 : Upper Center 1 : Middle Left 2 : Middle Right 3 : Lower Center
20	Sensor Input Level High	* Check OP-Amp circuit.	0 : Upper Center 1 : Middle Left 2 : Middle Right 3 : Lower Center
30	Loop Limit Over	* Check the registration information on the convergence board.	
40	Regi Data Overflow	* Check the convergence yoke driver ICs.	
50	Regi Data Overdraw		
60	Offset Data Overflow	* Convergence patterns displayed are out of normal range.	
70	Offset Data Overdraw		

* : In case of multiple error, last error is displayed.

[SENSOR POSITION]

0
1 SCREEN 2
3

0 : UPPER SENSOR
1 : LEFT SENSOR
2 : RIGHT SENSOR
3 : LOWER SENSOR

• ERROR CODE SCREEN DISPLAY
(When press " (AUTO CONVERGENCE)" button.)

E11B ⇨ **E11B**
- R, G, B
- SENSOR NUMBER
- ERROR CODE 10
- ERROR

• ERROR CODE SCREEN DISPLAY
(When select "PJE" ➔ "29 ERR".)

PJE   29   140
ERR |

⇨ **140**
- SENSOR NUMBER
- ERROR CODE 40
- G : 0 (Blank)
- R : 1
- B : 2

Category : PJE
Item : 29 ERR

7-1. BLOCK DIAGRAMS

J1 (AV SELECT SWITCH, VIDEOPROCESS)

B3 (DRC, MID-X, VIDEO PROCESS)

BD (PJED, REGI CORRECTION)

IC2619 PJED-CPU

IC2617 RESET
RST VCC
TO IC2621, IC2619B

CN2603
UPPER SENSOR — UPPER
LOWER SENSOR — LOWER
RIGHT SENSOR — RIGHT
LEFT SENSOR — LEFT

IC2626 (1/4) 1V CONV. PEAK HOLD   Q2611
IC2626 (2/4) 1V CONV. PEAK HOLD   Q2610
IC2626 (3/4) 1V CONV. PEAK HOLD   Q2613
IC2626 (4/4) 1V CONV. PEAK HOLD   Q2612

IC2627 (1/4)
IC2627 (2/4)
IC2627 (3/4)
IC2627 (4/4)

Q2614 SN

X2701 12MHz

IC2605 DIGITAL-REGI

IC2621 EEPROM
WP PSDA PSCL

IC2607 (1/3) OSD MIX
IC2607 (2/3) OSD MIX
IC2607 (3/3) OSD MIX

Q2606 ATT
Q2605 ATT

Q2602 BUFF
Q2607 BUFF
Q2604 BUFF
Q2601 BUFF

CN2602 (2/2)
RE-R
RE-G
RE-B
RE-YS

O FOCUS

TO D BOARD CN5015

CN2602 (1/2)
V SHIFT
H SHIFT
DISABLE
SDA
SCL
REGI MUTE
VP
-5V
+5V
+5V
+5V
D+5V
D+5V
+9V
+9V

Q2608 INV

IC2618 V/H DELAY
IC2620 EVEN/ODD

IC2613 16MHz PLL

IC2612 PLL

IC2615 VCO OUT FINA FINB

Q2611 I2C BUS SN

VS
HP
HS

CN2601
SCL
SDA
/BINT
PSCL
PSDA
D+5V
TO JIG

IC2609 RM DAC
IC2625 RV DAC
IC2604 GM DAC
IC2623 GV DAC
IC2602 BM DAC
IC2614 BV DAC

IC2608 (1/2) AMP
IC2622 (1/2) AMP
IC2601 (1/2) AMP
IC2616 (1/2) AMP
IC2601 (1/2) AMP
IC2610 (1/2) AMP

IC2608 (2/2) FILTER AMP
IC2622 (2/2) FILTER AMP
IC2603 (2/2) FILTER AMP
IC2616 (2/2) FILTER AMP
IC2601 (2/2) FILTER AMP
IC2610 (2/2) FILTER AMP

HR
VR
HG
VG
HB
VB

TO D BOARD CN5015

— 84 —   — 85 —   — 86 —

M1 (SYSTEM CONTROL, TELE TEXT)

IC003 TELE TEXT

CN001 (2/2)

Q008 TEXT R BUFF — B9 TEXT R
Q009 TEXT G BUFF — B8 TEXT G
Q010 TEXT B BUFF — B7 TEXT B

R (47)
G (48)
B (49)
BLAN (50) — B6 TEXT YS

CN001 (1/2)

CVBS IN B4 — (30) CVBS
HP 100 A23 — Q005 HP BUFF — (45) HS/SC
VP 100 A22 — Q006 VP INV — (46) VS

IC007 TEXT REST
RST (15) — 1 2 — +5V

X002 6MHz — (12) XTAL1 (13) XTAL2
P3.3 (36) SDA
P3.4 (43)
P3.2 (44) SCL

IC005 OSD SW

RE-R B18 — (12) X0
RE-G B11 — (2) Y0
RE-B B19 — (5) Z0
RE-YS B21

X (14) — Q017 OSD R BUFF — A18 R
Y (15) — Q016 OSD G BUFF — A19 G
Z (4) — Q018 OSD B BUFF — A20 B

IC002 MAIN U-COM

H SYNC (7)
V SYNC (8)

R (32) — Q021 OSD R BUFF — (13) X1
G (33) — Q020 OSD G BUFF — (1) Y1
B (34) — Q019 OSD B BUFF — (2) Z1

A (9) B C (11)

LED2 A14 — (53) LED2
RESPONS LED B13 — (54) LED1
KEY1 B12 — (14) KEY1
KEY2 A12 — (13) KEY2
SIRCS A11 — (64) SIRCS
COMB RESET B23 — (22) COMB RESET
TRAP B5 — (28) TRAP
HP MAIN IN B24 — (63) HS0

Q022,023 B-BACK

IC010 (1/3) IC009 (1/2) IC010 (2/3)
IC008 (1/2)

I (35) — Q004 ATT

AFT1 A1 — (17) AFT1
AFT2 B1 — (18) AFT2
ST B2 — (29) ST
ATT A3 — (45) ATT SW
AUDIO RESET A6 — (30) MSP RESET

YS (36) — IC008 (2/2) — Q015 YS MIX

CNT SP ON/OFF A5 — (58) CNT-SP
V-COMP A7 — (56) V-COMP
AUDIO MUTE A8 — (31) MUTE
OCP B14 — (3) OCP
OVP A15 — (6) OVP
AC ON/OFF B15 — (60) AC ON/OFF
APROT B20 — (57) AUDIO PROTECTION
ST-BY A24 — (62) ST-BY

YM (37) — IC010 (3/3) — IC009 (2/2) — Q014 YS MIX

IC008-010 YS PRIORITY

IC001 U-COM RESET
RESET (9) — 1 2 — +5V-STBY

ABL-CTR B10 — (55) ABL-CTR

SDA0 (48) SDA
SCL0 (50) SCL — A17 SDA / A16 SLC

RESET 100 B22 — (25) RESET 100

SDA1 (47)
SCL1 (49)

DISABLE A25 — (19) B-INT

XTAL (11)
EXTAL (12) — X001 20MHz

IC004 MEMORY   IC006 MEMORY
SCL SDA   SCL SDA

+5V — A10 +5V
+5V ST-BY — A15 STNDBY 5V

A21 YS

TO A1 BOARD CN1001

D TO A1 BOARD CN1001

G (POWER SUPPLY)

G1 (POWER SUPPLY)

• J1 BOARD SEMICONDUCTOR LOCATION

IC

	Component Side	Conductor Side
IC8302	A-1	
IC8304		C-2
IC8305		C-1
IC8306	C-1	
IC8308	C-2	
IC8309	D-1	
IC8310	D-1	
IC8311	D-1	
IC8312	E-2	
IC8601	C-2	

TRANSISTOR

	Component Side	Conductor Side	✱
Q8301		A-2	①
Q8302		A-2	①
Q8303		A-2	①
Q8304		A-2	①
Q8306		A-2	①
Q8307	E-2		
Q8308		A-2	②
Q8309		A-2	①
Q8316	D-2		②
Q8317	D-2		②
Q8318	D-2		②
Q8319	D-2		②
Q8321		B-1	①
Q8322		B-1	①

Q8323	D-2		
Q8324	D-2		
Q8326		D-2	②
Q8327		D-2	①
Q8328	D-2		①
Q8332	D-2		
Q8338		D-2	①
Q8340	D-1		
Q8401		C-1	①
Q8402		C-2	①
Q8405		D-2	②
Q8406		D-2	②
Q8407		D-2	②
Q8408		E-1	②
Q8410		E-1	②
Q8411		E-1	②
Q8412		E-1	②
Q8413		E-1	②
Q8414		E-1	②
Q8415		E-1	②
Q8416		E-1	②
Q8417		E-1	—
Q8418		E-1	—
Q8419		D-2	①
Q8420		D-2	①
Q8421		D-1	①
Q8422		D-1	②
Q8423		E-2	②
Q8424		E-2	②
Q8425		D-2	②
Q8426		D-2	②

Q8601	C-1		②
Q8602	C-1		①
Q8603	C-1		①
Q8604	C-1		①
Q8605	C-2		①
Q8606	C-2		①
Q8607	C-2		②
Q8801	C-2		②
Q8802		D-2	①
Q8803		D-1	②
Q8804		D-2	②
Q8805	D-2		①
Q8807	D-2		①
Q8808	D-2		②
Q8809	D-2		②
Q8810	C-2		②
Q8811	C-2		②

DIODE

	Component Side	Conductor Side	✱
D8101		A-1	③
D8102		A-1	③
D8103		A-1	③
D8104		A-1	③
D8301		A-2	③
D8302		B-2	③
D8303		B-2	③
D8304		B-2	③
D8305	C-2		③
D8306		B-2	③

D8307		B-2	③
D8308		C-2	③
D8309		B-2	③
D8310		B-2	③
D8311		B-2	③
D8312		A-2	③
D8313		A-2	③
D8314		A-2	③
D8315		B-2	④
D8316		B-2	③
D8317		B-2	④
D8318		B-2	③
D8319		B-2	③
D8320		A-2	③
D8321		A-2	③
D8322	A-2	A-1	③
D8323	A-2		③
D8324	A-2		
D8325	A-2		
D8331		D-2	③
D8332		B-1	③
D8333		B-1	③
D8334		B-1	③
D8335		B-2	③
D8336		B-1	③
D8337		B-1	③

CRYSTAL

	Component Side	Conductor Side
X8301	D-1	
X8302	D-1	

✱: Refer to Terminal name of
semiconductors in silk screen
printed circuit (see page 110)

7-3. CIRCUIT BOARDS LOCATION

• KP-ES43

G (KP-ES43HK1/SN1)
G1 (KP-ES43ME1/MN1)

• KP-ES48/ES53/ES61

G (KP-ES48HK1/SN1, ES53HK1/SN1, ES61HK1/SN1)
G1 (KP-ES48ME1/MN1, ES53ME1/MN1, ES61ME1/MN1)

7-4. SCHEMATIC DIAGRAMS AND PRINTED WIRING BOARDS

Note:
- The parts marked "#" on schematic diagrams are not mounted.
- All capacitors are in µF unless otherwise noted. (pF: µµF)
  Capacitors without voltage indication are all 50 V.
- Indication of resistance, which does not have one for rating
  electrical power, is as follows.

  Pitch: 5 mm
  Rating electrical power 1/4 W (CHIP : 1/10 W)

- All resistors are in ohms.
- ▭▭▭▭ : nonflammable resistor.
- ▪V▪▪▪ : fusible resistor.
- △ : internal component.
- ▭ : panel designation, and adjustment for repair.
- All variable and adjustable resistors have characteristic curve B,
  unless otherwise noted.
- ⊥ : earth-ground.
- ⊥ : earth-chassis.
- All voltages are in V.
- Readings are taken with a 10 M digital multimeter.
- Readings are taken with a color-bar signal input.
- Voltage variations may be noted due to normal production
  tolerance.
- ✱ : Can not be measured.
- NO MARK: Common
- < > : SECAM
- ( ) : NTSC 3.58 MHz
- Circled numbers are waveform references.
- ▭ᵛ : B + bus.
- ▭ : B – bus.
- ▭ : Signal path.

Reference Information
RESISTOR	: RN	METAL FILM
	: RC	SOLID
	: FPRD	NONFLAMMABLE CARBON
	: FUSE	NONFLAMMABLE FUSIBLE
	: RW	NONFLAMMABLE WIREWOUND
	: RS	NONFLAMMABLE METAL OXIDE
	: RB	NONFLAMMABLE CEMENT
COIL	: LF-SL	MICRO INDUCTOR
CAPACITOR	: TA	TANTALUM
	: PS	STYROL
	: PP	POLYPROPYLENE
	: PT	MYLAR
	: MPS	METALIZED POLYESTER
	: MPP	METALIZED POLYPROPYLENE
	: ALB	BIPOLAR
	: ALT	HIGH TEMPERATURE
	: ALR	HIGH RIPPLE

Note: The components identified by shading and mark
△ are critical for safety. Replace only with part
number specified.

Terminal name of semiconductors in silk screen printed circuit (✱)

	Device	Printed symbol	Terminal name	Circuit
①	Transistor	T	Collector / Base / Emitter	
②	Transistor	▬	Collector / Base / Emitter	
③	Diode	▭	Cathode — Anode	
④	Diode	T	Cathode / Anode (NC)	
⑤	Diode	▬	Cathode / Anode (NC)	
⑥	Diode	T	Common / Anode ┃ Cathode	
⑦	Diode	▬	Common / Anode ┃ Cathode	
⑧	Diode	T	Common / Anode ┃ Anode	
⑨	Diode	▬	Common / Anode ┃ Anode	
⑩	Diode	T	Common / Cathode ┃ Cathode	
⑪	Diode	▬	Cathode ┃ Cathode	
⑫	Diode	▮	Anode ┃ Cathode / Cathode ┃ Anode	
⑬	Transistor (FET)	▮	Drain ┃ Source / Gate	
⑭	Transistor (FET)	┣	Drain ┃ Source / Gate	
⑮	Transistor (FET)	▮	Source / Drain / Gate	
⑯	Transistor	▮	Emitter / Collector / Base	
—	Discrete semiconductor			

(Chip semiconductors that are not actually used are included.)

– J1 Board – (Component Side)

(Conductor Side)

• J1 (1/2) BOARD WAVEFORMS

①	② PAL/NTSC	② SECAM	③ PAL	③ SECAM	④ PAL/SECAM	⑤ NTSC	⑥ NTSC
0.3Vp-p (16.2MHz)	1.1Vp-p (H)	1.2Vp-p (H)	0.6Vp-p (H)	0.4Vp-p (H)	0.8Vp-p (H)	0.7Vp-p (H)	1.0Vp-p (H)

⑦ PAL/NTSC
2.1Vp-p (H)

⑦ SECAM
2.1Vp-p (H)

⑧
0.8Vp-p (H)

⑨
1.1Vp-p (H)

⑩
1.1Vp-p (H)

⑪
5.1Vp-p (H)

⑫
5.0Vp-p (V)

⑬ PAL/NTSC
2.1Vp-p (H)

⑬ SECAM
2.2Vp-p (H)

⑭ PAL/NTSC
1.0Vp-p (H)

⑭ SECAM
1.0 Vp-p (H)

J1 (1/2)
(AV SELECT SWITCH
VIDEO PROCESS)

• J1 (2/2) BOARD WAVEFORMS

⑮	⑯ PAL	⑯ SECAM	⑰ PAL	⑰ SECAM	⑱ PAL/SECAM	⑲ PAL/NTSC	⑲ SECAM
PAL: 0.8Vp-p (4.43MHz) SECAM: 0.8Vp-p (4.43MHz) NTSC: 0.9Vp-p (3.58MHz)	1.6Vp-p (H)	1.6Vp-p (H)	1.3Vp-p (H)	1.0Vp-p (H)	1.6Vp-p (H)	1.1Vp-p (H)	1.0Vp-p (H)

⑳	㉑	㉒	㉓	㉔	㉕	㉖
0.7Vp-p (H)	0.7Vp-p (H)	1.2Vp-p (H)	1.0Vp-p (H)	1.3Vp-p (H)	1.2Vp-p (H)	1.2Vp-p (H)

(2) Schematic Diagram of J1 (2/2) Board

J1 (2/2)
(DIGITAL COMB FILTER.)
(PICTURE BOOSTER)

DIGITAL COMB FILTER

– 115 –

– 116 –

Schematic diagram
← J1 (2/2) board

– 117 –

Schematic diagram
A1 board →

A1
(AUDIO OUT,
AUDIO PROTECT, TUNER)

• A1 BOARD WAVEFORMS

① NTSC	② NTSC	③ NTSC
1.4Vp-p (H)	2.0Vp-p (H)	2.1Vp-p (H)

• A1 BOARD SEMICONDUCTOR LOCATION

IC	(Component Side)	(Conductor Side)
IC1101		D-3
IC1201		C-3
IC1202		C-3
IC1301		B-5
IC1601	E-2	E-4
IC1602	E-1	E-4
IC1603	E-3	E-3
IC1604	E-4	E-3
IC1605	E-1	E-5

TRANSISTOR	(Component Side)	(Conductor Side)	★
Q1101		D-4	①
Q1102		D-4	①
Q1103		D-4	①
Q1104		C-4	①
Q1105		D-4	①
Q1106		D-4	①
Q1201		D-4	①

	(Component Side)	(Conductor Side)	★
Q1202		D-4	①
Q1203		D-4	①
Q1204		D-4	①
Q1205		C-2	①
Q1206		D-4	①
Q1207		D-3	①
Q1208		C-3	①
Q1209		E-1	①
Q1308		E-2	①
Q1309		A-4	①
Q1310		B-4	①
Q1311		B-5	①
Q1312		B-5	①
Q1401		E-3	①
Q1402		E-3	①
Q1409		B-2	①

DIODE	(Component Side)	(Conductor Side)	★
D1101		D-4	③
D1102		D-4	③
D1104		D-4	③

	(Component Side)	(Conductor Side)	★
D1105		D-4	④
D1106		D-4	④
D1107		C-3	④
D1108		C-3	④
D1109		C-4	④
D1110		C-3	④
D1111		C-3	④
D1112		C-3	④
D1201		D-3	④
D1202		E-3	④
D1204		E-3	④
D1205		D-3	③
D1206		D-2	③
D1301		B-5	④
D1401		B-3	③
D1402		B-3	③
D1403		B-3	③
D1404		B-3	③
D1405		B-2	③
D1406		B-2	④
D1409		E-3	④
D1410		D-3	③
D1411		D-3	③
D1412		D-2	③

●: Refer to Terminal name of
semiconductors in silk screen
printed circuit (see page 110)

– A1 Board – (Component Side)

(Conductor Side)

Schematic diagram
Bs (1/5)board ➡

• B3 BOARD SEMICONDUCTOR LOCATION

IC			TRANSISTOR		
	(Component Side)	(Conductor Side)		(Component Side)	(Conductor Side) ★
IC302	A-4		Q301	A-2	①
IC303	A-4		Q302	A-2	①
IC309		A-1	Q308	A-2	②
IC311	B-4	B-1	Q601	B-1	②
IC501	B-1		Q602	B-1	②
IC504	A-2		Q508	B-1	②
IC505	B-3		Q510	B-1	②
IC506	B-2		Q511	B-1	②
IC601	A-1		Q512	B-1	②
IC602	B-1		Q516		②
IC603	A-1		Q517	A-3	②
IC604		B-3	Q518	A-3	②
IC801	B-3		Q519	A-3	②
IC802	B-4		Q520		②
IC803		A-2	Q521	B-1	②
IC901	B-2		Q522	B-1	②
IC902	A-3		Q523		②
IC903		A-2	Q524	B-3	①
IC904	A-3		Q601	A-4	①
			Q602	A-4	①
			Q901	B-3	①

	(Component Side)	(Conductor Side) ★
Q902	B-3	①
Q903	B-3	①
Q904	A-1	⑩
Q905	A-1	⑨
Q906	A-1	⑨
Q907	B-2	⑨
Q908	B-2	⑨
Q909	B-2	⑨

DIODE

	(Component Side)	(Conductor Side) ★
D301	B-4	③
D302	B-4	③
D501	B-4	③
D901	A-2	③

CRYSTAL

	(Component Side)	(Conductor Side)
X801	B-3	
X802	B-3	
X901	A-3	

★: Refer to Terminal name of semiconductors in silk screen printed circuit (see page 110)

– B3 Board – (Component Side)

SONY MADE IN JAPAN

1-475-932-22 (171769422)

>EP-GW<

(Conductor Side)

SONY

1-475-932-22 (171769422)

(4) Schematic Diagram of B3 (1/5) Board

• B3 (1/5) BOARD WAVEFORMS

① 0.9Vp-p (H)	② 2.5Vp-p (H)	③ 3.2Vp-p (13.8MHz)	④ 3.4Vp-p (H)	⑤ 1.1Vp-p (H)
⑥ 1.1Vp-p (H)	⑦ 4.8Vp-p (H)	⑧ 4.8Vp-p (V)	⑨ 1.0Vp-p (54MHz)	

B3 (1/5)
(A/D CONVERTER)

B3 (2/5)
(DRC)

• B3 (2/5) BOARD WAVEFORMS

⑩ 3.1Vp-p (V)	⑪ 3.5Vp-p (13.8MHz)	⑫ 3.4Vp-p (H)	⑬ 3.4Vp-p (H)
⑭ 3.2Vp-p (H)	⑮ 1.1Vp-p (54MHz)	⑯ 1.0Vp-p (54MHz)	⑰ 3.5Vp-p (V)
⑱ 3.4Vp-p (H)			

(6) Schematic Diagram of B3 (3/5) Board

• B3 (3/5) BOARD WAVEFORMS

B3 (3/5)
(MID-X)

● B3 (4/5) BOARD WAVEFORMS

㉚	㉝
1.1Vp-p (H)	1.0Vp-p (54MHz)
㉛	㉞
1.1Vp-p (H)	3.2Vp-p (20MHz)
㉜	㉟
1.1Vp-p (H)	5.0Vp-p (V)

B3 (4/5)
(D/A CONVERTER,)
(SIGNAL CONTROL)

B-SS696-<GE.>-B3.-P4

• B3 (5/5) BOARD WAVEFORMS

36	40
2.9Vp-p (23MHz)	2.7Vp-p (23MHz)
37	41
1.2Vp-p (68.7MHz)	0.9Vp-p (H)
38	42
3.8Vp-p (H)	1.0Vp-p (H)
39	
1.0Vp-p (H)	

B3 (5/5)
(A/D CONVERTER, PLL)

• E BOARD WAVEFORMS

①	②	③	④	⑤
0.5Vp-p (H)	0.6Vp-p (H)	0.6Vp-p (H)	5.0Vp-p (H)	4.9Vp-p (V)

⑥	⑦	⑧	⑨	⑩
1.5Vp-p (V)	1.5Vp-p (V)	0.1Vp-p (503.5kHz)	5.7Vp-p (H)	2.3Vp-p (H)

⑪	⑫	⑬
2.3Vp-p (H)	2.2Vp-p (H)	2.3Vp-p (H)

– E Board – (Component Side)

(Conductor Side)

(9) Schematic Diagram of E Board

E
(R/G/B/VM OUT, Y-C/J)

• E BOARD SEMICONDUCTOR LOCATION

IC		Q4322	B-1	②
	(Component)(Conductor) Side Side	Q4323	B-1	①
IC4301	A-2	Q4324	B-1	①
		Q4601	B-1	③
TRANSISTOR		Q4602	B-1	①

	(Component)(Conductor) Side Side ★	DIODE		
Q4301	B-1 ①		(Component)(Conductor) Side Side ★
Q4303	A-2 ②	D4304	A-2	③
Q4304	B-1 ①	D4305	B-2	②
Q4307	A-1 ②	D4601	B-1	①
Q4306	A-1 ②	D4602	B-1	④
Q4310	A-2 ②	D4603	B-1	④
Q4316	A-1			
Q4317	A-1 ②	CRYSTAL		
Q4318	A-1 ②		(Component)(Conductor) Side Side
Q4319	B-1	X4300	B-2	
Q4320	A-1			
Q4321	A-1			

★: Refer to Terminal name of
semiconductors in silk screen
printed circuit (see page 116)

• M1 BOARD WAVEFORMS

①	②	③	④ PAL/NTSC
4.6Vp-p (V)	4.1Vp-p (H)	3.4Vp-p (6MHz)	1.2Vp-p (H)

④ SECAM	⑤	⑥	⑦
1.2Vp-p (H)	4.8Vp-p (H)	4.9Vp-p (V)	2.3Vp-p (20MHz)

(10)   Schematic Diagram of M1 Board

M1
(SYSTEM CONTROL, TELE TEXT)

– M1 Board – (Component Side)

A-1308-588-A

(Conductor Side)

• M1 BOARD SEMICONDUCTOR LOCATION

| IC			TRANSISTOR				DIODE		
	(Component) Side	(Conductor) Side		(Component) Side	(Conductor) Side	★		(Component) Side	(Conductor) Side	★
IC001	B-2		Q004		B-2	②	D003	A-2	③
IC002	B-2		Q005	A-1		②	D004	A-2	③
IC003	A-1	B-1	Q006	A-1		②	D007	A-2	③
IC004	B-1		Q008		B-2	①	D008	A-2	③
IC005	B-1		Q009		B-2	①	D009	A-2	③
IC006	B-1		Q010		B-2	①	D015	A-2	③
IC007		B-1	Q014	B-1		②	D017	A-2	③
IC008	B-1		Q015	B-1		②			
IC009	B-1		Q016	B-1		②	CRYSTAL		
IC010	B-1		Q017	B-1		②		(Component) Side	(Conductor) Side
			Q018	B-1		②	X001	B-2	
			Q019	B-1		②	X002	A-1	
			Q020	B-1		②			
			Q021	A-1		②			
			Q022	A-1		②			
			Q023		B-1	②			

★: Refer to Terminal name of
semiconductors in silk screen
printed circuit (see page 110)

H1 [MAIN SWITCH, IR RECEIVER] H2 [HP OUT, USER CONTROL, AV INPUT]

– H1 BOARD – (KP-ES43)

H1 BOARD
Terminal name of semiconductors
in silk screen printed circuit (●)

Ref.	●
D9108	①
Q9101, 9102	①

●: Refer to Terminal name of
semiconductors in silk screen
printed circuit (see page 116)

H1 (MAIN SWITCH, IR RECEIVER) (43 INCH MODEL)

– H2 BOARD – (KP-ES43)

H2 BOARD
Terminal name of semiconductors
in silk screen printed circuit (●)

Ref.	●
D9207	①
Q9201	①

●: Refer to Terminal name of
semiconductors in silk screen
printed circuit (see page 116)

H2 (HP OUT, USER CONTROL, AV INPUT) (43 INCH MODEL)

— 143 —

— 144 —

H1 [USER CONTROL, MAIN SWITCH] H2 [HP OUT, USER CONTROL] H3 [AV INPUT]

H1 (USER CONTROL, MAIN SWITCH) (48/53/61 INCH MODEL)

H2 (HP OUT, USER CONTROL) (48/53/61 INCH MODEL)

H3 (AV INPUT) (48/53/61 INCH MODEL)

– H1 BOARD – (KP-ES48/53/61)

H1 BOARD
Terminal name of semiconductors
in silk screen printed circuit (●)

Ref.	●
Q9101, Q9102	①

●: Refer to Terminal name of
semiconductors in silk screen
printed circuit (see page 116)

– H2 BOARD – (KP-ES48/53/61)

H2 BOARD
Terminal name of semiconductors
in silk screen printed circuit (●)

Ref.	●
D9208	①
Q9201	①

●: Refer to Terminal name of
semiconductors in silk screen
printed circuit (see page 116)

– H3 BOARD – (KP-ES48/53/61)

— 145 —

— 146 —

DS [SHADING]

• DS BOARD WAVEFORMS

① 1.2Vp-p (V)

② 1.5Vp-p (V)

③ 1.7Vp-p (V)

DS (SHADING)

– DS BOARD – (Component Side)

(Conductor Side)

DS BOARD
Terminal name of semiconductors
in silk screen printed circuit (∗)

Ref.	∗
D9501, D9505	③
D9502	①

∗: Refer to Terminal name of semiconductors in silk screen printed circuit (see page 116)

Schematic diagrams
← boards

– 147 –

– D BOARD –

D [H/V-DEF, HV. DY DRIVE]

SONY
1-878-707-11

NOTE:
The circuit indicated as left contains high voltage of over 600 Vp-p. Care must be paid to prevent an electric shock in inspection or repairing.

• D BOARD SEMICONDUCTOR LOCATION

IC		DIODE				
IC9103	C-6	Q9102	E-1	D9206	E-8	—
IC9104	C-6	Q9104	C-1	D9301	E-6	—
IC9105	C-4	Q9105	E-1	D9302	E-6	—
IC9106	E-3	Q9106	E-3	D9304	E-4	—
IC9107	D-6	Q9202	E-4 ①	D9305	E-4	—
IC9201	E-5	Q9203	E-4	D9306	E-6	—
IC9301	E-3	Q9401	D-4	D9307	E-8	—
IC9302	E-6	Q9402	D-4	D9308	E-6	—
IC9303	E-4	Q9403	E-4	D9309	E-6	—
IC9601	C-4	Q9201	A-4	D9401	D-4	—
IC9801	A-5	Q9501	A-4	D9402	D-4	—
IC9802	A-5	Q9502	A-2	D9114	D-4	—
IC9703	D-4	Q9503	A-2	D9116	A-1	—
		Q9505	B-4	D9117	D-3	—
TRANSISTOR		Q9506	B-4	D9118	A-4	—
		Q9703	B-3	D9121	D-3	—
Q9008	D-6 ③	Q9704	E-2	D9122	E-3	—
Q9009	D-6 ①	Q9705	E-2	D9201	E-4	—
		Q9706	E-3	D9202	E-4	—
		Q9707	E-3	D9203	E-4	—
		Q9710	E-3 ①	D9204	E-8	—
		Q9711	E-3 ③	D9205	E-8	—

∗: Refer to Terminal name of
semiconductors in silk screen
printed circuit (see page 116)

– 148 – – 149 – – 150 –

• D BOARD WAVEFORMS

① 1.5Vp-p (V)	⑨ 9.0Vp-p (H)
② 1.7Vp-p (V)	⑩ 1245Vp-p (H)
③ 1.0Vp-p (V)	⑪ 22.8Vp-p (H)
④ 56.0Vp-p (V)	⑫ 17.8Vp-p (H)
⑤ 0.8Vp-p (V)	⑬ 38.3Vp-p (V)
⑥ 12.5Vp-p (H)	⑭ 31.3Vp-p (V)
⑦ 5.4Vp-p (H)	⑮ 22.3Vp-p (V)
⑧ 221.5Vp-p (H)	⑯ 22.3Vp-p (V)

D
(H/V-DEF, HV, DY DRIVE)

Schematic diagram
⟸ D board

Schematic diagram
BD (1/2) board ⟹

BD (1/2)

(PJED. REGI CORRECTION)

• BD (1/2) BOARD WAVEFORMS

① 6.0Vp-p (8MHz)	② 5.1Vp-p (500kHz)	③ 4.6Vp-p (V)	④ 4.8Vp-p (H)
⑤ 4.9Vp-p (V)	⑥ 5.5Vp-p (16MHz)	⑦ 5.1Vp-p (H)	⑧ 4.5Vp-p (V)
⑨ 3.5Vp-p (12MHz)	⑩ 6.6Vp-p (32MHz)	⑪ 1.3Vp-p (V)	⑫ 0.9Vp-p (V)
⑬ 1.0Vp-p (V)	⑭ 2.1Vp-p (V)	⑮ 1.4Vp-p (V)	⑯ 1.9Vp-p (V)

(16) Schematic Diagram of BD (2/2) Board

BD (2/2)
(SENSOR SIGNAL RECEIVER)

BD — PJED, REGI CORRECTION

• BD BOARD SEMICONDUCTOR LOCATION

IC			Q2808	A-3	①
	(Component Side)	(Conductor Side)	Q2810	B-1	①
IC2601	B-1		Q2811	B-1	①
IC2602	A-1	B-1	Q2812		①
IC2603	B-1		Q2813	B-1	①
IC2604	A-2	B-2	Q2814	B-1	④
IC2605	A-4				
IC2606	A-3		**DIODE**		
IC2607	B-3			(Component Side)	(Conductor Side) ★
IC2608	B-1		D2601	A-3	③
IC2609	A-2	B-2	D2602	A-3	③
IC2610	B-3		D2603	A-3	③
IC2611	B-3		D2604	A-3	③
IC2612	A-3		D2605		B-1
IC2613	A-3		D2606	B-1	
IC2614	A-1	B-1	D2607	B-1	
IC2615	A-3		D2608	B-1	
IC2616	B-1		D2609	B-1	
IC2617	B-4		D2610	B-1	
IC2618	B-3		D2611	B-1	
IC2619	B-3		D2612	B-1	
IC2620	B-1		D2613		A-1
IC2621	A-4		D2614		B-1
IC2622	B-1		D2615	B-1	
IC2623	A-1	B-2	D2616	B-1	
IC2625	A-1	B-2	D2617	B-1	
IC2626	B-1		D2618		B-1
IC2627	B-1		D2619	B-1	
			D2620		A-1
TRANSISTOR			D2621	B-1	
	(Component Side)	(Conductor Side) ★	D2622	B-1	
Q2601	A-3	②	D2623	B-1	
Q2602	A-3	②	D2624	B-1	
Q2603	A-4	②			
Q2604	B-4	②	**CRYSTAL**		
Q2605	B-4	②		(Component Side)	(Conductor Side)
Q2606	B-3	②	X2701	B-3	
Q2607		A-4 ①			

★: Refer to Terminal name of semiconductors in silk screen printed circuit (see page 110)

– BD BOARD – (Component Side)

(Conductor Side)

Schematic diagram
← BD (1/2) board

CR [R CRT DRIVE]   ZR [DY, VM DRIVE]   CG [G CRT DRIVE]   ZG [DY, VM DRIVE]   CB [B CRT DRIVE]   ZB [DY, VM DRIVE]

– CR BOARD –

CR BOARD
Terminal name of semiconductors in silk screen printed circuit (*)

Ref.	*
D7106	②
Q7101, 7104	①

*: Refer to Terminal name of semiconductors in silk screen printed circuit (see page 110)

– CG BOARD –

CG BOARD
Terminal name of semiconductors in silk screen printed circuit (*)

Ref.	*
D7206	③
Q7201, 7202	①

*: Refer to Terminal name of semiconductors in silk screen printed circuit (see page 110)

– CB BOARD –

CB BOARD
Terminal name of semiconductors in silk screen printed circuit (*)

Ref.	*
D7307, 7309	③
Q7301, 7302, 7305, 7306	①

*: Refer to Terminal name of semiconductors in silk screen printed circuit (see page 110)

NOTE:
The circuit indicated as left contains high voltage of over 600 Vp-p. Care must be paid to prevent an electric shock in inspection or repairing.

– ZR BOARD –

ZR BOARD
Terminal name of semiconductors in silk screen printed circuit (*)

Ref.	*
D7401	②
Q7401 ~ 7405, 7410	①

*: Refer to Terminal name of semiconductors in silk screen printed circuit (see page 110)

– ZG BOARD –

ZG BOARD
Terminal name of semiconductors in silk screen printed circuit (*)

Ref.	*
D7603	②
Q7601, 7604 ~ 7607, Q7610	①

*: Refer to Terminal name of semiconductors in silk screen printed circuit (see page 110)

– ZB BOARD –

ZB BOARD
Terminal name of semiconductors in silk screen printed circuit (*)

Ref.	*
D7803	②
Q7801, 7804 ~ 7807, Q7810	①

*: Refer to Terminal name of semiconductors in silk screen printed circuit (see page 110)

CR
(R CRT DRIVE)

V901
PICTURE
TUBE

TO HV BLOCK

• CR BOARD WAVEFORMS

① 4.8 Vp-p

② 86 Vp-p (H)

③ 88 Vp-p (H)

CG
(G CRT DRIVE)

V902
PICTURE
TUBE

TO HV BLOCK

• CG BOARD WAVEFORMS

① 4.7 Vp-p (H)

② 114 Vp-p (H)

③ 114 Vp-p (H)

CB
(B CRT DRIVE)

V903
PICTURE
TUBE

HV BLOCK

• CB BOARD WAVEFORMS

① 4.6 Vp-p (H)

② 128 Vp-p (H)

③ 128 Vp-p (H)

ZR
(DY, VM DRIVE)

ZG
(DY, VM DRIVE)

ZB
(DY, VM DRIVE)

Schematic diagrams
CB CG CR
← ZB ZG ZR boards

Schematic diagram
G board →

G (AUS/HK model)
(POWER SUPPLY)

G1
(POWER SUPPLY)
(GE/ME MODEL)

• G BOARD SEMICONDUCTOR LOCATION

IC		DIODE					
IC6002	B-3	D6010	D-3	—	D6304	B-2	—
IC6004	A-4	D6015	C-4	—	D6305	D-2	③
IC6007	C-3	D6017	D-4	—	D6306	D-2	③
IC6301	A-2	D6019	A-5	—	D6307	D-1	—
IC6302	D-3	D6020	B-5	—	D6308	C-2	—
IC6303	A-1	D6021	A-5	—	D6309	C-2	—
IC6304	D-2	D6022	A-5	—	D6310	C-3	—
		D6023	A-5	①	D6311	D-2	—
TRANSISTOR		D6100	E-1	—	D6312	D-1	—
		D6101	D-4	—	D6316	D-1	—
		✱			D6316	D-1	③
Q6004	C-4	D6102	E-4	③	D6317	D-1	—
Q6100	D-4	D6103	D-4	—	D6318	A-1	—
Q6102	C-4	①	D6104	E-4	—	D6319	D-1	③
Q6300	D-2	①	D6105	D-4	—	D6320	D-1	—
Q6301	D-1	①	D6106	E-4	—	D6323	D-3	—
Q6302	D-1	①	D6108	D-4	—			
Q6303	A-1	—	D6300	C-2	—			
Q6304	D-2	—	D6301	C-2	—			
		D6302	A-2	—			
		D6305	D-2	—			

✱: Refer to Terminal name of
semiconductors in silk screen
printed circuit (see page 110)

NOTE:
The circuit indicated as left contains high voltage of over
600 Vp-p. Care must be paid to prevent an electric shock in
inspection or repairing.

• G1 BOARD SEMICONDUCTOR LOCATION

IC		DIODE					
IC6000	D-4	Q6003	D-4	①	D6007	D-4	③	D6302	A-2	—
IC6001	D-4	Q6004	D-3	①	D6008	D-4	③	D6304	B-2	—
IC6002	B-3	Q6005	D-5	—	D6009	D-6	③	D6305	D-2	③
IC6003	C-3	Q6009	D-6	③	D6010	D-6	③	D6307	D-1	—
IC6004	A-4	Q6010	D-5	③	D6011	D-4	—	D6308	C-1	—
IC6005	D-3	Q6102	E-3	①	D6015	B-5	—	D6309	B-2	—
IC6006	D-2	Q6300	B-3	—	D6017	D-3	—	D6310	C-2	—
IC6007	C-3	Q6301	D-1	①	D6019	A-4	—	D6312	D-1	③
IC6301	A-2	Q6302	D-1	①	D6021	A-5	—	D6315	C-1	③
IC6302	D-2	Q6303	A-1	—	D6022	A-5	—	D6316	D-1	—
IC6303	A-1				D6023	A-5	③	D6317	D-1	③
		DIODE			D6024	A-5	③	D6318	A-1	—
					D6025	D-4	③	D6319	D-1	③
TRANSISTOR		✱			D6100	E-4	—	D6320	D-1	③
		D6000	E-4	③	D6101	C-4	—	D6323	D-3	—
		D6001	C-4	—	D6102	D-4	—			
✱		D6002	C-4	①	D6103	D-3	③			
Q6000	D-4	—	D6003	D-4	—	D6105	D-3	③			
Q6002	D-4	—	D6004	D-4	—	D6300	C-2	—			
		D6005	D-4	—	D6301	C-2	—			
		D6006	D-5	③						

✱: Refer to Terminal name of
semiconductors in silk screen
printed circuit (see page 110)

– G BOARD – (AUS/HK)

– G1 BOARD – (GE/ME)

7-5. SEMICONDUCTORS

CA0007AM
LM339NS
MC74HC74AFEL
NJM2058M-TE2
SN74HC32ANS
SN74HC32ANSR
SN74HC74ANS
SN74HC74ANSR
TLC2932IPW
TLC2932IPW-E20
TLC2932IPWR
μPC339G2-T2

CXA3288Q-T6
CXD2064Q-T6
CXD2300Q-T6

48pin QFP

CXD2090Q

206pin QFP

14pin SOP

CM0006CF

80pin QFP

CXD2303AQ
CXD2303AQ-TL

TOP VIEW

CXA1875AM-T4
MC74HC4538AF
MC74HC4538AFEL
PCM56P
PCM56P-L

CXD9509Q

TOP VIEW

16pin SOP

240pin QFP

CXA2123BQ-T6

TOP VIEW

DM-58

CXA2069Q
CXA2100AQ-TL
CXP750098-925Q-TL
CXP86324-023Q

LF50CDT-TR

TOP VIEW

LM358D
LM358DR
M24C04-MN6T
M24C04-WMN6T
M24C08-MN6T(A)
M24C32-MN6T
TC7W02F
TC7W02F(TE12R)
TC7W04F
TC7W04F(TE12R)
TC7W08F
TC7W08F(TE12R)
TC7W32F
TC7W32F(TE12R)
TC7W66FU(TE12R)
TDA2822D013TR
μPC4570G2
μPC4570G2-E2

TOP VIEW

8pin SOP

LM7912CT

NJM2058D
μPC339C

TOP VIEW

14pin DIP

MB81F643242B-10FN

TOP VIEW

86pin SOP

MB94918RPF-G124-BND

INDEX

MCR5152

MC74HC4053AFEL

TOP VIEW

16pin DIP

MM1115XFBE

MARKING SIDE VIEW

8pin SIP

MM1476AF(TP)

NJM2058D
μPC339C

NJM78L05A
TA78L005AP-TPE6

NJM7812FA
NJM78M05FA
NJM78M09FA
NJM78M12FA
PQ09RF2

NJM79M05FA

TOP VIEW

PQ05RF11

PQ30RV21

PQ5EV3

PST9120NL
PST9145NL
TC7SET04F(TE85R)
TC7SET08F(TE85)
TC7SET08FU(TE85R)

5pin CHIP

PST9143NL

S-80743AL-A7-S
S-80743AL-A7-T1

SBX3081-01

TOP VIEW

SDA5254-2B006

TOP VIEW

52pin DIP

STK392-020

STV8379

TDA6111Q/N4

TDA7265

TDA7315D013TR

TOP VIEW

20pin SOP

TDA9178T/N1.118

TOP VIEW

24pin SOP

TLC5733AIPM

TOP VIEW

64pin QFP

TL431CLP
TL431CLP-Z20
μPC1093J-1-T

REF   *CATHODE*
ANODE

2SA1175-HFE
2SA1309A-QRSTA
2SA933AS-QT
2SA933AS-RT
2SC3311A-QRSTA

LETTER SIDE

E C B

2SA1208
2SA1208-T
2SC2551-O
2SC2551O-TPE2

E C B

2SA2005
2SC5022-02
2SC5811

2SB733-34
2SB734-34
2SB734-T-2
2SB734-T-4

2SC2688-LK

DTC144EKA
DTC144EKA-T146
2SA1037AK-T146-QR
2SA1037AK-T146-R
2SA1037K-T-146-R
2SA1162-G
2SB709A-QRS-TX
2SC1623-L5L6
2SC2412K-T-146-QR
2SC2412K-T-146-R
2SC2412K-T-146-S
2SD2114K
2SD2114KT146
2SD601A-Q
2SD601A-QRS-TX

2SC5047-YB

2SK2036(TE85L)

2SK2251-01-F19

2SK2663

DAN202K
DAN202K-T-146

LETTER SIDE

DA204K
DA204K-T-146

2SC4632LS-CB7

B C
E

DTZ-TT11-15B
DTZ24B
DTZ4.7C
DTZ5.1B
DTZ9.1
MA111-(K8).SO
MA111-TX
MA113-(TX)
RD12SB2
UDZ-TE-17-12B
UDZ-TE-17-15B
UDZ-TE-17-2.4B
UDZ-TE-17-24B
UDZ-TE-17-3.9B
UDZ-TE-17-4.7B
UDZ-TE-17-5.1B
UDZ-TE-17-6.2B
UDZ-TE-17-6.8B
UDZ-TE-17-8.2B
UDZ-TE-17-9.1B
1SS355TE-17

ANODE   *CATHODE*

D1NL20U-TR
D1N86
D1N86-TA2
EGP20G
EL1Z
EL1Z-V1
ERA22-06
ERA22-06TP3
GP08D
GP08DL-6563
GP08DPKG23
RGP02-20EL-6394
RGP10GPKG23
RGP15GPKG23
UF4005PKG23
1SS83
1SS83TD

CATHODE

ANODE

D1N20R
D1N20R-TA2
D1NL40-TA2
D1N84
MTZJ-13
MTZJ-13B
MTZJ-7.5B
MTZJ-T-72-13B
MTZJ-T-77-10B
MTZJ-T-77-13
MTZJ-T-77-13B
MTZJ-T-77-15
MTZJ-T-77-2.2A
MTZJ-T-77-24
MTZJ-T-77-36B
MTZJ-T-77-5.1B
MTZJ-T-77-7.5B
RD10ESB2
RD13ES-B2
RD6.1E5B2
1SS133T-77

D1NL20U-TR

D5L60

ERC04-06SE
MTZJ-T-72-18B

CATHODE

ANODE

ERC38-06

CATHODE

ANODE

D10SC4M
D10SC4M-F
D10SC6M-4012

ERD08M-15

CATHODE

ANODE

D10SC6MR

FMG-36S-LF024-104

D22SB60A-F04
D4SB60L
D4SBL20U
D4SB84
D4SB84-F
D6SB60L
RBA-406B
RBV-406B

MA3062M-TX
MA3220M-TX

MA8039

ANODE

CATHODE

ON3171-R

SPR-325MVW

ANODE (GREEN)   *ANODE (RED)*
CATHODE

7-6. IC BLOCK DIAGRAMS

- J1 (2/2) BOARD IC8601
  TDA9178T

- B3 (1/5) BOARD IC504
  TLC2933IPWR

- B3 (5/5) BOARD IC303
  CXA3266Q

- E BOARD IC4301
  CXA2100AQ

- BD (1/2) BOARD IC2602,
  2604, 2609, 2614, 2623, 2625
  PCM56P

- B3 (2/5) BOARD IC604
  CXA1875AM

- B3 (2/5) BOARD IC603
- BD (1/2) BOARD IC2612
  TLC2932IPW

- CR BOARD IC7101
- CG BOARD IC7201
- CB BOARD IC7301
 TDA6111Q

- G, G1 BOARD IC6301
  DM-58

- G, G1 BOARD IC6004
  MCR5152

SECTION 8

EXPLODED VIEWS

NOTE:
- Items with no part number and no description are not stocked because they are seldom required for routine service.
- The construction parts of an assembled part are indicated with a collation number in the remark column.

- Items marked " * " are not stocked since they are seldom required for routine service. Some delay should be anticipated when ordering these items.

The components identified by shading and mark ⚠ are critical for safety. Replace only with part number specified.

8-1. SCREEN AND COVER BLOCK (KP-ES43)

○ : 7-685-663-79   +BVTP 4X16

REF.NO.	PART NO.	DESCRIPTION	REMARK	REF.NO.	PART NO.	DESCRIPTION	REMARK
1	X-4037-770-1	BEZEL (43) ASSY		12	4-076-587-01	MIRROR (43)	
2	4-378-522-31	SCREW, TAPPING, HEXAGON HEAD		13	* 4-076-588-01	COVER (43), MIRROR	
3	4-076-507-11	SCREEN (43AR), CONTRAST		14	4-077-433-01	BUSHING, RUBBER	
4	4-075-439-11	PLATE (43L), DIFFUSION		15	4-058-870-01	SCREW, (4X16) W (+) P TAPPING	
5	4-070-285-11	PLATE (43F), DIFFUSION		16	* 4-076-578-01	BOARD (43), REAR	
6	* 4-205-155-01	COVER, SENSOR		17	1-529-792-11	SPEAKER (12 CM)	
7	1-528-864-11	BATTERY, SOLAR		18	1-529-791-11	SPEAKER (10 CM)	
8	* 4-066-132-01	HOLDER, SENSOR		19	* 4-075-384-01	COVER (R), FRONT	
9	* 4-076-698-01	HOLDER, SCREEN		20	* 4-075-385-01	COVER (L), FRONT	
10	* 4-076-698-31	HOLDER, SCREEN		21	X-4037-767-1	GRILLE ASSY, SPEAKER	
11	* 4-066-129-01	HOLDER, MIRROR					

8-2. CONTROL PANEL AND CABINET BLOCK (KP-ES43)

△ : 7-685-648-79   +BVTP 3X12
○ : 7-685-663-79   +BVTP 4X16

The components identified by shading
and mark △ are critical for safety.
Replace only with part number specified.

PICTURE
TUBE BLOCK

MAIN BRACKET
BLOCK

REF.NO.	PART NO.	DESCRIPTION	REMARK	REF.NO.	PART NO.	DESCRIPTION	REMARK
51	X-4037-769-1	DOOR ASSY	52	60	4-071-995-01	BUTTON, POWER	
52	4-076-581-01	PLATE, CATCHER		61	* A-1372-803-A	H1 BOARD, COMPLETE	
53	4-075-390-01	PANEL (F)		62	* 1-761-348-11	PWB, MOUNTED (NET WORK)	
54	X-4037-768-1	PANEL ASSY, CONTROL	55, 56	63	4-378-522-31	SCREW, TAPPING, HEXAGON HEAD	
55	3-736-779-01	MAGNET		64	4-076-577-01	FOOT	
56	4-075-383-01	DAMPER UNIT		65	4-063-421-02	LATCH (K)	
57	4-075-391-01	BUTTON, MALTI		66	* X-4037-766-1	CABINET (43) ASSY	63-65
58	* 4-075-389-01	BRACKET, H1		67	△ 1-223-925-11	RESISTOR ASSY (HIGH-VOLTAGE)	
59	* A-1372-804-A	H2 BOARD, COMPLETE				(FOCUS PACK)	

8-3. SCREEN AND COVER BLOCK (KP-ES48)

○ : 7-685-663-79   +BVTP 4X16

REF.NO.	PART NO.	DESCRIPTION	REMARK	REF.NO.	PART NO.	DESCRIPTION	REMARK
101	X-4037-794-1	BEZNET (48) ASSY		111	* 4-075-234-01	HOLDER (TOP), MIRROR	
102	4-378-522-31	SCREW, TAPPING, HEXAGON HEAD		112	* 4-076-705-01	HOLDER (SL), MIRROR	
103	4-064-041-11	SCREEN (48), CONTRAST		113	* 4-076-706-01	HOLDER (SR), MIRROR	
104	4-075-440-11	PLATE (48L), DIFFUSION		114	4-076-704-01	MIRROR (48)	
105	4-058-455-12	PLATE (F), DIFFUSION		115	* 4-076-707-01	COVER (48), MIRROR	
106	* 4-205-155-01	COVER, SENSOR		116	* 4-076-696-01	BOARD, REAR	
107	1-528-864-11	BATTERY, SOLAR		117	1-529-643-11	SPEAKER (13 CM)	
108	* 4-066-132-01	HOLDER, SENSOR		118	1-529-403-11	SPEAKER (6.6 CM)	
109	* 4-076-698-01	HOLDER, SCREEN		119	X-4037-793-1	GRILLE ASSY, SPEAKER	
110	* 4-076-698-11	HOLDER, SCREEN					

## 8-4. CONTROL PANEL AND CABINET BLOCK (KP-ES48)

▲ : 7-685-534-19   +BTP 2.6X8

△ : 7-685-648-79   +BTP 3X12

● : 7-685-663-71   +BVTP 4X16

> The components identified by shading and mark ⚠ are critical for safety. Replace only with part number specified.

PICTURE
TUBE BLOCK

MAIN BRACKET
BLOCK

REF.NO.	PART NO.	DESCRIPTION	REMARK	REF.NO.	PART NO.	DESCRIPTION	REMARK
151	X-4037-796-1	TRAY (L) ASSY	152-154	166	X-4037-795-1	TRAY (R) ASSY	167-169
152	4-072-001-03	TRAY (L)		167	4-076-701-01	LABEL (R), TOP	
153	4-071-990-11	LABEL (L), CONTROL		168	4-072-000-03	TRAY (R)	
154	4-076-702-01	LABEL (L), TOP		169	4-071-989-01	LABEL (R), CONTROL	
155	4-071-999-12	PANEL (T)		170	* A-1372-788-A	H2 BOARD, CONTROL	
156	4-072-007-21	PANEL (C)		171	* A-1372-789-A	H3 BOARD, CONTROL	
157	X-4037-024-6	PANEL ASSY, CONTROL	158, 159	172	* 4-075-256-01	SKIRT, FRONT	
158	4-071-997-01	BUTTON, MULTI		173	4-378-522-31	SCREW, TAPPING, HEXAGON HEAD	
159	4-919-393-01	DAMPER		174	* X-4037-792-1	CABINET (48) ASSY	173, 175-177
160	4-071-995-01	BUTTON, POWER		175	4-063-421-02	LATCH (K)	
161	* A-1372-787-A	H1 BOARD, COMPLETE		176	4-075-874-01	FOOT, PLASTIC	
162	* 4-071-998-01	BRACKET (HA)		177	4-075-244-01	CASTER (30 DIA.)	
163	X-4037-221-2	HOLDER ASSY, TRAY	164	178	* 4-054-825-01	BRACKET, FOCUS PACK	
164	4-047-464-01	CATCHER, PUSH		179	⚠ 1-223-925-11	RESISTOR ASSY (HIGH-VOLTAGE)	
165	4-071-987-02	SPRING (T)				(FOCUS PACK)	

## 8-5. SCREEN AND COVER BLOCK (KP-ES53)

■ : 7-685-661-79   +BVTP 4X12
○ : 7-685-663-79   +BVTP 4X16

| REF.NO.	PART NO.	DESCRIPTION	REMARK	REF.NO.	PART NO.	DESCRIPTION	REMARK
201	X-4037-799-1	BEZNET (53) ASSY		211	* 4-075-234-01	HOLDER (TOP), MIRROR	
202	4-378-522-31	SCREW, TAPPING, HEXAGON HEAD		212	* 4-069-687-01	HOLDER (LS), MIRROR	
203	4-064-186-11	SCREEN (53), CONTRAST		213	4-070-344-01	MIRROR, REFLECTION	
204	4-070-525-11	PLATE (L), DIFFUSION		214	* 4-069-688-01	HOLDER (RS), MIRROR	
205	4-076-506-11	PLATE (53FV), DIFFUSION		215	* 4-069-694-01	COVER, MIRROR	
206	* 4-205-155-01	COVER, SENSOR		216	* 4-076-711-01	BOARD, REAR	
207	1-528-864-11	BATTERY, SOLAR		217	1-529-403-11	SPEAKER (6.6 CM)	
208	* 4-066-132-01	HOLDER, SENSOR		218	1-529-405-11	SPEAKER (13 CM)	
209	* 4-075-270-01	HOLDER (53) S, SCREEN		219	X-4037-798-1	GRILLE ASSY, SPEAKER	
210	* 4-075-269-01	HOLDER (53) L, SCREEN					

8-6. CONTROL PANEL AND CABINET BLOCK (KP-ES53)

▲ : 7-685-534-19   +BTP 2.6X8
△ : 7-685-648-79   +BTP 3X12
● : 7-685-663-71   +BVTP 4X16

The components identified by shading
and mark △ are critical for safety.
Replace only with part number specified.

PICTURE
TUBE BLOCK

MAIN BRACKET
BLOCK

REF.NO.	PART NO.	DESCRIPTION	REMARK		REF.NO.	PART NO.	DESCRIPTION	REMARK
251	X-4037-796-1	TRAY (L) ASSY	252-254		266	X-4037-795-1	TRAY (R) ASSY	267-269
252	4-072-001-03	TRAY (L)			267	4-076-701-01	LABEL (R), TOP	
253	4-071-990-11	LABEL (L), CONTROL			268	4-072-000-03	TRAY (R)	
254	4-076-702-01	LABEL (L), TOP			269	4-071-989-01	LABEL (R), CONTROL	
255	4-071-999-12	PANEL (T)			270	* A-1372-788-A	H2 BOARD, COMPLETE	
256	4-072-007-21	PANEL (C)			271	* A-1372-789-A	H3 BOARD, COMPLETE	
257	X-4037-024-6	PANEL ASSY, CONTROL	258, 259		272	* 4-074-349-01	SKIRT (53), FRONT	
258	4-071-997-01	BUTTON, MULTI			273	4-378-522-31	SCREW, TAPPING, HEXAGON HEAD	
259	4-919-393-01	DAMPER			274	* X-4037-797-1	CABINET (53) ASSY, BOTTOM	
260	4-071-995-01	BUTTON, POWER						273, 275-277
					275	4-063-421-02	LATCH (K)	
261	* A-1372-787-A	H1 BOARD, COMPLETE						
262	* 4-071-998-01	BRACKET (HA)			276	4-075-874-01	FOOT, PLASTIC	
263	X-4037-221-2	HOLDER ASSY, TRAY	264		277	* 4-075-244-01	CASTER (DIA. 30)	
264	4-047-464-01	CATCHER, PUSH			278	* 4-054-825-01	BRACKET, FOCUS PACK	
265	4-071-987-02	SPRING (T)			279	△ 1-223-925-11	RESISTOR ASSY (HIGH-VOLTAGE)	
							(FOCUS PACK)	

8-7. SCREEN AND COVER BLOCK (KP-ES61)

■ : 7-685-661-79   +BVTP 4X12
○ : 7-685-663-79   +BVTP 4X16

REF.NO.	PART NO.	DESCRIPTION	REMARK	REF.NO.	PART NO.	DESCRIPTION	REMARK
301	X-4037-791-1	BEZNET (61) ASSY		311	* 4-070-345-01	HOLDER (TOP), MIRROR	
302	4-378-522-31	SCREW, TAPPING, HEXAGON HEAD		312	* 4-069-689-01	HOLDER (L), MIRROR	
303	4-071-950-11	SCREEN (61), CONTRAST		313	4-070-922-01	MIRROR, REFLECTION	
304	4-070-283-11	PLATE (L), DIFFUSION		314	* 4-069-690-01	HOLDER (R), MIRROR	
305	4-066-082-11	PLATE (F), DIFFUSION		315	* 4-069-695-01	COVER, MIRROR	
306	* 4-205-155-01	COVER, SENSOR		316	* 4-076-692-01	BOARD, REAR	
307	1-528-864-11	BATTERY, SOLAR		317	1-529-758-11	SPEAKER (8 CM)	
308	* 4-066-132-01	HOLHDER, SENSOR		318	1-529-759-11	SPEAKER (16 CM)	
309	4-072-006-01	HOLDER (V61), SCREEN		319	1-529-757-11	SPEAKER (2.7 CM)	
310	4-072-005-01	HOLDER (H61), SCREEN		320	X-4037-790-1	GRILLE (61) ASSY, SPEAKER	

8-8. CONTROL PANEL AND CABINET BLOCK (KP-ES61)

▲ : 7-685-534-19   +BTP 2.6X8

△ : 7-685-648-79   +BVTP 3X12

● : 7-685-663-71   +BVTP 4X16

> The components identified by shading
> and mark ⚠ are critical for safety.
> Replace only with part number specified.

PICTURE
TUBE BLOCK

MAIN BRACKET
BLOCK

REF.NO.	PART NO.	DESCRIPTION	REMARK	REF.NO.	PART NO.	DESCRIPTION	REMARK
351	X-4037-796-1	TRAY (L) ASSY	352-354	367	4-076-701-01	LABEL (R), TOP	
352	4-072-001-03	TRAY (L)		368	4-072-000-03	TRAY (R)	
353	4-071-990-11	LABEL (L), CONTROL		369	4-071-989-01	LABEL (R), CONTROL	
354	4-076-702-01	LABEL (L), TOP		370	* A-1372-788-A	H2 BOARD, COMPLETE	
355	4-071-999-12	PANEL (T)		371	* A-1372-789-A	H3 BOARD, COMPLETE	
356	4-072-007-21	PANEL (C)		372	4-072-013-11	SKIRT (61), FRONT	
357	X-4037-024-6	PANEL ASSY, CONTROL	358, 359	373	4-378-522-31	SCREW, TAPPING, HEXAGON HEAD	
358	4-071-997-01	BUTTON, MULTI		374	* X-4037-789-1	CABINET (61) ASSY	373, 375-378
359	4-919-393-01	DAMPER		375	4-063-421-02	LATCH (K)	
360	4-071-995-01	BUTTON, POWER		376	4-075-874-01	FOOT, PLASTIC	
361	* A-1372-787-A	H1 BOARD, COMPLETE		377	4-030-850-01	SOCKET, CASTER	
362	* 4-071-998-01	BRACKET (HA)		378	4-039-546-01	CASTER	
363	X-4037-221-2	HOLDER ASSY, TRAY	364	379	* 4-054-825-01	BRACKET, FOCUS PACK	
364	4-047-464-01	CATCHER, PUSH		380	⚠ 1-223-925-11	RESISTOR ASSY (HIGH-VOLTAGE) (FOCUS PACK)	
365	4-071-987-02	SPRING (T)					
366	X-4037-795-1	TRAY (R) ASSY	367-369				

8-9. MAIN BRACKET BLOCK

△ : 7-685-648-79   +BVTP 3X12
○ : 7-685-663-79   +BVTP 4X16

> The components identified by shading
> and mark ⚠ are critical for safety.
> Replace only with part number specified.

REF.NO.	PART NO.	DESCRIPTION	REMARK
401	* A-1299-176-A	A1 BOARD, COMPLETE	
402	* A-1346-922-A	E BOARD, COMPLETE	
404	* A-1306-588-A	M1 BOARD, COMPLETE	
405	1-543-982-11	CORE, FERRITE	
406	* A-1136-087-A	B3 BOARD, COMPLETE	
407	* A-1394-982-A	J1 BOARD, COMPLETE	
408	* A-1136-088-A	BD BOARD, COMPLETE	
409	4-076-679-01	TERMINAL BOARD	
410	1-790-082-11	CABLE, RF	
411	* 4-316-015-00	HOLDER, WIRE	
412	* 4-046-677-11	HOLDER (B), PRINTED CIRCUIT BOARD	
413	* A-1346-923-A	D BOARD, COMPLETE (ES48)	
413	* A-1346-924-A	D BOARD, COMPLETE (ES53)	
413	* A-1346-925-A	D BOARD, COMPLETE (ES61)	
413	* A-1346-937-A	D BOARD, COMPLETE (ES43)	
414	⚠ 1-574-062-52	CORD, POWER (WITH CONNECTOR) (ES43ME1/MN1, ES48ME1/MN1, ES53ME1/MN1. ES61ME1/MN1)	
414	⚠ 1-792-002-11	CORD. POWER (WITH FILTER) (ES43HK1, ES48HK1, ES53HK1, ES61HK1)	
414	⚠ 1-792-035-11	CORD. POWER (WITH FILTER) (ES43SN1, ES48SN1, ES53SN1, ES61SN1)	
415	4-022-115-00	HOLDER, AC CORD	
416	* A-1316-514-A	G1 BOARD, COMPLETE (ES43ME1/MN1, ES48ME1/MN1, ES53ME1/MN1, ES61ME1/MN1)	
416	* A-1316-528-A	G BOARD, COMPLETE (ES43HK1/SN1, ES48HK1/SN1, ES53HK1/SN1, ES61HK1/SN1)	
417	* A-1343-830-A	DS BOARD, COMPLETE	
418	⚠ 1-453-335-11	TRANSFORMER ASSY, FLYBACK NX-4010//M	

8-10. PICTURE TUBE BLOCK

● : 7-685-663-71   +BVTP 4X16

> The components identified by shading
> and mark ⚠ are critical for safety.
> Replace only with part number specified.

REF.NO.	PART NO.	DESCRIPTION	REMARK
451	* A-1332-037-A	CR BOARD, COMPLETE	
452	⚠ 1-452-790-41	NECK ASSY (NA-295)	
453	* A-1391-025-A	ZR BOARD, COMPLETE	454
454	⚠ 1-451-476-21	DEFLECTION YOKE	
455	⚠ 8-733-571-15	PICTURE TUBE 07MXC2 (R) (HEATER)	(ES43)
455	⚠ 8-733-572-15	PICTURE TUBE 07MXC3 (R) (HEATER)	(ES48. ES53)
455	⚠ 8-733-573-15	PICTURE TUBE 07MXC4 (R) (HEATER)	(ES61)
456	4-040-131-21	LENS (LINNIT POINT 6) (ES61)	
456	4-056-258-11	LENS (DELTA 78) (EXCEPT ES61)	
457	⚠ 8-733-570-15	PICTURE TUBE 07MXC2 (G) (HEATER)	
458	* A-1391-026-A	ZG BOARD, COMPLETE	454

REF.NO.	PART NO.	DESCRIPTION	REMARK
459	* A-1332-038-A	CG BOARD, COMPLETE	
460	⚠ 8-733-574-15	PICTURE TUBE 07MAC2 (B) (HEATER)	(ES43)
460	⚠ 8-733-575-15	PICTURE TUBE 07MAC3 (B) (HEATER)	(ES48, ES53)
460	⚠ 8-733-576-15	PICTURE TUBE 07MAC4 (B) (HEATER)	(ES61)
461	* A-1391-027-A	ZB BOARD, COMPLETE	454
462	* A-1332-039-A	CB BOARD, COMPLETE	
463	4-373-137-01	CAP (Z), RUBBER	
464	⚠ 8-598-955-12	BLOCK ASSY, HIGH-VOLTAGE	
465	* 4-066-144-02	HOLDER, HVR	
466	* 4-066-135-01	STAY (R), SIDE	
467	* 4-066-134-01	STAY (L), SIDE	

SECTION 9

ELECTRICAL PARTS LIST

H1

NOTE:

> The components identified by shading and mark ⚠ are critical for safety.
> Replace only with part number specified.

> When indicating parts by reference number, please include the board name.

The components identified by ⊠ in this manual have been carefully factory-selected for each set in order to satisfy regulations regarding X-ray radiation. Should replacement be required, replace only with the value originally used.

• All variable and adjustable resistors have characteristic curve B, unless otherwise noted.

RESISTORS
• All resistors are in ohms
• F : nonflammable

• Items marked " * " are not stocked since they are seldom required for routine service. Some delay should be anticipated when ordering these items.

• CAPACITORS
  PF : µµF

• There are some cases the reference number on one board overlaps on the other board. Therefore, when ordering parts by the reference number, please include the board name.

REF.NO.	PART NO.	DESCRIPTION			REMARK
	* A-1372-787-A	H1 BOARD, COMPLETE			
					(ES48, ES53, ES61)
		*****************************			
	* 4-072-004-01	HOLDER, LED (D3002)			
		<CAPACITOR>			
C3101	1-126-157-11	ELECT	10µF	20%	16V
		<CONNECTOR>			
CN3101	* 1-564-519-11	PLUG, CONNECTOR 4P			
CN3102	* 1-564-525-11	PLUG, CONNECTOR 10P			
CN3103	* 1-580-689-11	PIN, CONNECTOR (PC BOARD) 4P			
CN3104	* 1-691-291-11	PIN, CONNECTOR (PC BOARD) 5P			
		<DIODE>			
D3002	8-719-064-11	DIODE SPR-325MVW			
					(ON/STANDBY/TIMER)
		<IC>			
IC3101	8-742-205-30	HYB IC SBX3081-01(30)			
		<TRANSISTOR>			
Q3101	8-729-120-28	TRANSISTOR 2SC1623-L5L6			
Q3102	8-729-120-28	TRANSISTOR 2SC1623-L5L6			
		<RESISTOR>			
R3101	1-208-780-11	METAL CHIP	820	0.5%	1/10W
R3102	1-208-788-11	METAL CHIP	1.8K	0.5%	1/10W
R3103	1-208-793-11	METAL CHIP	3K	0.5%	1/10W
R3104	1-208-798-11	METAL CHIP	4.7K	0.5%	1/10W
R3105	1-216-041-00	RES-CHIP	470	5%	1/10W
R3106	1-216-037-00	RES-CHIP	330	5%	1/10W
R3107	1-208-806-11	METAL CHIP	10K	0.5%	1/10W

REF.NO.	PART NO.	DESCRIPTION			REMARK
R3108	1-216-049-91	RES-CHIP	1K	5%	1/10W
R3109	1-208-806-11	METAL CHIP	10K	0.5%	1/10W
R3110	1-216-295-91	SHORT	0		
R3111	1-216-295-91	SHORT	0		
R3112	1-216-295-91	SHORT	0		
R3113	1-216-033-00	RES-CHIP	220	5%	1/10W
R3115	1-208-804-11	METAL CHIP	8.2K	0.5%	1/10W
		<SWITCH>			
S3101	1-692-431-21	SWITCH, TACTIL (PROG +)			
S3102	1-692-431-21	SWITCH, TACTIL (PROG –)			
S3103	1-692-431-21	SWITCH, TACTIL (VOL +)			
S3104	1-692-431-21	SWITCH, TACTIL (VOL –)			
S3105	1-692-431-21	SWITCH, TACTIL (TV/VIDEO)			
S3106	⚠ 1-571-433-31	SWITCH, PUSH (AC POWER) (POWER)			
		***			
	* A-1372-803-A	H1 BOARD, COMPLETE (ES43)			
		*****************************			
	* 4-072-004-01	HOLDER, LED (D3101)			
		<CAPACITOR>			
C3101	1-126-157-11	ELECT	10µF	20%	16V
		<CONNECTOR>			
CN3101	* 1-580-689-11	PIN, CONNECTOR (PC BOARD) 4P			
CN3102	* 1-691-291-11	PIN, CONNECTOR (PC BOARD) 5P			
CN3103	* 1-564-508-11	PLUG, CONNECTOR 5P			
		<DIODE>			
D3103	8-719-064-11	DIODE SPR-325MVW			
					(ON/STANDBY/TIMER)
		<IC>			
IC3101	8-742-205-30	HYB IC SBX3081-01(30)			

H1 H2

The components identified by shading
and mark ⚠ are critical for safety.
Replace only with part number specified.

REF.NO.	PART NO.	DESCRIPTION			REMARK

\<TRANSISTOR\>

| Q3101 | 8-729-120-28 TRANSISTOR 2SC1623-L5L6 |
| Q3102 | 8-729-120-28 TRANSISTOR 2SC1623-L5L6 |

\<RESISTOR\>

REF.NO.	PART NO.	DESCRIPTION			REMARK
R3101	1-216-295-91 SHORT	0		
R3102	1-216-037-00 RES-CHIP	330	5%	1/10W
R3103	1-216-295-91 SHORT	0		
R3104	1-216-295-91 SHORT	0		
R3105	1-216-037-00 RES-CHIP	330	5%	1/10W
R3106	1-216-295-91 SHORT	0		
R3107	1-216-041-00 RES-CHIP	470	5%	1/10W
R3108	1-208-806-11 METAL CHIP	10K	0.5%	1/10W
R3109	1-208-806-11 METAL CHIP	10K	0.5%	1/10W

\<SWITCH\>

| S3101 | ⚠1-571-433-31 SWITCH, PUSH (AC POWER) (POWER) |

****

* A-1372-788-A H2 BOARD, COMPLETE
(ES48, ES53, ES61)
****

\<CAPACITOR\>

C3201	1-126-157-11 ELECT	10µF	20%	16V
C3202	1-163-037-11 CERAMIC CHIP 0.022µF		10%	50V
C3203	1-163-037-11 CERAMIC CHIP 0.022µF		10%	50V
C3204	1-163-037-11 CERAMIC CHIP 0.022µF		10%	50V

\<CONNECTOR\>

| CN3201 | *1-564-519-11 PLUG, CONNECTOR 4P |
| CN3202 | *1-564-520-11 PLUG, CONNECTOR 5P |

\<DIODE\>

| D3203 | 8-719-976-96 DIODE DTZ4.7C |

\<JACK\>

| J3201 | 1-691-293-11 JACK (HEAD PHONE) |

\<CHIP CONDUCTOR\>

| JR3206 | 1-216-295-91 SHORT | 0 |

\<COIL\>

| L3201 | 1-414-189-31 INDUCTOR | 100µH |
| L3202 | 1-414-189-31 INDUCTOR | 100µH |

\<TRANSISTOR\>

| Q3201 | 8-729-120-28 TRANSISTOR 2SC1623-L5L6 |

\<RESISTOR\>

REF.NO.	PART NO.	DESCRIPTION			REMARK
R3200	1-216-295-91 SHORT	0		
R3201	1-208-798-11 METAL CHIP	4.7K	0.5%	1/10W
R3202	1-208-792-11 METAL CHIP	2.7K	0.5%	1/10W
R3203	1-208-785-11 METAL CHIP	1.3K	0.5%	1/10W
R3204	1-208-806-11 METAL CHIP	10K	0.5%	1/10W
R3205	1-216-295-91 SHORT	0		
R3206	1-216-073-00 RES-CHIP	10K	5%	1/10W
R3207	1-216-033-00 RES-CHIP	220	5%	1/10W
R3208	1-216-033-00 RES-CHIP	220	5%	1/10W
R3209	1-216-033-00 RES-CHIP	220	5%	1/10W
R3210	1-216-033-00 RES-CHIP	220	5%	1/10W
R3212	1-216-295-91 SHORT	0		
R3213	1-216-295-91 SHORT	0		
R3219	1-216-033-00 RES-CHIP	220	5%	1/10W

\<SWITCH\>

S3201	1-572-198-11 SWITCH, KEYBOARD (MENU)
S3202	1-572-198-11 SWITCH, KEYBOARD (MENU +)
S3203	1-572-198-11 SWITCH, KEYBOARD (MENU –)
S3204	1-572-198-11 SWITCH, KEYBOARD (ENTER)
S3205	1-572-198-11 SWITCH, KEYBOARD (AUTO CONVER)
S3206	1-572-198-11 SWITCH, KEYBOARD (AUTO PROGR)

****

* A-1372-804-A H2 BOARD, COMPLETE (ES43)
****

\<CAPACITOR\>

C3201	1-126-157-11 ELECT	10µF	20%	16V
C3202	1-163-037-11 CERAMIC CHIP 0.022µF		10%	50V
C3203	1-163-037-11 CERAMIC CHIP 0.022µF		10%	50V
C3206	1-163-037-11 CERAMIC CHIP 0.022µF		10%	50V

\<CONNECTOR\>

CN3201	*1-564-519-11 PLUG, CONNECTOR 4P
CN3202	*1-564-520-11 PLUG, CONNECTOR 5P
CN3203	*1-564-526-31 PLUG, CONNECTOR 11P

\<DIODE\>

| D3207 | 8-719-976-96 DIODE DTZ4.7C |

\<JACK\>

J3201	1-691-293-11 JACK (HEAD PHONE)
J3202	1-565-665-12 TERMINAL, S 4P (VIDEO IN 4/S VIDEO)
J3203	1-565-745-11 PIN JACK BLOCK 3P (VIDEO IN 4)

KP-ES43HK1/ME1/MN1/SN1, ES48HK1/ME1/MN1/SN1, ES53HK1/ME1/MN1/SN1, ES61HK1/ME1/MN1/SN1 RM-961

H2 H3 ZR

REF.NO.	PART NO.	DESCRIPTION			REMARK
		<COIL>			
L3201	1-414-189-31	INDUCTOR	100µH		
L3202	1-414-189-31	INDUCTOR	100µH		
		<TRANSISTOR>			
Q3201	8-729-120-28	TRANSISTOR 2SC1623-L5L6			
		<RESISTOR>			
R3201	1-208-780-11	METAL CHIP	820	0.5%	1/10W
R3202	1-208-788-11	METAL CHIP	1.8K	0.5%	1/10W
R3203	1-208-793-11	METAL CHIP	3K	0.5%	1/10W
R3204	1-208-798-11	METAL CHIP	4.7K	0.5%	1/10W
R3205	1-208-804-11	METAL CHIP	8.2K	0.5%	1/10W
R3206	1-208-798-11	METAL CHIP	4.7K	0.5%	1/10W
R3207	1-208-792-11	METAL CHIP	2.7K	0.5%	1/10W
R3208	1-208-785-11	METAL CHIP	1.3K	0.5%	1/10W
R3209	1-208-806-11	METAL CHIP	10K	0.5%	1/10W
R3210	1-216-295-91	SHORT	0		
R3211	1-216-295-91	SHORT	0		
R3212	1-216-073-00	RES-CHIP	10K	5%	1/10W
R3213	1-216-033-00	RES-CHIP	220	5%	1/10W
R3214	1-216-033-00	RES-CHIP	220	5%	1/10W
R3215	1-216-033-00	RES-CHIP	220	5%	1/10W
R3216	1-216-033-00	RES-CHIP	220	5%	1/10W
R3217	1-216-025-91	RES-CHIP	100	5%	1/10W
R3218	1-216-025-91	RES-CHIP	100	5%	1/10W
R3219	1-216-033-00	RES-CHIP	220	5%	1/10W
		<SWITCH>			
S3201	1-572-198-11	SWITCH, KEYBOARD (PROG +)			
S3202	1-572-198-11	SWITCH, KEYBOARD (PROG –)			
S3203	1-572-198-11	SWITCH, KEYBOARD (VOL +)			
S3204	1-572-198-11	SWITCH, KEYBOARD (VOL –)			
S3205	1-572-198-11	SWITCH, KEYBOARD (TV/VIDEO)			
S3206	1-572-198-11	SWITCH, KEYBOARD (MENU)			
S3207	1-572-198-11	SWITCH, KEYBOARD (MENU +)			
S3208	1-572-198-11	SWITCH, KEYBOARD (MENU –)			
S3209	1-572-198-11	SWITCH, KEYBOARD (ENTER)			
S3210	1-572-198-11	SWITCH, KEYBOARD (AUTO CONVER)			
S3211	1-572-198-11	SWITCH, KEYBOARD (AUTO PROGR)			

****

* A-1372-789-A H3 BOARD, COMPLETE
(ES48, ES53, ES61)
****

REF.NO.	PART NO.	DESCRIPTION			REMARK
		<CAPACITOR>			
CN3301	* 1-564-526-31	PLUG, CONNECTOR 11P			
		<JACK>			
J3301	1-568-807-21	TERMINAL BLOCK, (S) 4P (VIDEO IN 4)			

REF.NO.	PART NO.	DESCRIPTION			REMARK
		<RESISTOR>			
R3301	1-216-025-00	RES-CHIP	100	5%	1/10W
R3302	1-216-025-00	RES-CHIP	100	5%	1/10W

****

* A-1391-025-A ZR BOARD, COMPLETE
****

4-382-854-11 SCREW (M3X10), P, SW (+)
(Q7408, Q7409)

REF.NO.	PART NO.	DESCRIPTION			REMARK
		<CAPACITOR>			
C7401	1-163-038-91	CERAMIC CHIP 0.1µF			25V
C7402	1-163-021-91	CERAMIC CHIP 0.01µF		10%	50V
C7403	1-163-021-91	CERAMIC CHIP 0.01µF		10%	50V
C7404	1-104-664-11	ELECT	47µF	20%	16V
C7405	1-163-021-91	CERAMIC CHIP 0.01µF		10%	50V
C7406	1-163-021-91	CERAMIC CHIP 0.01µF		10%	50V
C7407	1-104-989-91	MYLAR	0.0022µF	10%	200V
C7408	1-104-989-91	MYLAR	0.0022µF	10%	200V
C7409	1-107-667-11	ELECT	2.2µF	20%	160V
C7410	1-130-471-00	MYLAR	0.001µF	5%	50V
C7411	1-130-471-00	MYLAR	0.001µF	5%	50V
C7412	1-107-364-11	MYLAR	0.01µF	10%	200V
C7413	1-126-968-11	ELECT	100µF	20%	50V
C7414	1-126-968-11	ELECT	100µF	20%	50V
C7415	1-107-645-11	ELECT	22µF	20%	200V
C7416	1-161-830-00	CERAMIC	0.0047µF		500V
C7418	1-126-935-11	ELECT	470µF	20%	6.3V
		<CONNECTOR>			
CN7401	* 1-564-509-11	PLUG, CONNECTOR 6P			
CN7403	* 1-564-518-11	PLUG, CONNECTOR 3P			
CN7404	* 1-564-507-11	PLUG, CONNECTOR 4P			
CN7405	* 1-580-844-11	PIN, CONNECTOR (POWER)			
		<DIODE>			
D7401	8-719-988-61	DIODE 1SS355TE-17			
D7403	8-719-921-86	DIODE MTZJ-13			
D7404	8-719-921-86	DIODE MTZJ-13			
		<CONNECTOR>			
DY7401	⚠ 1-451-476-21	DEFLECTION YOKE (R)			
		<COIL>			
L7401	1-412-911-11	FERRITE	0µH		
L7402	1-414-187-11	INDUCTOR	47µH		
		<TRANSISTOR>			
Q7401	8-729-120-28	TRANSISTOR 2SC1623-L5L6			
Q7402	8-729-026-49	TRANSISTOR 2SA1037AK-T146-R			

ZR ZG

The components identified by shading
and mark ⚠ are critical for safety.
Replace only with part number specified.

REF.NO.	PART NO.	DESCRIPTION			REMARK
Q7403	8-729-120-28	TRANSISTOR 2SC1623-L5L6			
Q7404	8-729-026-49	TRANSISTOR 2SA1037AK-T146-R			
Q7405	8-729-120-28	TRANSISTOR 2SC1623-L5L6			
Q7406	8-729-119-76	TRANSISTOR 2SA1175-HFE			
Q7407	8-729-423-33	TRANSISTOR 2SC3311A-QRSTA			
Q7408	8-729-045-04	TRANSISTOR 2SC5511			
Q7409	8-729-045-05	TRANSISTOR 2SA2005			
Q7410	8-729-120-28	TRANSISTOR 2SC1623-L5L6			
		<RESISTOR>			
R7401	1-208-790-11	METAL CHIP	2.2K	0.5%	1/10W
R7402	1-208-800-11	METAL CHIP	5.6K	0.5%	1/10W
R7403	1-208-806-11	METAL CHIP	10K	0.5%	1/10W
R7404	1-208-806-11	METAL CHIP	10K	0.5%	1/10W
R7405	1-216-475-11	METAL OXIDE	120	5%	3W
R7406	1-216-073-00	RES-CHIP	10K	5%	1/10W
R7407	1-249-385-11	CARBON	2.2	5%	1/4W
R7408	1-216-475-11	METAL OXIDE	120	5%	3W
R7409	1-216-009-91	RES-CHIP	22	5%	1/10W
R7410	1-216-009-91	RES-CHIP	22	5%	1/10W
R7411	1-249-414-11	CARBON	560	5%	1/4W
R7412	1-216-033-00	RES-CHIP	220	5%	1/10W
R7413	1-216-049-91	RES-CHIP	1K	5%	1/10W
R7414	1-216-033-00	RES-CHIP	220	5%	1/10W
R7415	1-216-049-91	RES-CHIP	1K	5%	1/10W
R7416	1-216-001-00	RES-CHIP	10	5%	1/10W
R7417	1-249-414-11	CARBON	560	5%	1/4W
R7418	1-216-001-00	RES-CHIP	10	5%	1/10W
R7419	1-249-415-11	CARBON	680	5%	1/4W
R7420	1-249-433-11	CARBON	22K	5%	1/4W
R7421	1-249-433-11	CARBON	22K	5%	1/4W
R7422	1-249-415-11	CARBON	680	5%	1/4W
R7423	1-249-417-11	CARBON	1K	5%	1/4W
R7424	1-249-405-11	CARBON	100	5%	1/4W
R7425	1-249-385-11	CARBON	2.2	5%	1/4W
R7426	1-249-385-11	CARBON	2.2	5%	1/4W
R7427	1-249-405-11	CARBON	100	5%	1/4W
R7428	1-215-913-11	METAL OXIDE	220	5%	3W
R7431	1-216-049-91	RES-CHIP	1K	5%	1/10W
R7432	1-216-025-91	RES-CHIP	100	5%	1/10W
R7433	1-216-009-91	RES-CHIP	22	5%	1/10W
R7434	1-216-295-91	SHORT	0		

****

* A-1391-026-A ZG BOARD, COMPLETE
****

4-382-854-11 SCREW (M3X10), P, SW (+)
(Q7608, Q7609)

<CAPACITOR>

C7601	1-163-021-91	CERAMIC CHIP 0.01μF	10%	50V
C7602	1-163-021-91	CERAMIC CHIP 0.01μF	10%	50V
C7603	1-163-038-91	CERAMIC CHIP 0.1μF		25V
C7604	1-104-664-11	ELECT	47μF	20%	16V
C7605	1-104-989-91	MYLAR	0.0022μF	10%	200V

C7606	1-104-989-91	MYLAR	0.0022μF	10%	200V
C7607	1-107-667-11	ELECT	2.2μF	20%	160V
C7608	1-130-471-00	MYLAR	0.001μF	5%	50V
C7609	1-130-471-00	MYLAR	0.001μF	5%	50V
C7610	1-163-021-91	CERAMIC CHIP 0.01μF		10%	50V
C7611	1-163-021-91	CERAMIC CHIP 0.01μF		10%	50V
C7612	1-107-364-11	MYLAR	0.01μF	10%	200V
C7613	1-126-968-11	ELECT	100μF	20%	50V
C7614	1-126-968-11	ELECT	100μF	20%	50V
C7615	1-107-645-11	ELECT	22μF	20%	200V
C7616	1-161-830-00	CERAMIC	0.0047μF		500V
C7617	1-106-220-00	MYLAR	0.1μF	10%	100V
C7618	1-106-220-00	MYLAR	0.1μF	10%	100V
C7620	1-126-935-11	ELECT	470μF	20%	6.3V
C7621	1-126-960-11	ELECT	1μF	20%	50V

<CONNECTOR>

CN7601	* 1-564-509-11	PLUG, CONNECTOR 6P
CN7602	* 1-564-509-11	PLUG, CONNECTOR 6P
CN7603	* 1-564-507-11	PLUG, CONNECTOR 4P
CN7604	* 1-564-506-11	PLUG, CONNECTOR 3P
CN7605	* 1-564-506-11	PLUG, CONNECTOR 3P
CN7606	* 1-580-689-11	PIN, CONNECTOR (PC BOARD) 4P
CN7607	* 1-564-506-11	PLUG, CONNECTOR 3P
CN7608	* 1-564-507-11	PLUG, CONNECTOR 4P
CN7609	1-695-915-11	TAB (CONTACT)

<DIODE>

D7601	8-719-921-86	DIODE MTZJ-13
D7602	8-719-921-86	DIODE MTZJ-13
D7603	8-719-988-61	DIODE 1SS355TE-17

<CONNECTOR>

DY7601 ⚠ 1-451-476-21 DEFLECTION YOKE (G)

<COIL>

L7601	1-412-911-11	FERRITE	0μH
L7602	1-414-187-11	INDUCTOR	47μH

<TRANSISTOR>

Q7601	8-729-120-28	TRANSISTOR 2SC1623-L5L6
Q7602	8-729-119-76	TRANSISTOR 2SA1175-HFE
Q7603	8-729-423-33	TRANSISTOR 2SC3311A-QRSTA
Q7604	8-729-026-49	TRANSISTOR 2SA1037AK-T146-R
Q7605	8-729-120-28	TRANSISTOR 2SC1623-L5L6
Q7606	8-729-026-49	TRANSISTOR 2SA1037AK-T146-R
Q7607	8-729-120-28	TRANSISTOR 2SC1623-L5L6
Q7608	8-729-045-04	TRANSISTOR 2SC5511
Q7609	8-729-045-05	TRANSISTOR 2SA2005
Q7610	8-729-120-28	TRANSISTOR 2SC1623-L5L6

REF.NO.	PART NO.	DESCRIPTION			REMARK
		<RESISTOR>			
R7601	1-208-806-11	METAL CHIP	10K	0.5%	1/10W
R7602	1-208-790-11	METAL CHIP	2.2K	0.5%	1/10W
R7603	1-208-800-11	METAL CHIP	5.6K	0.5%	1/10W
R7604	1-208-806-11	METAL CHIP	10K	0.5%	1/10W
R7605	1-216-475-11	METAL OXIDE	120	5%	3W
R7606	1-216-033-00	RES-CHIP	220	5%	1/10W
R7607	1-216-033-00	RES-CHIP	220	5%	1/10W
R7608	1-249-393-11	CARBON	10	5%	1/4W
R7609	1-216-001-00	RES-CHIP	10	5%	1/10W
R7610	1-249-385-11	CARBON	2.2	5%	1/4W
R7611	1-216-475-11	METAL OXIDE	120	5%	3W
R7612	1-249-414-11	CARBON	560	5%	1/4W
R7613	1-216-073-00	RES-CHIP	10K	5%	1/10W
R7614	1-249-414-11	CARBON	560	5%	1/4W
R7615	1-249-415-11	CARBON	680	5%	1/4W
R7616	1-249-433-11	CARBON	22K	5%	1/4W
R7617	1-249-433-11	CARBON	22K	5%	1/4W
R7618	1-249-415-11	CARBON	680	5%	1/4W
R7619	1-216-009-91	RES-CHIP	22	5%	1/10W
R7620	1-216-009-91	RES-CHIP	22	5%	1/10W
R7621	1-249-417-11	CARBON	1K	5%	1/4W
R7622	1-216-049-91	RES-CHIP	1K	5%	1/10W
R7623	1-216-049-91	RES-CHIP	1K	5%	1/10W
R7624	1-249-405-11	CARBON	100	5%	1/4W
R7625	1-249-385-11	CARBON	2.2	5%	1/4W
R7626	1-249-385-11	CARBON	2.2	5%	1/4W
R7627	1-249-405-11	CARBON	100	5%	1/4W
R7628	1-215-913-11	METAL OXIDE	220	5%	3W
R7631	1-216-049-91	RES-CHIP	1K	5%	1/10W
R7632	1-216-025-91	RES-CHIP	100	5%	1/10W
R7633	1-216-009-91	RES-CHIP	22	5%	1/10W
R7634	1-216-295-91	SHORT	0		

****

* A-1391-027-A ZB BOARD, COMPLETE

****

4-382-854-11 SCREW (M3X10), P, SW (+)
(Q7808, Q7809)

<CAPACITOR>

C7801	1-163-021-91	CERAMIC CHIP	0.01µF	10%	50V
C7802	1-163-021-91	CERAMIC CHIP	0.01µF	10%	50V
C7803	1-163-038-91	CERAMIC CHIP	0.1µF		25V
C7804	1-104-664-11	ELECT	47µF	20%	16V
C7805	1-104-989-91	MYLAR	0.0022µF	10%	200V
C7806	1-104-989-91	MYLAR	0.0022µF	10%	200V
C7807	1-107-667-11	ELECT	2.2µF	20%	160V
C7808	1-130-471-00	MYLAR	0.001µF	5%	50V
C7809	1-130-471-00	MYLAR	0.001µF	5%	50V
C7810	1-163-021-91	CERAMIC CHIP	0.01µF	10%	50V
C7811	1-163-021-91	CERAMIC CHIP	0.01µF	10%	50V
C7812	1-107-364-11	MYLAR	0.01µF	10%	200V
C7813	1-126-968-11	ELECT	100µF	20%	50V
C7814	1-126-968-11	ELECT	100µF	20%	50V

REF.NO.	PART NO.	DESCRIPTION			REMARK
C7815	1-107-645-11	ELECT	22µF	20%	200V
C7816	1-161-830-00	CERAMIC	0.0047µF		500V
C7818	1-126-935-11	ELECT	470µF	20%	6.3V
		<CONNECTOR>			
CN7801	* 1-564-509-11	PLUG, CONNECTOR 6P			
CN7802	* 1-564-507-11	PLUG, CONNECTOR 4P			
CN7803	* 1-564-506-11	PLUG, CONNECTOR 3P			
CN7804	* 1-580-844-11	PIN, CONNECTOR (POWER)			
CN7805	* 1-564-506-11	PLUG, CONNECTOR 3P			
		<DIODE>			
D7801	8-719-921-86	DIODE MTZJ-13			
D7802	8-719-921-86	DIODE MTZJ-13			
D7803	8-719-988-61	DIODE 1SS355TE-17			
		<CONNECTOR>			
DY7801	⚠1-451-476-21	DEFLECTION YOKE (B)			
		<COIL>			
L7801	1-412-911-11	FERRITE	0µH		
L7802	1-414-187-11	INDUCTOR	47µH		
		<TRANSISTOR>			
Q7801	8-729-120-28	TRANSISTOR 2SC1623-L5L6			
Q7802	8-729-119-76	TRANSISTOR 2SA1175-HFE			
Q7803	8-729-423-33	TRANSISTOR 2SC3311A-QRSTA			
Q7804	8-729-026-49	TRANSISTOR 2SA1037AK-T146-R			
Q7805	8-729-120-28	TRANSISTOR 2SC1623-L5L6			
Q7806	8-729-026-49	TRANSISTOR 2SA1037AK-T146-R			
Q7807	8-729-120-28	TRANSISTOR 2SC1623-L5L6			
Q7808	8-729-045-04	TRANSISTOR 2SC5511			
Q7809	8-729-045-05	TRANSISTOR 2SA2005			
Q7810	8-729-120-28	TRANSISTOR 2SC1623-L5L6			
		<RESISTOR>			
R7801	1-208-806-11	METAL CHIP	10K	0.5%	1/10W
R7802	1-208-790-11	METAL CHIP	2.2K	0.5%	1/10W
R7803	1-208-800-11	METAL CHIP	5.6K	0.5%	1/10W
R7804	1-208-806-11	METAL CHIP	10K	0.5%	1/10W
R7805	1-216-033-00	RES-CHIP	220	5%	1/10W
R7806	1-216-033-00	RES-CHIP	220	5%	1/10W
R7807	1-216-475-11	METAL OXIDE	120	5%	3W
R7808	1-216-001-00	RES-CHIP	10	5%	1/10W
R7809	1-216-001-00	RES-CHIP	10	5%	1/10W
R7810	1-249-385-11	CARBON	2.2	5%	1/4W
R7811	1-216-475-11	METAL OXIDE	120	5%	3W
R7812	1-216-073-00	RES-CHIP	10K	5%	1/10W
R7813	1-249-414-11	CARBON	560	5%	1/4W
R7814	1-216-009-91	RES-CHIP	22	5%	1/10W
R7815	1-216-009-91	RES-CHIP	22	5%	1/10W

ZB CR

REF.NO.	PART NO.	DESCRIPTION			REMARK
R7816	1-249-414-11	CARBON	560	5%	1/4W
R7817	1-249-415-11	CARBON	680	5%	1/4W
R7818	1-249-433-11	CARBON	22K	5%	1/4W
R7819	1-249-433-11	CARBON	22K	5%	1/4W
R7820	1-249-415-11	CARBON	680	5%	1/4W
R7821	1-249-417-11	CARBON	1K	5%	1/4W
R7822	1-216-049-91	RES-CHIP	1K	5%	1/10W
R7823	1-216-049-91	RES-CHIP	1K	5%	1/10W
R7824	1-249-405-11	CARBON	100	5%	1/4W
R7825	1-249-385-11	CARBON	2.2	5%	1/4W
R7826	1-249-385-11	CARBON	2.2	5%	1/4W
R7827	1-249-405-11	CARBON	100	5%	1/4W
R7828	1-215-913-11	METAL OXIDE	220	5%	3W
R7831	1-216-049-91	RES-CHIP	1K	5%	1/10W
R7832	1-216-025-91	RES-CHIP	100	5%	1/10W
R7833	1-216-009-91	RES-CHIP	22	5%	1/10W
R7834	1-216-295-91	SHORT	0		

****

* A-1332-037-A CR BOARD, COMPLETE
****

4-382-854-01 SCREW (M3X8), P, SW (+) (IC7101)

<CAPACITOR>

C7102	1-162-115-00	CERAMIC	330pF	10%	2KV
C7103	1-107-652-11	ELECT	10µF	20%	250V
C7104	1-126-768-11	ELECT	2200µF	20%	16V
C7105	1-162-115-00	CERAMIC	330pF	10%	2KV
C7106	1-163-038-91	CERAMIC CHIP 0.1µF			25V
C7107	1-163-038-91	CERAMIC CHIP 0.1µF			25V
C7108	1-126-967-11	ELECT	47µF	20%	50V
C7110	1-102-050-00	CERAMIC	0.01µF	99%	500V
C7111	1-161-830-00	CERAMIC	0.0047µF		500V
C7112	1-163-224-11	CERAMIC CHIP 7pF		0.25pF	50V
C7116	1-107-957-11	ELECT	1µF	20%	250V
C7118	1-164-004-11	CERAMIC CHIP 0.1µF		10%	25V

<CONNECTOR>

CN7101	* 1-564-512-11	PLUG, CONNECTOR 9P	
CN7102	* 1-564-510-11	PLUG, CONNECTOR 7P	
CN7103	* 1-564-512-11	PLUG, CONNECTOR 9P	
CN7104	1-785-879-11	CONNECTOR, ONE TOUCH	
CN7107	1-695-915-11	TAB (CONTACT)	

<DIODE>

D7102	8-719-921-86	DIODE MTZJ-13
D7103	8-719-901-83	DIODE 1SS83
D7104	8-719-901-83	DIODE 1SS83
D7105	8-719-901-83	DIODE 1SS83
D7106	8-719-901-83	DIODE 1SS83
D7108	8-719-988-61	DIODE 1SS355TE-17
D7109	8-719-921-86	DIODE MTZJ-13
D7110	8-719-921-86	DIODE MTZJ-13

<IC>

IC7101	8-759-360-83	IC TDA6111Q/N4

<JACK>

J7101	⚠ 1-251-182-41	SOCKET, PICTURE TUBE

<COIL>

L7102	1-414-223-11	INDUCTOR	470µH
L7103	1-414-181-11	INDUCTOR	4.7µH
L7104	1-414-187-11	INDUCTOR	47µH

<NEON LAMP>

NL7101	1-576-354-21	GAP, SPARK
NL7102	1-517-729-31	GAP, SPARK
NL7103	1-576-354-21	GAP, SPARK
NL7104	1-576-354-21	GAP, SPARK
NL7105	1-576-354-21	GAP, SPARK

<TRANSISTOR>

Q7101	8-729-026-49	TRANSISTOR 2SA1037AK-T146-R
Q7103	8-729-255-12	TRANSISTOR 2SC2551-O
Q7104	8-729-026-49	TRANSISTOR 2SA1037AK-T146-R

<RESISTOR>

R7101	1-260-132-11	CARBON	560K	5%	1/2W
R7102	1-249-389-11	CARBON	4.7	5%	1/4W
R7103	1-216-295-91	SHORT	0		
R7105	1-260-117-11	CARBON	33K	5%	1/2W
R7106	1-219-743-11	CARBON	100	5%	1/2W
R7107	1-208-801-11	METAL CHIP	6.2K	0.5%	1/10W
R7108	1-260-133-11	CARBON	680K	5%	1/2W
R7109	1-208-808-11	METAL CHIP	12K	0.5%	1/10W
R7110	1-208-790-11	METAL CHIP	2.2K	0.5%	1/10W
R7111	1-216-033-00	RES-CHIP	220	5%	1/10W
R7112	1-249-424-11	CARBON	3.9K	5%	1/4W
R7113	1-216-295-91	SHORT	0		
R7114	1-216-660-11	METAL CHIP	2.4K	0.5%	1/10W
R7115	1-208-782-11	METAL CHIP	1K	0.5%	1/10W
R7116	1-215-929-11	METAL OXIDE	100K	5%	3W
R7117	1-260-093-11	CARBON	330	5%	1/2W
R7118	1-260-087-11	CARBON	100	5%	1/2W
R7119	1-260-099-11	CARBON	1K	5%	1/2W
R7120	1-216-081-00	RES-CHIP	22K	5%	1/10W
R7122	1-216-025-91	RES-CHIP	100	5%	1/10W
R7123	1-216-295-91	SHORT	0		
R7124	1-216-073-00	RES-CHIP	10K	5%	1/10W
R7128	1-208-818-11	METAL CHIP	33K	0.5%	1/10W
R7129	1-249-417-11	CARBON	1K	5%	1/4W
R7130	1-216-069-00	RES-CHIP	6.8K	5%	1/10W
R7131	1-216-049-91	RES-CHIP	1K	5%	1/10W
R7132	1-216-295-91	SHORT	0		

CR **CG**

REF.NO.	PART NO.	DESCRIPTION		REMARK	REF.NO.	PART NO.	DESCRIPTION		REMARK
R7133	1-208-834-11	METAL CHIP	150K	0.5% 1/10W			\<JACK\>		
R7134	1-216-049-91	RES-CHIP	1K	5% 1/10W					
R7135	1-216-053-00	RES-CHIP	1.5K	5% 1/10W	J7201	⚠1-251-182-41	SOCKET, PICTURE TUBE		
		\<SPARK GAP\>					\<COIL\>		
SG7101	1-519-422-11	GAP, SPARK			L7201	1-414-223-11	INDUCTOR	470µH	
SG7103	1-519-422-11	GAP, SPARK			L7203	1-414-181-11	INDUCTOR	4.7µH	
					L7204	1-414-187-11	INDUCTOR	47µH	
		\<TEST PIN\>							
							\<NEON LAMP\>		
TP7102	*1-535-881-21	TERMINAL, TP (AUTO INSERTION)							
TP7105	*1-535-881-21	TERMINAL, TP (AUTO INSERTION)			NL7201	1-576-354-21	GAP, SPARK		
***					NL7202	1-576-354-21	GAP, SPARK		
					NL7203	1-517-729-31	GAP, SPARK		
	*A-1332-038-A	CG BOARD, COMPLETE			NL7204	1-576-354-21	GAP, SPARK		
	******************************				NL7205	1-576-354-21	GAP, SPARK		
	4-382-854-01	SCREW (M3X8), P, SW (+) (IC7201)					\<TRANSISTOR\>		
					Q7201	8-729-026-49	TRANSISTOR 2SA1037AK-T146-R		
		\<CAPACITOR\>			Q7202	8-729-026-49	TRANSISTOR 2SA1037AK-T146-R		
					Q7203	8-729-255-12	TRANSISTOR 2SC2551-O		
C7202	1-162-115-00	CERAMIC	330pF	10% 2KV					
C7203	1-126-768-11	ELECT	2200µF	20% 16V					
C7204	1-107-652-11	ELECT	10µF	20% 250V			\<RESISTOR\>		
C7205	1-163-038-91	CERAMIC CHIP 0.1µF		25V					
C7206	1-163-038-91	CERAMIC CHIP 0.1µF		25V	R7201	1-260-132-11	CARBON	560K	5% 1/2W
					R7202	1-216-295-91	SHORT	0	
C7207	1-162-115-00	CERAMIC	330pF	10% 2KV	R7203	1-208-846-11	METAL CHIP	470K	0.5% 1/10W
C7208	1-126-967-11	ELECT	47µF	20% 50V	R7204	1-219-743-11	CARBON	100	5% 1/2W
C7209	1-102-050-00	CERAMIC	0.01µF	99% 500V	R7205	1-260-117-11	CARBON	33K	5% 1/2W
C7211	1-161-830-00	CERAMIC	0.0047µF	500V					
C7212	1-163-091-00	CERAMIC CHIP 8pF	0.25pF	50V	R7206	1-208-801-11	METAL CHIP	6.2K	0.5% 1/10W
					R7207	1-208-808-11	METAL CHIP	12K	0.5% 1/10W
C7213	1-163-085-00	CERAMIC CHIP 2pF	0.25pF	50V	R7208	1-216-033-00	RES-CHIP	220	5% 1/10W
C7214	1-126-964-11	ELECT	10µF	20% 50V	R7209	1-260-133-11	CARBON	680K	5% 1/2W
C7216	1-107-957-11	ELECT	1µF	20% 250V	R7210	1-208-790-11	METAL CHIP	2.2K	0.5% 1/10W
					R7211	1-249-424-11	CARBON	3.9K	5% 1/4W
		\<CONNECTOR\>			R7212	1-208-789-11	METAL CHIP	2K	0.5% 1/10W
CN7201	*1-564-510-11	PLUG, CONNECTOR 7P			R7213	1-215-929-11	METAL OXIDE	100K	5% 3W
CN7202	*1-564-509-11	PLUG, CONNECTOR 6P			R7214	1-216-295-91	SHORT	0	
CN7203	*1-564-512-11	PLUG, CONNECTOR 9P			R7215	1-208-782-11	METAL CHIP	1K	0.5% 1/10W
CN7204	*1-564-512-11	PLUG, CONNECTOR 9P							
CN7205	1-785-879-11	CONNECTOR, ONE TOUCH			R7216	1-260-093-11	CARBON	330	5% 1/2W
					R7217	1-216-295-91	SHORT	0	
CN7208	1-695-915-11	TAB (CONTACT)			R7218	1-260-099-11	CARBON	1K	5% 1/2W
					R7219	1-216-295-91	SHORT	0	
		\<DIODE\>			R7220	1-216-025-91	RES-CHIP	100	5% 1/10W
D7202	8-719-921-86	DIODE MTZJ-13			R7222	1-216-295-91	SHORT	0	
D7203	8-719-901-83	DIODE 1SS83			R7223	1-208-802-11	METAL CHIP	6.8K	0.5% 1/10W
D7204	8-719-901-83	DIODE 1SS83			R7224	1-208-799-11	METAL CHIP	5.1K	0.5% 1/10W
D7205	8-719-901-83	DIODE 1SS83			R7225	1-216-081-00	RES-CHIP	22K	5% 1/10W
D7206	8-719-901-83	DIODE 1SS83			R7229	1-249-417-11	CARBON	1K	5% 1/4W
D7208	8-719-988-61	DIODE 1SS355TE-17			R7235	1-216-053-00	RES-CHIP	1.5K	5% 1/10W
		\<IC\>					\<SPARK GAP\>		
IC7201	8-759-360-83	IC TDA6111Q/N4			SG7201	1-519-422-11	GAP, SPARK		
					SG7203	1-519-422-11	GAP, SPARK		

CG **CB**

The components identified by shading
and mark ⚠ are critical for safety.
Replace only with part number specified.

REF.NO.	PART NO.	DESCRIPTION			REMARK

<TEST PIN>

TP7202	* 1-535-881-21	TERMINAL, TP (AUTO INSERTION)
TP7205	* 1-535-881-21	TERMINAL, TP (AUTO INSERTION)

****

* A-1332-039-A CB BOARD, COMPLETE
****

4-382-854-01 SCREW (M3X8), P, SW (+) (IC7301)

<CAPACITOR>

REF.NO.	PART NO.	DESCRIPTION			
C7302	1-162-115-00	CERAMIC	330pF	10%	2KV
C7303	1-162-115-00	CERAMIC	330pF	10%	2KV
C7304	1-126-768-11	ELECT	2200µF	20%	16V
C7305	1-163-038-91	CERAMIC CHIP 0.1µF			25V
C7306	1-163-038-91	CERAMIC CHIP 0.1µF			25V
C7307	1-107-652-11	ELECT	10µF	20%	250V
C7308	1-126-967-11	ELECT	47µF	20%	50V
C7309	1-163-085-00	CERAMIC CHIP 2pF	0.25pF		50V
C7311	1-102-050-00	CERAMIC	0.01µF	99%	500V
C7312	1-161-830-00	CERAMIC	0.0047µF		500V
C7313	1-163-091-00	CERAMIC CHIP 8pF	0.25pF		50V
C7314	1-126-964-11	ELECT	10µF	20%	50V
C7315	1-126-960-11	ELECT	1µF	20%	50V
C7318	1-107-957-11	ELECT	1µF	20%	250V

<CONNECTOR>

CN7301	* 1-564-509-11	PLUG, CONNECTOR 6P
CN7302	* 1-564-512-11	PLUG, CONNECTOR 9P
CN7303	* 1-564-512-11	PLUG, CONNECTOR 9P
CN7304	1-785-879-11	CONNECTOR, ONE TOUCH
CN7307	1-695-915-11	TAB (CONTACT)

<DIODE>

D7302	8-719-921-86	DIODE MTZJ-13
D7303	8-719-901-83	DIODE 1SS83
D7304	8-719-901-83	DIODE 1SS83
D7305	8-719-901-83	DIODE 1SS83
D7306	8-719-901-83	DIODE 1SS83
D7307	8-719-988-61	DIODE 1SS355TE-17
D7308	8-719-921-88	DIODE MTZJ-13B
D7309	8-719-988-61	DIODE 1SS355TE-17
D7311	8-719-921-86	DIODE MTZJ-13
D7312	8-719-921-86	DIODE MTZJ-13

<IC>

IC7301	8-759-360-83	IC TDA6111Q/N4

<JACK>

J7301	⚠ 1-251-182-41	SOCKET, PICTURE TUBE

<COIL>

L7301	1-414-223-11	INDUCTOR	470µH
L7303	1-414-181-11	INDUCTOR	4.7µH
L7304	1-414-187-11	INDUCTOR	47µH

<NEON LAMP>

NL7301	1-576-354-21	GAP, SPARK
NL7302	1-517-729-31	GAP, SPARK
NL7303	1-576-354-21	GAP, SPARK
NL7304	1-576-354-21	GAP, SPARK
NL7305	1-576-354-21	GAP, SPARK

<TRANSISTOR>

Q7301	8-729-026-49	TRANSISTOR 2SA1037AK-T146-R
Q7302	8-729-026-49	TRANSISTOR 2SA1037AK-T146-R
Q7303	8-729-255-12	TRANSISTOR 2SC2551-O
Q7305	8-729-120-28	TRANSISTOR 2SC1623-L5L6
Q7306	8-729-026-49	TRANSISTOR 2SA1037AK-T146-R

<RESISTOR>

REF.NO.	PART NO.	DESCRIPTION			
R7301	1-219-743-11	CARBON	100	5%	1/2W
R7302	1-260-132-11	CARBON	560K	5%	1/2W
R7304	1-216-295-91	SHORT	0		
R7306	1-260-099-11	CARBON	1K	5%	1/2W
R7307	1-208-801-11	METAL CHIP	6.2K	0.5%	1/10W
R7308	1-260-133-11	CARBON	680K	5%	1/2W
R7309	1-208-790-11	METAL CHIP	2.2K	0.5%	1/10W
R7310	1-216-295-91	SHORT	0		
R7311	1-208-808-11	METAL CHIP	12K	0.5%	1/10W
R7312	1-216-660-11	METAL CHIP	2.4K	0.5%	1/10W
R7313	1-216-033-00	RES-CHIP	220	5%	1/10W
R7314	1-249-424-11	CARBON	3.9K	5%	1/4W
R7315	1-216-295-91	SHORT	0		
R7316	1-215-929-11	METAL OXIDE	100K	5%	3W
R7317	1-260-093-11	CARBON	330	5%	1/2W
R7318	1-216-295-91	SHORT	0		
R7319	1-208-798-11	METAL CHIP	4.7K	0.5%	1/10W
R7320	1-260-087-11	CARBON	100	5%	1/2W
R7321	1-260-117-11	CARBON	33K	5%	1/2W
R7322	1-208-782-11	METAL CHIP	1K	0.5%	1/10W
R7323	1-216-025-91	RES-CHIP	100	5%	1/10W
R7324	1-216-295-91	SHORT	0		
R7326	1-208-803-11	METAL CHIP	7.5K	0.5%	1/10W
R7327	1-208-798-11	METAL CHIP	4.7K	0.5%	1/10W
R7328	1-216-073-00	RES-CHIP	10K	5%	1/10W
R7329	1-216-091-00	RES-CHIP	56K	5%	1/10W
R7330	1-216-081-00	RES-CHIP	22K	5%	1/10W
R7331	1-216-055-00	RES-CHIP	1.8K	5%	1/10W
R7332	1-216-081-00	RES-CHIP	22K	5%	1/10W
R7335	1-249-417-11	CARBON	1K	5%	1/4W
R7336	1-216-053-00	RES-CHIP	1.5K	5%	1/10W

CB **B3**

REF.NO.	PART NO.	DESCRIPTION	REMARK		
		<SPARK GAP>			
SG7301	1-519-422-11	GAP, SPARK			
SG7303	1-519-422-11	GAP, SPARK			
		<TEST PIN>			
TP7302	*1-535-881-21	TERMINAL, TP (AUTO INSERTION)			
TP7304	*1-535-881-21	TERMINAL, TP (AUTO INSERTION)			
		***			
	*A-1136-087-A	B3 BOARD, COMPLETE			
		******************************			
		<CAPACITOR>			
C302	1-117-136-11	ELECT CHIP 10µF	20%	6.3V	
C305	1-163-038-91	CERAMIC CHIP 0.1µF		25V	
C306	1-163-038-91	CERAMIC CHIP 0.1µF		25V	
C309	1-163-038-91	CERAMIC CHIP 0.1µF		25V	
C310	1-163-038-91	CERAMIC CHIP 0.1µF		25V	
C312	1-163-275-11	CERAMIC CHIP 0.001µF	5%	50V	
C313	1-163-038-91	CERAMIC CHIP 0.1µF		25V	
C314	1-164-004-11	CERAMIC CHIP 0.1µF	10%	25V	
C315	1-163-251-11	CERAMIC CHIP 100pF	5%	50V	
C316	1-163-038-91	CERAMIC CHIP 0.1µF		25V	
C317	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V	
C318	1-124-779-00	ELECT CHIP 10µF	20%	16V	
C319	1-126-394-11	ELECT CHIP 10µF	20%	16V	
C320	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V	
C321	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V	
C323	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V	
C324	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V	
C325	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V	
C327	1-163-038-91	CERAMIC CHIP 0.1µF		25V	
C330	1-163-038-91	CERAMIC CHIP 0.1µF		25V	
C331	1-163-038-91	CERAMIC CHIP 0.1µF		25V	
C332	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V	
C333	1-216-295-91	SHORT 0			
C337	1-163-038-91	CERAMIC CHIP 0.1µF		25V	
C338	1-163-038-91	CERAMIC CHIP 0.1µF		25V	
C339	1-163-038-91	CERAMIC CHIP 0.1µF		25V	
C340	1-163-038-91	CERAMIC CHIP 0.1µF		25V	
C341	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V	
C346	1-163-038-91	CERAMIC CHIP 0.1µF		25V	
C347	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V	
C349	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V	
C350	1-126-396-11	ELECT CHIP 47µF	20%	16V	
C353	1-126-204-11	ELECT CHIP 47µF	20%	16V	
C354	1-117-136-11	ELECT CHIP 10µF	20%	6.3V	
C355	1-117-136-11	ELECT CHIP 10µF	20%	6.3V	
C361	1-124-779-00	ELECT CHIP 10µF	20%	16V	
C362	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V	
C363	1-163-017-00	CERAMIC CHIP 0.0047µF	10%	50V	
C501	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V	
C502	1-124-779-00	ELECT CHIP 10µF	20%	16V	
C503	1-124-779-00	ELECT CHIP 10µF	20%	16V	

REF.NO.	PART NO.	DESCRIPTION	REMARK		
C505	1-124-779-00	ELECT CHIP 10µF	20%	16V	
C507	1-124-779-00	ELECT CHIP 10µF	20%	16V	
C509	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V	
C510	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V	
C511	1-163-038-91	CERAMIC CHIP 0.1µF		25V	
C512	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V	
C514	1-164-004-11	CERAMIC CHIP 0.1µF	10%	25V	
C515	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V	
C516	1-164-004-11	CERAMIC CHIP 0.1µF	10%	25V	
C517	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V	
C518	1-126-204-11	ELECT CHIP 47µF	20%	16V	
C519	1-163-038-91	CERAMIC CHIP 0.1µF		25V	
C520	1-163-038-91	CERAMIC CHIP 0.1µF		25V	
C521	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V	
C522	1-163-038-91	CERAMIC CHIP 0.1µF		25V	
C523	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V	
C524	1-124-779-00	ELECT CHIP 10µF	20%	16V	
C525	1-126-394-11	ELECT CHIP 10µF	20%	16V	
C526	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V	
C527	1-164-004-11	CERAMIC CHIP 0.1µF	10%	25V	
C528	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V	
C530	1-216-295-91	SHORT 0			
C532	1-216-295-91	SHORT 0			
C534	1-216-295-91	SHORT 0			
C538	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V	
C539	1-126-204-11	ELECT CHIP 47µF	20%	16V	
C540	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V	
C542	1-126-204-11	ELECT CHIP 47µF	20%	16V	
C543	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V	
C545	1-126-396-11	ELECT CHIP 47µF	20%	16V	
C546	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V	
C548	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V	
C549	1-126-204-11	ELECT CHIP 47µF	20%	16V	
C550	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V	
C551	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V	
C554	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V	
C555	1-163-038-91	CERAMIC CHIP 0.1µF		25V	
C556	1-126-392-11	ELECT CHIP 100µF	20%	6.3V	
C557	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V	
C559	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V	
C560	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V	
C601	1-126-394-11	ELECT CHIP 10µF	20%	16V	
C602	1-126-394-11	ELECT CHIP 10µF	20%	16V	
C603	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V	
C604	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V	
C605	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V	
C606	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V	
C607	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V	
C608	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V	
C609	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V	
C610	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V	
C611	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V	
C612	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V	
C613	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V	
C614	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V	
C615	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V	

B3

REF.NO.	PART NO.	DESCRIPTION	REMARK		REF.NO.	PART NO.	DESCRIPTION	REMARK	
C616	1-126-396-11	ELECT CHIP 47µF	20%	16V	C835	1-163-038-91	CERAMIC CHIP 0.1µF		25V
C617	1-163-038-91	CERAMIC CHIP 0.1µF		25V	C837	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V
C618	1-163-038-91	CERAMIC CHIP 0.1µF		25V					
					C839	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V
C619	1-163-038-91	CERAMIC CHIP 0.1µF		25V	C840	1-126-206-11	ELECT CHIP 100µF	20%	6.3V
C620	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V	C841	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V
C621	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V	C842	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V
C622	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V	C843	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V
C623	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V					
					C844	1-163-038-91	CERAMIC CHIP 0.1µF		25V
C624	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V	C848	1-163-017-00	CERAMIC CHIP 0.0047µF	10%	50V
C625	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V	C849	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V
C626	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V	C850	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V
C627	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V	C851	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V
C628	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V					
					C852	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V
C629	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V	C853	1-164-182-11	CERAMIC CHIP 0.0033µF	10%	50V
C630	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V	C854	1-163-038-91	CERAMIC CHIP 0.1µF		25V
C631	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V	C901	1-163-038-91	CERAMIC CHIP 0.1µF		25V
C632	1-126-206-11	ELECT CHIP 100µF	20%	6.3V	C902	1-163-038-91	CERAMIC CHIP 0.1µF		25V
C633	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V					
					C903	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V
C634	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V	C904	1-124-779-00	ELECT CHIP 10µF	20%	16V
C635	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V	C905	1-109-982-11	CERAMIC CHIP 1µF	10%	10V
C636	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V	C906	1-124-779-00	ELECT CHIP 10µF	20%	16V
C637	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V	C907	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V
C638	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V					
					C908	1-163-031-11	CERAMIC CHIP 0.01µF		50V
C639	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V	C909	1-126-396-11	ELECT CHIP 47µF	20%	16V
C640	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V	C910	1-163-009-11	CERAMIC CHIP 0.001µF	10%	50V
C642	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V	C913	1-163-031-11	CERAMIC CHIP 0.01µF		50V
C643	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V	C914	1-126-394-11	ELECT CHIP 10µF	20%	16V
C644	1-126-398-11	ELECT CHIP 4.7µF	20%	35V					
					C950	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V
C645	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V	C954	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V
C801	1-124-779-00	ELECT CHIP 10µF	20%	16V					
C802	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V					
C803	1-124-779-00	ELECT CHIP 10µF	20%	16V			<CONNECTOR>		
C804	1-124-779-00	ELECT CHIP 10µF	20%	16V					
					CN502	1-695-302-11	CONNECTOR, BOARD TO BOARD 50P		
C806	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V					
C807	1-124-779-00	ELECT CHIP 10µF	20%	16V			<DIODE>		
C808	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V					
C809	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V	D301	8-719-041-97	DIODE MA113-(TX)		
C810	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V	D302	8-719-041-97	DIODE MA113-(TX)		
					D501	8-719-422-12	DIODE MA8039		
C811	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V	D601	8-719-073-01	DIODE MA111-(K8).S0		
C812	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V					
C813	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V					
C814	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V			<FERRITBEAD>		
C815	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V					
					FB501	1-414-813-11	FERRITE 0µH		
C816	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V	FB502	1-414-813-11	FERRITE 0µH		
C817	1-163-229-11	CERAMIC CHIP 12pF	5%	50V	FB503	1-414-813-11	FERRITE 0µH		
C818	1-163-229-11	CERAMIC CHIP 12pF	5%	50V	FB504	1-414-813-11	FERRITE 0µH		
C819	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V	FB601	1-414-553-11	FERRITE 0µH		
C820	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V					
C821	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V	FB801	1-414-553-11	FERRITE 0µH		
C822	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V	FB802	1-414-553-11	FERRITE 0µH		
C823	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V					
C824	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V					
C825	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V			<FILTER>		
C827	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V	FL304	1-234-177-21	FILTER, CHIP EMI		
C829	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V	FL305	1-234-177-21	FILTER, CHIP EMI		
C834	1-163-038-91	CERAMIC CHIP 0.1µF		25V	FL306	1-239-558-11	FILTER, CHIP EMI		

REF.NO.	PART NO.	DESCRIPTION	REMARK
FL501	1-233-877-11	FILTER, LOW PASS	
FL502	1-233-504-21	FILTER, LOW PASS	
FL503	1-233-504-21	FILTER, LOW PASS	
FL504	1-234-177-21	FILTER, CHIP EMI	
FL505	1-234-177-21	FILTER, CHIP EMI	
FL506	1-234-177-21	FILTER, CHIP EMI	
FL508	1-234-177-21	FILTER, CHIP EMI	
FL509	1-234-177-21	FILTER, CHIP EMI	
FL510	1-234-177-21	FILTER, CHIP EMI	
FL511	1-234-177-21	FILTER, CHIP EMI	
FL512	1-234-177-21	FILTER, CHIP EMI	
FL601	1-234-177-21	FILTER, CHIP EMI	
FL602	1-234-177-21	FILTER, CHIP EMI	
FL603	1-234-177-21	FILTER, CHIP EMI	
FL606	1-239-560-11	FILTER, CHIP EMI	
FL801	1-234-177-21	FILTER, CHIP EMI	
FL802	1-234-177-21	FILTER, CHIP EMI	
FL803	1-234-177-21	FILTER, CHIP EMI	
FL804	1-234-177-21	FILTER, CHIP EMI	
FL805	1-234-177-21	FILTER, CHIP EMI	
FL806	1-234-177-21	FILTER, CHIP EMI	
FL807	1-234-177-21	FILTER, CHIP EMI	
FL808	1-234-177-21	FILTER, CHIP EMI	
FL810	1-234-177-21	FILTER, CHIP EMI	
FL901	1-234-509-21	FILTER, LOW PASS	
FL902	1-233-876-11	FILTER, LOW PASS	
FL903	1-233-876-11	FILTER, LOW PASS	
FL904	1-234-177-21	FILTER, CHIP EMI	
FL905	1-234-177-21	FILTER, CHIP EMI	
FL906	1-234-177-21	FILTER, CHIP EMI	
FL907	1-234-177-21	FILTER, CHIP EMI	
		<IC>	
IC302	8-752-388-98	IC CXD2303AQ	
IC303	8-752-088-27	IC CXA3266Q-T6	
IC309	8-759-640-16	IC TC7SET04F(TE85R)	
IC311	8-759-708-05	IC NJM78L05A	
IC501	8-759-447-90	IC TLC5733AIPM	
IC504	8-759-669-78	IC TLC2933IPWR-12	
IC505	8-759-640-16	IC TC7SET04F(TE85R)	
IC506	8-759-640-16	IC TC7SET04F(TE85R)	
IC601	8-752-398-47	IC CXD2090Q	
IC602	8-759-665-38	IC MB81F161622C-80FN	
IC603	8-759-669-75	IC TLC2932IPWR	
IC604	8-752-072-94	IC CXA1875AM-T4	
IC801	8-759-672-57	IC CXD9509AQ	
IC802	8-759-595-53	IC MB81F643242B-10FN	
IC803	8-759-460-29	IC PST9120NL	
IC901	8-752-369-84	IC CXD2309Q-T6	
IC902	8-759-683-19	IC MB94918RPF-G124-BND	
IC903	8-759-575-71	IC M24C04-WMN6T	
IC904	8-759-349-11	IC PST9145NL	

REF.NO.	PART NO.	DESCRIPTION			REMARK
		<COIL>			
L302	1-412-029-11	INDUCTOR CHIP	10µH		
L303	1-412-029-11	INDUCTOR CHIP	10µH		
L501	1-412-026-11	INDUCTOR CHIP	1µH		
L502	1-412-026-11	INDUCTOR CHIP	1µH		
L503	1-412-026-11	INDUCTOR CHIP	1µH		
L504	1-412-026-11	INDUCTOR CHIP	1µH		
L505	1-412-029-11	INDUCTOR CHIP	10µH		
L506	1-412-026-11	INDUCTOR CHIP	1µH		
L508	1-412-029-11	INDUCTOR CHIP	10µH		
L509	1-412-029-11	INDUCTOR CHIP	10µH		
L511	1-412-026-11	INDUCTOR CHIP	1µH		
L512	1-412-026-11	INDUCTOR CHIP	1µH		
L604	1-412-029-11	INDUCTOR CHIP	10µH		
L605	1-412-029-11	INDUCTOR CHIP	10µH		
		<TRANSISTOR>			
Q301	8-729-120-28	TRANSISTOR 2SC1623-L5L6			
Q302	8-729-120-28	TRANSISTOR 2SC1623-L5L6			
Q303	8-729-120-28	TRANSISTOR 2SC1623-L5L6			
Q501	8-729-216-22	TRANSISTOR 2SA1162-G			
Q502	8-729-120-28	TRANSISTOR 2SC1623-L5L6			
Q503	8-729-120-28	TRANSISTOR 2SC1623-L5L6			
Q510	8-729-120-28	TRANSISTOR 2SC1623-L5L6			
Q511	8-729-120-28	TRANSISTOR 2SC1623-L5L6			
Q512	8-729-120-28	TRANSISTOR 2SC1623-L5L6			
Q516	8-729-120-28	TRANSISTOR 2SC1623-L5L6			
Q517	8-729-120-28	TRANSISTOR 2SC1623-L5L6			
Q518	8-729-216-22	TRANSISTOR 2SA1162-G			
Q519	1-801-806-11	TRANSISTOR DTC144EKA			
Q520	1-801-806-11	TRANSISTOR DTC144EKA			
Q521	8-729-120-28	TRANSISTOR 2SC1623-L5L6			
Q522	8-729-120-28	TRANSISTOR 2SC1623-L5L6			
Q523	8-729-120-28	TRANSISTOR 2SC1623-L5L6			
Q524	8-729-120-28	TRANSISTOR 2SC1623-L5L6			
Q601	8-729-120-28	TRANSISTOR 2SC1623-L5L6			
Q602	8-729-120-28	TRANSISTOR 2SC1623-L5L6			
Q901	8-729-216-22	TRANSISTOR 2SA1162-G			
Q902	8-729-216-22	TRANSISTOR 2SA1162-G			
Q903	8-729-216-22	TRANSISTOR 2SA1162-G			
Q904	8-729-028-28	TRANSISTOR 2SK2036(TE85L)			
Q905	8-729-028-28	TRANSISTOR 2SK2036(TE85L)			
Q906	1-801-806-11	TRANSISTOR DTC144EKA			
Q907	8-729-216-22	TRANSISTOR 2SA1162-G			
Q908	8-729-216-22	TRANSISTOR 2SA1162-G			
Q909	8-729-216-22	TRANSISTOR 2SA1162-G			
		<RESISTOR>			
R302	1-216-013-00	RES-CHIP	33	5%	1/10W
R303	1-208-798-11	METAL CHIP	4.7K	0.5%	1/10W
R305	1-216-049-91	RES-CHIP	1K	5%	1/10W
R306	1-208-789-11	METAL CHIP	2K	0.5%	1/10W
R309	1-216-009-91	RES-CHIP	22	5%	1/10W
R310	1-216-009-91	RES-CHIP	22	5%	1/10W

B3

REF.NO.	PART NO.	DESCRIPTION		REMARK		REF.NO.	PART NO.	DESCRIPTION		REMARK	
R311	1-216-009-91	RES-CHIP	22	5%	1/10W	R551	1-208-756-11	METAL CHIP	82	0.5%	1/10W
R313	1-216-009-91	RES-CHIP	22	5%	1/10W	R552	1-208-750-11	METAL CHIP	47	0.5%	1/10W
R316	1-216-009-91	RES-CHIP	22	5%	1/10W	R553	1-216-295-91	SHORT	0		
R318	1-216-009-91	RES-CHIP	22	5%	1/10W						
						R554	1-208-750-11	METAL CHIP	47	0.5%	1/10W
R319	1-216-049-91	RES-CHIP	1K	5%	1/10W	R555	1-216-077-91	RES-CHIP	15K	5%	1/10W
R321	1-216-009-91	RES-CHIP	22	5%	1/10W	R557	1-216-049-91	RES-CHIP	1K	5%	1/10W
R323	1-216-009-91	RES-CHIP	22	5%	1/10W	R558	1-216-025-91	RES-CHIP	100	5%	1/10W
R324	1-216-009-91	RES-CHIP	22	5%	1/10W	R559	1-216-077-91	RES-CHIP	15K	5%	1/10W
R325	1-216-073-00	RES-CHIP	10K	5%	1/10W						
						R560	1-208-750-11	METAL CHIP	47	0.5%	1/10W
R328	1-216-025-91	RES-CHIP	100	5%	1/10W	R561	1-216-043-91	RES-CHIP	560	5%	1/10W
R330	1-216-037-00	RES-CHIP	330	5%	1/10W	R562	1-216-043-91	RES-CHIP	560	5%	1/10W
R331	1-216-033-00	RES-CHIP	220	5%	1/10W	R563	1-216-043-91	RES-CHIP	560	5%	1/10W
R332	1-216-037-00	RES-CHIP	330	5%	1/10W	R571	1-216-295-91	SHORT	0		
R333	1-216-295-91	SHORT	0								
						R572	1-208-750-11	METAL CHIP	47	0.5%	1/10W
R335	1-216-013-00	RES-CHIP	33	5%	1/10W	R573	1-208-810-11	METAL CHIP	15K	0.5%	1/10W
R336	1-216-013-00	RES-CHIP	33	5%	1/10W	R574	1-208-782-11	METAL CHIP	1K	0.5%	1/10W
R337	1-216-097-91	RES-CHIP	100K	5%	1/10W	R575	1-208-756-11	METAL CHIP	82	0.5%	1/10W
R338	1-216-295-91	SHORT	0			R576	1-208-756-11	METAL CHIP	82	0.5%	1/10W
R339	1-216-295-91	SHORT	0								
						R577	1-208-750-11	METAL CHIP	47	0.5%	1/10W
R347	1-216-295-91	SHORT	0			R578	1-208-750-11	METAL CHIP	47	0.5%	1/10W
R350	1-216-295-91	SHORT	0			R579	1-216-077-91	RES-CHIP	15K	5%	1/10W
R501	1-216-025-91	RES-CHIP	100	5%	1/10W	R580	1-216-295-91	SHORT	0		
R502	1-216-025-91	RES-CHIP	100	5%	1/10W	R582	1-216-041-00	RES-CHIP	470	5%	1/10W
R503	1-216-295-91	SHORT	0								
						R584	1-216-041-00	RES-CHIP	470	5%	1/10W
R504	1-216-295-91	SHORT	0			R594	1-216-041-00	RES-CHIP	470	5%	1/10W
R505	1-216-295-91	SHORT	0			R596	1-216-049-91	RES-CHIP	1K	5%	1/10W
R506	1-216-009-91	RES-CHIP	22	5%	1/10W	R597	1-216-073-00	RES-CHIP	10K	5%	1/10W
R507	1-216-009-91	RES-CHIP	22	5%	1/10W	R598	1-216-025-91	RES-CHIP	100	5%	1/10W
R508	1-216-025-91	RES-CHIP	100	5%	1/10W						
						R600	1-216-066-00	RES-CHIP	5.1K	5%	1/10W
R509	1-216-025-91	RES-CHIP	100	5%	1/10W	R601	1-216-073-00	RES-CHIP	10K	5%	1/10W
R510	1-216-043-91	RES-CHIP	560	5%	1/10W	R602	1-216-073-00	RES-CHIP	10K	5%	1/10W
R511	1-216-043-91	RES-CHIP	560	5%	1/10W	R603	1-216-073-00	RES-CHIP	10K	5%	1/10W
R512	1-216-043-91	RES-CHIP	560	5%	1/10W	R604	1-216-033-00	RES-CHIP	220	5%	1/10W
R513	1-216-043-91	RES-CHIP	560	5%	1/10W						
						R605	1-216-295-91	SHORT	0		
R514	1-216-043-91	RES-CHIP	560	5%	1/10W	R608	1-216-295-91	SHORT	0		
R515	1-216-043-91	RES-CHIP	560	5%	1/10W	R609	1-216-073-00	RES-CHIP	10K	5%	1/10W
R516	1-216-049-91	RES-CHIP	1K	5%	1/10W	R610	1-216-033-00	RES-CHIP	220	5%	1/10W
R517	1-216-049-91	RES-CHIP	1K	5%	1/10W	R611	1-216-073-00	RES-CHIP	10K	5%	1/10W
R518	1-216-295-91	SHORT	0								
						R612	1-216-073-00	RES-CHIP	10K	5%	1/10W
R520	1-208-776-11	METAL CHIP	560	0.5%	1/10W	R613	1-216-065-91	RES-CHIP	4.7K	5%	1/10W
R521	1-216-295-91	SHORT	0			R615	1-216-089-91	RES-CHIP	47K	5%	1/10W
R523	1-208-776-11	METAL CHIP	560	0.5%	1/10W	R616	1-216-073-00	RES-CHIP	10K	5%	1/10W
R524	1-216-295-91	SHORT	0			R617	1-216-295-91	SHORT	0		
R526	1-208-776-11	METAL CHIP	560	0.5%	1/10W						
						R619	1-216-073-00	RES-CHIP	10K	5%	1/10W
R528	1-216-037-00	RES-CHIP	330	5%	1/10W	R621	1-216-295-91	SHORT	0		
R529	1-208-800-11	METAL CHIP	5.6K	0.5%	1/10W	R622	1-216-295-91	SHORT	0		
R530	1-208-800-11	METAL CHIP	5.6K	0.5%	1/10W	R623	1-216-295-91	SHORT	0		
R531	1-216-031-00	RES-CHIP	180	5%	1/10W	R624	1-216-295-91	SHORT	0		
R532	1-208-800-11	METAL CHIP	5.6K	0.5%	1/10W						
						R625	1-216-295-91	SHORT	0		
R533	1-216-031-00	RES-CHIP	180	5%	1/10W	R626	1-216-073-00	RES-CHIP	10K	5%	1/10W
R536	1-216-057-00	RES-CHIP	2.2K	5%	1/10W	R628	1-216-295-91	SHORT	0		
R537	1-208-790-11	METAL CHIP	2.2K	0.5%	1/10W	R629	1-216-073-00	RES-CHIP	10K	5%	1/10W
R540	1-216-049-91	RES-CHIP	1K	5%	1/10W	R631	1-216-295-91	SHORT	0		
R548	1-208-750-11	METAL CHIP	47	0.5%	1/10W						
						R634	1-216-295-91	SHORT	0		
R549	1-208-750-11	METAL CHIP	47	0.5%	1/10W	R635	1-216-295-91	SHORT	0		
R550	1-208-756-11	METAL CHIP	82	0.5%	1/10W	R638	1-216-295-91	SHORT	0		

REF.NO.	PART NO.	DESCRIPTION			REMARK	REF.NO.	PART NO.	DESCRIPTION			REMARK
R639	1-216-017-91	RES-CHIP	47	5%	1/10W	R814	1-216-073-00	RES-CHIP	10K	5%	1/10W
R640	1-216-009-91	RES-CHIP	22	5%	1/10W						
						R815	1-216-073-00	RES-CHIP	10K	5%	1/10W
R642	1-216-295-91	SHORT	0			R816	1-216-073-00	RES-CHIP	10K	5%	1/10W
R643	1-216-295-91	SHORT	0			R817	1-211-962-11	METAL CHIP	27	0.5%	1/10W
R645	1-216-295-91	SHORT	0			R819	1-216-295-91	SHORT	0		
R651	1-216-295-91	SHORT	0			R820	1-216-295-91	SHORT	0		
R653	1-216-025-91	RES-CHIP	100	5%	1/10W						
						R823	1-216-073-00	RES-CHIP	10K	5%	1/10W
R654	1-216-033-00	RES-CHIP	220	5%	1/10W	R824	1-216-073-00	RES-CHIP	10K	5%	1/10W
R655	1-216-295-91	SHORT	0			R825	1-208-752-11	METAL CHIP	56	0.5%	1/10W
R657	1-216-009-91	RES-CHIP	22	5%	1/10W	R826	1-208-772-11	METAL CHIP	390	0.5%	1/10W
R658	1-216-049-91	RES-CHIP	1K	5%	1/10W	R827	1-216-607-11	METAL CHIP	15	0.5%	1/10W
R659	1-216-025-91	RES-CHIP	100	5%	1/10W						
						R834	1-208-760-11	METAL CHIP	120	0.5%	1/10W
R660	1-216-025-91	RES-CHIP	100	5%	1/10W	R835	1-208-754-11	METAL CHIP	68	0.5%	1/10W
R661	1-216-025-91	RES-CHIP	100	5%	1/10W	R836	1-211-960-11	METAL CHIP	22	0.5%	1/10W
R664	1-216-009-91	RES-CHIP	22	5%	1/10W	R838	1-216-295-91	SHORT	0		
R665	1-216-035-00	RES-CHIP	270	5%	1/10W	R840	1-216-295-91	SHORT	0		
R666	1-216-646-11	METAL CHIP	620	0.5%	1/10W						
						R844	1-216-009-91	RES-CHIP	22	5%	1/10W
R667	1-208-794-11	METAL CHIP	3.3K	0.5%	1/10W	R845	1-216-009-91	RES-CHIP	22	5%	1/10W
R668	1-216-009-91	RES-CHIP	22	5%	1/10W	R846	1-216-009-91	RES-CHIP	22	5%	1/10W
R670	1-216-295-91	SHORT	0			R847	1-216-009-91	RES-CHIP	22	5%	1/10W
R671	1-216-073-00	RES-CHIP	10K	5%	1/10W	R848	1-216-009-91	RES-CHIP	22	5%	1/10W
R672	1-216-073-00	RES-CHIP	10K	5%	1/10W						
						R849	1-216-009-91	RES-CHIP	22	5%	1/10W
R673	1-216-073-00	RES-CHIP	10K	5%	1/10W	R850	1-216-009-91	RES-CHIP	22	5%	1/10W
R674	1-216-073-00	RES-CHIP	10K	5%	1/10W	R851	1-216-009-91	RES-CHIP	22	5%	1/10W
R675	1-216-073-00	RES-CHIP	10K	5%	1/10W	R852	1-216-009-91	RES-CHIP	22	5%	1/10W
R676	1-216-073-00	RES-CHIP	10K	5%	1/10W	R853	1-216-009-91	RES-CHIP	22	5%	1/10W
R677	1-216-073-00	RES-CHIP	10K	5%	1/10W						
						R854	1-216-009-91	RES-CHIP	22	5%	1/10W
R678	1-216-073-00	RES-CHIP	10K	5%	1/10W	R855	1-216-009-91	RES-CHIP	22	5%	1/10W
R679	1-216-073-00	RES-CHIP	10K	5%	1/10W	R856	1-216-009-91	RES-CHIP	22	5%	1/10W
R680	1-216-073-00	RES-CHIP	10K	5%	1/10W	R857	1-216-009-91	RES-CHIP	22	5%	1/10W
R681	1-216-073-00	RES-CHIP	10K	5%	1/10W	R858	1-216-009-91	RES-CHIP	22	5%	1/10W
R682	1-216-073-00	RES-CHIP	10K	5%	1/10W						
						R859	1-216-009-91	RES-CHIP	22	5%	1/10W
R683	1-216-073-00	RES-CHIP	10K	5%	1/10W	R860	1-216-009-91	RES-CHIP	22	5%	1/10W
R684	1-216-073-00	RES-CHIP	10K	5%	1/10W	R861	1-216-009-91	RES-CHIP	22	5%	1/10W
R685	1-216-073-00	RES-CHIP	10K	5%	1/10W	R862	1-216-009-91	RES-CHIP	22	5%	1/10W
R686	1-216-073-00	RES-CHIP	10K	5%	1/10W	R863	1-216-009-91	RES-CHIP	22	5%	1/10W
R687	1-216-295-91	SHORT	0								
						R864	1-216-009-91	RES-CHIP	22	5%	1/10W
R688	1-216-061-00	RES-CHIP	3.3K	5%	1/10W	R865	1-216-009-91	RES-CHIP	22	5%	1/10W
R689	1-216-057-00	RES-CHIP	2.2K	5%	1/10W	R866	1-216-009-91	RES-CHIP	22	5%	1/10W
R690	1-216-295-91	SHORT	0			R867	1-216-009-91	RES-CHIP	22	5%	1/10W
R691	1-216-061-00	RES-CHIP	3.3K	5%	1/10W	R868	1-216-009-91	RES-CHIP	22	5%	1/10W
R692	1-216-057-00	RES-CHIP	2.2K	5%	1/10W						
						R869	1-216-009-91	RES-CHIP	22	5%	1/10W
R693	1-216-009-91	RES-CHIP	22	5%	1/10W	R870	1-216-009-91	RES-CHIP	22	5%	1/10W
R694	1-216-295-91	SHORT	0			R871	1-216-009-91	RES-CHIP	22	5%	1/10W
R695	1-216-047-91	RES-CHIP	820	5%	1/10W	R872	1-216-009-91	RES-CHIP	22	5%	1/10W
R696	1-216-049-91	RES-CHIP	1K	5%	1/10W	R873	1-216-009-91	RES-CHIP	22	5%	1/10W
R697	1-216-117-00	RES-CHIP	680K	5%	1/10W						
						R874	1-216-009-91	RES-CHIP	22	5%	1/10W
R698	1-216-117-00	RES-CHIP	680K	5%	1/10W	R875	1-216-009-91	RES-CHIP	22	5%	1/10W
R699	1-216-295-91	SHORT	0			R876	1-216-009-91	RES-CHIP	22	5%	1/10W
R801	1-216-009-91	RES-CHIP	22	5%	1/10W	R877	1-216-009-91	RES-CHIP	22	5%	1/10W
R802	1-216-009-91	RES-CHIP	22	5%	1/10W	R878	1-216-009-91	RES-CHIP	22	5%	1/10W
R804	1-216-073-00	RES-CHIP	10K	5%	1/10W						
						R879	1-216-009-91	RES-CHIP	22	5%	1/10W
R806	1-208-806-11	METAL CHIP	10K	0.5%	1/10W	R880	1-216-009-91	RES-CHIP	22	5%	1/10W
R807	1-208-768-11	METAL CHIP	270	0.5%	1/10W	R881	1-216-009-91	RES-CHIP	22	5%	1/10W
R812	1-216-073-00	RES-CHIP	10K	5%	1/10W	R882	1-216-009-91	RES-CHIP	22	5%	1/10W
R813	1-216-295-91	SHORT	0			R883	1-216-009-91	RES-CHIP	22	5%	1/10W

B3

REF.NO.	PART NO.	DESCRIPTION			REMARK	REF.NO.	PART NO.	DESCRIPTION			REMARK
R884	1-216-009-91	RES-CHIP	22	5%	1/10W	R958	1-216-635-11	METAL CHIP	220	0.5%	1/10W
R885	1-216-009-91	RES-CHIP	22	5%	1/10W	R959	1-216-635-11	METAL CHIP	220	0.5%	1/10W
R886	1-216-009-91	RES-CHIP	22	5%	1/10W	R960	1-216-635-11	METAL CHIP	220	0.5%	1/10W
R887	1-216-009-91	RES-CHIP	22	5%	1/10W	R961	1-216-635-11	METAL CHIP	220	0.5%	1/10W
R888	1-216-009-91	RES-CHIP	22	5%	1/10W						
						R962	1-216-635-11	METAL CHIP	220	0.5%	1/10W
R889	1-216-009-91	RES-CHIP	22	5%	1/10W	R979	1-216-295-91	SHORT	0		
R890	1-216-009-91	RES-CHIP	22	5%	1/10W	R981	1-216-037-00	RES-CHIP	330	5%	1/10W
R891	1-216-009-91	RES-CHIP	22	5%	1/10W	R982	1-216-037-00	RES-CHIP	330	5%	1/10W
R892	1-216-009-91	RES-CHIP	22	5%	1/10W	R983	1-216-089-91	RES-CHIP	47K	5%	1/10W
R893	1-216-009-91	RES-CHIP	22	5%	1/10W						
R894	1-216-009-91	RES-CHIP	22	5%	1/10W	R984	1-216-061-00	RES-CHIP	3.3K	5%	1/10W
R895	1-216-009-91	RES-CHIP	22	5%	1/10W	R985	1-216-113-00	RES-CHIP	470K	5%	1/10W
R896	1-216-009-91	RES-CHIP	22	5%	1/10W	R986	1-216-061-00	RES-CHIP	3.3K	5%	1/10W
R897	1-216-009-91	RES-CHIP	22	5%	1/10W	R987	1-216-049-91	RES-CHIP	1K	5%	1/10W
R898	1-216-009-91	RES-CHIP	22	5%	1/10W	R988	1-216-033-00	RES-CHIP	220	5%	1/10W
R899	1-216-073-00	RES-CHIP	10K	5%	1/10W	R989	1-216-081-00	RES-CHIP	22K	5%	1/10W
R901	1-216-061-00	RES-CHIP	3.3K	5%	1/10W	R990	1-216-113-00	RES-CHIP	470K	5%	1/10W
R902	1-208-790-11	METAL CHIP	2.2K	0.5%	1/10W	R991	1-216-295-91	SHORT	0		
R903	1-208-794-11	METAL CHIP	3.3K	0.5%	1/10W	R993	1-216-089-91	RES-CHIP	47K	5%	1/10W
R904	1-216-635-11	METAL CHIP	220	0.5%	1/10W	R994	1-216-033-00	RES-CHIP	220	5%	1/10W
R905	1-216-635-11	METAL CHIP	220	0.5%	1/10W	R995	1-216-033-00	RES-CHIP	220	5%	1/10W
R906	1-216-635-11	METAL CHIP	220	0.5%	1/10W	R996	1-216-037-00	RES-CHIP	330	5%	1/10W
R907	1-216-635-11	METAL CHIP	220	0.5%	1/10W	R997	1-216-037-00	RES-CHIP	330	5%	1/10W
R908	1-216-635-11	METAL CHIP	220	0.5%	1/10W	R998	1-216-073-00	RES-CHIP	10K	5%	1/10W
R909	1-216-635-11	METAL CHIP	220	0.5%	1/10W	R2801	1-208-760-11	METAL CHIP	120	0.5%	1/10W
R910	1-216-049-91	RES-CHIP	1K	5%	1/10W	R2802	1-208-754-11	METAL CHIP	68	0.5%	1/10W
R911	1-216-049-91	RES-CHIP	1K	5%	1/10W	R2803	1-216-603-11	METAL CHIP	10	0.5%	1/10W
R912	1-216-049-91	RES-CHIP	1K	5%	1/10W	R2804	1-208-758-11	METAL CHIP	100	0.5%	1/10W
R914	1-216-065-91	RES-CHIP	4.7K	5%	1/10W	R2805	1-208-754-11	METAL CHIP	68	0.5%	1/10W
R916	1-216-065-91	RES-CHIP	4.7K	5%	1/10W	R2806	1-211-960-11	METAL CHIP	22	0.5%	1/10W
R923	1-216-057-00	RES-CHIP	2.2K	5%	1/10W	R2809	1-216-295-91	SHORT	0		
R926	1-216-057-00	RES-CHIP	2.2K	5%	1/10W	R2810	1-216-295-91	SHORT	0		
R927	1-216-295-91	SHORT	0			R2813	1-216-295-91	SHORT	0		
R929	1-216-025-91	RES-CHIP	100	5%	1/10W	R2815	1-216-295-91	SHORT	0		
R930	1-216-025-91	RES-CHIP	100	5%	1/10W	R2817	1-216-295-91	SHORT	0		
R931	1-216-041-00	RES-CHIP	470	5%	1/10W	R2818	1-216-295-91	SHORT	0		
R933	1-216-025-91	RES-CHIP	100	5%	1/10W	R2820	1-216-295-91	SHORT	0		
R934	1-216-025-91	RES-CHIP	100	5%	1/10W	R2822	1-216-295-91	SHORT	0		
R935	1-216-073-00	RES-CHIP	10K	5%	1/10W						
R936	1-216-041-00	RES-CHIP	470	5%	1/10W			<NETWORK RESISTOR>			
R937	1-216-025-91	RES-CHIP	100	5%	1/10W	RB001	1-239-409-11	NETWORK RESISTOR (CHIP) 47			
R938	1-216-025-91	RES-CHIP	100	5%	1/10W	RB002	1-239-409-11	NETWORK RESISTOR (CHIP) 47			
R939	1-216-295-91	SHORT	0			RB003	1-239-409-11	NETWORK RESISTOR (CHIP) 47			
R940	1-216-295-91	SHORT	0			RB004	1-239-409-11	NETWORK RESISTOR (CHIP) 47			
R941	1-216-295-91	SHORT	0			RB005	1-239-409-11	NETWORK RESISTOR (CHIP) 47			
R942	1-216-037-00	RES-CHIP	330	5%	1/10W	RB006	1-239-409-11	NETWORK RESISTOR (CHIP) 47			
R943	1-216-033-00	RES-CHIP	220	5%	1/10W	RB007	1-239-414-11	NETWORK RESISTOR (CHIP) 150			
R944	1-216-295-91	SHORT	0			RB008	1-239-414-11	NETWORK RESISTOR (CHIP) 150			
R945	1-216-295-91	SHORT	0			RB009	1-239-414-11	NETWORK RESISTOR (CHIP) 150			
R951	1-216-057-00	RES-CHIP	2.2K	5%	1/10W	RB010	1-239-414-11	NETWORK RESISTOR (CHIP) 150			
R952	1-216-057-00	RES-CHIP	2.2K	5%	1/10W	RB011	1-239-414-11	NETWORK RESISTOR (CHIP) 150			
R953	1-216-295-91	SHORT	0			RB012	1-239-414-11	NETWORK RESISTOR (CHIP) 150			
R954	1-216-295-91	SHORT	0			RB013	1-239-621-11	NETWORK RESISTOR (CHIP) 22			
R955	1-216-295-91	SHORT	0			RB014	1-239-621-11	NETWORK RESISTOR (CHIP) 22			
R956	1-216-089-91	RES-CHIP	47K	5%	1/10W	RB015	1-239-621-11	NETWORK RESISTOR (CHIP) 22			
R957	1-216-635-11	METAL CHIP	220	0.5%	1/10W	RB016	1-239-621-11	NETWORK RESISTOR (CHIP) 22			

REF.NO.	PART NO.	DESCRIPTION		REMARK		REF.NO.	PART NO.	DESCRIPTION		REMARK	
RB017	1-239-621-11	NETWORK RESISTOR (CHIP) 22				C1204	1-115-419-11	CERAMIC CHIP 3300pF		5%	25V
RB018	1-239-621-11	NETWORK RESISTOR (CHIP) 22				C1205	1-115-419-11	CERAMIC CHIP 3300pF		5%	25V
RB019	1-239-409-11	NETWORK RESISTOR (CHIP) 47				C1206	1-164-492-11	CERAMIC CHIP 0.15µF		10%	16V
RB020	1-239-409-11	NETWORK RESISTOR (CHIP) 47									
RB021	1-239-409-11	NETWORK RESISTOR (CHIP) 47				C1208	1-107-725-11	CERAMIC CHIP 0.1µF		10%	16V
RB022	1-239-409-11	NETWORK RESISTOR (CHIP) 47				C1209	1-107-823-11	CERAMIC CHIP 0.47µF		10%	16V
RB023	1-239-409-11	NETWORK RESISTOR (CHIP) 47				C1210	1-164-492-11	CERAMIC CHIP 0.15µF		10%	16V
RB024	1-239-409-11	NETWORK RESISTOR (CHIP) 47				C1211	1-107-823-11	CERAMIC CHIP 0.47µF		10%	16V
RB025	1-239-409-11	NETWORK RESISTOR (CHIP) 47				C1213	1-107-725-11	CERAMIC CHIP 0.1µF		10%	16V
RB026	1-239-409-11	NETWORK RESISTOR (CHIP) 47				C1215	1-164-505-11	CERAMIC CHIP 2.2µF			16V
RB027	1-239-409-11	NETWORK RESISTOR (CHIP) 47				C1217	1-164-505-11	CERAMIC CHIP 2.2µF			16V
RB301	1-239-621-11	NETWORK RESISTOR (CHIP) 22				C1219	1-163-251-11	CERAMIC CHIP 100pF		5%	50V
RB302	1-239-621-11	NETWORK RESISTOR (CHIP) 22				C1220	1-107-715-11	ELECT	22µF	20%	16V
RB701	1-239-711-91	NETWORK RESISTOR (CHIP) 0				C1221	1-137-150-11	MYLAR	0.01µF	5%	50V
RB702	1-239-711-91	NETWORK RESISTOR (CHIP) 0				C1222	1-126-962-11	ELECT	3.3µF	20%	50V
RB703	1-239-711-91	NETWORK RESISTOR (CHIP) 0				C1223	1-164-004-11	CERAMIC CHIP 0.1µF		10%	25V
RB704	1-239-711-91	NETWORK RESISTOR (CHIP) 0				C1224	1-126-933-11	ELECT	100µF	20%	16V
RB705	1-239-711-91	NETWORK RESISTOR (CHIP) 0				C1225	1-126-933-11	ELECT	100µF	20%	16V
RB706	1-239-711-91	NETWORK RESISTOR (CHIP) 0				C1226	1-126-933-11	ELECT	100µF	20%	16V
						C1227	1-164-004-11	CERAMIC CHIP 0.1µF		10%	25V
		<CRYSTAL>				C1228	1-164-004-11	CERAMIC CHIP 0.1µF		10%	25V
						C1229	1-126-767-11	ELECT	1000µF	20%	16V
X801	1-781-649-21	OSCILLATOR, CRYSTAL (54MHz)				C1230	1-126-933-11	ELECT	100µF	20%	16V
X802	1-781-650-21	VIBRATOR, CRYSTAL (17.28MHz)				C1231	1-107-725-11	CERAMIC CHIP 0.1µF		10%	16V
X901	1-760-014-11	VIBRATOR, CERAMIC (20MHz)				C1310	1-115-339-11	CERAMIC CHIP 0.1µF		10%	50V
						C1311	1-163-251-11	CERAMIC CHIP 100pF		5%	50V
	*A-1299-176-A	A1 BOARD, COMPLETE				C1312	1-104-664-11	ELECT	47µF	20%	16V
						C1314	1-126-933-11	ELECT	100µF	20%	16V
	*1-555-110-00	CABLE, PIN				C1315	1-107-725-11	CERAMIC CHIP 0.1µF		10%	16V
	4-382-854-11	SCREW (M3X10), P, SW (+)				C1316	1-126-933-11	ELECT	100µF	20%	16V
		(IC1601, IC1602, IC1603, IC1604, IC1605)				C1317	1-163-005-11	CERAMIC CHIP 470pF		10%	50V
	4-389-026-11	SHEET, BN (IC1604)				C1321	1-126-933-11	ELECT	100µF	20%	16V
						C1323	1-107-725-11	CERAMIC CHIP 0.1µF		10%	16V
		<COMFILTER MODULE>				C1324	1-163-005-11	CERAMIC CHIP 470pF		10%	50V
BC4	1-772-694-11	3D COMFILTER MODULE, DIGITAL				C1325	1-126-933-11	ELECT	100µF	20%	16V
						C1326	1-126-933-11	ELECT	100µF	20%	16V
		<CAPACITOR>				C1327	1-104-665-11	ELECT	100µF	20%	25V
						C1328	1-126-967-11	ELECT	47µF	20%	50V
C1101	1-126-935-11	ELECT	470µF	20%	16V	C1329	1-163-005-11	CERAMIC CHIP 470pF		10%	50V
C1102	1-126-964-11	ELECT	10µF	20%	50V	C1330	1-163-005-11	CERAMIC CHIP 470pF		10%	50V
C1103	1-126-960-11	ELECT	1µF	20%	50V	C1331	1-163-005-11	CERAMIC CHIP 470pF		10%	50V
C1104	1-126-960-11	ELECT	1µF	20%	50V	C1332	1-126-967-11	ELECT	47µF	20%	50V
C1105	1-126-041-11	ELECT	2200µF	20%	35V	C1333	1-104-665-11	ELECT	100µF	20%	25V
C1106	1-136-165-00	MYLAR	0.1µF	5%	50V	C1334	1-126-933-11	ELECT	100µF	20%	16V
C1107	1-136-165-00	MYLAR	0.1µF	5%	50V	C1335	1-163-005-11	CERAMIC CHIP 470pF		10%	50V
C1108	1-104-664-11	ELECT	47µF	20%	16V	C1336	1-163-005-11	CERAMIC CHIP 470pF		10%	50V
C1109	1-104-664-11	ELECT	47µF	20%	16V	C1337	1-163-005-11	CERAMIC CHIP 470pF		10%	50V
C1110	1-164-004-11	CERAMIC CHIP 0.1µF		10%	25V	C1401	1-164-346-11	CERAMIC CHIP 1µF			16V
C1111	1-126-041-11	ELECT	2200µF	20%	35V	C1601	1-164-004-11	CERAMIC CHIP 0.1µF		10%	25V
C1114	1-164-004-11	CERAMIC CHIP 0.1µF		10%	25V	C1602	1-164-004-11	CERAMIC CHIP 0.1µF		10%	25V
C1116	1-126-933-11	ELECT	100µF	20%	16V	C1603	1-164-004-11	CERAMIC CHIP 0.1µF		10%	25V
C1117	1-164-004-11	CERAMIC CHIP 0.1µF		10%	25V	C1604	1-126-933-11	ELECT	100µF	20%	16V
C1201	1-107-725-11	CERAMIC CHIP 0.1µF		10%	16V	C1605	1-164-004-11	CERAMIC CHIP 0.1µF		10%	25V
C1202	1-126-934-11	ELECT	220µF	20%	16V	C1606	1-126-933-11	ELECT	100µF	20%	16V
C1203	1-126-965-11	ELECT	22µF	20%	50V	C1607	1-164-004-11	CERAMIC CHIP 0.1µF		10%	25V
						C1608	1-126-933-11	ELECT	100µF	20%	16V
						C1610	1-164-004-11	CERAMIC CHIP 0.1µF		10%	25V

A1

REF.NO.	PART NO.	DESCRIPTION			REMARK
C1611	1-126-916-11	ELECT	1000µF	20%	6.3V
C1612	1-126-925-11	ELECT	470µF	20%	10V
C1615	1-164-004-11	CERAMIC CHIP 0.1µF		10%	25V
C1616	1-126-916-11	ELECT	1000µF	20%	6.3V
C1617	1-126-925-11	ELECT	470µF	20%	10V
C1619	1-164-004-11	CERAMIC CHIP 0.1µF		10%	25V

<CONNECTOR>

REF.NO.	PART NO.	DESCRIPTION	REMARK
CN1001	1-695-299-11	CONNECTOR, BOARD TO BOARD 50P	
CN1102	* 1-564-507-11	PLUG, CONNECTOR 4P	
CN1201	1-695-299-11	CONNECTOR, BOARD TO BOARD 50P	
CN1301	* 1-564-508-11	PLUG, CONNECTOR 5P	
CN1302	* 1-764-333-11	PLUG, CONNECTOR 10P	
CN1404	1-695-298-11	CONNECTOR, BOARD TO BOARD 40P	
CN1501	1-785-802-11	PIN, CONNECTOR (WITH PWB) 20P	
CN1502	1-785-802-11	PIN, CONNECTOR (WITH PWB) 20P	
CN1503	* 1-564-511-11	PLUG, CONNECTOR 8P	
CN1504	* 1-564-508-11	PLUG, CONNECTOR 5P	
CN1603	* 1-764-333-11	PLUG, CONNECTOR 10P	
CN1605	* 1-508-765-00	PIN, CONNECTOR (5MM PITCH) 3P	
CN1606	* 1-564-508-11	PLUG, CONNECTOR 5P	
CN1661	1-695-915-11	TAB (CONTACT)	
CN1665	1-695-915-11	TAB (CONTACT)	
CN1666	1-695-915-11	TAB (CONTACT)	
CN1801	1-695-299-11	CONNECTOR, BOARD TO BOARD 50P	

<COMPOSITION CIRCUIT BLOCK>

REF.NO.	PART NO.	DESCRIPTION	REMARK
CP1302	1-251-658-31	SPLITTER RF	

<DIODE>

REF.NO.	PART NO.	DESCRIPTION	REMARK
D1101	8-719-988-61	DIODE 1SS355TE-17	
D1102	8-719-988-61	DIODE 1SS355TE-17	
D1103	8-719-988-61	DIODE 1SS355TE-17	
D1104	8-719-988-61	DIODE 1SS355TE-17	
D1105	8-719-914-43	DIODE DAN202K	
D1106	8-719-914-43	DIODE DAN202K	
D1107	8-719-402-92	DIODE MA3220M-TX	
D1108	8-719-988-61	DIODE 1SS355TE-17	
D1109	8-719-988-61	DIODE 1SS355TE-17	
D1110	8-719-402-92	DIODE MA3220M-TX	
D1111	8-719-402-92	DIODE MA3220M-TX	
D1112	8-719-402-92	DIODE MA3220M-TX	
D1201	8-719-988-61	DIODE 1SS355TE-17	
D1202	8-719-914-43	DIODE DAN202K	
D1204	8-719-914-43	DIODE DAN202K	
D1205	8-719-988-61	DIODE 1SS355TE-17	
D1206	8-719-056-72	DIODE UDZ-TE-17-2.4B	
D1301	8-719-073-01	DIODE MA111-(K8).S0	
D1401	8-719-056-82	DIODE UDZ-TE-17-6.2B	
D1402	8-719-056-82	DIODE UDZ-TE-17-6.2B	
D1403	8-719-056-82	DIODE UDZ-TE-17-6.2B	
D1404	8-719-056-82	DIODE UDZ-TE-17-6.2B	
D1405	8-719-056-83	DIODE UDZ-TE-17-6.8B	

REF.NO.	PART NO.	DESCRIPTION	REMARK
D1406	8-719-914-43	DIODE DAN202K	
D1409	8-719-422-12	DIODE MA8039	
D1410	8-719-402-92	DIODE MA3220M-TX	
D1411	8-719-402-92	DIODE MA3220M-TX	
D1412	8-719-988-61	DIODE 1SS355TE-17	

<FERRITBEAD>

REF.NO.	PART NO.	DESCRIPTION	REMARK
FB1301	1-216-295-91	SHORT	0

<IC>

REF.NO.	PART NO.	DESCRIPTION	REMARK
IC1101	8-759-190-89	IC TDA7265	
IC1201	8-759-273-12	IC TDA7315D013TR	
IC1202	8-759-576-76	IC TDA2822D013TR	
IC1301	8-759-042-02	IC S-80743AL-A7-S	
IC1601	8-759-069-28	IC PQ05RF11	
IC1602	8-759-095-63	IC PQ09RF2	
IC1603	8-759-520-49	IC PQ30RV21	
IC1604	8-759-644-37	IC PQ5EV3	
IC1605	8-759-069-28	IC PQ05RF11	

<CHIP CONDUCTOR>

REF.NO.	PART NO.	DESCRIPTION	REMARK
JR1001	1-216-295-91	SHORT	0
JR1002	1-216-295-91	SHORT	0
JR1003	1-216-295-91	SHORT	0
JR1004	1-216-295-91	SHORT	0
JR1005	1-216-295-91	SHORT	0
JR1006	1-216-295-91	SHORT	0
JR1007	1-216-295-91	SHORT	0
JR1008	1-216-295-91	SHORT	0
JR1009	1-216-295-91	SHORT	0
JR1010	1-216-295-91	SHORT	0
JR1011	1-216-295-91	SHORT	0
JR1013	1-216-295-91	SHORT	0
JR1014	1-216-295-91	SHORT	0
JR1015	1-216-295-91	SHORT	0
JR1016	1-216-295-91	SHORT	0
JR1017	1-216-295-91	SHORT	0
JR1018	1-216-295-91	SHORT	0
JR1019	1-216-295-91	SHORT	0
JR1020	1-216-295-91	SHORT	0
JR1023	1-216-295-91	SHORT	0
JR1028	1-216-295-91	SHORT	0
JR1031	1-216-295-91	SHORT	0
JR1032	1-216-295-91	SHORT	0
JR1033	1-216-295-91	SHORT	0
JR1034	1-216-295-91	SHORT	0
JR1035	1-216-295-91	SHORT	0
JR1201	1-216-295-91	SHORT	0
JR1202	1-216-295-91	SHORT	0
JR1303	1-216-295-91	SHORT	0
JR1305	1-216-295-91	SHORT	0
JR1306	1-216-295-91	SHORT	0
JR1601	1-216-295-91	SHORT	0

REF.NO.	PART NO.	DESCRIPTION			REMARK	REF.NO.	PART NO.	DESCRIPTION			REMARK
JR1603	1-216-295-91	SHORT	0			R1112	1-216-295-91	SHORT	0		
JR1604	1-414-193-41	INDUCTOR	220µH			R1113	1-216-061-00	RES-CHIP	3.3K	5%	1/10W
						R1114	1-216-089-91	RES-CHIP	47K	5%	1/10W
						R1115	1-216-089-91	RES-CHIP	47K	5%	1/10W
		<COIL>				R1116	1-216-295-91	SHORT	0		
L1304	1-414-856-11	INDUCTOR	10µH			R1117	1-216-061-00	RES-CHIP	3.3K	5%	1/10W
L1305	1-414-856-11	INDUCTOR	10µH			R1118	1-216-079-00	RES-CHIP	18K	5%	1/10W
L1306	1-414-856-11	INDUCTOR	10µH			R1119	1-216-079-00	RES-CHIP	18K	5%	1/10W
L1307	1-414-856-11	INDUCTOR	10µH			R1120	1-216-043-91	RES-CHIP	560	5%	1/10W
L1308	1-414-856-11	INDUCTOR	10µH			R1121	1-216-043-91	RES-CHIP	560	5%	1/10W
L1309	1-414-856-11	INDUCTOR	10µH			R1122	1-216-357-00	METAL OXIDE	4.7	5%	1W
L1310	1-414-856-11	INDUCTOR	10µH			R1123	1-249-381-11	CARBON	1	5%	1/4W
L1311	1-414-856-11	INDUCTOR	10µH			R1124	1-216-357-00	METAL OXIDE	4.7	5%	1W
L1312	1-414-856-11	INDUCTOR	10µH			R1126	1-216-073-00	RES-CHIP	10K	5%	1/10W
L1313	1-414-856-11	INDUCTOR	10µH			R1127	1-216-073-00	RES-CHIP	10K	5%	1/10W
L1314	1-414-856-11	INDUCTOR	10µH			R1128	1-216-049-91	RES-CHIP	1K	5%	1/10W
						R1130	1-216-089-91	RES-CHIP	47K	5%	1/10W
		<TRANSISTOR>				R1131	1-216-089-91	RES-CHIP	47K	5%	1/10W
Q1101	8-729-120-28	TRANSISTOR 2SC1623-L5L6				R1201	1-216-033-00	RES-CHIP	220	5%	1/10W
Q1102	8-729-026-49	TRANSISTOR 2SA1037AK-T-146-R				R1202	1-216-033-00	RES-CHIP	220	5%	1/10W
Q1103	8-729-120-28	TRANSISTOR 2SC1623-L5L6				R1203	1-216-033-00	RES-CHIP	220	5%	1/10W
Q1104	8-729-120-28	TRANSISTOR 2SC1623-L5L6				R1204	1-216-033-00	RES-CHIP	220	5%	1/10W
Q1105	8-729-120-28	TRANSISTOR 2SC1623-L5L6				R1206	1-216-067-00	RES-CHIP	5.6K	5%	1/10W
Q1106	8-729-026-49	TRANSISTOR 2SA1037AK-T-146-R				R1207	1-216-295-91	SHORT	0		
Q1201	8-729-026-49	TRANSISTOR 2SA1037AK-T-146-R				R1209	1-216-067-00	RES-CHIP	5.6K	5%	1/10W
Q1202	8-729-120-28	TRANSISTOR 2SC1623-L5L6				R1210	1-216-295-91	SHORT	0		
Q1203	8-729-026-49	TRANSISTOR 2SA1037AK-T-146-R				R1211	1-216-065-91	RES-CHIP	4.7K	5%	1/10W
Q1204	8-729-120-28	TRANSISTOR 2SC1623-L5L6				R1212	1-216-089-91	RES-CHIP	47K	5%	1/10W
Q1205	8-729-120-28	TRANSISTOR 2SC1623-L5L6				R1213	1-216-089-91	RES-CHIP	47K	5%	1/10W
Q1206	8-729-120-28	TRANSISTOR 2SC1623-L5L6				R1214	1-216-073-00	RES-CHIP	10K	5%	1/10W
Q1207	8-729-120-28	TRANSISTOR 2SC1623-L5L6				R1215	1-216-067-00	RES-CHIP	5.6K	5%	1/10W
Q1208	8-729-120-28	TRANSISTOR 2SC1623-L5L6				R1216	1-216-097-91	RES-CHIP	100K	5%	1/10W
Q1209	8-729-026-49	TRANSISTOR 2SA1037AK-T-146-R				R1217	1-216-097-91	RES-CHIP	100K	5%	1/10W
Q1308	8-729-026-49	TRANSISTOR 2SA1037AK-T-146-R				R1218	1-216-089-91	RES-CHIP	47K	5%	1/10W
Q1309	8-729-026-49	TRANSISTOR 2SA1037AK-T-146-R				R1219	1-216-073-00	RES-CHIP	10K	5%	1/10W
Q1310	8-729-120-28	TRANSISTOR 2SC1623-L5L6				R1220	1-216-089-91	RES-CHIP	47K	5%	1/10W
Q1311	8-729-026-49	TRANSISTOR 2SA1037AK-T-146-R				R1221	1-216-073-00	RES-CHIP	10K	5%	1/10W
Q1312	8-729-120-28	TRANSISTOR 2SC1623-L5L6				R1222	1-216-081-00	RES-CHIP	22K	5%	1/10W
Q1401	8-729-026-49	TRANSISTOR 2SA1037AK-T-146-R				R1223	1-216-065-91	RES-CHIP	4.7K	5%	1/10W
Q1402	8-729-120-28	TRANSISTOR 2SC1623-L5L6				R1224	1-216-081-00	RES-CHIP	22K	5%	1/10W
Q1409	8-729-026-49	TRANSISTOR 2SA1037AK-T-146-R				R1225	1-216-033-00	RES-CHIP	220	5%	1/10W
						R1226	1-216-033-00	RES-CHIP	220	5%	1/10W
						R1228	1-216-057-00	RES-CHIP	2.2K	5%	1/10W
						R1229	1-216-057-00	RES-CHIP	2.2K	5%	1/10W
		<RESISTOR>				R1230	1-216-308-00	RES-CHIP	4.7	5%	1/10W
R1101	1-216-081-00	RES-CHIP	22K	5%	1/10W	R1231	1-216-295-91	SHORT	0		
R1102	1-216-097-91	RES-CHIP	100K	5%	1/10W	R1232	1-216-295-91	SHORT	0		
R1103	1-249-377-11	CARBON	0.47	5%	1/4W	R1233	1-216-295-91	SHORT	0		
R1104	1-216-089-91	RES-CHIP	47K	5%	1/10W	R1234	1-216-295-91	SHORT	0		
R1105	1-216-113-00	RES-CHIP	470K	5%	1/10W	R1235	1-216-081-00	RES-CHIP	22K	5%	1/10W
R1106	1-216-089-91	RES-CHIP	47K	5%	1/10W	R1236	1-216-089-91	RES-CHIP	47K	5%	1/10W
R1107	1-216-057-00	RES-CHIP	2.2K	5%	1/10W	R1237	1-216-081-00	RES-CHIP	22K	5%	1/10W
R1108	1-216-073-00	RES-CHIP	10K	5%	1/10W	R1249	1-216-308-00	RES-CHIP	4.7	5%	1/10W
R1109	1-216-041-00	RES-CHIP	470	5%	1/10W	R1329	1-216-057-00	RES-CHIP	2.2K	5%	1/10W
R1110	1-216-073-00	RES-CHIP	10K	5%	1/10W	R1330	1-216-057-00	RES-CHIP	2.2K	5%	1/10W
R1111	1-216-041-00	RES-CHIP	470	5%	1/10W	R1331	1-216-065-91	RES-CHIP	4.7K	5%	1/10W

A1 M1

The components identified by shading and mark ⚠ are critical for safety.
Replace only with part number specified.

REF.NO.	PART NO.	DESCRIPTION			REMARK
R1332	1-216-043-91	RES-CHIP	560	5%	1/10W
R1333	1-216-039-00	RES-CHIP	390	5%	1/10W
R1334	1-216-025-91	RES-CHIP	100	5%	1/10W
R1335	1-216-049-91	RES-CHIP	1K	5%	1/10W
R1336	1-216-025-91	RES-CHIP	100	5%	1/10W
R1337	1-216-017-91	RES-CHIP	47	5%	1/10W
R1338	1-216-295-91	SHORT	0		
R1341	1-216-025-91	RES-CHIP	100	5%	1/10W
R1342	1-216-295-91	SHORT	0		
R1344	1-216-043-91	RES-CHIP	560	5%	1/10W
R1345	1-216-039-00	RES-CHIP	390	5%	1/10W
R1346	1-216-073-00	RES-CHIP	10K	5%	1/10W
R1347	1-216-025-91	RES-CHIP	100	5%	1/10W
R1348	1-216-025-91	RES-CHIP	100	5%	1/10W
R1349	1-216-025-91	RES-CHIP	100	5%	1/10W
R1350	1-216-025-91	RES-CHIP	100	5%	1/10W
R1351	1-216-017-91	RES-CHIP	47	5%	1/10W
R1352	1-216-049-91	RES-CHIP	1K	5%	1/10W
R1402	1-216-081-00	RES-CHIP	22K	5%	1/10W
R1403	1-208-782-11	METAL CHIP	1K	0.5%	1/10W
R1404	1-216-025-91	RES-CHIP	100	5%	1/10W
R1405	1-208-826-11	METAL CHIP	68K	0.5%	1/10W
R1406	1-208-822-11	METAL CHIP	47K	0.5%	1/10W
R1407	1-208-817-11	METAL CHIP	30K	0.5%	1/10W
R1408	1-208-798-11	METAL CHIP	4.7K	0.5%	1/10W
R1409	1-216-081-00	RES-CHIP	22K	5%	1/10W
R1436	1-216-295-91	SHORT	0		
R1437	1-216-295-91	SHORT	0		
R1438	1-216-295-91	SHORT	0		
R1439	1-216-295-91	SHORT	0		
R1440	1-216-295-91	SHORT	0		
R1441	1-216-295-91	SHORT	0		
R1452	1-216-295-91	SHORT	0		
R1453	1-216-295-91	SHORT	0		
R1460	1-216-049-91	RES-CHIP	1K	5%	1/10W
R1461	1-216-073-00	RES-CHIP	10K	5%	1/10W
R1462	1-216-073-00	RES-CHIP	10K	5%	1/10W
R1601	1-216-295-91	SHORT	0		
R1608	1-208-778-11	METAL CHIP	680	0.5%	1/10W
R1610	1-208-772-11	METAL CHIP	390	0.5%	1/10W
R1611	1-208-772-11	METAL CHIP	390	0.5%	1/10W
R1613	1-208-772-11	METAL CHIP	390	0.5%	1/10W

<RELAY>

REF.NO.	PART NO.	DESCRIPTION
RY1101	1-755-028-11	RELAY
RY1102	1-755-028-11	RELAY

<TUNER>

REF.NO.	PART NO.	DESCRIPTION
TU1303 ⚠	8-598-508-10	TUNER, FSS BTF-LG436
TU1304 ⚠	8-598-452-20	TUNER, FSS BTF-WG442

****

* A-1306-588-A   M1 BOARD, COMPLETE
****

<CAPACITOR>

REF.NO.	PART NO.	DESCRIPTION			REMARK	
C001	1-126-960-11	ELECT	1µF	20%	50V	
C002	1-163-038-91	CERAMIC CHIP	0.1µF		25V	
C003	1-163-037-11	CERAMIC CHIP	0.022µF	10%	50V	
C004	1-163-038-91	CERAMIC CHIP	0.1µF		25V	
C007	1-163-038-91	CERAMIC CHIP	0.1µF		25V	
C010	1-126-933-11	ELECT	100µF	20%	16V	
C013	1-163-989-11	CERAMIC CHIP	0.033µF	10%	25V	
C014	1-163-021-91	CERAMIC CHIP	0.01µF	10%	50V	
C015	1-163-239-11	CERAMIC CHIP	33pF	5%	50V	
C016	1-163-239-11	CERAMIC CHIP	33pF	5%	50V	
C017	1-163-227-11	CERAMIC CHIP	10pF	0.50pF	50V	
C018	1-163-021-91	CERAMIC CHIP	0.01µF	10%	50V	
C019	1-163-243-11	CERAMIC CHIP	47pF	5%	50V	
C020	1-163-245-11	CERAMIC CHIP	56pF	5%	50V	
C021	1-163-227-11	CERAMIC CHIP	10pF	0.50pF	50V	
C022	1-163-227-11	CERAMIC CHIP	10pF	0.50pF	50V	
C023	1-126-967-11	ELECT	47µF	20%	50V	
C024	1-163-021-91	CERAMIC CHIP	0.01µF	10%	50V	
C025	1-126-933-11	ELECT	100µF	20%	16V	
C026	1-163-009-11	CERAMIC CHIP	0.001µF	10%	50V	
C027	1-163-021-91	CERAMIC CHIP	0.01µF	10%	50V	
C028	1-126-933-11	ELECT	100µF	20%	16V	
C030	1-163-021-91	CERAMIC CHIP	0.01µF	10%	50V	
C032	1-126-933-11	ELECT	100µF	20%	16V	
C033	1-163-038-91	CERAMIC CHIP	0.1µF		25V	
C034	1-163-243-11	CERAMIC CHIP	47pF	5%	50V	
C035	1-163-001-11	CERAMIC CHIP	220pF	10%	50V	
C036	1-163-251-11	CERAMIC CHIP	100pF	5%	50V	
C037	1-163-251-11	CERAMIC CHIP	100pF	5%	50V	
C038	1-163-251-11	CERAMIC CHIP	100pF	5%	50V	
C039	1-163-251-11	CERAMIC CHIP	100pF	5%	50V	
C040	1-164-005-11	CERAMIC CHIP	0.47µF		25V	
C041	1-163-001-11	CERAMIC CHIP	220pF	10%	50V	
C042	1-163-001-11	CERAMIC CHIP	220pF	10%	50V	
C043	1-126-933-11	ELECT	100µF	20%	16V	
C045	1-104-665-11	ELECT	100µF	20%	25V	
C046	1-163-038-91	CERAMIC CHIP	0.1µF		25V	
C048	1-163-021-91	CERAMIC CHIP	0.01µF	10%	50V	
C049	1-163-021-91	CERAMIC CHIP	0.01µF	10%	50V	
C050	1-163-021-91	CERAMIC CHIP	0.01µF	10%	50V	
C051	1-163-021-91	CERAMIC CHIP	0.01µF	10%	50V	
C052	1-163-038-91	CERAMIC CHIP	0.1µF		25V	
C054	1-126-933-11	ELECT	100µF	20%	16V	
C055	1-163-021-91	CERAMIC CHIP	0.01µF	10%	50V	
C056	1-163-021-91	CERAMIC CHIP	0.01µF	10%	50V	
C059	1-163-038-91	CERAMIC CHIP	0.1µF		25V	
C060	1-163-038-91	CERAMIC CHIP	0.1µF		25V	
C061	1-163-021-91	CERAMIC CHIP	0.01µF	10%	50V	
C062	1-163-259-91	CERAMIC CHIP	220pF	5%	50V	

M1

REF.NO.	PART NO.	DESCRIPTION		REMARK	REF.NO.	PART NO.	DESCRIPTION			REMARK
		<CONNECTOR>			L006	1-408-603-31	INDUCTOR	10µH		
CN001	1-695-302-11	CONNECTOR, BOARD TO BOARD 50P								
							<TRANSISTOR>			
		<DIODE>			Q004	8-729-026-49	TRANSISTOR 2SA1037AK-T-146-R			
					Q005	8-729-120-28	TRANSISTOR 2SC1623-L5L6			
D003	8-719-988-61	DIODE 1SS355TE-17			Q006	8-729-120-28	TRANSISTOR 2SC1623-L5L6			
D004	8-719-988-61	DIODE 1SS355TE-17			Q008	8-729-026-49	TRANSISTOR 2SA1037AK-T-146-R			
D007	8-719-988-61	DIODE 1SS355TE-17			Q009	8-729-026-49	TRANSISTOR 2SA1037AK-T-146-R			
D008	8-719-988-61	DIODE 1SS355TE-17								
D009	8-719-988-61	DIODE 1SS355TE-17			Q010	8-729-026-49	TRANSISTOR 2SA1037AK-T-146-R			
					Q014	8-729-120-28	TRANSISTOR 2SC1623-L5L6			
D015	8-719-988-61	DIODE 1SS355TE-17			Q015	8-729-120-28	TRANSISTOR 2SC1623-L5L6			
D017	8-719-988-61	DIODE 1SS355TE-17			Q016	8-729-026-49	TRANSISTOR 2SA1037AK-T-146-R			
					Q017	8-729-026-49	TRANSISTOR 2SA1037AK-T-146-R			
		<FERRITBEAD>			Q018	8-729-026-49	TRANSISTOR 2SA1037AK-T-146-R			
					Q019	8-729-026-49	TRANSISTOR 2SA1037AK-T-146-R			
FB001	1-414-233-22	INDUCTOR CHIP	0µH		Q020	8-729-026-49	TRANSISTOR 2SA1037AK-T-146-R			
FB002	1-414-233-22	INDUCTOR CHIP	0µH		Q021	8-729-026-49	TRANSISTOR 2SA1037AK-T-146-R			
FB003	1-414-233-22	INDUCTOR CHIP	0µH		Q022	8-729-120-28	TRANSISTOR 2SC1623-L5L6			
FB004	1-414-233-22	INDUCTOR CHIP	0µH							
FB005	1-414-233-22	INDUCTOR CHIP	0µH		Q023	8-729-120-28	TRANSISTOR 2SC1623-L5L6			
FB006	1-414-233-22	INDUCTOR CHIP	0µH							
FB007	1-414-233-22	INDUCTOR CHIP	0µH				**<RESISTOR>**			
FB008	1-414-233-22	INDUCTOR CHIP	0µH							
FB009	1-414-233-22	INDUCTOR CHIP	0µH		R001	1-216-073-00	RES-CHIP	10K	5%	1/10W
FB010	1-414-233-22	INDUCTOR CHIP	0µH		R002	1-216-065-91	RES-CHIP	4.7K	5%	1/10W
					R003	1-216-065-91	RES-CHIP	4.7K	5%	1/10W
FB011	1-414-233-22	INDUCTOR CHIP	0µH		R004	1-216-025-91	RES-CHIP	100	5%	1/10W
FB012	1-414-233-22	INDUCTOR CHIP	0µH		R005	1-216-025-91	RES-CHIP	100	5%	1/10W
					R006	1-216-025-91	RES-CHIP	100	5%	1/10W
		<FILTER>			R007	1-216-025-91	RES-CHIP	100	5%	1/10W
					R008	1-216-025-91	RES-CHIP	100	5%	1/10W
FL001	1-236-071-11	ENCAPSULATED COMPONENT			R009	1-216-025-91	RES-CHIP	100	5%	1/10W
					R011	1-216-025-91	RES-CHIP	100	5%	1/10W
		<IC>			R012	1-216-025-91	RES-CHIP	100	5%	1/10W
IC001	8-759-042-02	IC S-80743AL-A7-S			R013	1-216-025-91	RES-CHIP	100	5%	1/10W
IC002	8-752-916-27	IC CXP750096-025Q-TL			R015	1-216-295-91	SHORT	0		
IC003	8-759-652-13	IC SDA5254-2B006			R021	1-216-025-91	RES-CHIP	100	5%	1/10W
IC004	8-759-675-64	IC M24C08-MN6T(A)			R022	1-216-025-91	RES-CHIP	100	5%	1/10W
IC005	8-759-671-94	IC MC74HC4053AFEL								
					R023	1-216-025-91	RES-CHIP	100	5%	1/10W
IC006	8-759-575-71	IC M24C04-WMN6T			R024	1-216-049-91	RES-CHIP	1K	5%	1/10W
IC007	8-759-042-02	IC S-80743AL-A7-S			R026	1-216-025-91	RES-CHIP	100	5%	1/10W
IC008	8-759-242-68	IC TC7W32F			R027	1-216-033-00	RES-CHIP	220	5%	1/10W
IC009	8-759-242-78	IC TC7W02F			R030	1-216-025-91	RES-CHIP	100	5%	1/10W
IC010	8-759-242-74	IC TC7W04F								
					R031	1-216-049-91	RES-CHIP	1K	5%	1/10W
					R032	1-216-049-91	RES-CHIP	1K	5%	1/10W
		<CHIP CONDUCTOR>			R033	1-216-049-91	RES-CHIP	1K	5%	1/10W
JR001	1-216-295-91	SHORT	0		R034	1-216-049-91	RES-CHIP	1K	5%	1/10W
JR002	1-216-295-91	SHORT	0		R035	1-208-792-11	METAL CHIP	2.7K	0.5%	1/10W
					R036	1-216-025-91	RES-CHIP	100	5%	1/10W
		<COIL>			R037	1-216-049-91	RES-CHIP	1K	5%	1/10W
					R038	1-216-025-91	RES-CHIP	100	5%	1/10W
L002	1-408-591-11	INDUCTOR	1µH		R039	1-216-049-91	RES-CHIP	1K	5%	1/10W
L003	1-408-603-31	INDUCTOR	10µH		R040	1-216-025-91	RES-CHIP	100	5%	1/10W
L004	1-408-603-31	INDUCTOR	10µH							
L005	1-408-602-31	INDUCTOR	8.2µH		R042	1-216-057-00	RES-CHIP	2.2K	5%	1/10W
					R043	1-216-033-00	RES-CHIP	220	5%	1/10W
					R044	1-216-045-00	RES-CHIP	680	5%	1/10W

M1 E

REF.NO.	PART NO.	DESCRIPTION			REMARK
R047	1-216-065-91	RES-CHIP	4.7K	5%	1/10W
R048	1-216-049-91	RES-CHIP	1K	5%	1/10W
R049	1-216-057-00	RES-CHIP	2.2K	5%	1/10W
R050	1-216-057-00	RES-CHIP	2.2K	5%	1/10W
R051	1-216-065-91	RES-CHIP	4.7K	5%	1/10W
R052	1-216-065-91	RES-CHIP	4.7K	5%	1/10W
R053	1-216-045-00	RES-CHIP	680	5%	1/10W
R054	1-216-025-91	RES-CHIP	100	5%	1/10W
R055	1-216-025-91	RES-CHIP	100	5%	1/10W
R058	1-208-816-11	METAL CHIP	27K	0.5%	1/10W
R059	1-216-065-91	RES-CHIP	4.7K	5%	1/10W
R060	1-216-045-00	RES-CHIP	680	5%	1/10W
R061	1-216-025-91	RES-CHIP	100	5%	1/10W
R063	1-216-025-91	RES-CHIP	100	5%	1/10W
R064	1-216-025-91	RES-CHIP	100	5%	1/10W
R065	1-208-758-11	METAL CHIP	100	0.5%	1/10W
R067	1-208-758-11	METAL CHIP	100	0.5%	1/10W
R068	1-216-295-91	SHORT	0		
R069	1-208-758-11	METAL CHIP	100	0.5%	1/10W
R070	1-216-295-91	SHORT	0		
R071	1-216-295-91	SHORT	0		
R072	1-216-295-91	SHORT	0		
R073	1-216-025-91	RES-CHIP	100	5%	1/10W
R078	1-216-025-91	RES-CHIP	100	5%	1/10W
R079	1-216-025-91	RES-CHIP	100	5%	1/10W
R080	1-216-121-91	RES-CHIP	1M	5%	1/10W
R081	1-216-041-00	RES-CHIP	470	5%	1/10W
R082	1-216-089-91	RES-CHIP	47K	5%	1/10W
R083	1-216-049-91	RES-CHIP	1K	5%	1/10W
R085	1-216-037-00	RES-CHIP	330	5%	1/10W
R086	1-216-053-00	RES-CHIP	1.5K	5%	1/10W
R088	1-216-063-91	RES-CHIP	3.9K	5%	1/10W
R089	1-216-073-00	RES-CHIP	10K	5%	1/10W
R090	1-216-033-00	RES-CHIP	220	5%	1/10W
R091	1-216-033-00	RES-CHIP	220	5%	1/10W
R092	1-216-073-00	RES-CHIP	10K	5%	1/10W
R093	1-216-025-91	RES-CHIP	100	5%	1/10W
R094	1-216-025-91	RES-CHIP	100	5%	1/10W
R095	1-216-033-00	RES-CHIP	220	5%	1/10W
R099	1-216-295-91	SHORT	0		
R100	1-216-055-00	RES-CHIP	1.8K	5%	1/10W
R101	1-216-055-00	RES-CHIP	1.8K	5%	1/10W
R102	1-216-295-91	SHORT	0		
R103	1-216-055-00	RES-CHIP	1.8K	5%	1/10W
R104	1-216-295-91	SHORT	0		
R105	1-216-065-91	RES-CHIP	4.7K	5%	1/10W
R106	1-216-065-91	RES-CHIP	4.7K	5%	1/10W
R107	1-216-065-91	RES-CHIP	4.7K	5%	1/10W
R108	1-216-049-91	RES-CHIP	1K	5%	1/10W
R109	1-216-025-91	RES-CHIP	100	5%	1/10W
R110	1-216-049-91	RES-CHIP	1K	5%	1/10W
R111	1-216-025-91	RES-CHIP	100	5%	1/10W
R112	1-216-049-91	RES-CHIP	1K	5%	1/10W
R113	1-216-025-91	RES-CHIP	100	5%	1/10W
R114	1-216-049-91	RES-CHIP	1K	5%	1/10W
R119	1-216-295-91	SHORT	0		

REF.NO.	PART NO.	DESCRIPTION			REMARK
R120	1-216-073-00	RES-CHIP	10K	5%	1/10W
R121	1-216-065-91	RES-CHIP	4.7K	5%	1/10W
R123	1-216-017-91	RES-CHIP	47	5%	1/10W
R124	1-216-025-91	RES-CHIP	100	5%	1/10W
R125	1-216-025-91	RES-CHIP	100	5%	1/10W
R126	1-216-049-91	RES-CHIP	1K	5%	1/10W
R127	1-216-049-91	RES-CHIP	1K	5%	1/10W
R128	1-216-049-91	RES-CHIP	1K	5%	1/10W
R129	1-216-049-91	RES-CHIP	1K	5%	1/10W
R131	1-216-073-00	RES-CHIP	10K	5%	1/10W
R132	1-216-049-91	RES-CHIP	1K	5%	1/10W
R133	1-216-025-91	RES-CHIP	100	5%	1/10W
R134	1-216-041-00	RES-CHIP	470	5%	1/10W
R135	1-216-025-91	RES-CHIP	100	5%	1/10W
R137	1-216-295-91	SHORT	0		
R138	1-216-041-00	RES-CHIP	470	5%	1/10W
R139	1-216-049-91	RES-CHIP	1K	5%	1/10W
R140	1-216-073-00	RES-CHIP	10K	5%	1/10W
R141	1-216-057-00	RES-CHIP	2.2K	5%	1/10W
R142	1-216-057-00	RES-CHIP	2.2K	5%	1/10W
R143	1-216-057-00	RES-CHIP	2.2K	5%	1/10W
R144	1-216-033-00	RES-CHIP	220	5%	1/10W

<CRYSTAL>

| X001 | 1-567-928-11 | VIBLATOR, CERAMIC (20MHz) |
| X002 | 1-781-685-21 | VIBRATOR, CRYSTAL (6MHz) |

****

* A-1346-922-A E BOARD, COMPLETE

****

<CAPACITOR>

C4301	1-126-960-11	ELECT	1µF	20%	50V
C4302	1-164-489-11	CERAMIC CHIP	0.22µF	10%	16V
C4303	1-163-809-11	CERAMIC CHIP	0.047µF	10%	25V
C4304	1-164-004-11	CERAMIC CHIP	0.1µF	10%	25V
C4306	1-126-964-11	ELECT	10µF	20%	50V
C4307	1-163-137-00	CERAMIC CHIP	680pF	5%	50V
C4311	1-164-004-11	CERAMIC CHIP	0.1µF	10%	25V
C4312	1-164-004-11	CERAMIC CHIP	0.1µF	10%	25V
C4313	1-164-004-11	CERAMIC CHIP	0.1µF	10%	25V
C4315	1-163-222-11	CERAMIC CHIP	5pF	0.25pF	50V
C4316	1-104-664-11	ELECT	47µF	20%	25V
C4317	1-164-004-11	CERAMIC CHIP	0.1µF	10%	25V
C4318	1-164-004-11	CERAMIC CHIP	0.1µF	10%	25V
C4319	1-164-004-11	CERAMIC CHIP	0.1µF	10%	25V
C4324	1-164-004-11	CERAMIC CHIP	0.1µF	10%	25V
C4325	1-163-093-00	CERAMIC CHIP	10pF	5%	50V
C4329	1-126-963-11	ELECT	4.7µF	20%	50V
C4330	1-137-581-11	FILM	0.1µF	5%	100V
C4331	1-126-959-11	ELECT	0.47µF	20%	50V
C4333	1-164-004-11	CERAMIC CHIP	0.1µF	10%	25V
C4334	1-126-967-11	ELECT	47µF	20%	50V
C4336	1-126-967-11	ELECT	47µF	20%	50V

REF.NO.	PART NO.	DESCRIPTION	REMARK				REF.NO.	PART NO.	DESCRIPTION	REMARK		
C4338	1-164-004-11	CERAMIC CHIP 0.1µF	10%	25V					<IC>			
C4340	1-126-967-11	ELECT 47µF	20%	50V								
C4342	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V			IC4301	8-752-090-87	IC CXA2100AQ			
C4343	1-164-004-11	CERAMIC CHIP 0.1µF	10%	25V					<CHIP CONDUCTOR>			
C4344	1-126-960-11	ELECT 1µF	20%	50V								
C4345	1-126-967-11	ELECT 47µF	20%	50V			JR4301	1-216-295-91	SHORT 0			
C4346	1-164-004-11	CERAMIC CHIP 0.1µF	10%	25V			JR4302	1-216-037-00	RES-CHIP 330	5%	1/10W	
C4347	1-164-004-11	CERAMIC CHIP 0.1µF	10%	25V								
C4348	1-164-004-11	CERAMIC CHIP 0.1µF	10%	25V					<COIL>			
C4349	1-164-004-11	CERAMIC CHIP 0.1µF	10%	25V								
C4350	1-164-004-11	CERAMIC CHIP 0.1µF	10%	25V			L4301	1-412-029-11	INDUCTOR CHIP	10µH		
C4351	1-164-161-11	CERAMIC CHIP 0.0022µF	10%	50V			L4302	1-412-029-11	INDUCTOR CHIP	10µH		
C4352	1-126-967-11	ELECT 47µF	20%	50V			L4303	1-412-029-11	INDUCTOR CHIP	10µH		
							L4304	1-412-029-11	INDUCTOR CHIP	10µH		
C4353	1-107-823-11	CERAMIC CHIP 0.47µF	10%	16V			L4305	1-412-029-11	INDUCTOR CHIP	10µH		
C4354	1-107-823-11	CERAMIC CHIP 0.47µF	10%	16V								
C4355	1-164-004-11	CERAMIC CHIP 0.1µF	10%	25V			L4306	1-412-029-11	INDUCTOR CHIP	10µH		
C4356	1-164-004-11	CERAMIC CHIP 0.1µF	10%	25V			L4308	1-412-031-11	INDUCTOR CHIP	47µH		
C4357	1-164-004-11	CERAMIC CHIP 0.1µF	10%	25V			L4309	1-412-031-11	INDUCTOR CHIP	47µH		
C4358	1-164-004-11	CERAMIC CHIP 0.1µF	10%	25V								
C4359	1-164-161-11	CERAMIC CHIP 0.0022µF	10%	50V					<TRANSISTOR>			
C4360	1-126-964-11	ELECT 10µF	20%	50V								
C4362	1-164-004-11	CERAMIC CHIP 0.1µF	10%	25V			Q4301	8-729-120-28	TRANSISTOR 2SC1623-L5L6			
C4363	1-126-967-11	ELECT 47µF	20%	50V			Q4303	8-729-216-22	TRANSISTOR 2SA1162-G			
							Q4304	8-729-216-22	TRANSISTOR 2SA1162-G			
C4364	1-126-967-11	ELECT 47µF	20%	50V			Q4307	8-729-216-22	TRANSISTOR 2SA1162-G			
C4368	1-164-004-11	CERAMIC CHIP 0.1µF	10%	25V			Q4308	8-729-216-22	TRANSISTOR 2SA1162-G			
C4369	1-164-004-11	CERAMIC CHIP 0.1µF	10%	25V								
C4370	1-126-967-11	ELECT 47µF	20%	50V			Q4310	8-729-216-22	TRANSISTOR 2SA1162-G			
C4371	1-164-004-11	CERAMIC CHIP 0.1µF	10%	25V			Q4316	8-729-216-22	TRANSISTOR 2SA1162-G			
							Q4317	8-729-216-22	TRANSISTOR 2SA1162-G			
C4372	1-164-505-11	CERAMIC CHIP 2.2µF		16V			Q4318	8-729-216-22	TRANSISTOR 2SA1162-G			
C4373	1-164-004-11	CERAMIC CHIP 0.1µF	10%	25V			Q4319	8-729-120-28	TRANSISTOR 2SC1623-L5L6			
C4374	1-164-004-11	CERAMIC CHIP 0.1µF	10%	25V								
C4377	1-126-960-11	ELECT 1µF	20%	50V			Q4320	8-729-216-22	TRANSISTOR 2SA1162-G			
C4382	1-164-004-11	CERAMIC CHIP 0.1µF	10%	25V			Q4321	8-729-216-22	TRANSISTOR 2SA1162-G			
							Q4322	8-729-216-22	TRANSISTOR 2SA1162-G			
C4383	1-164-004-11	CERAMIC CHIP 0.1µF	10%	25V			Q4323	8-729-216-22	TRANSISTOR 2SA1162-G			
C4384	1-164-004-11	CERAMIC CHIP 0.1µF	10%	25V			Q4324	8-729-216-22	TRANSISTOR 2SA1162-G			
C4601	1-164-161-11	CERAMIC CHIP 0.0022µF	10%	50V								
							Q4601	1-801-806-11	TRANSISTOR DTC144EKA			
		<CONNECTOR>					Q4602	8-729-120-28	TRANSISTOR 2SC1623-L5L6			
CN4101	1-695-301-11	CONNECTOR, BOARD TO BOARD 40P							<RESISTOR>			
CN4500	*1-564-512-11	PLUG, CONNECTOR 9P										
CN4502	*1-564-507-11	PLUG, CONNECTOR 4P					R4301	1-216-025-91	RES-CHIP 100	5%	1/10W	
							R4302	1-216-025-91	RES-CHIP 100	5%	1/10W	
							R4303	1-216-025-91	RES-CHIP 100	5%	1/10W	
		<DIODE>					R4304	1-216-025-91	RES-CHIP 100	5%	1/10W	
							R4305	1-216-025-91	RES-CHIP 100	5%	1/10W	
D4304	8-719-977-22	DIODE DTZ9.1										
D4305	8-719-977-22	DIODE DTZ9.1					R4306	1-216-045-00	RES-CHIP 680	5%	1/10W	
D4601	8-719-401-63	DIODE MA3062M-TX					R4307	1-216-295-91	SHORT 0			
D4602	8-719-914-43	DIODE DAN202K					R4309	1-216-295-91	SHORT 0			
D4603	8-719-914-43	DIODE DAN202K					R4313	1-216-033-00	RES-CHIP 220	5%	1/10W	
							R4314	1-216-049-91	RES-CHIP 1K	5%	1/10W	
		<FERRITBEAD>										
							R4315	1-216-063-91	RES-CHIP 3.9K	5%	1/10W	
FB4387	1-216-295-91	SHORT 0					R4316	1-216-037-00	RES-CHIP 330	5%	1/10W	
FB4388	1-216-295-91	SHORT 0					R4317	1-216-049-91	RES-CHIP 1K	5%	1/10W	
FB4389	1-216-295-91	SHORT 0					R4319	1-216-073-00	RES-CHIP 10K	5%	1/10W	
							R4320	1-216-689-11	RES-CHIP 39K	5%	1/10W	

E J1

REF.NO.	PART NO.	DESCRIPTION			REMARK
R4321	1-216-105-91	RES-CHIP	220K	5%	1/10W
R4322	1-216-073-00	RES-CHIP	10K	5%	1/10W
R4323	1-216-091-00	RES-CHIP	56K	5%	1/10W
R4324	1-208-830-11	METAL CHIP	100K	0.5%	1/10W
R4325	1-216-093-91	RES-CHIP	68K	5%	1/10W
R4331	1-216-061-00	RES-CHIP	3.3K	5%	1/10W
R4334	1-216-025-91	RES-CHIP	100	5%	1/10W
R4335	1-216-025-91	RES-CHIP	100	5%	1/10W
R4336	1-216-025-91	RES-CHIP	100	5%	1/10W
R4337	1-216-025-91	RES-CHIP	100	5%	1/10W
R4339	1-249-409-11	CARBON	220	5%	1/4W
R4340	1-216-111-00	RES-CHIP	390K	5%	1/10W
R4341	1-216-295-91	SHORT	0		
R4343	1-216-025-91	RES-CHIP	100	5%	1/10W
R4344	1-216-025-91	RES-CHIP	100	5%	1/10W
R4345	1-216-075-00	RES-CHIP	12K	5%	1/10W
R4346	1-208-812-11	METAL CHIP	18K	0.5%	1/10W
R4347	1-216-025-91	RES-CHIP	100	5%	1/10W
R4348	1-216-025-91	RES-CHIP	100	5%	1/10W
R4349	1-216-033-00	RES-CHIP	220	5%	1/10W
R4350	1-216-025-91	RES-CHIP	100	5%	1/10W
R4352	1-216-073-00	RES-CHIP	10K	5%	1/10W
R4354	1-208-806-11	METAL CHIP	10K	0.5%	1/10W
R4355	1-216-295-91	SHORT	0		
R4357	1-208-814-91	METAL CHIP	22K	0.5%	1/10W
R4358	1-208-804-11	METAL CHIP	8.2K	0.5%	1/10W
R4359	1-216-041-00	RES-CHIP	470	5%	1/10W
R4360	1-216-061-00	RES-CHIP	3.3K	5%	1/10W
R4361	1-216-133-00	RES-CHIP	3.3M	5%	1/10W
R4363	1-216-025-91	RES-CHIP	100	5%	1/10W
R4365	1-216-017-91	RES-CHIP	47	5%	1/10W
R4366	1-216-017-91	RES-CHIP	47	5%	1/10W
R4367	1-216-017-91	RES-CHIP	47	5%	1/10W
R4370	1-216-049-91	RES-CHIP	1K	5%	1/10W
R4372	1-216-065-91	RES-CHIP	4.7K	5%	1/10W
R4375	1-216-033-00	RES-CHIP	220	5%	1/10W
R4377	1-216-033-00	RES-CHIP	220	5%	1/10W
R4380	1-216-073-00	RES-CHIP	10K	5%	1/10W
R4382	1-216-073-00	RES-CHIP	10K	5%	1/10W
R4384	1-216-025-91	RES-CHIP	100	5%	1/10W
R4385	1-216-129-00	RES-CHIP	2.2M	5%	1/10W
R4387	1-216-017-91	RES-CHIP	47	5%	1/10W
R4388	1-216-017-91	RES-CHIP	47	5%	1/10W
R4389	1-216-017-91	RES-CHIP	47	5%	1/10W
R4393	1-216-025-91	RES-CHIP	100	5%	1/10W
R4395	1-216-295-91	SHORT	0		
R4396	1-216-295-91	SHORT	0		
R4397	1-216-295-91	SHORT	0		
R4400	1-216-071-00	RES-CHIP	8.2K	5%	1/10W
R4401	1-216-071-00	RES-CHIP	8.2K	5%	1/10W
R4402	1-216-049-91	RES-CHIP	1K	5%	1/10W
R4403	1-216-298-00	RES-CHIP	2.2	5%	1/10W
R4404	1-216-081-00	RES-CHIP	22K	5%	1/10W
R4405	1-216-061-00	RES-CHIP	3.3K	5%	1/10W
R4406	1-216-073-00	RES-CHIP	10K	5%	1/10W
R4407	1-216-017-91	RES-CHIP	47	5%	1/10W
R4408	1-249-409-11	CARBON	220	5%	1/4W
R4504	1-216-025-91	RES-CHIP	100	5%	1/10W
R4514	1-216-061-00	RES-CHIP	3.3K	5%	1/10W
R4515	1-216-061-00	RES-CHIP	3.3K	5%	1/10W
R4516	1-216-049-91	RES-CHIP	1K	5%	1/10W
R4517	1-216-049-91	RES-CHIP	1K	5%	1/10W
R4518	1-216-025-91	RES-CHIP	100	5%	1/10W
R4519	1-216-025-91	RES-CHIP	100	5%	1/10W
R4520	1-216-045-00	RES-CHIP	680	5%	1/10W
R4521	1-216-045-00	RES-CHIP	680	5%	1/10W
R4522	1-216-025-91	RES-CHIP	100	5%	1/10W
R4523	1-216-025-91	RES-CHIP	100	5%	1/10W
R4524	1-216-049-91	RES-CHIP	1K	5%	1/10W
R4601	1-208-291-11	RES-CHIP	4.7M	5%	1/10W
R4602	1-216-057-00	RES-CHIP	2.2K	5%	1/10W
R4603	1-216-065-91	RES-CHIP	4.7K	5%	1/10W

\<INDUCTOR\>

T4301	1-469-893-21	INDUCTOR (EMI REMOVE FILTER)	

\<CRYSTAL\>

X4300	1-767-127-11	VIBRATOR, CERAMIC (503.5kHz)

****

* A-1394-982-A J1 BOARD, COMPLETE

****

\<CAPACITOR\>

REF.NO.	PART NO.	DESCRIPTION			REMARK
C8301	1-163-133-00	CERAMIC CHIP 470pF		5%	50V
C8302	1-163-133-00	CERAMIC CHIP 470pF		5%	50V
C8303	1-163-133-00	CERAMIC CHIP 470pF		5%	50V
C8304	1-163-133-00	CERAMIC CHIP 470pF		5%	50V
C8305	1-163-133-00	CERAMIC CHIP 470pF		5%	50V
C8306	1-163-133-00	CERAMIC CHIP 470pF		5%	50V
C8307	1-163-133-00	CERAMIC CHIP 470pF		5%	50V
C8308	1-163-133-00	CERAMIC CHIP 470pF		5%	50V
C8309	1-163-133-00	CERAMIC CHIP 470pF		5%	50V
C8310	1-163-133-00	CERAMIC CHIP 470pF		5%	50V
C8311	1-164-346-11	CERAMIC CHIP 1μF			16V
C8312	1-164-346-11	CERAMIC CHIP 1μF			16V
C8313	1-164-346-11	CERAMIC CHIP 1μF			16V
C8314	1-164-346-11	CERAMIC CHIP 1μF			16V
C8315	1-163-133-00	CERAMIC CHIP 470pF		5%	50V
C8316	1-163-133-00	CERAMIC CHIP 470pF		5%	50V
C8317	1-164-004-11	CERAMIC CHIP 0.1μF		10%	25V
C8318	1-104-664-11	ELECT	47μF	20%	16V
C8319	1-104-664-11	ELECT	47μF	20%	16V
C8320	1-117-720-11	CERAMIC CHIP 4.7μF			10V
C8321	1-117-720-11	CERAMIC CHIP 4.7μF			10V
C8322	1-164-346-11	CERAMIC CHIP 1μF			16V
C8323	1-164-346-11	CERAMIC CHIP 1μF			16V
C8324	1-117-720-11	CERAMIC CHIP 4.7μF			10V
C8325	1-126-935-11	ELECT	470μF	20%	16V

REF.NO.	PART NO.	DESCRIPTION	REMARK		REF.NO.	PART NO.	DESCRIPTION	REMARK	
C8326	1-107-823-11	CERAMIC CHIP 0.47µF	10%	16V	C8402	1-164-346-11	CERAMIC CHIP 1µF		16V
C8327	1-164-346-11	CERAMIC CHIP 1µF		16V	C8403	1-163-037-11	CERAMIC CHIP 0.022µF	10%	50V
C8328	1-164-346-11	CERAMIC CHIP 1µF		16V	C8405	1-126-933-11	ELECT 100µF	20%	16V
C8329	1-164-004-11	CERAMIC CHIP 0.1µF	10%	25V	C8406	1-104-664-11	ELECT 47µF	20%	16V
C8330	1-164-346-11	CERAMIC CHIP 1µF		16V					
					C8407	1-104-664-11	ELECT 47µF	20%	16V
C8331	1-164-346-11	CERAMIC CHIP 1µF		16V	C8408	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V
C8332	1-107-823-11	CERAMIC CHIP 0.47µF	10%	16V	C8409	1-126-933-11	ELECT 100µF	20%	16V
C8333	1-117-720-11	CERAMIC CHIP 4.7µF		10V	C8410	1-164-004-11	CERAMIC CHIP 0.1µF	10%	25V
C8334	1-163-249-11	CERAMIC CHIP 82pF	5%	50V	C8412	1-164-004-11	CERAMIC CHIP 0.1µF	10%	25V
C8336	1-104-664-11	ELECT 47µF	20%	16V					
					C8414	1-104-664-11	ELECT 47µF	20%	16V
C8337	1-164-004-11	CERAMIC CHIP 0.1µF	10%	25V	C8415	1-164-346-11	CERAMIC CHIP 1µF		16V
C8338	1-164-346-11	CERAMIC CHIP 1µF		16V	C8416	1-164-004-11	CERAMIC CHIP 0.1µF	10%	25V
C8339	1-164-346-11	CERAMIC CHIP 1µF		16V	C8417	1-163-227-11	CERAMIC CHIP 10pF	0.50pF	50V
C8340	1-107-823-11	CERAMIC CHIP 0.47µF	10%	16V	C8418	1-126-964-11	ELECT 10µF	20%	50V
C8341	1-107-823-11	CERAMIC CHIP 0.47µF	10%	16V					
					C8419	1-164-004-11	CERAMIC CHIP 0.1µF	10%	25V
C8342	1-126-964-11	ELECT 10µF	20%	50V	C8424	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V
C8343	1-104-664-11	ELECT 47µF	20%	16V	C8425	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V
C8344	1-164-004-11	CERAMIC CHIP 0.1µF	10%	25V	C8437	1-126-963-11	ELECT 4.7µF	20%	50V
C8345	1-104-664-11	ELECT 47µF	20%	16V	C8438	1-164-004-11	CERAMIC CHIP 0.1µF	10%	25V
C8346	1-164-004-11	CERAMIC CHIP 0.1µF	10%	25V					
					C8439	1-164-004-11	CERAMIC CHIP 0.1µF	10%	25V
C8347	1-163-133-00	CERAMIC CHIP 470pF	5%	50V	C8440	1-164-004-11	CERAMIC CHIP 0.1µF	10%	25V
C8348	1-163-133-00	CERAMIC CHIP 470pF	5%	50V	C8446	1-104-664-11	ELECT 47µF	20%	16V
C8349	1-104-664-11	ELECT 47µF	20%	16V	C8447	1-164-004-11	CERAMIC CHIP 0.1µF	10%	25V
C8350	1-164-346-11	CERAMIC CHIP 1µF		16V	C8448	1-164-690-91	CERAMIC CHIP 0.0022µF	5%	50V
C8351	1-164-346-11	CERAMIC CHIP 1µF		16V					
					C8450	1-107-823-11	CERAMIC CHIP 0.47µF	10%	16V
C8352	1-104-664-11	ELECT 47µF	20%	16V	C8451	1-164-505-11	CERAMIC CHIP 2.2µF		16V
C8354	1-107-823-11	CERAMIC CHIP 0.47µF	10%	16V	C8453	1-164-004-11	CERAMIC CHIP 0.1µF	10%	25V
C8355	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V	C8454	1-164-004-11	CERAMIC CHIP 0.1µF	10%	25V
C8356	1-164-346-11	CERAMIC CHIP 1µF		16V	C8455	1-104-664-11	ELECT 47µF	20%	16V
C8357	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V					
					C8464	1-115-340-11	CERAMIC CHIP 0.22µF	10%	25V
C8358	1-164-346-11	CERAMIC CHIP 1µF		16V	C8465	1-115-340-11	CERAMIC CHIP 0.22µF	10%	25V
C8359	1-163-037-11	CERAMIC CHIP 0.022µF	10%	50V	C8466	1-104-664-11	ELECT 47µF	20%	16V
C8360	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V	C8467	1-104-664-11	ELECT 47µF	20%	16V
C8361	1-126-961-11	ELECT 2.2µF	20%	50V	C8468	1-115-340-11	CERAMIC CHIP 0.22µF	10%	25V
C8362	1-164-004-11	CERAMIC CHIP 0.1µF	10%	25V					
					C8469	1-115-340-11	CERAMIC CHIP 0.22µF	10%	25V
C8363	1-164-004-11	CERAMIC CHIP 0.1µF	10%	25V	C8474	1-164-004-11	CERAMIC CHIP 0.1µF	10%	25V
C8366	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V	C8477	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V
C8367	1-104-664-11	ELECT 47µF	20%	16V	C8478	1-163-243-11	CERAMIC CHIP 47pF	5%	50V
C8368	1-104-664-11	ELECT 47µF	20%	16V	C8479	1-163-239-11	CERAMIC CHIP 33pF	5%	50V
C8369	1-104-664-11	ELECT 47µF	20%	16V					
					C8481	1-104-664-11	ELECT 47µF	20%	16V
C8370	1-164-004-11	CERAMIC CHIP 0.1µF	10%	25V	C8482	1-104-664-11	ELECT 47µF	20%	16V
C8371	1-164-004-11	CERAMIC CHIP 0.1µF	10%	25V	C8483	1-104-664-11	ELECT 47µF	20%	16V
C8372	1-164-004-11	CERAMIC CHIP 0.1µF	10%	25V	C8485	1-164-004-11	CERAMIC CHIP 0.1µF	10%	25V
C8373	1-163-227-11	CERAMIC CHIP 10pF	0.50pF	50V	C8492	1-164-004-11	CERAMIC CHIP 0.1µF	10%	25V
C8374	1-164-346-11	CERAMIC CHIP 1µF		16V					
					C8501	1-163-113-00	CERAMIC CHIP 68pF	5%	50V
C8375	1-126-964-11	ELECT 10µF	20%	50V	C8601	1-117-720-11	CERAMIC CHIP 4.7µF		10V
C8376	1-164-004-11	CERAMIC CHIP 0.1µF	10%	25V	C8602	1-117-720-11	CERAMIC CHIP 4.7µF		10V
C8381	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V	C8603	1-117-720-11	CERAMIC CHIP 4.7µF		10V
C8386	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V	C8604	1-117-720-11	CERAMIC CHIP 4.7µF		10V
C8390	1-126-963-11	ELECT 4.7µF	20%	50V					
					C8605	1-117-720-11	CERAMIC CHIP 4.7µF		10V
C8391	1-164-004-11	CERAMIC CHIP 0.1µF	10%	25V	C8606	1-117-720-11	CERAMIC CHIP 4.7µF		10V
C8392	1-164-004-11	CERAMIC CHIP 0.1µF	10%	25V	C8801	1-115-340-11	CERAMIC CHIP 0.22µF	10%	25V
C8393	1-164-004-11	CERAMIC CHIP 0.1µF	10%	25V	C8802	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V
C8396	1-107-823-11	CERAMIC CHIP 0.47µF	10%	16V	C8804	1-164-004-11	CERAMIC CHIP 0.1µF	10%	25V
C8399	1-126-961-11	ELECT 2.2µF	20%	50V					
					C8805	1-126-933-11	ELECT 100µF	20%	16V
C8401	1-163-021-91	CERAMIC CHIP 0.01µF	10%	50V	C8806	1-164-004-11	CERAMIC CHIP 0.1µF	10%	25V

J1

REF.NO.	PART NO.	DESCRIPTION	REMARK		REF.NO.	PART NO.	DESCRIPTION	REMARK
C8807	1-163-037-11	CERAMIC CHIP 0.022µF	10% 50V		D8324	8-719-056-85	DIODE UDZ-TE-17-8.2B	
C8808	1-126-933-11	ELECT 100µF	20% 16V		D8325	8-719-056-85	DIODE UDZ-TE-17-8.2B	
C8809	1-163-021-91	CERAMIC CHIP 0.01µF	10% 50V		D8331	8-719-073-01	DIODE MA111-(K8).S0	
C8810	1-164-004-11	CERAMIC CHIP 0.1µF	10% 25V		D8332	8-719-914-42	DIODE DA204K	
C8811	1-164-004-11	CERAMIC CHIP 0.1µF	10% 25V		D8333	8-719-056-85	DIODE UDZ-TE-17-8.2B	
C8812	1-104-664-11	ELECT 47µF	20% 16V		D8334	8-719-914-42	DIODE DA204K	
C8813	1-164-004-11	CERAMIC CHIP 0.1µF	10% 25V		D8335	8-719-914-42	DIODE DA204K	
C8814	1-164-004-11	CERAMIC CHIP 0.1µF	10% 25V		D8336	8-719-056-85	DIODE UDZ-TE-17-8.2B	
C8815	1-164-004-11	CERAMIC CHIP 0.1µF	10% 25V		D8337	8-719-073-01	DIODE MA111-(K8).S0	
C8816	1-164-004-11	CERAMIC CHIP 0.1µF	10% 25V					
C8817	1-164-004-11	CERAMIC CHIP 0.1µF	10% 25V					
C8818	1-164-004-11	CERAMIC CHIP 0.1µF	10% 25V				**<FILTER>**	
C8819	1-164-004-11	CERAMIC CHIP 0.1µF	10% 25V					
					FL8301	1-236-071-11	ENCAPSULATED COMPONENT	
C8820	1-164-004-11	CERAMIC CHIP 0.1µF	10% 25V		FL8302	1-236-071-11	ENCAPSULATED COMPONENT	
C8821	1-164-004-11	CERAMIC CHIP 0.1µF	10% 25V		FL8303	1-236-071-11	ENCAPSULATED COMPONENT	
C8823	1-164-004-11	CERAMIC CHIP 0.1µF	10% 25V		FL8304	1-236-071-11	ENCAPSULATED COMPONENT	
C8824	1-164-004-11	CERAMIC CHIP 0.1µF	10% 25V		FL8305	1-236-071-11	ENCAPSULATED COMPONENT	
C8826	1-164-004-11	CERAMIC CHIP 0.1µF	10% 25V					
					FL8307	1-236-071-11	ENCAPSULATED COMPONENT	
C8828	1-104-664-11	ELECT 47µF	20% 16V		FL8308	1-236-071-11	ENCAPSULATED COMPONENT	
C8829	1-163-241-11	CERAMIC CHIP 39pF	5% 50V		FL8309	1-236-071-11	ENCAPSULATED COMPONENT	
C8830	1-104-664-11	ELECT 47µF	20% 16V		FL8311	1-236-071-11	ENCAPSULATED COMPONENT	
					FL8312	1-236-071-11	ENCAPSULATED COMPONENT	
		<CONNECTOR>			FL8313	1-233-877-11	FILTER, LOW PASS	
					FL8314	1-233-504-21	FILTER, LOW PASS	
CN8101	1-695-302-11	CONNECTOR, BOARD TO BOARD 50P			FL8315	1-233-504-21	FILTER, LOW PASS	
CN8301	* 1-564-526-31	PLUG, CONNECTOR 11P			FL8801	1-236-071-11	ENCAPSULATED COMPONENT	
					FL8802	1-236-071-11	ENCAPSULATED COMPONENT	
		<DIODE>			FL8803	1-233-765-21	FILTER	
					FL8804	1-233-766-21	FILTER	
D8101	8-719-977-69	DIODE DTZ24B			FL8805	1-233-768-21	FILTER	
D8102	8-719-977-69	DIODE DTZ24B						
D8103	8-719-977-69	DIODE DTZ24B						
D8104	8-719-977-69	DIODE DTZ24B					**<IC>**	
D8301	8-719-056-85	DIODE UDZ-TE-17-8.2B						
					IC8302	8-752-080-04	IC CXA2069Q	
D8302	8-719-056-85	DIODE UDZ-TE-17-8.2B			IC8304	8-759-242-76	IC TC7W08F	
D8303	8-719-056-85	DIODE UDZ-TE-17-8.2B			IC8305	8-759-242-76	IC TC7W08F	
D8304	8-719-056-85	DIODE UDZ-TE-17-8.2B			IC8306	8-752-096-08	IC CXA2123BQ-T6	
D8305	8-719-056-85	DIODE UDZ-TE-17-8.2B			IC8308	8-752-096-08	IC CXA2123BQ-T6	
D8306	8-719-056-85	DIODE UDZ-TE-17-8.2B						
					IC8309	8-759-337-26	IC MM1115XFBE	
D8307	8-719-056-85	DIODE UDZ-TE-17-8.2B			IC8310	8-759-572-04	IC TDA9178T/N1.118	
D8308	8-719-056-85	DIODE UDZ-TE-17-8.2B			IC8311	8-759-576-72	IC LF50CDT-TR	
D8309	8-719-056-85	DIODE UDZ-TE-17-8.2B			IC8312	8-759-576-72	IC LF50CDT-TR	
D8310	8-719-056-85	DIODE UDZ-TE-17-8.2B			IC8801	8-752-390-37	IC CXD2064Q-T6	
D8311	8-719-056-85	DIODE UDZ-TE-17-8.2B						
D8312	8-719-056-85	DIODE UDZ-TE-17-8.2B					**<JACK>**	
D8313	8-719-056-85	DIODE UDZ-TE-17-8.2B						
D8314	8-719-056-85	DIODE UDZ-TE-17-8.2B			J8301	1-774-748-11	TERMINAL BLOCK, S (VIDEO IN 1)	
D8315	8-719-914-42	DIODE DA204K			J8302	1-774-746-11	JACK BLOCK, PIN (VIDEO IN 2)	
D8316	8-719-914-42	DIODE DA204K			J8303	1-774-746-11	JACK BLOCK, PIN (VIDEO IN 3)	
					J8304	1-774-746-11	JACK BLOCK, PIN (MONITOR OUT)	
D8317	8-719-914-42	DIODE DA204K			J8305	1-774-358-11	JACK BLOCK, PIN (COMPONENT IN)	
D8318	8-719-056-85	DIODE UDZ-TE-17-8.2B						
D8319	8-719-056-85	DIODE UDZ-TE-17-8.2B			J8901	1-565-838-11	JACK BLOCK, PIN 2P (AUDIO OUT)	
D8320	8-719-056-85	DIODE UDZ-TE-17-8.2B						
D8321	8-719-056-85	DIODE UDZ-TE-17-8.2B					**<COIL>**	
D8322	8-719-056-85	DIODE UDZ-TE-17-8.2B			L8101	1-402-711-11	INDUCTOR 0µH	
D8323	8-719-056-85	DIODE UDZ-TE-17-8.2B						

REF.NO.	PART NO.	DESCRIPTION	REMARK	REF.NO.	PART NO.	DESCRIPTION	REMARK
L8102	1-402-711-11 INDUCTOR	0µH		Q8426	8-729-120-28 TRANSISTOR 2SC1623-L5L6		
L8304	1-412-029-11 INDUCTOR CHIP	10µH		Q8601	8-729-120-28 TRANSISTOR 2SC1623-L5L6		
L8305	1-414-196-41 INDUCTOR	47µH		Q8602	8-729-120-28 TRANSISTOR 2SC1623-L5L6		
L8306	1-414-196-41 INDUCTOR	47µH		Q8603	8-729-120-28 TRANSISTOR 2SC1623-L5L6		
				Q8604	8-729-026-49 TRANSISTOR 2SA1037AK-T-146-R		
L8307	1-414-196-41 INDUCTOR	47µH					
L8501	1-412-029-11 INDUCTOR CHIP	10µH		Q8605	8-729-120-28 TRANSISTOR 2SC1623-L5L6		
L8801	1-412-029-11 INDUCTOR CHIP	10µH		Q8606	8-729-120-28 TRANSISTOR 2SC1623-L5L6		
L8802	1-412-029-11 INDUCTOR CHIP	10µH		Q8607	8-729-120-28 TRANSISTOR 2SC1623-L5L6		
				Q8801	8-729-120-28 TRANSISTOR 2SC1623-L5L6		
				Q8802	8-729-026-49 TRANSISTOR 2SA1037AK-T-146-R		
		<TRANSISTOR>					
				Q8803	8-729-026-49 TRANSISTOR 2SA1037AK-T-146-R		
Q8301	8-729-026-49 TRANSISTOR 2SA1037AK-T-146-R			Q8804	8-729-026-49 TRANSISTOR 2SA1037AK-T-146-R		
Q8302	8-729-120-28 TRANSISTOR 2SC1623-L5L6			Q8805	8-729-026-49 TRANSISTOR 2SA1037AK-T-146-R		
Q8303	8-729-120-28 TRANSISTOR 2SC1623-L5L6			Q8807	8-729-120-28 TRANSISTOR 2SC1623-L5L6		
Q8304	8-729-120-28 TRANSISTOR 2SC1623-L5L6			Q8808	8-729-026-49 TRANSISTOR 2SA1037AK-T-146-R		
Q8306	8-729-120-28 TRANSISTOR 2SC1623-L5L6						
				Q8809	8-729-026-49 TRANSISTOR 2SA1037AK-T-146-R		
Q8307	8-729-026-49 TRANSISTOR 2SA1037AK-T-146-R			Q8810	8-729-120-28 TRANSISTOR 2SC1623-L5L6		
Q8308	8-729-120-28 TRANSISTOR 2SC1623-L5L6			Q8811	8-729-120-28 TRANSISTOR 2SC1623-L5L6		
Q8309	8-729-120-28 TRANSISTOR 2SC1623-L5L6						
Q8316	8-729-120-28 TRANSISTOR 2SC1623-L5L6						
Q8317	8-729-026-49 TRANSISTOR 2SA1037AK-T-146-R					<RESISTOR>	
Q8318	8-729-120-28 TRANSISTOR 2SC1623-L5L6			R8301	1-216-041-00 RES-CHIP	470	5% 1/10W
Q8319	8-729-120-28 TRANSISTOR 2SC1623-L5L6			R8302	1-216-041-00 RES-CHIP	470	5% 1/10W
Q8321	8-729-120-28 TRANSISTOR 2SC1623-L5L6			R8303	1-216-021-00 RES-CHIP	68	5% 1/10W
Q8322	8-729-120-28 TRANSISTOR 2SC1623-L5L6			R8304	1-216-057-00 RES-CHIP	2.2K	5% 1/10W
Q8323	8-729-026-49 TRANSISTOR 2SA1037AK-T-146-R			R8305	1-216-105-91 RES-CHIP	220K	5% 1/10W
Q8324	8-729-120-28 TRANSISTOR 2SC1623-L5L6			R8306	1-216-022-00 RES-CHIP	75	5% 1/10W
Q8326	8-729-120-28 TRANSISTOR 2SC1623-L5L6			R8307	1-216-022-00 RES-CHIP	75	5% 1/10W
Q8327	1-801-806-11 TRANSISTOR DTC144EKA			R8308	1-216-105-91 RES-CHIP	220K	5% 1/10W
Q8328	1-801-806-11 TRANSISTOR DTC144EKA			R8309	1-216-105-91 RES-CHIP	220K	5% 1/10W
Q8332	8-729-026-49 TRANSISTOR 2SA1037AK-T-146-R			R8310	1-216-022-00 RES-CHIP	75	5% 1/10W
Q8338	8-729-120-28 TRANSISTOR 2SC1623-L5L6			R8311	1-216-105-91 RES-CHIP	220K	5% 1/10W
Q8340	8-729-120-28 TRANSISTOR 2SC1623-L5L6			R8312	1-216-105-91 RES-CHIP	220K	5% 1/10W
Q8401	8-729-120-28 TRANSISTOR 2SC1623-L5L6			R8313	1-216-022-00 RES-CHIP	75	5% 1/10W
Q8402	8-729-120-28 TRANSISTOR 2SC1623-L5L6			R8314	1-216-105-91 RES-CHIP	220K	5% 1/10W
Q8405	8-729-026-49 TRANSISTOR 2SA1037AK-T-146-R			R8315	1-216-105-91 RES-CHIP	220K	5% 1/10W
Q8406	8-729-026-49 TRANSISTOR 2SA1037AK-T-146-R			R8316	1-216-113-00 RES-CHIP	470K	5% 1/10W
Q8407	8-729-026-49 TRANSISTOR 2SA1037AK-T-146-R			R8317	1-216-022-00 RES-CHIP	75	5% 1/10W
Q8408	8-729-120-28 TRANSISTOR 2SC1623-L5L6			R8318	1-216-022-00 RES-CHIP	75	5% 1/10W
Q8409	8-729-026-49 TRANSISTOR 2SA1037AK-T-146-R			R8319	1-216-022-00 RES-CHIP	75	5% 1/10W
Q8410	8-729-120-28 TRANSISTOR 2SC1623-L5L6			R8320	1-216-105-91 RES-CHIP	220K	5% 1/10W
Q8411	8-729-026-49 TRANSISTOR 2SA1037AK-T-146-R			R8321	1-216-105-91 RES-CHIP	220K	5% 1/10W
Q8412	1-801-806-11 TRANSISTOR DTC144EKA			R8322	1-216-022-00 RES-CHIP	75	5% 1/10W
Q8413	1-801-806-11 TRANSISTOR DTC144EKA			R8323	1-216-025-91 RES-CHIP	100	5% 1/10W
Q8414	1-801-806-11 TRANSISTOR DTC144EKA			R8324	1-216-025-91 RES-CHIP	100	5% 1/10W
Q8415	8-729-120-28 TRANSISTOR 2SC1623-L5L6			R8325	1-216-025-91 RES-CHIP	100	5% 1/10W
Q8416	8-729-120-28 TRANSISTOR 2SC1623-L5L6			R8326	1-216-105-91 RES-CHIP	220K	5% 1/10W
Q8417	8-729-120-28 TRANSISTOR 2SC1623-L5L6			R8327	1-216-025-91 RES-CHIP	100	5% 1/10W
Q8418	8-729-120-28 TRANSISTOR 2SC1623-L5L6			R8328	1-216-113-00 RES-CHIP	470K	5% 1/10W
Q8419	8-729-026-49 TRANSISTOR 2SA1037AK-T-146-R			R8329	1-216-113-00 RES-CHIP	470K	5% 1/10W
Q8420	8-729-026-49 TRANSISTOR 2SA1037AK-T-146-R			R8330	1-216-022-00 RES-CHIP	75	5% 1/10W
Q8421	8-729-026-49 TRANSISTOR 2SA1037AK-T-146-R			R8331	1-216-025-91 RES-CHIP	100	5% 1/10W
Q8422	8-729-026-49 TRANSISTOR 2SA1037AK-T-146-R			R8332	1-216-025-91 RES-CHIP	100	5% 1/10W
Q8423	8-729-026-49 TRANSISTOR 2SA1037AK-T-146-R			R8333	1-216-025-91 RES-CHIP	100	5% 1/10W
Q8424	8-729-026-49 TRANSISTOR 2SA1037AK-T-146-R			R8334	1-216-025-91 RES-CHIP	100	5% 1/10W
Q8425	8-729-120-28 TRANSISTOR 2SC1623-L5L6			R8335	1-216-065-91 RES-CHIP	4.7K	5% 1/10W

J1

REF.NO.	PART NO.	DESCRIPTION			REMARK	REF.NO.	PART NO.	DESCRIPTION			REMARK
R8336	1-216-065-91	RES-CHIP	4.7K	5%	1/10W	R8398	1-216-025-91	RES-CHIP	100	5%	1/10W
R8337	1-216-022-00	RES-CHIP	75	5%	1/10W	R8399	1-216-025-91	RES-CHIP	100	5%	1/10W
R8338	1-216-065-91	RES-CHIP	4.7K	5%	1/10W	R8400	1-216-025-91	RES-CHIP	100	5%	1/10W
R8339	1-216-065-91	RES-CHIP	4.7K	5%	1/10W	R8401	1-216-017-91	RES-CHIP	47	5%	1/10W
R8340	1-216-065-91	RES-CHIP	4.7K	5%	1/10W						
						R8402	1-216-067-00	RES-CHIP	5.6K	5%	1/10W
R8341	1-216-065-91	RES-CHIP	4.7K	5%	1/10W	R8403	1-216-067-00	RES-CHIP	5.6K	5%	1/10W
R8342	1-216-065-91	RES-CHIP	4.7K	5%	1/10W	R8404	1-216-025-91	RES-CHIP	100	5%	1/10W
R8343	1-216-065-91	RES-CHIP	4.7K	5%	1/10W	R8405	1-216-033-00	RES-CHIP	220	5%	1/10W
R8344	1-216-022-00	RES-CHIP	75	5%	1/10W	R8406	1-216-033-00	RES-CHIP	220	5%	1/10W
R8345	1-216-025-91	RES-CHIP	100	5%	1/10W						
R8346	1-216-025-91	RES-CHIP	100	5%	1/10W	R8407	1-216-033-00	RES-CHIP	220	5%	1/10W
R8347	1-216-025-91	RES-CHIP	100	5%	1/10W	R8408	1-216-033-00	RES-CHIP	220	5%	1/10W
R8348	1-216-057-00	RES-CHIP	2.2K	5%	1/10W	R8409	1-216-295-91	SHORT	0		
R8349	1-216-049-91	RES-CHIP	1K	5%	1/10W	R8410	1-216-295-91	SHORT	0		
R8350	1-216-049-91	RES-CHIP	1K	5%	1/10W	R8411	1-216-083-00	RES-CHIP	27K	5%	1/10W
R8351	1-216-065-91	RES-CHIP	4.7K	5%	1/10W	R8412	1-216-025-91	RES-CHIP	100	5%	1/10W
R8352	1-216-065-91	RES-CHIP	4.7K	5%	1/10W	R8413	1-216-041-00	RES-CHIP	470	5%	1/10W
R8353	1-216-295-91	SHORT	0			R8414	1-208-796-11	METAL CHIP	3.9K	0.5%	1/10W
R8354	1-216-041-00	RES-CHIP	470	5%	1/10W	R8417	1-216-025-91	RES-CHIP	100	5%	1/10W
R8355	1-216-017-91	RES-CHIP	47	5%	1/10W	R8418	1-216-025-91	RES-CHIP	100	5%	1/10W
R8356	1-216-017-91	RES-CHIP	47	5%	1/10W	R8419	1-216-017-91	RES-CHIP	47	5%	1/10W
R8357	1-216-041-00	RES-CHIP	470	5%	1/10W	R8420	1-216-017-91	RES-CHIP	47	5%	1/10W
R8362	1-216-642-11	METAL CHIP	430	0.5%	1/10W	R8421	1-216-295-91	SHORT	0		
R8363	1-208-774-11	METAL CHIP	470	0.5%	1/10W	R8422	1-216-295-91	SHORT	0		
R8364	1-216-041-00	RES-CHIP	470	5%	1/10W	R8424	1-216-083-00	RES-CHIP	27K	5%	1/10W
R8365	1-216-067-00	RES-CHIP	5.6K	5%	1/10W	R8425	1-216-089-91	RES-CHIP	47K	5%	1/10W
R8366	1-216-067-00	RES-CHIP	5.6K	5%	1/10W	R8426	1-208-796-11	METAL CHIP	3.9K	0.5%	1/10W
R8367	1-216-041-00	RES-CHIP	470	5%	1/10W	R8427	1-216-295-91	SHORT	0		
R8368	1-216-041-00	RES-CHIP	470	5%	1/10W	R8428	1-216-295-91	SHORT	0		
R8369	1-216-295-91	SHORT	0			R8431	1-216-295-91	SHORT	0		
						R8432	1-216-295-91	SHORT	0		
R8370	1-216-025-91	RES-CHIP	100	5%	1/10W	R8436	1-216-017-91	RES-CHIP	47	5%	1/10W
R8373	1-216-039-00	RES-CHIP	390	5%	1/10W	R8437	1-208-291-11	RES-CHIP	4.7M	5%	1/10W
R8374	1-216-041-00	RES-CHIP	470	5%	1/10W	R8438	1-208-291-11	RES-CHIP	4.7M	5%	1/10W
R8375	1-216-017-91	RES-CHIP	47	5%	1/10W	R8439	1-208-291-11	RES-CHIP	4.7M	5%	1/10W
R8376	1-216-049-91	RES-CHIP	1K	5%	1/10W						
						R8440	1-208-291-11	RES-CHIP	4.7M	5%	1/10W
R8377	1-216-025-91	RES-CHIP	100	5%	1/10W	R8441	1-208-291-11	RES-CHIP	4.7M	5%	1/10W
R8378	1-216-033-00	RES-CHIP	220	5%	1/10W	R8443	1-216-025-91	RES-CHIP	100	5%	1/10W
R8379	1-216-033-00	RES-CHIP	220	5%	1/10W	R8444	1-216-025-91	RES-CHIP	100	5%	1/10W
R8380	1-216-025-91	RES-CHIP	100	5%	1/10W	R8445	1-216-017-91	RES-CHIP	47	5%	1/10W
R8381	1-216-025-91	RES-CHIP	100	5%	1/10W						
						R8446	1-216-295-91	SHORT	0		
R8382	1-216-033-00	RES-CHIP	220	5%	1/10W	R8447	1-216-041-00	RES-CHIP	470	5%	1/10W
R8383	1-216-033-00	RES-CHIP	220	5%	1/10W	R8448	1-216-033-00	RES-CHIP	220	5%	1/10W
R8384	1-216-025-91	RES-CHIP	100	5%	1/10W	R8449	1-216-041-00	RES-CHIP	470	5%	1/10W
R8385	1-216-025-91	RES-CHIP	100	5%	1/10W	R8451	1-216-041-00	RES-CHIP	470	5%	1/10W
R8386	1-216-025-91	RES-CHIP	100	5%	1/10W						
						R8452	1-216-041-00	RES-CHIP	470	5%	1/10W
R8387	1-216-017-91	RES-CHIP	47	5%	1/10W	R8453	1-216-033-00	RES-CHIP	220	5%	1/10W
R8388	1-216-031-00	RES-CHIP	180	5%	1/10W	R8454	1-216-041-00	RES-CHIP	470	5%	1/10W
R8389	1-216-033-00	RES-CHIP	220	5%	1/10W	R8455	1-216-041-00	RES-CHIP	470	5%	1/10W
R8390	1-216-017-91	RES-CHIP	47	5%	1/10W	R8456	1-216-041-00	RES-CHIP	470	5%	1/10W
R8391	1-216-017-91	RES-CHIP	47	5%	1/10W						
						R8458	1-216-049-91	RES-CHIP	1K	5%	1/10W
R8392	1-216-017-91	RES-CHIP	47	5%	1/10W	R8461	1-216-049-91	RES-CHIP	1K	5%	1/10W
R8393	1-216-017-91	RES-CHIP	47	5%	1/10W	R8464	1-216-041-00	RES-CHIP	470	5%	1/10W
R8394	1-216-025-91	RES-CHIP	100	5%	1/10W	R8465	1-216-089-91	RES-CHIP	47K	5%	1/10W
R8395	1-216-033-00	RES-CHIP	220	5%	1/10W	R8466	1-216-089-91	RES-CHIP	47K	5%	1/10W
R8396	1-216-033-00	RES-CHIP	220	5%	1/10W						
						R8467	1-216-113-00	RES-CHIP	470K	5%	1/10W
R8397	1-216-025-91	RES-CHIP	100	5%	1/10W	R8468	1-216-113-00	RES-CHIP	470K	5%	1/10W

REF.NO.	PART NO.	DESCRIPTION			REMARK	REF.NO.	PART NO.	DESCRIPTION			REMARK
R8469	1-216-049-91	RES-CHIP	1K	5%	1/10W	R8572	1-216-049-91	RES-CHIP	1K	5%	1/10W
R8470	1-216-069-00	RES-CHIP	6.8K	5%	1/10W	R8573	1-208-776-11	METAL CHIP	560	0.5%	1/10W
R8471	1-216-069-00	RES-CHIP	6.8K	5%	1/10W						
						R8574	1-208-800-11	METAL CHIP	5.6K	0.5%	1/10W
R8472	1-216-057-00	RES-CHIP	2.2K	5%	1/10W	R8575	1-216-049-91	RES-CHIP	1K	5%	1/10W
R8473	1-216-025-91	RES-CHIP	100	5%	1/10W	R8577	1-216-295-91	SHORT	0		
R8478	1-216-089-91	RES-CHIP	47K	5%	1/10W	R8580	1-216-025-91	RES-CHIP	100	5%	1/10W
R8479	1-216-097-91	RES-CHIP	100K	5%	1/10W	R8581	1-216-049-91	RES-CHIP	1K	5%	1/10W
R8480	1-216-073-00	RES-CHIP	10K	5%	1/10W						
						R8582	1-208-776-11	METAL CHIP	560	0.5%	1/10W
R8481	1-216-095-00	RES-CHIP	82K	5%	1/10W	R8583	1-208-800-11	METAL CHIP	5.6K	0.5%	1/10W
R8482	1-216-089-91	RES-CHIP	47K	5%	1/10W	R8584	1-216-049-91	RES-CHIP	1K	5%	1/10W
R8484	1-216-045-00	RES-CHIP	680	5%	1/10W	R8586	1-216-295-91	SHORT	0		
R8485	1-216-013-00	RES-CHIP	33	5%	1/10W	R8589	1-216-025-91	RES-CHIP	100	5%	1/10W
R8487	1-216-045-00	RES-CHIP	680	5%	1/10W						
						R8590	1-216-049-91	RES-CHIP	1K	5%	1/10W
R8488	1-216-041-00	RES-CHIP	470	5%	1/10W	R8591	1-208-776-11	METAL CHIP	560	0.5%	1/10W
R8490	1-216-049-91	RES-CHIP	1K	5%	1/10W	R8592	1-208-800-11	METAL CHIP	5.6K	0.5%	1/10W
R8494	1-216-295-91	SHORT	0			R8593	1-216-049-91	RES-CHIP	1K	5%	1/10W
R8496	1-216-025-91	RES-CHIP	100	5%	1/10W	R8595	1-216-295-91	SHORT	0		
R8502	1-216-295-91	SHORT	0								
						R8596	1-216-295-91	SHORT	0		
R8503	1-216-057-00	RES-CHIP	2.2K	5%	1/10W	R8601	1-216-089-91	RES-CHIP	47K	5%	1/10W
R8504	1-216-025-91	RES-CHIP	100	5%	1/10W	R8602	1-216-025-91	RES-CHIP	100	5%	1/10W
R8510	1-216-049-91	RES-CHIP	1K	5%	1/10W	R8603	1-216-097-91	RES-CHIP	100K	5%	1/10W
R8514	1-216-295-91	SHORT	0			R8604	1-216-049-91	RES-CHIP	1K	5%	1/10W
R8515	1-216-295-91	SHORT	0								
						R8605	1-216-089-91	RES-CHIP	47K	5%	1/10W
R8519	1-216-025-91	RES-CHIP	100	5%	1/10W	R8606	1-216-025-91	RES-CHIP	100	5%	1/10W
R8523	1-216-049-91	RES-CHIP	1K	5%	1/10W	R8607	1-216-097-91	RES-CHIP	100K	5%	1/10W
R8525	1-216-025-91	RES-CHIP	100	5%	1/10W	R8608	1-216-049-91	RES-CHIP	1K	5%	1/10W
R8526	1-216-037-00	RES-CHIP	330	5%	1/10W	R8609	1-216-089-91	RES-CHIP	47K	5%	1/10W
R8529	1-216-049-91	RES-CHIP	1K	5%	1/10W						
						R8610	1-216-025-91	RES-CHIP	100	5%	1/10W
R8530	1-216-025-91	RES-CHIP	100	5%	1/10W	R8611	1-216-097-91	RES-CHIP	100K	5%	1/10W
R8531	1-216-295-91	SHORT	0			R8612	1-216-049-91	RES-CHIP	1K	5%	1/10W
R8535	1-216-049-91	RES-CHIP	1K	5%	1/10W	R8613	1-216-033-00	RES-CHIP	220	5%	1/10W
R8536	1-216-025-91	RES-CHIP	100	5%	1/10W	R8614	1-216-031-00	RES-CHIP	180	5%	1/10W
R8537	1-216-025-91	RES-CHIP	100	5%	1/10W						
						R8615	1-216-025-91	RES-CHIP	100	5%	1/10W
R8539	1-216-025-91	RES-CHIP	100	5%	1/10W	R8616	1-216-295-91	SHORT	0		
R8542	1-216-041-00	RES-CHIP	470	5%	1/10W	R8617	1-216-089-91	RES-CHIP	47K	5%	1/10W
R8543	1-216-039-00	RES-CHIP	390	5%	1/10W	R8618	1-216-097-91	RES-CHIP	100K	5%	1/10W
R8544	1-216-041-00	RES-CHIP	470	5%	1/10W	R8619	1-216-025-91	RES-CHIP	100	5%	1/10W
R8545	1-216-049-91	RES-CHIP	1K	5%	1/10W						
						R8620	1-216-049-91	RES-CHIP	1K	5%	1/10W
R8546	1-216-295-91	SHORT	0			R8621	1-216-089-91	RES-CHIP	47K	5%	1/10W
R8547	1-216-295-91	SHORT	0			R8622	1-216-097-91	RES-CHIP	100K	5%	1/10W
R8548	1-216-025-91	RES-CHIP	100	5%	1/10W	R8623	1-216-025-91	RES-CHIP	100	5%	1/10W
R8552	1-216-049-91	RES-CHIP	1K	5%	1/10W	R8624	1-216-049-91	RES-CHIP	1K	5%	1/10W
R8554	1-216-025-91	RES-CHIP	100	5%	1/10W						
						R8625	1-216-089-91	RES-CHIP	47K	5%	1/10W
R8555	1-208-774-11	METAL CHIP	470	0.5%	1/10W	R8626	1-216-097-91	RES-CHIP	100K	5%	1/10W
R8556	1-216-081-00	RES-CHIP	22K	5%	1/10W	R8627	1-216-025-91	RES-CHIP	100	5%	1/10W
R8557	1-208-768-11	METAL CHIP	270	0.5%	1/10W	R8628	1-216-049-91	RES-CHIP	1K	5%	1/10W
R8558	1-216-081-00	RES-CHIP	22K	5%	1/10W	R8629	1-216-295-91	SHORT	0		
R8559	1-216-049-91	RES-CHIP	1K	5%	1/10W						
						R8630	1-208-765-11	METAL CHIP	200	0.5%	1/10W
R8561	1-216-025-91	RES-CHIP	100	5%	1/10W	R8631	1-216-033-00	RES-CHIP	220	5%	1/10W
R8562	1-216-043-91	RES-CHIP	560	5%	1/10W	R8632	1-216-025-91	RES-CHIP	100	5%	1/10W
R8563	1-216-081-00	RES-CHIP	22K	5%	1/10W	R8633	1-216-025-91	RES-CHIP	100	5%	1/10W
R8564	1-216-033-00	RES-CHIP	220	5%	1/10W	R8634	1-216-025-91	RES-CHIP	100	5%	1/10W
R8565	1-216-081-00	RES-CHIP	22K	5%	1/10W						
						R8801	1-216-017-91	RES-CHIP	47	5%	1/10W
R8566	1-216-049-91	RES-CHIP	1K	5%	1/10W	R8803	1-216-075-00	RES-CHIP	12K	5%	1/10W
R8568	1-216-295-91	SHORT	0			R8804	1-216-069-00	RES-CHIP	6.8K	5%	1/10W
R8571	1-216-025-91	RES-CHIP	100	5%	1/10W	R8805	1-216-037-00	RES-CHIP	330	5%	1/10W

| J1 | BD |

REF.NO.	PART NO.	DESCRIPTION			REMARK
R8806	1-216-041-00 RES-CHIP	470	5%	1/10W
R8807	1-216-033-00 RES-CHIP	220	5%	1/10W
R8808	1-216-053-00 RES-CHIP	1.5K	5%	1/10W
R8809	1-216-037-00 RES-CHIP	330	5%	1/10W
R8810	1-216-043-91 RES-CHIP	560	5%	1/10W
R8811	1-216-091-00 RES-CHIP	56K	5%	1/10W
R8812	1-216-067-00 RES-CHIP	5.6K	5%	1/10W
R8813	1-216-049-91 RES-CHIP	1K	5%	1/10W
R8814	1-216-017-91 RES-CHIP	47	5%	1/10W
R8815	1-216-295-91 SHORT	0		
R8816	1-208-782-11 METAL CHIP	1K	0.5%	1/10W
R8819	1-216-295-91 SHORT	0		
R8820	1-208-770-11 METAL CHIP	330	0.5%	1/10W
R8821	1-208-782-11 METAL CHIP	1K	0.5%	1/10W
R8822	1-208-770-11 METAL CHIP	330	0.5%	1/10W
R8823	1-216-049-91 RES-CHIP	1K	5%	1/10W
R8824	1-208-793-11 METAL CHIP	3K	0.5%	1/10W
R8825	1-216-049-91 RES-CHIP	1K	5%	1/10W
R8826	1-216-047-91 RES-CHIP	820	5%	1/10W
R8827	1-208-789-11 METAL CHIP	2K	0.5%	1/10W
R8828	1-216-047-91 RES-CHIP	820	5%	1/10W
R8829	1-216-061-00 RES-CHIP	3.3K	5%	1/10W
R8830	1-216-295-91 SHORT	0		
R8832	1-216-295-91 SHORT	0		
R8834	1-216-053-00 RES-CHIP	1.5K	5%	1/10W
R8835	1-216-051-00 RES-CHIP	1.2K	5%	1/10W
R8838	1-216-053-00 RES-CHIP	1.5K	5%	1/10W
R8840	1-216-081-00 RES-CHIP	22K	5%	1/10W
R8841	1-216-081-00 RES-CHIP	22K	5%	1/10W
R8844	1-216-049-91 RES-CHIP	1K	5%	1/10W
R8847	1-216-295-91 SHORT	0		
R8848	1-216-295-91 SHORT	0		
R8849	1-216-035-00 RES-CHIP	270	5%	1/10W
R8851	1-216-041-00 RES-CHIP	470	5%	1/10W
R8852	1-216-041-00 RES-CHIP	470	5%	1/10W
R8853	1-216-093-91 RES-CHIP	68K	5%	1/10W
R8854	1-216-083-00 RES-CHIP	27K	5%	1/10W
R8855	1-216-043-91 RES-CHIP	560	5%	1/10W
R8856	1-216-051-00 RES-CHIP	1.2K	5%	1/10W
R8857	1-216-051-00 RES-CHIP	1.2K	5%	1/10W
	<TERMINALBOARD>			
TB8101	1-537-712-11 TERMINAL, PUSH (CENTER SP IN)			
	<CRYSTAL>			
X8301	1-781-612-11 VIBRATOR, CRYSTAL (16.2MHz)			
X8302	1-781-612-11 VIBRATOR, CRYSTAL (16.2MHz)			

****

REF.NO.	PART NO.	DESCRIPTION			REMARK	
	* A-1136-088-A BD BOARD, COMPLETE					
	******************************					
	<CAPACITOR>					
C2601	1-104-664-11 ELECT	47μF	20%	25V	
C2602	1-163-259-91 CERAMIC CHIP	220pF	5%	50V	
C2603	1-104-664-11 ELECT	47μF	20%	25V	
C2604	1-163-038-91 CERAMIC CHIP	0.1μF		25V	
C2607	1-163-275-11 CERAMIC CHIP	0.001μF	5%	50V	
C2608	1-104-664-11 ELECT	47μF	20%	25V	
C2609	1-163-038-91 CERAMIC CHIP	0.1μF		25V	
C2610	1-163-038-91 CERAMIC CHIP	0.1μF		25V	
C2611	1-104-664-11 ELECT	47μF	20%	25V	
C2612	1-163-038-91 CERAMIC CHIP	0.1μF		25V	
C2613	1-104-664-11 ELECT	47μF	20%	25V	
C2615	1-163-038-91 CERAMIC CHIP	0.1μF		25V	
C2616	1-163-038-91 CERAMIC CHIP	0.1μF		25V	
C2617	1-163-038-91 CERAMIC CHIP	0.1μF		25V	
C2618	1-163-038-91 CERAMIC CHIP	0.1μF		25V	
C2619	1-164-690-91 CERAMIC CHIP	0.0022μF	5%	50V	
C2620	1-163-038-91 CERAMIC CHIP	0.1μF		25V	
C2621	1-104-664-11 ELECT	47μF	20%	25V	
C2622	1-104-664-11 ELECT	47μF	20%	25V	
C2623	1-163-038-91 CERAMIC CHIP	0.1μF		25V	
C2624	1-164-161-11 CERAMIC CHIP	0.0022μF	10%	50V	
C2625	1-104-664-11 ELECT	47μF	20%	25V	
C2626	1-115-339-11 CERAMIC CHIP	0.1μF	10%	50V	
C2627	1-163-038-91 CERAMIC CHIP	0.1μF		25V	
C2628	1-104-664-11 ELECT	47μF	20%	25V	
C2631	1-163-275-11 CERAMIC CHIP	0.001μF	5%	50V	
C2633	1-115-339-11 CERAMIC CHIP	0.1μF	10%	50V	
C2635	1-163-038-91 CERAMIC CHIP	0.1μF		25V	
C2636	1-104-664-11 ELECT	47μF	20%	25V	
C2637	1-163-259-91 CERAMIC CHIP	220pF	5%	50V	
C2639	1-104-664-11 ELECT	47μF	20%	25V	
C2640	1-104-664-11 ELECT	47μF	20%	25V	
C2641	1-163-038-91 CERAMIC CHIP	0.1μF		25V	
C2643	1-163-038-91 CERAMIC CHIP	0.1μF		25V	
C2644	1-164-690-91 CERAMIC CHIP	0.0022μF	5%	50V	
C2645	1-163-038-91 CERAMIC CHIP	0.1μF		25V	
C2647	1-104-664-11 ELECT	47μF	20%	25V	
C2648	1-163-038-91 CERAMIC CHIP	0.1μF		25V	
C2649	1-163-038-91 CERAMIC CHIP	0.1μF		25V	
C2650	1-163-038-91 CERAMIC CHIP	0.1μF		25V	
C2651	1-104-664-11 ELECT	47μF	20%	25V	
C2652	1-163-038-91 CERAMIC CHIP	0.1μF		25V	
C2655	1-163-275-11 CERAMIC CHIP	0.001μF	5%	50V	
C2656	1-104-664-11 ELECT	47μF	20%	25V	
C2658	1-163-038-91 CERAMIC CHIP	0.1μF		25V	
C2659	1-163-038-91 CERAMIC CHIP	0.1μF		25V	
C2660	1-104-664-11 ELECT	47μF	20%	25V	
C2661	1-163-259-91 CERAMIC CHIP	220pF	5%	50V	
C2662	1-163-038-91 CERAMIC CHIP	0.1μF		25V	
C2663	1-104-664-11 ELECT	47μF	20%	25V	
C2666	1-163-038-91 CERAMIC CHIP	0.1μF		25V	

REF.NO.	PART NO.	DESCRIPTION	REMARK		REF.NO.	PART NO.	DESCRIPTION	REMARK	
C2667	1-164-690-91	CERAMIC CHIP 0.0022µF	5%	50V	C2742	1-163-231-11	CERAMIC CHIP 15pF	5%	50V
C2668	1-163-038-91	CERAMIC CHIP 0.1µF		25V	C2744	1-163-038-91	CERAMIC CHIP 0.1µF		25V
C2670	1-104-664-11	ELECT 47µF	20%	25V	C2745	1-104-664-11	ELECT 47µF	20%	25V
C2673	1-163-038-91	CERAMIC CHIP 0.1µF		25V					
					C2746	1-104-664-11	ELECT 47µF	20%	25V
C2674	1-163-038-91	CERAMIC CHIP 0.1µF		25V	C2747	1-104-664-11	ELECT 47µF	20%	25V
C2675	1-163-038-91	CERAMIC CHIP 0.1µF		25V	C2748	1-163-259-91	CERAMIC CHIP 220pF	5%	50V
C2678	1-163-275-11	CERAMIC CHIP 0.001µF	5%	50V	C2749	1-163-038-91	CERAMIC CHIP 0.1µF		25V
C2679	1-104-664-11	ELECT 47µF	20%	25V	C2750	1-126-935-11	ELECT 470µF	20%	6.3V
C2680	1-163-038-91	CERAMIC CHIP 0.1µF		25V					
					C2751	1-126-935-11	ELECT 470µF	20%	6.3V
C2681	1-104-664-11	ELECT 47µF	20%	25V	C2753	1-163-038-91	CERAMIC CHIP 0.1µF		25V
C2683	1-104-664-11	ELECT 47µF	20%	25V	C2754	1-163-038-91	CERAMIC CHIP 0.1µF		25V
C2685	1-163-038-91	CERAMIC CHIP 0.1µF		25V	C2755	1-163-038-91	CERAMIC CHIP 0.1µF		25V
C2686	1-164-690-91	CERAMIC CHIP 0.0022µF	5%	50V	C2756	1-104-664-11	ELECT 47µF	20%	25V
C2689	1-163-038-91	CERAMIC CHIP 0.1µF		25V					
					C2757	1-163-038-91	CERAMIC CHIP 0.1µF		25V
C2690	1-126-967-11	ELECT 47µF	20%	50V	C2758	1-163-038-91	CERAMIC CHIP 0.1µF		25V
C2691	1-163-038-91	CERAMIC CHIP 0.1µF		25V	C2759	1-163-038-91	CERAMIC CHIP 0.1µF		25V
C2692	1-126-967-11	ELECT 47µF	20%	50V	C2760	1-163-235-11	CERAMIC CHIP 22pF	5%	50V
C2693	1-163-038-91	CERAMIC CHIP 0.1µF		25V	C2761	1-163-263-11	CERAMIC CHIP 330pF	5%	50V
C2694	1-104-664-11	ELECT 47µF	20%	25V					
					C2762	1-107-823-11	CERAMIC CHIP 0.47µF	10%	16V
C2695	1-163-259-91	CERAMIC CHIP 220pF	5%	50V	C2763	1-104-664-11	ELECT 47µF	20%	16V
C2696	1-163-038-91	CERAMIC CHIP 0.1µF		25V	C2764	1-163-038-91	CERAMIC CHIP 0.1µF		25V
C2697	1-104-664-11	ELECT 47µF	20%	25V	C2765	1-107-823-11	CERAMIC CHIP 0.47µF	10%	16V
C2698	1-163-038-91	CERAMIC CHIP 0.1µF		25V	C2766	1-163-016-00	CERAMIC CHIP 0.0039µF	10%	50V
C2699	1-163-038-91	CERAMIC CHIP 0.1µF		25V					
					C2767	1-163-016-00	CERAMIC CHIP 0.0039µF	10%	50V
C2700	1-163-001-11	CERAMIC CHIP 220pF	10%	50V	C2768	1-163-038-91	CERAMIC CHIP 0.1µF		25V
C2701	1-164-346-11	CERAMIC CHIP 1µF		16V	C2769	1-104-664-11	ELECT 47µF	20%	16V
C2705	1-163-275-11	CERAMIC CHIP 0.001µF	5%	50V	C2770	1-163-263-11	CERAMIC CHIP 330pF	5%	50V
C2706	1-163-038-91	CERAMIC CHIP 0.1µF		25V	C2771	1-163-016-00	CERAMIC CHIP 0.0039µF	10%	50V
C2707	1-163-038-91	CERAMIC CHIP 0.1µF		25V					
					C2772	1-163-038-91	CERAMIC CHIP 0.1µF		25V
C2708	1-163-038-91	CERAMIC CHIP 0.1µF		25V	C2773	1-163-038-91	CERAMIC CHIP 0.1µF		25V
C2709	1-104-664-11	ELECT 47µF	20%	25V	C2774	1-163-016-00	CERAMIC CHIP 0.0039µF	10%	50V
C2710	1-126-935-11	ELECT 470µF	20%	6.3V	C2775	1-104-664-11	ELECT 47µF	20%	16V
C2711	1-126-935-11	ELECT 470µF	20%	6.3V	C2776	1-104-664-11	ELECT 47µF	20%	16V
C2713	1-163-038-91	CERAMIC CHIP 0.1µF		25V					
					C2777	1-163-263-11	CERAMIC CHIP 330pF	5%	50V
C2714	1-104-664-11	ELECT 47µF	20%	25V	C2778	1-163-263-11	CERAMIC CHIP 330pF	5%	50V
C2715	1-164-690-91	CERAMIC CHIP 0.0022µF	5%	50V	C2779	1-107-823-11	CERAMIC CHIP 0.47µF	10%	16V
C2716	1-163-038-91	CERAMIC CHIP 0.1µF		25V	C2780	1-107-823-11	CERAMIC CHIP 0.47µF	10%	16V
C2717	1-104-664-11	ELECT 47µF	20%	25V	C2781	1-163-038-91	CERAMIC CHIP 0.1µF		25V
C2718	1-164-346-11	CERAMIC CHIP 1µF		16V					
					C2782	1-163-038-91	CERAMIC CHIP 0.1µF		25V
C2719	1-164-004-11	CERAMIC CHIP 0.1µF	10%	25V					
C2720	1-104-664-11	ELECT 47µF	20%	25V					
C2721	1-163-259-91	CERAMIC CHIP 220pF	5%	50V			<CONNECTOR>		
C2724	1-163-275-11	CERAMIC CHIP 0.001µF	5%	50V					
C2725	1-163-038-91	CERAMIC CHIP 0.1µF		25V	CN2601	*1-564-522-11	PLUG, CONNECTOR 7P		
					CN2602	1-695-301-11	CONNECTOR, BOARD TO BOARD 40P		
C2726	1-126-964-11	ELECT 10µF	20%	50V	CN2603	*1-564-511-11	PLUG, CONNECTOR 8P		
C2727	1-164-346-11	CERAMIC CHIP 1µF		16V	CN2604	1-695-915-11	TAB (CONTACT)		
C2728	1-163-009-11	CERAMIC CHIP 0.001µF	10%	50V					
C2729	1-163-009-11	CERAMIC CHIP 0.001µF	10%	50V					
C2730	1-104-664-11	ELECT 47µF	20%	25V			<DIODE>		
C2731	1-164-346-11	CERAMIC CHIP 1µF		16V	D2601	8-719-988-61	DIODE 1SS355TE-17		
C2733	1-163-038-91	CERAMIC CHIP 0.1µF		25V	D2602	8-719-988-61	DIODE 1SS355TE-17		
C2737	1-164-690-91	CERAMIC CHIP 0.0022µF	5%	50V	D2603	8-719-988-61	DIODE 1SS355TE-17		
C2738	1-163-038-91	CERAMIC CHIP 0.1µF		25V	D2604	8-719-988-61	DIODE 1SS355TE-17		
C2739	1-163-038-91	CERAMIC CHIP 0.1µF		25V	D2605	8-719-976-99	DIODE DTZ5.1B		
					D2606	8-719-988-61	DIODE 1SS355TE-17		
C2740	1-163-038-91	CERAMIC CHIP 0.1µF		25V	D2607	8-719-158-49	DIODE RD12SB2		
C2741	1-163-237-11	CERAMIC CHIP 27pF	5%	50V					

BD

REF.NO.	PART NO.	DESCRIPTION	REMARK	REF.NO.	PART NO.	DESCRIPTION	REMARK
D2608	8-719-976-99	DIODE DTZ5.1B				<CHIP CONDUCTOR>	
D2609	8-719-988-61	DIODE 1SS355TE-17					
D2610	8-719-988-61	DIODE 1SS355TE-17		JR2605	1-216-295-91	SHORT	0
D2611	8-719-988-61	DIODE 1SS355TE-17					
D2612	8-719-976-99	DIODE DTZ5.1B				<COIL>	
D2613	8-719-158-49	DIODE RD12SB2					
D2614	8-719-976-99	DIODE DTZ5.1B		L2601	1-414-234-22	INDUCTOR CHIP	0μH
D2615	8-719-988-61	DIODE 1SS355TE-17		L2602	1-414-234-22	INDUCTOR CHIP	0μH
				L2605	1-469-555-21	INDUCTOR	10μH
D2616	8-719-976-99	DIODE DTZ5.1B		L2606	1-414-234-22	INDUCTOR CHIP	0μH
D2617	8-719-158-49	DIODE RD12SB2		L2608	1-469-555-21	INDUCTOR	10μH
D2618	8-719-976-99	DIODE DTZ5.1B					
D2619	8-719-988-61	DIODE 1SS355TE-17		L2609	1-414-234-22	INDUCTOR CHIP	0μH
D2620	8-719-158-49	DIODE RD12SB2		L2610	1-414-234-22	INDUCTOR CHIP	0μH
				L2611	1-412-029-11	INDUCTOR CHIP	10μH
D2621	8-719-976-99	DIODE DTZ5.1B		L2612	1-414-234-22	INDUCTOR CHIP	0μH
D2622	8-719-976-99	DIODE DTZ5.1B		L2615	1-414-234-22	INDUCTOR CHIP	0μH
D2623	8-719-988-61	DIODE 1SS355TE-17					
D2624	8-719-988-61	DIODE 1SS355TE-17		L2616	1-414-234-22	INDUCTOR CHIP	0μH
				L2617	1-469-555-21	INDUCTOR	10μH
				L2618	1-469-555-21	INDUCTOR	10μH
		<FERRITBEAD>		L2619	1-414-234-22	INDUCTOR CHIP	0μH
				L2621	1-414-234-22	INDUCTOR CHIP	0μH
FB2601	1-216-295-91	SHORT	0				
FB2602	1-216-295-91	SHORT	0	L2622	1-414-234-22	INDUCTOR CHIP	0μH
FB2603	1-216-295-91	SHORT	0	L2625	1-414-234-22	INDUCTOR CHIP	0μH
FB2604	1-216-295-91	SHORT	0	L2626	1-469-555-21	INDUCTOR	10μH
				L2627	1-414-234-22	INDUCTOR CHIP	0μH
				L2628	1-469-555-21	INDUCTOR	10μH
		<IC>					
				L2629	1-414-234-22	INDUCTOR CHIP	0μH
IC2601	8-759-106-02	IC μPC4570G2		L2633	1-412-029-11	INDUCTOR CHIP	10μH
IC2602	8-759-998-22	IC PCM56P		L2634	1-414-234-22	INDUCTOR CHIP	0μH
IC2603	8-759-106-02	IC μPC4570G2		L2635	1-414-234-22	INDUCTOR CHIP	0μH
IC2604	8-759-998-22	IC PCM56P		L2636	1-469-555-21	INDUCTOR	10μH
IC2605	8-759-589-66	IC CM0006CF					
				L2637	1-414-234-22	INDUCTOR CHIP	0μH
IC2606	8-759-485-79	IC TC7SET08FU(TE85)		L2638	1-414-234-22	INDUCTOR CHIP	0μH
IC2607	8-759-925-85	IC SN74HC32ANS		L2639	1-469-555-21	INDUCTOR	10μH
IC2608	8-759-106-02	IC μPC4570G2		L2640	1-414-234-22	INDUCTOR CHIP	0μH
IC2609	8-759-998-22	IC PCM56P		L2643	1-414-234-22	INDUCTOR CHIP	0μH
IC2610	8-759-106-02	IC μPC4570G2					
				L2645	1-469-555-21	INDUCTOR	10μH
IC2611	8-759-488-29	IC TC7W66FU(TE12R)		L2646	1-414-234-22	INDUCTOR CHIP	0μH
IC2612	8-759-669-75	IC TLC2932IPWR		L2647	1-414-234-22	INDUCTOR CHIP	0μH
IC2613	8-759-925-90	IC SN74HC74ANS		L2648	1-469-555-21	INDUCTOR	10μH
IC2614	8-759-998-22	IC PCM56P		L2649	1-412-029-11	INDUCTOR CHIP	10μH
IC2615	8-759-485-79	IC TC7SET08FU(TE85)					
				L2652	1-414-234-22	INDUCTOR CHIP	0μH
IC2616	8-759-106-02	IC μPC4570G2		L2653	1-469-555-21	INDUCTOR	10μH
IC2617	8-759-352-91	IC PST9143NL		L2654	1-414-234-22	INDUCTOR CHIP	0μH
IC2618	8-759-038-15	IC MC74HC4538AF		L2656	1-469-555-21	INDUCTOR	10μH
IC2619	8-752-916-83	IC CXP86324-028Q		L2657	1-414-234-22	INDUCTOR CHIP	0μH
IC2620	8-759-367-69	IC MC74HC74AFEL					
				L2658	1-414-234-22	INDUCTOR CHIP	0μH
IC2621	8-759-564-06	IC M24C32-MN6T		L2659	1-414-234-22	INDUCTOR CHIP	0μH
IC2622	8-759-106-02	IC μPC4570G2		L2661	1-414-234-22	INDUCTOR CHIP	0μH
IC2623	8-759-998-22	IC PCM56P		L2663	1-414-234-22	INDUCTOR CHIP	0μH
IC2625	8-759-998-22	IC PCM56P		L2664	1-414-234-22	INDUCTOR CHIP	0μH
IC2626	8-759-394-80	IC NJM2058M-TE2					
				L2665	1-216-295-91	SHORT	0
IC2627	8-759-394-80	IC NJM2058M-TE2		L2666	1-216-295-91	SHORT	0
				L2667	1-216-295-91	SHORT	0
				L2668	1-216-295-91	SHORT	0
				L2669	1-216-295-91	SHORT	0

BD

REF.NO.	PART NO.	DESCRIPTION			REMARK
L2670	1-216-295-91	SHORT	0		
		<TRANSISTOR>			
Q2601	8-729-120-28	TRANSISTOR 2SC1623-L5L6			
Q2602	8-729-026-49	TRANSISTOR 2SA1037AK-T-146-R			
Q2603	1-801-806-11	TRANSISTOR DTC144EKA			
Q2604	8-729-026-49	TRANSISTOR 2SA1037AK-T-146-R			
Q2605	8-729-120-28	TRANSISTOR 2SC1623-L5L6			
Q2606	8-729-120-28	TRANSISTOR 2SC1623-L5L6			
Q2607	8-729-026-49	TRANSISTOR 2SA1037AK-T-146-R			
Q2608	1-801-806-11	TRANSISTOR DTC144EKA			
Q2610	1-801-806-11	TRANSISTOR DTC144EKA			
Q2611	1-801-806-11	TRANSISTOR DTC144EKA			
Q2612	1-801-806-11	TRANSISTOR DTC144EKA			
Q2613	1-801-806-11	TRANSISTOR DTC144EKA			
Q2614	8-729-120-28	TRANSISTOR 2SC1623-L5L6			
		<RESISTOR>			
R2601	1-208-782-11	METAL CHIP	1K	0.5%	1/10W
R2602	1-208-799-11	METAL CHIP	5.1K	0.5%	1/10W
R2603	1-208-782-11	METAL CHIP	1K	0.5%	1/10W
R2606	1-208-799-11	METAL CHIP	5.1K	0.5%	1/10W
R2607	1-216-295-91	SHORT	0		
R2608	1-216-295-91	SHORT	0		
R2609	1-216-025-91	RES-CHIP	100	5%	1/10W
R2610	1-216-025-91	RES-CHIP	100	5%	1/10W
R2611	1-216-025-91	RES-CHIP	100	5%	1/10W
R2612	1-216-025-91	RES-CHIP	100	5%	1/10W
R2613	1-216-025-91	RES-CHIP	100	5%	1/10W
R2621	1-216-025-91	RES-CHIP	100	5%	1/10W
R2622	1-216-025-91	RES-CHIP	100	5%	1/10W
R2623	1-216-025-91	RES-CHIP	100	5%	1/10W
R2624	1-216-081-00	RES-CHIP	22K	5%	1/10W
R2625	1-216-025-91	RES-CHIP	100	5%	1/10W
R2628	1-216-049-91	RES-CHIP	1K	5%	1/10W
R2629	1-208-782-11	METAL CHIP	1K	0.5%	1/10W
R2630	1-208-816-11	METAL CHIP	27K	0.5%	1/10W
R2631	1-216-065-91	RES-CHIP	4.7K	5%	1/10W
R2632	1-208-782-11	METAL CHIP	1K	0.5%	1/10W
R2634	1-216-049-91	RES-CHIP	1K	5%	1/10W
R2635	1-208-802-11	METAL CHIP	6.8K	0.5%	1/10W
R2636	1-216-295-91	SHORT	0		
R2637	1-216-071-00	RES-CHIP	8.2K	5%	1/10W
R2638	1-216-049-91	RES-CHIP	1K	5%	1/10W
R2639	1-208-801-11	METAL CHIP	6.2K	0.5%	1/10W
R2640	1-216-033-00	RES-CHIP	220	5%	1/10W
R2641	1-208-799-11	METAL CHIP	5.1K	0.5%	1/10W
R2643	1-216-033-00	RES-CHIP	220	5%	1/10W
R2644	1-216-071-00	RES-CHIP	8.2K	5%	1/10W
R2645	1-216-033-00	RES-CHIP	220	5%	1/10W
R2646	1-208-799-11	METAL CHIP	5.1K	0.5%	1/10W
R2647	1-216-025-91	RES-CHIP	100	5%	1/10W
R2648	1-216-295-91	SHORT	0		
R2649	1-216-295-91	SHORT	0		
R2650	1-216-025-91	RES-CHIP	100	5%	1/10W
R2651	1-216-025-91	RES-CHIP	100	5%	1/10W
R2652	1-216-025-91	RES-CHIP	100	5%	1/10W
R2653	1-216-025-91	RES-CHIP	100	5%	1/10W
R2654	1-216-071-00	RES-CHIP	8.2K	5%	1/10W
R2655	1-216-025-91	RES-CHIP	100	5%	1/10W
R2657	1-216-025-91	RES-CHIP	100	5%	1/10W
R2658	1-216-025-91	RES-CHIP	100	5%	1/10W
R2659	1-216-025-91	RES-CHIP	100	5%	1/10W
R2661	1-216-057-00	RES-CHIP	2.2K	5%	1/10W
R2662	1-216-025-91	RES-CHIP	100	5%	1/10W
R2663	1-216-025-91	RES-CHIP	100	5%	1/10W
R2664	1-216-049-91	RES-CHIP	1K	5%	1/10W
R2665	1-208-782-11	METAL CHIP	1K	0.5%	1/10W
R2666	1-216-033-00	RES-CHIP	220	5%	1/10W
R2667	1-216-049-91	RES-CHIP	1K	5%	1/10W
R2668	1-216-049-91	RES-CHIP	1K	5%	1/10W
R2669	1-208-782-11	METAL CHIP	1K	0.5%	1/10W
R2671	1-216-025-91	RES-CHIP	100	5%	1/10W
R2672	1-216-025-91	RES-CHIP	100	5%	1/10W
R2673	1-216-049-91	RES-CHIP	1K	5%	1/10W
R2674	1-216-049-91	RES-CHIP	1K	5%	1/10W
R2675	1-216-049-91	RES-CHIP	1K	5%	1/10W
R2676	1-216-049-91	RES-CHIP	1K	5%	1/10W
R2677	1-216-049-91	RES-CHIP	1K	5%	1/10W
R2678	1-216-025-91	RES-CHIP	100	5%	1/10W
R2679	1-216-025-91	RES-CHIP	100	5%	1/10W
R2680	1-216-033-00	RES-CHIP	220	5%	1/10W
R2681	1-216-025-91	RES-CHIP	100	5%	1/10W
R2682	1-216-025-91	RES-CHIP	100	5%	1/10W
R2683	1-216-073-00	RES-CHIP	10K	5%	1/10W
R2684	1-208-799-11	METAL CHIP	5.1K	0.5%	1/10W
R2685	1-216-057-00	RES-CHIP	2.2K	5%	1/10W
R2688	1-216-037-00	RES-CHIP	330	5%	1/10W
R2689	1-216-057-00	RES-CHIP	2.2K	5%	1/10W
R2690	1-208-799-11	METAL CHIP	5.1K	0.5%	1/10W
R2691	1-216-295-91	SHORT	0		
R2692	1-216-065-91	RES-CHIP	4.7K	5%	1/10W
R2693	1-216-295-91	SHORT	0		
R2694	1-216-057-00	RES-CHIP	2.2K	5%	1/10W
R2695	1-216-065-91	RES-CHIP	4.7K	5%	1/10W
R2698	1-216-037-00	RES-CHIP	330	5%	1/10W
R2699	1-216-057-00	RES-CHIP	2.2K	5%	1/10W
R2701	1-216-041-00	RES-CHIP	470	5%	1/10W
R2703	1-216-037-00	RES-CHIP	330	5%	1/10W
R2704	1-216-049-91	RES-CHIP	1K	5%	1/10W
R2705	1-216-057-00	RES-CHIP	2.2K	5%	1/10W
R2706	1-208-782-11	METAL CHIP	1K	0.5%	1/10W
R2707	1-216-065-91	RES-CHIP	4.7K	5%	1/10W
R2708	1-216-049-91	RES-CHIP	1K	5%	1/10W
R2709	1-216-025-91	RES-CHIP	100	5%	1/10W
R2710	1-216-025-91	RES-CHIP	100	5%	1/10W
R2712	1-208-782-11	METAL CHIP	1K	0.5%	1/10W
R2714	1-216-065-91	RES-CHIP	4.7K	5%	1/10W
R2715	1-216-049-91	RES-CHIP	1K	5%	1/10W
R2716	1-216-025-91	RES-CHIP	100	5%	1/10W

BD

REF.NO.	PART NO.	DESCRIPTION			REMARK	REF.NO.	PART NO.	DESCRIPTION			REMARK
R2717	1-208-799-11	METAL CHIP	5.1K	0.5%	1/10W	R2785	1-216-041-00	RES-CHIP	470	5%	1/10W
R2719	1-208-799-11	METAL CHIP	5.1K	0.5%	1/10W	R2786	1-216-041-00	RES-CHIP	470	5%	1/10W
R2720	1-216-295-91	SHORT	0								
						R2787	1-208-782-11	METAL CHIP	1K	0.5%	1/10W
R2721	1-216-295-91	SHORT	0			R2789	1-208-799-11	METAL CHIP	5.1K	0.5%	1/10W
R2723	1-208-793-11	METAL CHIP	3K	0.5%	1/10W	R2790	1-208-798-11	METAL CHIP	4.7K	0.5%	1/10W
R2725	1-208-776-11	METAL CHIP	560	0.5%	1/10W	R2791	1-216-073-00	RES-CHIP	10K	5%	1/10W
R2726	1-208-790-11	METAL CHIP	2.2K	0.5%	1/10W	R2792	1-216-033-00	RES-CHIP	220	5%	1/10W
R2728	1-216-025-91	RES-CHIP	100	5%	1/10W						
						R2793	1-216-033-00	RES-CHIP	220	5%	1/10W
R2729	1-216-033-00	RES-CHIP	220	5%	1/10W	R2794	1-216-025-91	RES-CHIP	100	5%	1/10W
R2730	1-216-025-91	RES-CHIP	100	5%	1/10W	R2796	1-216-049-91	RES-CHIP	1K	5%	1/10W
R2731	1-208-850-11	METAL CHIP	680K	0.5%	1/10W	R2797	1-216-065-91	RES-CHIP	4.7K	5%	1/10W
R2732	1-208-782-11	METAL CHIP	1K	0.5%	1/10W	R2799	1-208-810-11	METAL CHIP	15K	0.5%	1/10W
R2733	1-216-025-91	RES-CHIP	100	5%	1/10W						
						R2800	1-216-065-91	RES-CHIP	4.7K	5%	1/10W
R2734	1-216-025-91	RES-CHIP	100	5%	1/10W	R2803	1-208-799-11	METAL CHIP	5.1K	0.5%	1/10W
R2735	1-216-025-91	RES-CHIP	100	5%	1/10W	R2804	1-216-295-91	SHORT	0		
R2736	1-216-025-91	RES-CHIP	100	5%	1/10W	R2805	1-216-073-00	RES-CHIP	10K	5%	1/10W
R2737	1-216-025-91	RES-CHIP	100	5%	1/10W	R2806	1-216-025-91	RES-CHIP	100	5%	1/10W
R2738	1-216-049-91	RES-CHIP	1K	5%	1/10W						
						R2807	1-216-295-91	SHORT	0		
R2739	1-216-025-91	RES-CHIP	100	5%	1/10W	R2808	1-216-073-00	RES-CHIP	10K	5%	1/10W
R2740	1-216-025-91	RES-CHIP	100	5%	1/10W	R2809	1-216-073-00	RES-CHIP	10K	5%	1/10W
R2741	1-216-033-00	RES-CHIP	220	5%	1/10W	R2810	1-216-025-91	RES-CHIP	100	5%	1/10W
R2742	1-216-025-91	RES-CHIP	100	5%	1/10W	R2811	1-216-025-91	RES-CHIP	100	5%	1/10W
R2743	1-216-025-91	RES-CHIP	100	5%	1/10W						
						R2812	1-216-025-91	RES-CHIP	100	5%	1/10W
R2744	1-216-025-91	RES-CHIP	100	5%	1/10W	R2813	1-216-073-00	RES-CHIP	10K	5%	1/10W
R2745	1-216-025-91	RES-CHIP	100	5%	1/10W	R2814	1-216-025-91	RES-CHIP	100	5%	1/10W
R2746	1-208-850-11	METAL CHIP	680K	0.5%	1/10W	R2815	1-216-073-00	RES-CHIP	10K	5%	1/10W
R2747	1-208-782-11	METAL CHIP	1K	0.5%	1/10W	R2818	1-216-025-91	RES-CHIP	100	5%	1/10W
R2750	1-208-799-11	METAL CHIP	5.1K	0.5%	1/10W						
						R2821	1-216-025-91	RES-CHIP	100	5%	1/10W
R2751	1-216-025-91	RES-CHIP	100	5%	1/10W	R2823	1-216-033-00	RES-CHIP	220	5%	1/10W
R2752	1-216-025-91	RES-CHIP	100	5%	1/10W	R2824	1-216-033-00	RES-CHIP	220	5%	1/10W
R2753	1-216-025-91	RES-CHIP	100	5%	1/10W	R2825	1-216-033-00	RES-CHIP	220	5%	1/10W
R2755	1-216-073-00	RES-CHIP	10K	5%	1/10W	R2826	1-216-033-00	RES-CHIP	220	5%	1/10W
R2756	1-216-073-00	RES-CHIP	10K	5%	1/10W						
						R2827	1-216-033-00	RES-CHIP	220	5%	1/10W
R2758	1-216-025-91	RES-CHIP	100	5%	1/10W	R2831	1-216-025-91	RES-CHIP	100	5%	1/10W
R2759	1-216-033-00	RES-CHIP	220	5%	1/10W	R2832	1-216-025-91	RES-CHIP	100	5%	1/10W
R2760	1-208-799-11	METAL CHIP	5.1K	0.5%	1/10W	R2834	1-216-025-91	RES-CHIP	100	5%	1/10W
R2761	1-216-295-91	SHORT	0			R2835	1-216-025-91	RES-CHIP	100	5%	1/10W
R2762	1-216-295-91	SHORT	0								
						R2836	1-216-118-00	RES-CHIP	750K	5%	1/10W
R2763	1-216-025-91	RES-CHIP	100	5%	1/10W	R2837	1-216-049-91	RES-CHIP	1K	5%	1/10W
R2764	1-216-049-91	RES-CHIP	1K	5%	1/10W	R2838	1-216-122-11	RES-CHIP	1.1M	5%	1/10W
R2765	1-216-025-91	RES-CHIP	100	5%	1/10W	R2839	1-216-049-91	RES-CHIP	1K	5%	1/10W
R2766	1-216-049-91	RES-CHIP	1K	5%	1/10W	R2840	1-216-025-91	RES-CHIP	100	5%	1/10W
R2767	1-216-033-00	RES-CHIP	220	5%	1/10W						
						R2841	1-216-073-00	RES-CHIP	10K	5%	1/10W
R2768	1-216-049-91	RES-CHIP	1K	5%	1/10W	R2842	1-216-073-00	RES-CHIP	10K	5%	1/10W
R2769	1-216-025-91	RES-CHIP	100	5%	1/10W	R2843	1-216-295-91	SHORT	0		
R2771	1-216-033-00	RES-CHIP	220	5%	1/10W	R2844	1-216-073-00	RES-CHIP	10K	5%	1/10W
R2773	1-216-025-91	RES-CHIP	100	5%	1/10W	R2845	1-216-073-00	RES-CHIP	10K	5%	1/10W
R2774	1-216-073-00	RES-CHIP	10K	5%	1/10W						
						R2846	1-216-049-91	RES-CHIP	1K	5%	1/10W
R2775	1-216-025-91	RES-CHIP	100	5%	1/10W	R2847	1-216-025-91	RES-CHIP	100	5%	1/10W
R2777	1-216-025-91	RES-CHIP	100	5%	1/10W	R2848	1-216-049-91	RES-CHIP	1K	5%	1/10W
R2778	1-216-025-91	RES-CHIP	100	5%	1/10W	R2849	1-216-025-91	RES-CHIP	100	5%	1/10W
R2779	1-216-025-91	RES-CHIP	100	5%	1/10W	R2850	1-216-124-11	RES-CHIP	1.3M	5%	1/10W
R2781	1-208-782-11	METAL CHIP	1K	0.5%	1/10W						
						R2851	1-216-124-11	RES-CHIP	1.3M	5%	1/10W
R2782	1-216-073-00	RES-CHIP	10K	5%	1/10W	R2852	1-216-057-00	RES-CHIP	2.2K	5%	1/10W
R2783	1-216-295-91	SHORT	0			R2853	1-216-073-00	RES-CHIP	10K	5%	1/10W
R2784	1-216-025-91	RES-CHIP	100	5%	1/10W	R2872	1-216-049-91	RES-CHIP	1K	5%	1/10W

| BD | DS | D |

REF.NO.	PART NO.	DESCRIPTION			REMARK	REF.NO.	PART NO.	DESCRIPTION			REMARK
R2873	1-216-049-91	RES-CHIP	1K	5%	1/10W	R3502	1-216-093-91	RES-CHIP	68K	5%	1/10W
						R3503	1-216-073-00	RES-CHIP	10K	5%	1/10W
						R3504	1-216-689-11	RES-CHIP	39K	5%	1/10W
		<CRYSTAL>				R3506	1-216-057-00	RES-CHIP	2.2K	5%	1/10W
X2701	1-767-925-21	VIBRATOR, CRYSTAL (12MHz)				R3507	1-216-689-11	RES-CHIP	39K	5%	1/10W
						R3508	1-216-073-00	RES-CHIP	10K	5%	1/10W
						R3509	1-216-073-00	RES-CHIP	10K	5%	1/10W
	* A-1343-830-A	DS BOARD, COMPLETE				R3511	1-208-803-11	METAL CHIP	7.5K	0.5%	1/10W
						R3512	1-216-033-00	RES-CHIP	220	5%	1/10W
						R3513	1-216-033-00	RES-CHIP	220	5%	1/10W
		<CAPACITOR>				R3514	1-216-073-00	RES-CHIP	10K	5%	1/10W
						R3515	1-216-033-00	RES-CHIP	220	5%	1/10W
C3501	1-104-664-11	ELECT	47µF	20%	25V	R3518	1-216-053-00	RES-CHIP	1.5K	5%	1/10W
C3502	1-104-664-11	ELECT	47µF	20%	25V	R3519	1-216-081-00	RES-CHIP	22K	5%	1/10W
C3503	1-104-664-11	ELECT	47µF	20%	25V						
C3504	1-104-664-11	ELECT	47µF	20%	25V	R3520	1-216-081-00	RES-CHIP	22K	5%	1/10W
C3505	1-104-664-11	ELECT	47µF	20%	25V	R3521	1-216-103-00	RES-CHIP	180K	5%	1/10W
						R3523	1-216-099-00	RES-CHIP	120K	5%	1/10W
C3506	1-163-275-11	CERAMIC CHIP	0.001µF	5%	50V	R3524	1-216-097-91	RES-CHIP	100K	5%	1/10W
C3507	1-126-964-11	ELECT	10µF	20%	50V	R3526	1-216-039-00	RES-CHIP	390	5%	1/10W
C3508	1-107-714-11	ELECT	10µF	20%	16V						
C3509	1-137-371-11	MYLAR	0.015µF	5%	50V	R3529	1-216-107-00	RES-CHIP	270K	5%	1/10W
C3510	1-163-038-91	CERAMIC CHIP	0.1µF		25V	R3530	1-216-081-00	RES-CHIP	22K	5%	1/10W
						R3531	1-216-041-00	RES-CHIP	470	5%	1/10W
C3511	1-163-038-91	CERAMIC CHIP	0.1µF		25V	R3532	1-216-037-00	RES-CHIP	330	5%	1/10W
C3512	1-104-664-11	ELECT	47µF	20%	25V	R3533	1-216-075-00	RES-CHIP	12K	5%	1/10W
C3513	1-163-038-91	CERAMIC CHIP	0.1µF		25V						
C3514	1-163-038-91	CERAMIC CHIP	0.1µF		25V	R3535	1-216-097-91	RES-CHIP	100K	5%	1/10W
C3515	1-104-664-11	ELECT	47µF	20%	25V	R3537	1-216-081-00	RES-CHIP	22K	5%	1/10W
						R3538	1-216-073-00	RES-CHIP	10K	5%	1/10W
C3518	1-163-224-11	CERAMIC CHIP	7pF	0.25pF	50V	R3541	1-216-079-00	RES-CHIP	18K	5%	1/10W
C3519	1-104-664-11	ELECT	47µF	20%	25V						
C3520	1-137-374-11	MYLAR	0.047µF	5%	50V						
C3523	1-163-243-11	CERAMIC CHIP	47pF	5%	50V		* A-1346-923-A	D BOARD, COMPLETE (ES48)			
C3525	1-104-664-11	ELECT	47µF	20%	25V		* A-1346-924-A	D BOARD, COMPLETE (ES53)			
							* A-1346-925-A	D BOARD, COMPLETE (ES61)			
C3526	1-104-664-11	ELECT	47µF	20%	25V		* A-1346-937-A	D BOARD, COMPLETE (ES43)			
C3528	1-107-714-11	ELECT	10µF	20%	16V						
C3529	1-164-161-11	CERAMIC CHIP	0.0022µF	10%	50V		1-500-048-11	FERRITE	0µH (Q5104)		
							4-363-414-00	SPACER, MICA (IC5302, Q5104)			
		<CONNECTOR>					4-382-854-11	SCREW (M3X10), P, SW (+)			
								(D5107, D5108, IC5103, IC5104, IC5105,			
CN3501	* 1-691-632-21	CONNECTOR, BOARD TO BOARD 15P						IC5106, IC5302, Q5104, Q5705)			
							* 4-393-506-01	RETAINER, TR (IC5302)			
		<DIODE>					7-682-952-09	SCREW +PSW 3X16 (IC5501, IC5502)			
D3501	8-719-158-15	DIODE RD5.6S-B									
D3502	8-719-914-44	DIODE DAP202K						<CAPACITOR>			
D3503	8-719-158-15	DIODE RD5.6S-B				C5001	1-104-664-11	ELECT	47µF	20%	16V
						C5002	1-126-963-11	ELECT	4.7µF	20%	50V
		<IC>				C5011	1-126-934-11	ELECT	220µF	20%	16V
						C5020	1-126-961-11	ELECT	2.2µF	20%	50V
IC3502	8-759-251-31	IC CA0007AM				C5102	1-102-973-00	CERAMIC	100pF	5%	50V
IC3503	8-759-251-31	IC CA0007AM									
IC3504	8-759-251-31	IC CA0007AM				C5103	1-126-960-11	ELECT	1µF	20%	50V
IC3505	8-759-711-28	IC NJM2058D				C5104	1-137-415-11	MYLAR	0.0068µF	10%	100V
IC3506	8-759-100-96	IC µPC4558G2				C5105	1-102-973-00	CERAMIC	100pF	5%	50V
						C5112	1-162-117-00	CERAMIC	100pF	10%	500V
		<RESISTOR>				C5113	1-136-207-11	MYLAR	0.047µF	10%	250V
						C5115	1-124-347-51	ELECT	100µF	20%	160V
R3501	1-216-073-00	RES-CHIP	10K	5%	1/10W	C5117	1-162-116-00	CERAMIC	680pF	10%	2KV

D

REF.NO.	PART NO.	DESCRIPTION			REMARK	REF.NO.	PART NO.	DESCRIPTION			REMARK
C5118	1-137-391-11	MYLAR	0.0047µF	5%	100V	C5224	1-126-967-11	ELECT	47µF	20%	50V
C5119	1-162-116-00	CERAMIC	680pF	10%	2KV	C5225	1-163-021-91	CERAMIC CHIP	0.01µF	10%	50V
C5120	1-162-116-00	CERAMIC	680pF	10%	2KV						
						C5226	1-164-161-11	CERAMIC CHIP	0.0022µF	10%	50V
C5123	1-129-718-00	FILM	0.022µF	5%	630V	C5301	1-104-664-11	ELECT	47µF	20%	25V
C5127	1-117-643-11	FILM	9100pF	3%	1.2KV	C5302	1-104-665-11	ELECT	100µF	20%	25V
C5130	1-115-521-11	FILM	0.82µF	5%	250V	C5303	1-126-933-11	ELECT	100µF	20%	16V
C5133	1-104-665-11	ELECT	100µF	20%	25V	C5304	1-163-005-11	CERAMIC CHIP	470pF	10%	50V
C5135	1-164-161-11	CERAMIC CHIP	0.0022µF	10%	50V						
						C5305	1-137-399-11	MYLAR	0.1µF	5%	100V
C5136	1-164-161-11	CERAMIC CHIP	0.0022µF	10%	50V	C5307	1-164-004-11	CERAMIC CHIP	0.1µF	10%	25V
C5137	1-137-043-11	MYLAR	0.0047µF	10%	400V	C5308	1-126-960-11	ELECT	1µF	20%	50V
C5138	1-126-965-11	ELECT	22µF	20%	50V	C5310	1-126-964-11	ELECT	10µF	20%	50V
C5141	1-136-189-00	MYLAR	0.1µF	10%	250V	C5311	1-136-177-00	MYLAR	1µF	5%	50V
C5142	1-162-117-00	CERAMIC	100pF	10%	500V						
						C5312	1-163-021-91	CERAMIC CHIP	0.01µF	10%	50V
C5143	1-115-521-11	FILM	0.82µF	5%	250V	C5313	1-126-933-11	ELECT	100µF	20%	16V
C5145	1-104-665-11	ELECT	100µF	20%	25V	C5314	1-126-969-11	ELECT	220µF	20%	50V
C5146	1-107-655-11	ELECT	47µF	20%	250V	C5315	1-126-964-11	ELECT	10µF	20%	50V
C5147	1-102-228-00	CERAMIC	470pF	10%	500V	C5316	1-137-401-11	MYLAR	0.22µF	10%	100V
C5148	1-126-941-11	ELECT	470µF	20%	25V						
						C5317	1-104-664-11	ELECT	47µF	20%	16V
C5149	1-126-941-11	ELECT	470µF	20%	25V	C5318	1-163-021-91	CERAMIC CHIP	0.01µF	10%	50V
C5150	1-164-161-11	CERAMIC CHIP	0.0022µF	10%	50V	C5319	1-126-941-11	ELECT	470µF	20%	25V
C5151	1-164-161-11	CERAMIC CHIP	0.0022µF	10%	50V	C5320	1-126-972-11	ELECT	1000µF	20%	50V
C5152	1-126-972-11	ELECT	1000µF	20%	50V	C5321	1-163-243-11	CERAMIC CHIP	47pF	5%	50V
C5153	1-126-972-11	ELECT	1000µF	20%	50V						
						C5323	1-163-021-91	CERAMIC CHIP	0.01µF	10%	50V
C5158	1-124-347-51	ELECT	100µF	20%	160V	C5326	1-126-972-11	ELECT	1000µF	20%	50V
C5159	1-126-935-11	ELECT	470µF	20%	16V	C5327	1-163-251-11	CERAMIC CHIP	100pF	5%	50V
C5160	1-126-935-11	ELECT	470µF	20%	16V	C5328	1-163-021-91	CERAMIC CHIP	0.01µF	10%	50V
C5163	1-164-161-11	CERAMIC CHIP	0.0022µF	10%	50V	C5329	1-163-251-11	CERAMIC CHIP	100pF	5%	50V
C5164	1-164-161-11	CERAMIC CHIP	0.0022µF	10%	50V						
						C5331	1-126-960-11	ELECT	1µF	20%	50V
C5165	1-126-967-11	ELECT	47µF	20%	50V	C5332	1-163-021-91	CERAMIC CHIP	0.01µF	10%	50V
C5166	1-107-909-11	ELECT	47µF	20%	50V	C5333	1-163-021-91	CERAMIC CHIP	0.01µF	10%	50V
C5167	1-126-967-11	ELECT	47µF	20%	50V	C5334	1-126-960-11	ELECT	1µF	20%	50V
C5168	1-107-909-11	ELECT	47µF	20%	50V	C5401	1-126-967-11	ELECT	47µF	20%	50V
C5170	1-163-037-11	CERAMIC CHIP	0.022µF	10%	50V						
						C5402	1-104-664-11	ELECT	47µF	20%	25V
C5171	1-106-387-00	MYLAR	0.068µF	10%	200V	C5403	1-102-125-00	CERAMIC	0.0047µF	10%	50V
C5172	1-163-037-11	CERAMIC CHIP	0.022µF	10%	50V	C5404	1-102-125-00	CERAMIC	0.0047µF	10%	50V
C5173	1-163-037-11	CERAMIC CHIP	0.022µF	10%	50V	C5405	1-102-125-00	CERAMIC	0.0047µF	10%	50V
C5174	1-163-037-11	CERAMIC CHIP	0.022µF	10%	50V	C5406	1-104-664-11	ELECT	47µF	20%	25V
C5175	1-126-967-11	ELECT	47µF	20%	50V						
						C5407	1-130-495-00	MYLAR	0.1µF	5%	50V
C5176	1-126-967-11	ELECT	47µF	20%	50V	C5507	1-102-973-00	CERAMIC	100pF	5%	50V
C5204	1-126-933-11	ELECT	100µF	20%	16V	C5508	1-102-973-00	CERAMIC	100pF	5%	50V
C5205	1-130-495-00	MYLAR	0.1µF	5%	50V	C5509	1-102-973-00	CERAMIC	100pF	5%	50V
C5206	1-126-960-11	ELECT	1µF	20%	50V	C5510	1-102-973-00	CERAMIC	100pF	5%	50V
C5207	1-126-965-11	ELECT	22µF	20%	50V						
						C5511	1-102-973-00	CERAMIC	100pF	5%	50V
C5208	1-163-037-11	CERAMIC CHIP	0.022µF	10%	50V	C5512	1-102-973-00	CERAMIC	100pF	5%	50V
C5209	1-163-275-11	CERAMIC CHIP	0.001µF	5%	50V	C5517	1-126-965-11	ELECT	22µF	20%	50V
C5211	1-130-495-00	MYLAR	0.1µF	5%	50V	C5518	1-126-965-11	ELECT	22µF	20%	50V
C5214	1-126-935-11	ELECT	470µF	20%	16V	C5519	1-126-969-11	ELECT	220µF	20%	50V
C5215	1-126-964-11	ELECT	10µF	20%	50V						
						C5520	1-126-969-11	ELECT	220µF	20%	50V
C5216	1-164-096-11	CERAMIC	0.01µF		50V	C5521	1-130-495-00	MYLAR	0.1µF	5%	50V
C5217	1-164-096-11	CERAMIC	0.01µF		50V	C5522	1-130-495-00	MYLAR	0.1µF	5%	50V
C5218	1-164-096-11	CERAMIC	0.01µF		50V	C5523	1-126-971-11	ELECT	470µF	20%	50V
C5219	1-164-096-11	CERAMIC	0.01µF		50V	C5524	1-126-971-11	ELECT	470µF	20%	50V
C5220	1-164-096-11	CERAMIC	0.01µF		50V						
						C5527	1-126-969-11	ELECT	220µF	20%	50V
C5221	1-164-096-11	CERAMIC	0.01µF		50V	C5528	1-126-969-11	ELECT	220µF	20%	50V
C5222	1-164-096-11	CERAMIC	0.01µF		50V	C5529	1-137-150-11	MYLAR	0.01µF	5%	50V
C5223	1-126-960-11	ELECT	1µF	20%	50V	C5530	1-137-150-11	MYLAR	0.01µF	5%	50V

REF.NO.	PART NO.	DESCRIPTION			REMARK
C5711	1-136-165-00	MYLAR	0.1µF	5%	50V
C5712	1-136-177-00	MYLAR	1µF	5%	50V
C5713	1-104-665-11	ELECT	100µF	20%	25V
C5714	1-130-471-00	MYLAR	0.001µF	5%	50V
C5715	1-137-150-11	MYLAR	0.01µF	5%	50V
C5716	1-104-665-11	ELECT	100µF	20%	25V
C5717	1-126-968-11	ELECT	100µF	20%	50V
C5718	1-162-114-00	CERAMIC	0.0047µF		2KV
C5719	1-126-968-11	ELECT	100µF	20%	50V
C5720	1-137-372-11	MYLAR	0.022µF	5%	50V
C5721	1-104-661-91	ELECT	330µF	20%	16V
C5722	1-126-934-11	ELECT	220µF	20%	16V
C5727	1-163-021-91	CERAMIC CHIP	0.01µF	10%	50V
C5728	1-163-021-91	CERAMIC CHIP	0.01µF	10%	50V
C5759	1-126-964-11	ELECT	10µF	20%	50V
C5760	1-164-182-11	CERAMIC CHIP	0.0033µF	10%	50V

\<CONNECTOR\>

CN5001	*1-564-506-11	PLUG, CONNECTOR 3P
CN5002	*1-573-963-11	PIN, CONNECTOR (PC BOARD) 3P
CN5003	*1-506-371-00	PIN, CONNECTOR 2P
CN5004	1-695-915-11	TAB (CONTACT)
CN5006	*1-564-512-11	PLUG, CONNECTOR 9P
CN5007	*1-580-689-11	PIN, CONNECTOR (PC BOARD) 4P
CN5008	*1-580-689-11	PIN, CONNECTOR (PC BOARD) 4P
CN5009	*1-580-689-11	PIN, CONNECTOR (PC BOARD) 4P
CN5010	*1-564-507-11	PLUG, CONNECTOR 4P
CN5011	*1-564-507-11	PLUG, CONNECTOR 4P
CN5012	*1-564-507-11	PLUG, CONNECTOR 4P
CN5013	*1-764-333-11	PLUG, CONNECTOR 10P
CN5014	*1-691-135-11	PIN, CONNECTOR (PC BOARD) 4P
CN5015	1-695-298-11	CONNECTOR, BOARD TO BOARD 40P
CN5016	1-900-903-64	CONNECTOR ASSY 20P
CN5017	1-900-903-64	CONNECTOR ASSY 20P
CN5018	*1-564-511-11	PLUG, CONNECTOR 8P
CN5019	*1-564-507-11	PLUG, CONNECTOR 4P
CN5020	*1-564-506-11	PLUG, CONNECTOR 3P
CN5402	*1-691-616-21	CONNECTOR, BOARD TO BOARD 15P

\<DIODE\>

D5001	8-719-991-33	DIODE 1SS133T-77
D5002	8-719-991-33	DIODE 1SS133T-77
D5006	8-719-991-33	DIODE 1SS133T-77
D5008	8-719-991-33	DIODE 1SS133T-77
D5101	8-719-983-38	DIODE MTZJ-T-77-36B
D5107	8-719-979-99	DIODE ERD08M-15
D5108	8-719-052-09	DIODE FMG-36S-LF024-104
D5114	8-719-971-20	DIODE ERC38-06
D5115	8-719-302-43	DIODE EL1Z
D5116	8-719-979-85	DIODE EGP20G
D5117	8-719-302-43	DIODE EL1Z
D5118	8-719-979-85	DIODE EGP20G
D5121	8-719-979-85	DIODE EGP20G
D5122	8-719-979-85	DIODE EGP20G
D5201	8-719-991-33	DIODE 1SS133T-77

REF.NO.	PART NO.	DESCRIPTION	REMARK
D5202	8-719-109-85	DIODE RD5.1ESB2	
D5203	8-719-923-86	DIODE MTZJ-T-77-15	
D5204	8-719-921-63	DIODE MTZJ-7.5B	
D5205	8-719-991-33	DIODE 1SS133T-77	
D5207	8-719-991-33	DIODE 1SS133T-77	
D5208	8-719-991-33	DIODE 1SS133T-77	
D5301	8-719-923-86	DIODE MTZJ-T-77-15	
D5302	8-719-991-33	DIODE 1SS133T-77	
D5303	8-719-908-03	DIODE GP08D	
D5304	8-719-908-03	DIODE GP08D	
D5305	8-719-991-33	DIODE 1SS133T-77	
D5306	8-719-923-86	DIODE MTZJ-T-77-15	
D5307	8-719-923-86	DIODE MTZJ-T-77-15	
D5308	8-719-924-16	DIODE MTZJ-T-77-24	
D5309	8-719-924-16	DIODE MTZJ-T-77-24	
D5401	8-719-110-17	DIODERD10ESB2	
D5402	8-719-982-96	DIODE MTZJ-T-77-2.2A	
D5701	8-719-991-33	DIODE 1SS133T-77	
D5704	8-719-991-33	DIODE 1SS133T-77	
D5719	8-719-923-86	DIODE MTZJ-T-77-15	
D5721	8-719-923-86	DIODE MTZJ-T-77-15	
D5724	8-719-018-82	DIODE RGP02-20EL-6394	
D5726	8-719-991-33	DIODE 1SS133T-77	
D5727	8-719-991-33	DIODE 1SS133T-77	
D5732	8-719-991-33	DIODE 1SS133T-77	

\<FERRITBEAD\>

FB5102	1-412-911-11	FERRITE	0µH
FB5103	1-412-911-11	FERRITE	0µH

\<IC\>

IC5103	8-759-701-79	IC NJM7812FA
IC5104	8-759-929-65	IC LM7912CT
IC5105	8-759-701-56	IC NJM78M05FA
IC5106	8-759-701-84	IC NJM7905FA
IC5107	8-759-701-59	IC NJM78M09FA
IC5201	8-759-085-67	IC LM339NS
IC5301	8-759-251-31	IC CA0007AM
IC5302	8-759-192-71	IC STV9379
IC5303	8-759-998-98	IC LM358D
IC5401	8-759-711-28	IC NJM2058D
IC5501	8-749-014-67	IC STK392-020
IC5502	8-749-014-67	IC STK392-020
IC5703	8-759-711-28	IC NJM2058D

\<CHIP CONDUCTOR\>

JR5301	1-216-295-91	SHORT	0
JR5303	1-216-295-91	SHORT	0

\<COIL\>

L5101	1-406-665-11	INDUCTOR	100µH
L5105	1-459-111-00	INDUCTOR	10mH
L5107	1-412-533-21	INDUCTOR	47µH

D

The components identified by shading
and mark ⚠ are critical for safety.
Replace only with part number specified.

REF.NO.	PART NO.	DESCRIPTION		REMARK
L5108	1-412-533-21	INDUCTOR	47µH	
L5109	1-412-519-11	INDUCTOR	3.3µH	
L5201	1-414-187-11	INDUCTOR	47µH	
L5301	1-412-524-11	INDUCTOR	8.2µH	
L5501	1-412-533-21	INDUCTOR	47µH	
L5502	1-412-533-21	INDUCTOR	47µH	
L5503	1-412-533-21	INDUCTOR	47µH	
L5504	1-412-533-21	INDUCTOR	47µH	
		<NEON LAMP>		
NL5101	1-517-778-21	LAMP, NEON		
NL5102	1-517-778-21	LAMP, NEON		
NL5103	1-517-778-21	LAMP, NEON		
NL5402	1-517-778-21	LAMP, NEON		
		<IC LINK>		
PS5101 ⚠	1-533-590-31	LINK, IC (1A/90V AC, 60V DC)		
PS5501 ⚠	1-533-597-31	LINK, IC (5A/90V AC, 60V DC)		
PS5502 ⚠	1-533-597-31	LINK, IC (5A/90V AC, 60V DC)		
PS5503 ⚠	1-533-597-31	LINK, IC (5A/90V AC, 60V DC)		
PS5504 ⚠	1-533-597-31	LINK, IC (5A/90V AC, 60V DC)		
PS5539 ⚠	1-533-595-31	LINK, IC (3.15A/90V AC, 60V DC)		
PS5540 ⚠	1-533-595-31	LINK, IC (3.15A/90V AC, 60V DC)		
PS5543 ⚠	1-533-595-31	LINK, IC (3.15A/90V AC, 60V DC)		
PS5544 ⚠	1-533-595-31	LINK, IC (3.15A/90V AC, 60V DC)		
PS5549 ⚠	1-533-595-31	LINK, IC (3.15A/90V AC, 60V DC)		
PS5550 ⚠	1-533-595-31	LINK, IC (3.15A/90V AC, 60V DC)		
		<TRANSISTOR>		
Q5006	1-801-806-11	TRANSISTOR DTC144EKA		
Q5009	8-729-026-49	TRANSISTOR 2SA1037AK-T-146-R		
Q5102	8-729-119-80	TRANSISTOR 2SC2688-LK		
Q5104	8-729-051-81	TRANSISTOR 2SC5047-YB		
Q5105	8-729-038-83	TRANSISTOR 2SK2251-01-F19		
Q5106	8-729-119-76	TRANSISTOR 2SA1175-HFE		
Q5201	8-729-120-28	TRANSISTOR 2SC1623-L5L6		
Q5302	8-729-026-49	TRANSISTOR 2SA1037AK-T-146-R		
Q5303	8-729-120-28	TRANSISTOR 2SC1623-L5L6		
Q5401	8-729-422-27	TRANSISTOR 2SD601A-Q		
Q5402	8-729-216-22	TRANSISTOR 2SA1162-G		
Q5403	1-801-806-11	TRANSISTOR DTC144EKA		
Q5501	8-729-423-33	TRANSISTOR 2SC3311A-QRSTA		
Q5502	8-729-423-33	TRANSISTOR 2SC3311A-QRSTA		
Q5503	8-729-119-76	TRANSISTOR 2SA1175-HFE		
Q5504	8-729-423-33	TRANSISTOR 2SC3311A-QRSTA		
Q5505	8-729-119-76	TRANSISTOR 2SA1175-HFE		
Q5506	8-729-423-33	TRANSISTOR 2SC3311A-QRSTA		
Q5704	8-729-423-33	TRANSISTOR 2SC3311A-QRSTA		
Q5705	8-729-053-73	TRANSISTOR 2SC5022		
Q5706	8-729-119-76	TRANSISTOR 2SA1175-HFE		
Q5707	8-729-823-81	TRANSISTOR 2SC4632LS-CB7		
Q5710	8-729-026-49	TRANSISTOR 2SA1037AK-T-146-R		
Q5711	8-729-120-28	TRANSISTOR 2SC1623-L5L6		

REF.NO.	PART NO.	DESCRIPTION			REMARK
		<RESISTOR>			
R5004	1-216-089-91	RES-CHIP	47K	5%	1/10W
R5013	1-216-089-91	RES-CHIP	47K	5%	1/10W
R5023	1-216-065-91	RES-CHIP	4.7K	5%	1/10W
R5048	1-216-041-00	RES-CHIP	470	5%	1/10W
R5101	1-215-926-00	METAL OXIDE	33K	5%	3W
R5112	1-247-843-11	CARBON	3.3K	5%	1/4W
R5115	1-216-435-11	METAL OXIDE	2.7K	5%	1W
R5119	1-215-922-11	METAL OXIDE	6.8K	5%	3W
R5120	1-216-486-00	METAL OXIDE	8.2K	5%	3W
R5122	1-215-905-11	METAL OXIDE	10	5%	3W
R5136	1-215-443-00	METAL	8.2K	1%	1/4W
R5138	1-215-457-00	METAL	33K	1%	1/4W
R5139	1-216-391-00	METAL OXIDE	1.5	5%	3W
R5140	1-215-449-00	METAL	15K	1%	1/4W
R5141	1-215-911-11	METAL OXIDE	100	5%	3W
R5146	1-215-910-00	METAL OXIDE	68	5%	3W
R5147	1-215-910-00	METAL OXIDE	68	5%	3W
R5148	1-249-377-11	CARBON	0.47	5%	1/4W
R5149	1-247-807-31	CARBON	100	5%	1/4W
R5152	1-216-377-11	METAL OXIDE	4.7	5%	2W
R5153	1-249-379-11	CARBON	0.68	5%	1/4W
R5154	1-260-127-11	CARBON	220K	5%	1/2W
R5155	1-214-909-00	METAL	68K	1%	1/2W
R5157	1-215-908-00	METAL OXIDE	33	5%	3W (ES43,ES48)
R5157	1-216-474-11	METAL OXIDE	33	5%	3W (ES53)
R5157	1-216-472-00	METAL OXIDE	33	5%	3W (ES61)
R5158	1-216-349-00	METAL OXIDE	1	5%	1W
R5159	1-215-908-00	METAL OXIDE	33	5%	3W (ES43,ES48)
R5159	1-216-474-11	METAL OXIDE	33	5%	3W (ES53)
R5159	1-216-472-00	METAL OXIDE	33	5%	3W (ES61)
R5160	1-249-377-11	CARBON	0.47	5%	1/4W
R5161	1-249-377-11	CARBON	0.47	5%	1/4W
R5162	1-216-393-00	METAL OXIDE	2.2	5%	3W
R5163	1-216-392-11	METAL OXIDE	1.8	5%	3W
R5164	1-249-393-11	CARBON	10	5%	1/4W
R5166	1-215-905-11	METAL OXIDE	10	5%	3W
R5169	1-249-424-11	CARBON	3.9K	5%	1/4W
R5171	1-249-429-11	CARBON	10K	5%	1/4W
R5172	1-249-417-11	CARBON	1K	5%	1/4W
R5173	1-215-905-11	METAL OXIDE	10	5%	3W
R5174	1-215-905-11	METAL OXIDE	10	5%	3W
R5175	1-215-905-11	METAL OXIDE	10	5%	3W
R5201	1-216-059-00	RES-CHIP	2.7K	5%	1/10W
R5202	1-216-049-91	RES-CHIP	1K	5%	1/10W
R5203	1-215-879-11	METAL OXIDE	47K	5%	1W
R5204	1-216-059-00	RES-CHIP	2.7K	5%	1/10W
R5205	1-216-059-00	RES-CHIP	2.7K	5%	1/10W
R5206	1-208-837-11	METAL CHIP	200K	0.5%	1/10W
R5209	1-208-760-11	METAL CHIP	120	0.5%	1/10W
R5210	1-216-113-00	RES-CHIP	470K	5%	1/10W

D

REF.NO.	PART NO.	DESCRIPTION			REMARK	REF.NO.	PART NO.	DESCRIPTION			REMARK
R5211	1-216-081-00	RES-CHIP	22K	5%	1/10W	R5340	1-249-377-11	CARBON	0.47	5%	1/4W
R5212	1-216-071-00	RES-CHIP	8.2K	5%	1/10W	R5341	1-249-377-11	CARBON	0.47	5%	1/4W
R5213	1-216-089-91	RES-CHIP	47K	5%	1/10W	R5344	1-216-117-00	RES-CHIP	680K	5%	1/10W
R5214	1-216-073-00	RES-CHIP	10K	5%	1/10W	R5345	1-216-117-00	RES-CHIP	680K	5%	1/10W
R5215	1-216-089-91	RES-CHIP	47K	5%	1/10W						
						R5401	1-216-295-91	SHORT	0		
R5216	1-247-895-91	CARBON	470K	5%	1/4W	R5405	1-260-087-11	CARBON	100	5%	1/2W
R5217	1-216-071-00	RES-CHIP	8.2K	5%	1/10W	R5406	1-216-295-91	SHORT	0		
R5218	1-216-049-91	RES-CHIP	1K	5%	1/10W	R5408	1-216-295-91	SHORT	0		
R5219	1-216-075-00	RES-CHIP	12K	5%	1/10W	R5409	1-216-295-91	SHORT	0		
R5220	1-216-105-91	RES-CHIP	220K	5%	1/10W						
						R5410	1-260-087-11	CARBON	100	5%	1/2W
R5221	1-216-061-00	RES-CHIP	3.3K	5%	1/10W	R5411	1-216-295-91	SHORT	0		
R5222	1-216-105-91	RES-CHIP	220K	5%	1/10W	R5412	1-208-812-11	METAL CHIP	18K	0.5%	1/10W
R5223	1-216-081-00	RES-CHIP	22K	5%	1/10W	R5415	1-216-067-00	RES-CHIP	5.6K	5%	1/10W
R5224	1-249-405-11	CARBON	100	5%	1/4W	R5416	1-216-295-91	SHORT	0		
R5225	1-208-806-11	METAL CHIP	10K	0.5%	1/10W						
						R5419	1-216-049-91	RES-CHIP	1K	5%	1/10W
R5226	1-216-089-91	RES-CHIP	47K	5%	1/10W	R5420	1-216-077-91	RES-CHIP	15K	5%	1/10W
R5227	1-260-135-11	CARBON	1M	5%	1/2W	R5421	1-216-081-00	RES-CHIP	22K	5%	1/10W
R5229	1-216-045-00	RES-CHIP	680	5%	1/10W	R5422	1-216-105-91	RES-CHIP	220K	5%	1/10W
R5230	1-216-097-91	RES-CHIP	100K	5%	1/10W	R5501	1-247-807-31	CARBON	100	5%	1/4W
R5231	1-216-065-91	RES-CHIP	4.7K	5%	1/10W						
						R5502	1-247-807-31	CARBON	100	5%	1/4W
R5232	1-216-089-91	RES-CHIP	47K	5%	1/10W	R5503	1-247-807-31	CARBON	100	5%	1/4W
R5233	1-247-807-31	CARBON	100	5%	1/4W	R5504	1-247-807-31	CARBON	100	5%	1/4W
R5234	1-216-049-91	RES-CHIP	1K	5%	1/10W	R5505	1-247-807-31	CARBON	100	5%	1/4W
R5235	1-208-810-11	METAL CHIP	15K	0.5%	1/10W	R5506	1-247-807-31	CARBON	100	5%	1/4W
R5236	1-216-065-91	RES-CHIP	4.7K	5%	1/10W						
						R5507	1-247-843-11	CARBON	3.3K	5%	1/4W
R5302	1-216-073-00	RES-CHIP	10K	5%	1/10W	R5508	1-247-843-11	CARBON	3.3K	5%	1/4W
R5303	1-216-083-00	RES-CHIP	27K	5%	1/10W	R5509	1-247-843-11	CARBON	3.3K	5%	1/4W
R5304	1-216-081-00	RES-CHIP	22K	5%	1/10W	R5510	1-247-843-11	CARBON	3.3K	5%	1/4W
R5305	1-208-801-11	METAL CHIP	6.2K	0.5%	1/10W	R5511	1-249-417-11	CARBON	1K	5%	1/4W
R5306	1-208-806-11	METAL CHIP	10K	0.5%	1/10W						
						R5512	1-249-417-11	CARBON	1K	5%	1/4W
R5307	1-216-089-91	RES-CHIP	47K	5%	1/10W	R5513	1-247-843-11	CARBON	3.3K	5%	1/4W
R5308	1-216-353-00	METAL OXIDE	2.2	5%	1W	R5515	1-247-843-11	CARBON	3.3K	5%	1/4W
R5309	1-216-097-91	RES-CHIP	100K	5%	1/10W	R5517	1-249-417-11	CARBON	1K	5%	1/4W
R5310	1-216-353-00	METAL OXIDE	2.2	5%	1W	R5518	1-249-417-11	CARBON	1K	5%	1/4W
R5311	1-216-073-00	RES-CHIP	10K	5%	1/10W						
						R5519	1-249-429-11	CARBON	10K	5%	1/4W
R5312	1-216-073-00	RES-CHIP	10K	5%	1/10W	R5520	1-249-429-11	CARBON	10K	5%	1/4W
R5313	1-216-083-00	RES-CHIP	27K	5%	1/10W	R5521	1-214-808-11	METAL	4.7	1%	1/2W
R5314	1-216-073-00	RES-CHIP	10K	5%	1/10W	R5522	1-214-808-11	METAL	4.7	1%	1/2W
R5315	1-215-913-11	METAL OXIDE	220	5%	3W	R5523	1-247-807-31	CARBON	100	5%	1/4W
R5316	1-216-089-91	RES-CHIP	47K	5%	1/10W						
						R5524	1-249-429-11	CARBON	10K	5%	1/4W
R5317	1-216-049-91	RES-CHIP	1K	5%	1/10W	R5525	1-214-808-11	METAL	4.7	1%	1/2W
R5318	1-216-097-91	RES-CHIP	100K	5%	1/10W	R5526	1-247-807-31	CARBON	100	5%	1/4W
R5319	1-216-085-00	RES-CHIP	33K	5%	1/10W	R5527	1-214-808-11	METAL	4.7	1%	1/2W
R5320	1-249-383-11	CARBON	1.5	5%	1/4W	R5528	1-249-429-11	CARBON	10K	5%	1/4W
R5321	1-216-089-91	RES-CHIP	47K	5%	1/10W						
						R5529	1-214-808-11	METAL	4.7	1%	1/2W
R5323	1-216-083-00	RES-CHIP	27K	5%	1/10W	R5530	1-214-808-11	METAL	4.7	1%	1/2W
R5325	1-208-801-11	METAL CHIP	6.2K	0.5%	1/10W	R5531	1-249-417-11	CARBON	1K	5%	1/4W
R5326	1-208-806-11	METAL CHIP	10K	0.5%	1/10W	R5532	1-249-417-11	CARBON	1K	5%	1/4W
R5328	1-216-089-91	RES-CHIP	47K	5%	1/10W	R5533	1-214-808-11	METAL	4.7	1%	1/2W
R5329	1-216-025-91	RES-CHIP	100	5%	1/10W						
						R5534	1-214-808-11	METAL	4.7	1%	1/2W
R5330	1-216-295-91	SHORT	0			R5535	1-214-808-11	METAL	4.7	1%	1/2W
R5331	1-216-073-00	RES-CHIP	10K	5%	1/10W	R5536	1-214-808-11	METAL	4.7	1%	1/2W
R5335	1-216-117-00	RES-CHIP	680K	5%	1/10W	R5537	1-214-808-11	METAL	4.7	1%	1/2W
R5337	1-216-117-00	RES-CHIP	680K	5%	1/10W	R5538	1-214-808-11	METAL	4.7	1%	1/2W
R5338	1-216-295-91	SHORT	0								
						R5541	1-214-808-11	METAL	4.7	1%	1/2W
R5339	1-247-807-31	CARBON	100	5%	1/4W	R5542	1-214-808-11	METAL	4.7	1%	1/2W

D | **G1, G**

• The components identified by ⊠ in this manual have been carefully factory-selected for each set in order to satisfy regulations regarding X-ray radiation. Should replacement be required, replace only with the value originally used.

The components identified by shading and mark ⚠ are critical for safety.
Replace only with part number specified.

REF.NO.	PART NO.	DESCRIPTION			REMARK
R5545	1-214-808-11	METAL	4.7	1%	1/2W
R5546	1-214-808-11	METAL	4.7	1%	1/2W
R5547	1-214-808-11	METAL	4.7	1%	1/2W
R5548	1-214-808-11	METAL	4.7	1%	1/2W
R5551	1-214-808-11	METAL	4.7	1%	1/2W
R5552	1-214-808-11	METAL	4.7	1%	1/2W
R5553	1-214-808-11	METAL	4.7	1%	1/2W
R5554	1-214-808-11	METAL	4.7	1%	1/2W
R5555	1-214-808-11	METAL	4.7	1%	1/2W
R5556	1-214-808-11	METAL	4.7	1%	1/2W
R5557	1-214-808-11	METAL	4.7	1%	1/2W
R5558	1-214-808-11	METAL	4.7	1%	1/2W
R5559	1-214-808-11	METAL	4.7	1%	1/2W
R5560	1-214-808-11	METAL	4.7	1%	1/2W
R5561	1-214-808-11	METAL	4.7	1%	1/2W
R5562	1-214-808-11	METAL	4.7	1%	1/2W
R5563	1-249-429-11	CARBON	10K	5%	1/4W
R5564	1-249-429-11	CARBON	10K	5%	1/4W
R5565	1-249-429-11	CARBON	10K	5%	1/4W
R5566	1-249-429-11	CARBON	10K	5%	1/4W
R5567	1-249-429-11	CARBON	10K	5%	1/4W
R5568	1-249-429-11	CARBON	10K	5%	1/4W
R5569	1-249-429-11	CARBON	10K	5%	1/4W
R5570	1-249-429-11	CARBON	10K	5%	1/4W
R5723	1-216-073-00	RES-CHIP	10K	5%	1/10W
R5724	1-247-807-31	CARBON	100	5%	1/4W
R5725	1-216-093-91	RES-CHIP	68K	5%	1/10W
R5726	1-216-071-00	RES-CHIP	8.2K	5%	1/10W
R5727	1-216-085-00	RES-CHIP	33K	5%	1/10W
R5728	1-216-051-00	RES-CHIP	1.2K	5%	1/10W
R5729	1-216-025-91	RES-CHIP	100	5%	1/10W
R5730	1-249-431-11	CARBON	15K	5%	1/4W
R5731	1-216-073-00	RES-CHIP	10K	5%	1/10W
R5732	1-249-441-11	CARBON	100K	5%	1/4W
R5734	1-216-061-00	RES-CHIP	3.3K	5%	1/10W
R5735	1-216-057-00	RES-CHIP	2.2K	5%	1/10W
R5737	1-216-089-91	RES-CHIP	47K	5%	1/10W
R5738	1-249-405-11	CARBON	100	5%	1/4W
R5739	1-216-025-91	RES-CHIP	100	5%	1/10W
R5740	1-215-917-11	METAL OXIDE	1K	5%	3W
R5744	1-216-089-91	RES-CHIP	47K	5%	1/10W
R5745	1-216-099-00	RES-CHIP	120K	5%	1/10W
R5746	1-215-925-11	METAL OXIDE	22K	5%	3W
R5747	1-215-925-11	METAL OXIDE	22K	5%	3W
R5748	1-216-041-00	RES-CHIP	470	5%	1/10W
R5749	1-216-025-91	RES-CHIP	100	5%	1/10W
R5750	1-216-025-91	RES-CHIP	100	5%	1/10W
R5751	1-260-099-11	CARBON	1K	5%	1/2W
R5753	1-216-065-91	RES-CHIP	4.7K	5%	1/10W
R5754	1-216-073-00	RES-CHIP	10K	5%	1/10W
R5755	1-216-065-91	RES-CHIP	4.7K	5%	1/10W
R5756	1-216-065-91	RES-CHIP	4.7K	5%	1/10W
R5757	1-219-752-11	CARBON	100K	5%	1/2W
R5758	1-215-925-11	METAL OXIDE	22K	5%	3W
R5759	1-215-925-11	METAL OXIDE	22K	5%	3W
R5762	1-219-743-11	CARBON	100	5%	1/2W

REF.NO.	PART NO.	DESCRIPTION			REMARK
R5763	1-216-065-91	RES-CHIP	4.7K	5%	1/10W
R5768	1-249-429-11	CARBON	10K	5%	1/4W
R5769	1-216-073-00	RES-CHIP	10K	5%	1/10W
R5770	1-216-073-00	RES-CHIP	10K	5%	1/10W
R5771	1-216-097-91	RES-CHIP	100K	5%	1/10W
R5772	1-249-429-11	CARBON	10K	5%	1/4W
⊠R9901 ⚠		METAL			1/4W

<SPARK GAP>

SG5702	1-519-466-11	GAP, SPARK

<TRANSFORMER>

T5101	1-437-209-11	TRANSFORMER, HORIZONTAL DRIVE
T5102	1-419-553-11	COIL,HORIZONTAL LINEARITY(HLC)
T5103	⚠1-453-335-11	TRANSFORMER ASSY, FLY BACK (NX-4010//M3P4)
T5104	1-435-439-11	TRANSFORMER, FERRITE (PMT)

****

* A-1316-514-A G1 BOARD, COMPLETE (ES43ME1/MN1, ES48ME1/MN1, ES53ME1/MN1, ES61ME1/MN1)
* A-1316-528-A G BOARD, COMPLETE (ES43HK1/SN1, ES48HK1/SN1, ES53HK1/SN1, ES61HK1/SN1)

****

* 1-533-725-11 HOLDER, FUSE (F6001)
* 4-374-846-01 COVER, CAPACITOR, CAP TYPE (VD6001, VD6002)
4-382-854-11 SCREW (M3X10), P, SW (+) (D6015 : G BOARD, D6301, D6302, D6304, D6308, D6309, IC6004)

<CAPACITOR>

C6000	⚠1-104-708-51	MYLAR	0.47µF	20%	250V
C6001	1-163-251-11	CERAMIC CHIP 100pF		5%	50V
		(ES43ME1/MN1, ES48ME1/MN1, ES53ME1/MN1, ES61ME1/MN1)			
C6003	⚠1-104-706-51	MYLAR	0.22µF	20%	250V
C6006	1-126-961-11	ELECT	2.2µF	20%	50V
		(ES43ME1/MN1, ES48ME1/MN1, ES53ME1/MN1, ES61ME1/MN1)			
C6007	1-163-251-11	CERAMIC CHIP 100pF		5%	50V
		(ES43ME1/MN1, ES48ME1/MN1, ES53ME1/MN1, ES61ME1/MN1)			
C6008	1-163-251-11	CERAMIC CHIP 100pF		5%	50V
		(ES43ME1/MN1, ES48ME1/MN1, ES53ME1/MN1, ES61ME1/MN1)			
C6009	⚠1-104-706-51	MYLAR	0.22µF	20%	250V
C6010	⚠1-119-894-51	CERAMIC	2200pF	20%	250V
C6011	⚠1-119-894-51	CERAMIC	2200pF	20%	250V
C6013	⚠1-161-964-91	CERAMIC	0.0047µF		250V
C6014	1-163-021-91	CERAMIC CHIP 0.01µF		10%	50V
		(ES43ME1/MN1, ES48ME1/MN1, ES53ME1/MN1, ES61ME1/MN1)			
C6015	⚠1-161-964-91	CERAMIC	0.0047µF		250V

G1, G

REF.NO.	PART NO.	DESCRIPTION			REMARK
C6016	1-163-251-11	CERAMIC CHIP	100pF	5%	50V
		(ES43ME1/MN1, ES48ME1/MN1, ES53ME1/MN1, ES61ME1/MN1)			
C6017	⚠1-161-964-51	CERAMIC	0.0047µF		250V
C6018	⚠1-161-964-51	CERAMIC	0.0047µF		250V
C6019	1-126-961-11	ELECT	2.2µF	20%	50V
		(ES43ME1/MN1, ES48ME1/MN1, ES53ME1/MN1, ES61ME1/MN1)			
C6020	1-126-968-11	ELECT	100µF	20%	50V
C6022	1-109-834-11	ELECT(BLOCK)	1500µF	20%	50V
		(ES43ME1/MN1, ES48ME1/MN1, ES53ME1/MN1, ES61ME1/MN1)			
C6022	1-131-940-11	ELECT	1200µF	20%	250V
		(ES43HK1/SN1, ES48HK1/SN1, ES53HK1/SN1, ES61HK1/SN1)			
C6023	1-109-834-11	ELECT(BLOCK)	1500µF	20%	250V
		(ES43ME1/MN1, ES48ME1/MN1, ES53ME1/MN1, ES61ME1/MN1)			
C6023	1-131-940-11	ELECT	1200µF	20%	250V
		(ES43HK1/SN1, ES48HK1/SN1, ES53HK1/SN1, ES61HK1/SN1)			
C6024	1-117-227-11	MYLAR	1µF	10%	450V
		(ES43HK1/SN1, ES48HK1/SN1, ES53HK1/SN1, ES61HK1/SN1)			
C6025	1-115-389-11	FILM	0.018µF	3%	800V
C6026	1-125-969-91	CERAMIC	680pF	10%	1KV
C6027	1-115-824-11	ELECT	18µF	20%	50V
C6028	1-104-588-11	FILM	0.0082µF	2.50%	1.25KV
C6029	1-102-106-00	CERAMIC	100pF	10%	50V
C6030	1-136-189-00	MYLAR	0.1µF	10%	250V
C6031	1-125-969-91	CERAMIC	680pF	10%	1KV
C6032	1-115-405-11	FILM	0.039µF	3%	1KV
		(ES43HK1/SN1, ES48HK1/SN1, ES53HK1/SN1, ES61HK1/SN1)			
C6033	1-126-963-11	ELECT	4.7µF	20%	50V
C6034	1-130-029-00	FILM	8200pF	2%	50V
C6035	1-104-665-11	ELECT	100µF	20%	25V
C6036	1-107-906-11	ELECT	10µF	20%	50V
C6037	1-137-150-11	MYLAR	0.01µF	5%	50V
C6038	1-104-588-11	FILM	0.0082µF	2.50%	1.25KV
C6039	1-115-389-11	FILM	0.018µF	3%	800V
C6040	1-117-227-11	MYLAR	1µF	10%	450V
		(ES43HK1/SN1, ES48HK1/SN1, ES53HK1/SN1, ES61HK1/SN1)			
C6041	1-163-009-11	CERAMIC CHIP	0.001µF	10%	50V
C6042	1-163-009-11	CERAMIC CHIP	0.001µF	10%	50V
C6043	1-104-663-11	ELECT	33µF	20%	16V
		(ES43ME1/MN1, ES48ME1/MN1, ES53ME1/MN1, ES61ME1/MN1)			
C6044	1-117-703-11	CERAMIC	0.0047µF	99%	250V
C6045	1-107-675-11	ELECT	1µF	20%	450V
		(ES43ME1/MN1, ES48ME1/MN1, ES53ME1/MN1, ES61ME1/MN1)			
C6046	1-107-675-11	ELECT	1µF	20%	450V
		(ES43ME1/MN1, ES48ME1/MN1, ES53ME1/MN1, ES61ME1/MN1)			
C6100	⚠1-161-964-51	CERAMIC	0.0047µF		250V
C6101	1-107-680-11	ELECT	22µF	20%	450V
		(ES43ME1/MN1, ES48ME1/MN1, ES53ME1/MN1, ES61ME1/MN1)			
C6101	1-107-679-91	ELECT	10µF	20%	450V
		(ES43HK1/SN1, ES48HK1/SN1, ES53HK1/SN1, ES61HK1/SN1)			
C6102	⚠1-161-964-51	CERAMIC	0.0047µF		250V
C6103	1-163-005-11	CERAMIC CHIP	470pF	10%	50V
C6104	1-163-009-11	CERAMIC CHIP	0.001µF	10%	50V
C6105	1-164-004-11	CERAMIC CHIP	0.1µF	10%	25V
C6106	1-163-009-11	CERAMIC CHIP	0.001µF	10%	50V
		(ES43ME1/MN1, ES48ME1/MN1, ES53ME1/MN1, ES61ME1/MN1)			
C6106	1-163-275-11	CERAMIC CHIP	0.001µF	5%	50V
		(ES43HK1/SN1, ES48HK1/SN1, ES53HK1/SN1, ES61HK1/SN1)			
C6107	1-137-605-11	MYLAR	0.01µF	10%	250V
C6108	⚠1-161-964-51	CERAMIC	0.0047µF		250V
		(ES43ME1/MN1, ES48ME1/MN1, ES53ME1/MN1, ES61ME1/MN1)			
C6109	1-104-665-11	ELECT	100µF	20%	25V
		(ES43ME1/MN1, ES48ME1/MN1, ES53ME1/MN1, ES61ME1/MN1)			
C6109	1-126-965-11	ELECT	22µF	20%	50V
		(ES43HK1/SN1, ES48HK1/SN1, ES53HK1/SN1, ES61HK1/SN1)			
C6110	1-163-009-11	CERAMIC CHIP	0.001µF	10%	50V
C6111	⚠1-161-964-51	CERAMIC	0.0047µF		250V
C6300	1-101-810-00	CERAMIC	100pF	5%	500V
C6301	1-101-810-00	CERAMIC	100pF	5%	500V
C6302	1-102-114-00	CERAMIC	470pF	10%	50V
C6303	1-102-114-00	CERAMIC	470pF	10%	50V
C6306	1-101-810-00	CERAMIC	100pF	5%	500V
C6307	1-126-943-11	ELECT	2200µF	20%	25V
C6308	1-126-937-11	ELECT	4700µF	20%	16V
C6309	1-101-810-00	CERAMIC	100pF	5%	500V
C6310	1-101-810-00	CERAMIC	100pF	5%	500V
C6311	1-104-665-11	ELECT	100µF	20%	25V
C6312	1-104-665-11	ELECT	100µF	20%	25V
C6313	1-126-960-11	ELECT	1µF	20%	50V
C6314	1-128-567-51	ELECT	1000µF	20%	100V
C6315	1-128-567-51	ELECT	1000µF	20%	100V
C6317	1-109-954-11	ELECT	0.47µF	20%	160V
C6321	1-128-549-11	ELECT	3300µF	20%	35V
C6322	1-128-549-11	ELECT	3300µF	20%	35V
C6323	1-128-549-11	ELECT	3300µF	20%	35V
C6324	1-128-549-11	ELECT	3300µF	20%	35V
C6325	1-126-935-11	ELECT	470µF	20%	6.3V
C6327	1-126-968-11	ELECT	100µF	20%	50V
C6328	1-126-968-11	ELECT	100µF	20%	50V
C6329	1-126-943-11	ELECT	2200µF	20%	25V
C6330	1-126-943-11	ELECT	2200µF	20%	25V
C6331	1-107-641-11	ELECT	220µF	20%	160V
C6332	1-104-665-11	ELECT	100µF	20%	25V
C6333	1-104-665-11	ELECT	100µF	20%	25V
C6334	1-126-940-11	ELECT	330µF	20%	25V
C6335	1-126-967-11	ELECT	47µF	20%	50V
C6337	1-101-810-00	CERAMIC	100pF	5%	500V
C6338	1-162-117-00	CERAMIC	100pF	10%	500V
C6339	1-104-987-11	MYLAR	0.001µF	10%	200V

G1, G

The components identified by shading
and mark ⚠ are critical for safety.
Replace only with part number specified.

REF.NO.	PART NO.	DESCRIPTION	REMARK

C6340   1-164-004-11 CERAMIC CHIP 0.1µF   10%   25V
(ES43ME1/MN1, ES48ME1/MN1,
ES53ME1/MN1, ES61ME1/MN1)
C6341   1-137-150-11 MYLAR   0.01µF   5%   50V
(ES43HK1/SN1, ES48HK1/SN1,
ES53HK1/SN1, ES61HK1/SN1)
C6342   1-136-165-00 MYLAR   0.1µF   5%   50V
(ES43HK1/SN1, ES48HK1/SN1,
ES53HK1/SN1, ES61HK1/SN1)

<CONNECTOR>

CN6002   1-695-915-11 TAB (CONTACT)
CN6004 * 1-580-689-11 PIN, CONNECTOR (PC BOARD) 4P
(ES43ME1/MN1, ES48ME1/MN1,
ES53ME1/MN1, ES61ME1/MN1)
CN6004 * 1-580-843-11 PIN, CONNECTOR (POWER)
(ES43HK1/SN1, ES48HK1/SN1,
ES53HK1/SN1, ES61HK1/SN1)
CN6006 * 1-580-689-11 PIN, CONNECTOR (PC BOARD) 4P
CN6007 * 1-691-291-11 PIN, CONNECTOR (PC BOARD) 5P

CN6011 * 1-508-784-21 PIN, CONNECTOR (5MM PITCH) 1P
CN6300 * 1-564-508-11 PLUG, CONNECTOR 5P
CN6301 * 1-508-765-00 PIN, CONNECTOR (5MM PITCH) 3P
CN6302 * 1-764-333-11 PLUG, CONNECTOR 10P
CN6303 * 1-764-333-11 PLUG, CONNECTOR 10P

CN6304 * 1-573-963-11 PIN, CONNECTOR (PC BOARD) 3P
CN6306   1-695-915-11 TAB (CONTACT)
CN6307   1-695-915-11 TAB (CONTACT)
CN6308   1-695-915-11 TAB (CONTACT)

<DIODE>

D6000   8-719-052-90 DIODE D1NL40-TA2
(ES43ME1/MN1, ES48ME1/MN1,
ES53ME1/MN1, ES61ME1/MN1)
D6001   8-719-052-90 DIODE D1NL40-TA2
(ES43ME1/MN1, ES48ME1/MN1,
ES53ME1/MN1, ES61ME1/MN1)
D6002   8-719-988-61 DIODE 1SS355TE-17
(ES43ME1/MN1, ES48ME1/MN1,
ES53ME1/MN1, ES61ME1/MN1)
D6003   8-719-158-49 DIODE RD12SB2
(ES43ME1/MN1, ES48ME1/MN1,
ES53ME1/MN1, ES61ME1/MN1)
D6004   8-719-991-33 DIODE 1SS133T-77
(ES43ME1/MN1, ES48ME1/MN1,
ES53ME1/MN1, ES61ME1/MN1)
D6005   8-719-988-61 DIODE 1SS355TE-17
(ES43ME1/MN1, ES48ME1/MN1,
ES53ME1/MN1, ES61ME1/MN1)
D6006   8-719-988-61 DIODE 1SS355TE-17
(ES43ME1/MN1, ES48ME1/MN1,
ES53ME1/MN1, ES61ME1/MN1)
D6007   8-719-988-61 DIODE 1SS355TE-17
(ES43ME1/MN1, ES48ME1/MN1,
ES53ME1/MN1, ES61ME1/MN1)
D6008   8-719-991-33 DIODE 1SS133T-77
(ES43ME1/MN1, ES48ME1/MN1,
ES53ME1/MN1, ES61ME1/MN1)

D6009   8-719-158-49 DIODE RD12SB2
(ES43ME1/MN1, ES48ME1/MN1,
ES53ME1/MN1, ES61ME1/MN1)
D6010   8-719-988-61 DIODE 1SS355TE-17
D6011   8-719-988-61 DIODE 1SS355TE-17
(ES43ME1/MN1, ES48ME1/MN1,
ES53ME1/MN1, ES61ME1/MN1)
D6015 ⚠ 8-719-022-99 DIODE D6SB60L
(ES43ME1/MN1, ES48ME1/MN1,
ES53ME1/MN1, ES61ME1/MN1)
D6015 ⚠ 8-719-510-53 DIODE D4SB60L
(ES43HK1/SN1, ES48HK1/SN1,
ES53HK1/SN1, ES61HK1/SN1)
D6017   8-719-063-73 DIODE D1NL20U-TR

D6019   8-719-510-02 DIODE D1NS4
D6020   8-719-029-04 DIODE D5L60
(ES43HK1/SN1, ES48HK1/SN1,
ES53HK1/SN1, ES61HK1/SN1)
D6021   8-719-921-88 DIODE MTZJ-13B
(ES43ME1/MN1, ES48ME1/MN1,
ES53ME1/MN1, ES61ME1/MN1)
D6021   8-719-110-36 DIODE RD13ES-B2
(ES43HK1/SN1, ES48HK1/SN1,
ES53HK1/SN1, ES61HK1/SN1)
D6022   8-719-979-64 DIODE UF4005PKG23

D6023   8-719-979-64 DIODE UF4005PKG23
D6024   8-719-988-61 DIODE 1SS355TE-17
(ES43ME1/MN1, ES48ME1/MN1,
ES53ME1/MN1, ES61ME1/MN1)
D6025   8-719-988-61 DIODE 1SS355TE-17
(ES43ME1/MN1, ES48ME1/MN1,
ES53ME1/MN1, ES61ME1/MN1)
D6100 ⚠ 8-719-077-76 DIODE D2SB60A-F04
(ES43ME1/MN1, ES48ME1/MN1,
ES53ME1/MN1, ES61ME1/MN1)
D6100 ⚠ 8-719-068-00 DIODE ERC04-06SE
(ES43HK1/SN1, ES48HK1/SN1,
ES53HK1/SN1, ES61HK1/SN1)

D6101   8-719-068-00 DIODE ERC04-06SE
(ES43ME1/MN1, ES48ME1/MN1,
ES53ME1/MN1, ES61ME1/MN1)
D6101   8-719-947-69 DIODE MTZJ-T-72-18B
(ES43HK1/SN1, ES48HK1/SN1,
ES53HK1/SN1, ES61HK1/SN1)
D6102   8-719-978-65 DIODE DTZ-TT11-15B
D6103   8-719-988-61 DIODE 1SS355TE-17
D6104 ⚠ 8-719-068-00 DIODE ERC04-06SE
(ES43HK1/SN1, ES48HK1/SN1,
ES53HK1/SN1, ES61HK1/SN1)

D6105   8-719-948-45 DIODE ERA22-08
D6106 ⚠ 8-719-068-00 DIODE ERC04-06SE
(ES43HK1/SN1, ES48HK1/SN1,
ES53HK1/SN1, ES61HK1/SN1)
D6108   8-719-063-73 DIODE D1NL20U-TR
(ES43ME1/MN1, ES48ME1/MN1,
ES53ME1/MN1, ES61ME1/MN1)
D6108   8-719-510-48 DIODE D1N20R
(ES43HK1/SN1, ES48HK1/SN1,
ES53HK1/SN1, ES61HK1/SN1)
D6300   8-719-057-96 DIODE D10SC6M-4012

D6301   8-719-510-12 DIODE D10SC4M

REF.NO.	PART NO.	DESCRIPTION	REMARK
D6302	8-719-312-47	DIODE RBA-406B	
D6303	8-719-063-73	DIODE D1NL20U-TR	(ES43HK1/SN1, ES48HK1/SN1, ES53HK1/SN1, ES61HK1/SN1)
D6304	8-719-050-18	DIODE D4SBL20U	
D6305	8-719-988-61	DIODE 1SS355TE-17	
D6306	8-719-988-61	DIODE 1SS355TE-17	(ES43HK1/SN1, ES48HK1/SN1, ES53HK1/SN1, ES61HK1/SN1)
D6307	8-719-988-61	DIODE 1SS355TE-17	
D6308	8-719-988-31	DIODE D10SC6MR	
D6309	8-719-057-96	DIODE D10SC6M-4012	
D6310	8-719-052-91	DIODE D4SBS4-F	
D6311	8-719-988-61	DIODE 1SS355TE-17	(ES43HK1/SN1, ES48HK1/SN1, ES53HK1/SN1, ES61HK1/SN1)
D6312	8-719-988-61	DIODE 1SS355TE-17	
D6315	8-719-988-61	DIODE 1SS355TE-17	
D6316	8-719-988-61	DIODE 1SS355TE-17	
D6317	8-719-988-61	DIODE 1SS355TE-17	
D6318	8-719-921-88	DIODE MTZJ-13B	
D6319	8-719-976-96	DIODE DTZ4.7C	
D6320	8-719-976-96	DIODE DTZ4.7C	
D6323	8-719-032-12	DIODE D1NS6	

<FUSE>

REF.NO.	PART NO.	DESCRIPTION	REMARK
F6001	⚠1-532-506-51	FUSE 6.3A/250V	(ES43ME1/MN1, ES48ME1/MN1, ES53ME1/MN1, ES61ME1/MN1)
F6001	⚠1-576-232-11	FUSE (H.B.C.) 5A/250V	(ES43HK1/SN1, ES48HK1/SN1, ES53HK1/SN1, ES61HK1/SN1)

<FERRITBEAD>

REF.NO.	PART NO.	DESCRIPTION		REMARK
FB6002	1-412-911-11	FERRITE	0µH	
FB6101	⚠1-412-911-21	FERRITE	0µH	(ES43ME1/MN1, ES48ME1/MN1, ES53ME1/MN1, ES61ME1/MN1)
FB6103	⚠1-412-911-21	FERRITE	0µH	
FB6301	1-412-911-11	FERRITE	0µH	
FB6302	1-412-911-11	FERRITE	0µH	
FB6303	1-412-911-11	FERRITE	0µH	
FB6304	1-412-911-11	FERRITE	0µH	
FB6305	1-412-911-11	FERRITE	0µH	
FB6306	1-412-911-11	FERRITE	0µH	
FB6309	1-412-911-11	FERRITE	0µH	
FB6310	1-412-911-11	FERRITE	0µH	

<IC>

REF.NO.	PART NO.	DESCRIPTION	REMARK
IC6000	8-759-198-31	IC µPC1093J-1-T	(ES43ME1/MN1, ES48ME1/MN1, ES53ME1/MN1, ES61ME1/MN1)
IC6001	8-759-133-90	IC µPC339C	(ES43ME1/MN1, ES48ME1/MN1, ES53ME1/MN1, ES61ME1/MN1)
IC6002	⚠8-749-924-35	PHOTO COUPLER ON3171-R	
IC6003	⚠8-749-924-35	PHOTO COUPLER ON3171-R	(ES43ME1/MN1, ES48ME1/MN1, ES53ME1/MN1, ES61ME1/MN1)
IC6004	8-749-016-66	IC MCR5152	
IC6005	⚠8-749-924-35	PHOTO COUPLER ON3171-R	(ES43ME1/MN1, ES48ME1/MN1, ES53ME1/MN1, ES61ME1/MN1)
IC6006	8-759-198-31	IC µPC1093J-1-T	(ES43ME1/MN1, ES48ME1/MN1, ES53ME1/MN1, ES61ME1/MN1)
IC6007	⚠8-749-924-35	PHOTO COUPLER ON3171-R	
IC6301	8-749-012-13	IC DM-58	
IC6302	8-759-663-29	IC MM1476AF(TP)	
IC6303	8-759-198-31	IC µPC1093J-1-T	
IC6304	8-759-908-15	IC TL431CLP	(ES43HK1/SN1, ES48HK1/SN1, ES53HK1/SN1, ES61HK1/SN1)

<COIL>

REF.NO.	PART NO.	DESCRIPTION		REMARK
L6303	1-412-525-31	INDUCTOR	10µH	
L6304	1-406-659-11	INDUCTOR	10µH	
L6307	1-412-525-31	INDUCTOR	10µH	
L6308	1-412-525-31	INDUCTOR	10µH	
L6309	1-412-525-31	INDUCTOR	10µH	
L6310	1-412-525-31	INDUCTOR	10µH	
L6311	1-412-525-31	INDUCTOR	10µH	
L6314	1-412-524-11	INDUCTOR	8.2µH	
L6315	1-412-524-11	INDUCTOR	8.2µH	

<IC LINK>

REF.NO.	PART NO.	DESCRIPTION	REMARK
PS6300	⚠1-801-549-21	PROTECTOR, MODULE (4.0A)	
PS6301	⚠1-801-549-21	PROTECTOR, MODULE (4.0A)	
PS6302	⚠1-801-549-21	PROTECTOR, MODULE (4.0A)	
PS6303	⚠1-801-549-21	PROTECTOR, MODULE (4.0A)	
PS6306	⚠1-801-550-21	PROTECTOR, MODULE (2.5A)	
PS6307	⚠1-801-550-21	PROTECTOR, MODULE (2.5A)	
PS6310	⚠1-801-550-21	PROTECTOR, MODULE (2.5A)	
PS6311	⚠1-801-550-21	PROTECTOR, MODULE (2.5A)	

<TRANSISTOR>

REF.NO.	PART NO.	DESCRIPTION	REMARK
Q6000	8-729-120-28	TRANSISTOR 2SC1623-L5L6	(ES43ME1/MN1, ES48ME1/MN1, ES53ME1/MN1, ES61ME1/MN1)
Q6002	8-729-140-97	TRANSISTOR 2SB734-34	(ES43ME1/MN1, ES48ME1/MN1, ES53ME1/MN1, ES61ME1/MN1)
Q6003	8-729-120-28	TRANSISTOR 2SC1623-L5L6	(ES43ME1/MN1, ES48ME1/MN1, ES53ME1/MN1, ES61ME1/MN1)
Q6004	8-729-140-93	TRANSISTOR 2SB733-34	
Q6005	8-729-026-49	TRANSISTOR 2SA1037AK-T-146-R	(ES43ME1/MN1, ES48ME1/MN1, ES53ME1/MN1, ES61ME1/MN1)
Q6100	8-729-046-40	TRANSISTOR 2SK2663	
Q6102	8-729-023-22	TRANSISTOR 2SD2114K	

G1, G

The components identified by shading and mark ⚠ are critical for safety. Replace only with part number specified.

REF.NO.	PART NO.	DESCRIPTION			REMARK
Q6300	8-729-120-28	TRANSISTOR 2SC1623-L5L6 (ES43ME1/MN1, ES48ME1/MN1, ES53ME1/MN1, ES61ME1/MN1)			
Q6300	8-729-023-22	TRANSISTOR 2SD2114K (ES43HK1/SN1, ES48HK1/SN1, ES53HK1/SN1, ES61HK1/SN1)			
Q6301	8-729-120-28	TRANSISTOR 2SC1623-L5L6			
Q6302	8-729-026-49	TRANSISTOR 2SA1037AK-T-146-R			
Q6303	8-729-820-82	TRANSISTOR 2SA1208			
Q6304	8-729-026-39	TRANSISTOR 2SA933AS-QT (ES43HK1/SN1, ES48HK1/SN1, ES53HK1/SN1, ES61HK1/SN1)			
		<RESISTOR>			
R6000	1-260-131-11	CARBON	470K	5%	1/2W
R6001	1-260-131-11	CARBON	470K	5%	1/2W
R6002	1-202-981-11	CEMENTED	0.82	5%	20W
		(ES43ME1/MN1, ES48ME1/MN1, ES53ME1/MN1, ES61ME1/MN1)			
R6002	1-216-057-00	RES-CHIP	2.2K	5%	1/10W
		(ES43HK1/SN1, ES48HK1/SN1, ES53HK1/SN1, ES61HK1/SN1)			
R6003	⚠1-219-759-91	CARBON	1M	5%	1/2W
R6004	1-208-806-11	METAL CHIP	10K	0.5%	1/10W
		(ES43ME1/MN1, ES48ME1/MN1, ES53ME1/MN1, ES61ME1/MN1)			
R6005	1-208-806-11	METAL CHIP	10K	0.5%	1/10W
		(ES43ME1/MN1, ES48ME1/MN1, ES53ME1/MN1, ES61ME1/MN1)			
R6006	1-208-832-11	METAL CHIP	120K	0.5%	1/10W
		(ES43ME1/MN1, ES48ME1/MN1, ES53ME1/MN1, ES61ME1/MN1)			
R6007	1-208-827-11	METAL CHIP	75K	0.5%	1/10W
		(ES43ME1/MN1, ES48ME1/MN1, ES53ME1/MN1, ES61ME1/MN1)			
R6008	1-215-489-00	METAL	680K	1%	1/4W
		(ES43ME1/MN1, ES48ME1/MN1, ES53ME1/MN1, ES61ME1/MN1)			
R6009	1-215-489-00	METAL	680K	1%	1/4W
		(ES43ME1/MN1, ES48ME1/MN1, ES53ME1/MN1, ES61ME1/MN1)			
R6010	1-215-489-00	METAL	680K	1%	1/4W
		(ES43ME1/MN1, ES48ME1/MN1, ES53ME1/MN1, ES61ME1/MN1)			
R6011	1-208-798-11	METAL CHIP	4.7K	0.5%	1/10W
		(ES43ME1/MN1, ES48ME1/MN1, ES53ME1/MN1, ES61ME1/MN1)			
R6012	1-208-832-11	METAL CHIP	120K	0.5%	1/10W
		(ES43ME1/MN1, ES48ME1/MN1, ES53ME1/MN1, ES61ME1/MN1)			
R6013	1-215-489-00	METAL	680K	1%	1/4W
		(ES43ME1/MN1, ES48ME1/MN1, ES53ME1/MN1, ES61ME1/MN1)			
R6014	1-215-489-00	METAL	680K	1%	1/4W
		(ES43ME1/MN1, ES48ME1/MN1, ES53ME1/MN1, ES61ME1/MN1)			
R6015	1-215-489-00	METAL	680K	1%	1/4W
		(ES43ME1/MN1, ES48ME1/MN1, ES53ME1/MN1, ES61ME1/MN1)			
R6016	1-216-081-00	RES-CHIP	22K	5%	1/10W
		(ES43ME1/MN1, ES48ME1/MN1, ES53ME1/MN1, ES61ME1/MN1)			
R6017	1-208-830-11	METAL CHIP	100K	0.5%	1/10W
		(ES43ME1/MN1, ES48ME1/MN1, ES53ME1/MN1, ES61ME1/MN1)			
R6018	1-208-844-11	METAL CHIP	390K	0.5%	1/10W
		(ES43ME1/MN1, ES48ME1/MN1, ES53ME1/MN1, ES61ME1/MN1)			
R6019	1-208-806-11	METAL CHIP	10K	0.5%	1/10W
		(ES43ME1/MN1, ES48ME1/MN1, ES53ME1/MN1, ES61ME1/MN1)			
R6020	1-208-827-11	METAL CHIP	75K	0.5%	1/10W
		(ES43ME1/MN1, ES48ME1/MN1, ES53ME1/MN1, ES61ME1/MN1)			
R6021	1-208-830-11	METAL CHIP	100K	0.5%	1/10W
		(ES43ME1/MN1, ES48ME1/MN1, ES53ME1/MN1, ES61ME1/MN1)			
R6022	1-208-846-11	METAL CHIP	470K	0.5%	1/10W
		(ES43ME1/MN1, ES48ME1/MN1, ES53ME1/MN1, ES61ME1/MN1)			
R6023	1-216-057-00	RES-CHIP	2.2K	5%	1/10W
		(ES43ME1/MN1, ES48ME1/MN1, ES53ME1/MN1, ES61ME1/MN1)			
R6024	1-208-846-11	METAL CHIP	470K	0.5%	1/10W
		(ES43ME1/MN1, ES48ME1/MN1, ES53ME1/MN1, ES61ME1/MN1)			
R6025	1-216-057-00	RES-CHIP	2.2K	5%	1/10W
		(ES43ME1/MN1, ES48ME1/MN1, ES53ME1/MN1, ES61ME1/MN1)			
R6026	⚠1-218-265-21	METAL	8.2M	5%	1W
R6027	1-249-389-11	CARBON	4.7	5%	1/4W
		(ES43ME1/MN1, ES48ME1/MN1, ES53ME1/MN1, ES61ME1/MN1)			
R6029	1-216-065-91	RES-CHIP	4.7K	5%	1/10W
		(ES43ME1/MN1, ES48ME1/MN1, ES53ME1/MN1, ES61ME1/MN1)			
R6030	1-216-089-91	RES-CHIP	47K	5%	1/10W
		(ES43ME1/MN1, ES48ME1/MN1, ES53ME1/MN1, ES61ME1/MN1)			
R6031	1-216-073-00	RES-CHIP	10K	5%	1/10W
		(ES43ME1/MN1, ES48ME1/MN1, ES53ME1/MN1, ES61ME1/MN1)			
R6033	1-216-065-91	RES-CHIP	4.7K	5%	1/10W
		(ES43ME1/MN1, ES48ME1/MN1, ES53ME1/MN1, ES61ME1/MN1)			
R6035	⚠1-205-998-11	CEMENTED	1	5%	10W
		(ES43HK1/SN1, ES48HK1/SN1, ES53HK1/SN1, ES61HK1/SN1)			
R6036	1-208-830-11	METAL CHIP	100K	0.5%	1/10W
		(ES43ME1/MN1, ES48ME1/MN1, ES53ME1/MN1, ES61ME1/MN1)			
R6038	1-216-073-00	RES-CHIP	10K	5%	1/10W
		(ES43ME1/MN1, ES48ME1/MN1, ES53ME1/MN1, ES61ME1/MN1)			
R6041	1-208-822-11	METAL CHIP	47K	0.5%	1/10W
		(ES43ME1/MN1, ES48ME1/MN1, ES53ME1/MN1, ES61ME1/MN1)			
R6042	1-208-822-11	METAL CHIP	47K	0.5%	1/10W
		(ES43ME1/MN1, ES48ME1/MN1, ES53ME1/MN1, ES61ME1/MN1)			
R6043	1-216-073-00	RES-CHIP	10K	5%	1/10W

G1, G

REF.NO.	PART NO.	DESCRIPTION			REMARK
R6044	1-216-073-00	RES-CHIP	10K	5%	1/10W
		(ES43ME1/MN1, ES48ME1/MN1, ES53ME1/MN1, ES61ME1/MN1)			
R6045	1-208-819-11	METAL CHIP	36K	0.5%	1/10W
		(ES43ME1/MN1, ES48ME1/MN1, ES53ME1/MN1, ES61ME1/MN1)			
R6046	1-215-489-00	METAL	680K	1%	1/4W
		(ES43ME1/MN1, ES48ME1/MN1, ES53ME1/MN1, ES61ME1/MN1)			
R6047	1-215-489-00	METAL	680K	1%	1/4W
		(ES43ME1/MN1, ES48ME1/MN1, ES53ME1/MN1, ES61ME1/MN1)			
R6048	1-215-489-00	METAL	680K	1%	1/4W
		(ES43ME1/MN1, ES48ME1/MN1, ES53ME1/MN1, ES61ME1/MN1)			
R6049	⚠1-205-998-11	CEMENTED	1	5%	10W
		(ES43HK1/SN1, ES48HK1/SN1, ES53HK1/SN1, ES61HK1/SN1)			
R6050	1-205-943-11	CEMENTED	1	5%	20W
		(ES43ME1/MN1, ES48ME1/MN1, ES53ME1/MN1, ES61ME1/MN1)			
R6051	1-208-824-11	METAL CHIP	56K	0.5%	1/10W
		(ES43ME1/MN1, ES48ME1/MN1, ES53ME1/MN1, ES61ME1/MN1)			
R6052	1-249-417-11	CARBON	1K	5%	1/4W
R6053	1-208-792-11	METAL CHIP	2.7K	0.5%	1/10W
		(ES43ME1/MN1, ES48ME1/MN1, ES53ME1/MN1, ES61ME1/MN1)			
R6053	1-216-660-11	METAL CHIP	2.4K	0.5%	1/10W
		(ES43HK1/SN1, ES48HK1/SN1, ES53HK1/SN1, ES61HK1/SN1)			
R6054	1-208-774-11	METAL CHIP	470	0.5%	1/10W
R6055	1-208-805-11	METAL CHIP	9.1K	0.5%	1/10W
R6056	1-217-625-00	METAL	0.05	10%	2W
R6057	1-215-477-00	METAL	220K	1%	1/4W
R6058	1-215-477-00	METAL	220K	1%	1/4W
R6059	1-215-477-00	METAL	220K	1%	1/4W
R6060	1-219-512-11	CARBON	2.2M	5%	1/2W
R6061	⚠1-220-886-61	FUSIBLE	0.1	10%	1W
R6062	1-208-800-11	METAL CHIP	5.6K	0.5%	1/10W
		(ES43ME1/MN1, ES48ME1/MN1, ES53ME1/MN1, ES61ME1/MN1)			
R6062	1-208-796-11	METAL CHIP	3.9K	0.5%	1/10W
		(ES43HK1/SN1, ES48HK1/SN1, ES53HK1/SN1, ES61HK1/SN1)			
R6065	1-219-512-11	CARBON	2.2M	5%	1/2W
R6067	1-249-397-11	CARBON	22	5%	1/4W
R6068	⚠1-205-998-11	CEMENTED	1	5%	10W
		(ES43HK1/SN1, ES48HK1/SN1, ES53HK1/SN1, ES61HK1/SN1)			
R6069	⚠1-205-998-11	CEMENTED	1	5%	10W
		(ES43HK1/SN1, ES48HK1/SN1, ES53HK1/SN1, ES61HK1/SN1)			
R6071	⚠1-240-881-11	CEMENTED	0.82	5%	10W
		(ES43ME1/MN1, ES48ME1/MN1, ES53ME1/MN1, ES61ME1/MN1)			
R6072	1-249-417-11	CARBON	1K	5%	1/4W
R6076	1-249-389-11	CARBON	4.7	5%	1/4W
R6077	1-216-689-11	RES-CHIP	39K	5%	1/10W
		(ES43ME1/MN1, ES48ME1/MN1, ES53ME1/MN1, ES61ME1/MN1)			
R6078	1-216-073-00	RES-CHIP	10K	5%	1/10W
		(ES43ME1/MN1, ES48ME1/MN1, ES53ME1/MN1, ES61ME1/MN1)			
R6079	1-216-073-00	RES-CHIP	10K	5%	1/10W
R6100	1-260-298-51	CARBON	3.3	5%	1/2W
R6101	1-216-045-00	RES-CHIP	680	5%	1/10W
R6102	1-249-389-11	CARBON	4.7	5%	1/4W
R6103	1-216-009-91	RES-CHIP	22	5%	1/10W
R6104	1-240-205-11	CARBON	22M	5%	1/2W
R6105	1-216-097-91	RES-CHIP	100K	5%	1/10W
R6106	1-216-057-00	RES-CHIP	2.2K	5%	1/10W
R6107	1-216-089-91	RES-CHIP	47K	5%	1/10W
R6108	1-215-493-00	METAL	1M	1%	1/4W
R6109	1-216-025-91	RES-CHIP	100	5%	1/10W
		(ES43ME1/MN1, ES48ME1/MN1, ES53ME1/MN1, ES61ME1/MN1)			
R6109	1-216-041-00	RES-CHIP	470	5%	1/10W
		(ES43HK1/SN1, ES48HK1/SN1, ES53HK1/SN1, ES61HK1/SN1)			
R6300	1-216-065-91	RES-CHIP	4.7K	5%	1/10W
R6301	1-249-413-11	CARBON	470	5%	1/4W
R6302	1-216-073-00	RES-CHIP	10K	5%	1/10W
R6304	1-216-073-00	RES-CHIP	10K	5%	1/10W
R6305	1-216-073-00	RES-CHIP	10K	5%	1/10W
R6306	1-216-041-00	RES-CHIP	470	5%	1/10W
R6307	1-216-073-00	RES-CHIP	10K	5%	1/10W
R6308	1-216-049-91	RES-CHIP	1K	5%	1/10W
R6309	1-249-417-11	CARBON	1K	5%	1/4W
R6310	1-216-065-91	RES-CHIP	4.7K	5%	1/10W
R6311	1-215-477-00	METAL	220K	1%	1/4W
R6312	1-249-417-11	CARBON	1K	5%	1/4W
R6313	1-216-097-91	RES-CHIP	100K	5%	1/10W
R6314	1-216-385-11	METAL OXIDE	0.47	5%	3W
R6316	1-215-477-00	METAL	220K	1%	1/4W
R6317	1-249-417-11	CARBON	1K	5%	1/4W
R6318	1-215-453-00	METAL	22K	1%	1/4W
R6319	1-215-476-00	METAL	200K	1%	1/4W
R6320	1-208-806-11	METAL CHIP	10K	0.5%	1/10W
R6321	1-208-822-11	METAL CHIP	47K	0.5%	1/10W
R6322	1-216-057-00	RES-CHIP	2.2K	5%	1/10W
R6323	1-216-041-00	RES-CHIP	470	5%	1/10W
R6324	1-216-049-91	RES-CHIP	1K	5%	1/10W
R6325	1-208-819-11	METAL CHIP	36K	0.5%	1/10W
R6326	1-208-798-11	METAL CHIP	4.7K	0.5%	1/10W
R6327	1-208-782-11	METAL CHIP	1K	0.5%	1/10W
		(ES43HK1/SN1, ES48HK1/SN1, ES53HK1/SN1, ES61HK1/SN1)			
R6328	1-216-065-91	RES-CHIP	4.7K	5%	1/10W
		(ES43ME1/MN1, ES48ME1/MN1, ES53ME1/MN1, ES61ME1/MN1)			
R6328	1-215-906-11	METAL OXIDE	15	5%	3W
		(ES43HK1/SN1, ES48HK1/SN1, ES53HK1/SN1, ES61HK1/SN1)			
R6329	1-216-041-00	RES-CHIP	470	5%	1/10W
		(ES43ME1/MN1, ES48ME1/MN1, ES53ME1/MN1, ES61ME1/MN1)			

G1, G

The components identified by shading
and mark ⚠ are critical for safety.
Replace only with part number specified.

REF.NO.	PART NO.	DESCRIPTION	REMARK
R6329	1-208-807-11	METAL CHIP 11K 0.5% 1/10W (ES43HK1/SN1, ES48HK1/SN1, ES53HK1/SN1, ES61HK1/SN1)	
R6330	1-208-813-11	METAL CHIP 20K 0.5% 1/10W (ES43ME1/MN1, ES48ME1/MN1, ES53ME1/MN1, ES61ME1/MN1)	
R6332	1-208-819-11	METAL CHIP 36K 0.5% 1/10W (ES43ME1/MN1, ES48ME1/MN1, ES53ME1/MN1, ES61ME1/MN1)	
R6333	1-208-806-11	METAL CHIP 10K 0.5% 1/10W (ES43HK1/SN1, ES48HK1/SN1, ES53HK1/SN1, ES61HK1/SN1)	
R6334	1-216-041-00	RES-CHIP 470 5% 1/10W (ES43HK1/SN1, ES48HK1/SN1, ES53HK1/SN1, ES61HK1/SN1)	
R6335	1-216-071-00	RES-CHIP 8.2K 5% 1/10W (ES43HK1/SN1, ES48HK1/SN1, ES53HK1/SN1, ES61HK1/SN1)	
R6336	1-208-802-11	METAL CHIP 6.8K 0.5% 1/10W (ES43HK1/SN1, ES48HK1/SN1, ES53HK1/SN1, ES61HK1/SN1)	

<RELAY>

REF.NO.	PART NO.	DESCRIPTION	REMARK
RY6000	⚠1-755-357-11	RELAY, AC POWER (ES43ME1/MN1, ES48ME1/MN1, ES53ME1/MN1, ES61ME1/MN1)	
RY6000	⚠1-755-352-11	RELAY, AC POWER (ES43HK1/SN1, ES48HK1/SN1, ES53HK1/SN1, ES61HK1/SN1)	
RY6001	⚠1-755-357-11	RELAY, AC POWER (ES43ME1/MN1, ES48ME1/MN1, ES53ME1/MN1, ES61ME1/MN1)	

<TRANSFORMER>

REF.NO.	PART NO.	DESCRIPTION	REMARK
T6001	⚠1-431-493-11	TRANSFORMER, LINE FILTER (ES43ME1/MN1, ES48ME1/MN1, ES53ME1/MN1, ES61ME1/MN1)	
T6001	⚠1-424-505-11	TRANSFORMER, LINE FILTER (ES43HK1/SN1, ES48HK1/SN1, ES53HK1/SN1, ES61HK1/SN1)	
T6002	⚠1-431-493-11	TRANSFORMER, LINE FILTER (ES43ME1/MN1, ES48ME1/MN1, ES53ME1/MN1, ES61ME1/MN1)	
T6002	⚠1-424-505-11	TRANSFORMER, LINE FILTER (ES43HK1/SN1, ES48HK1/SN1, ES53HK1/SN1, ES61HK1/SN1)	
T6003	⚠1-431-445-11	TRANSFORMER, CONVERTER (PFT) (ES43HK1/SN1, ES48HK1/SN1, ES53HK1/SN1, ES61HK1/SN1)	
T6004	⚠1-435-443-11	TRANSFORMER, CONVERTER (PIT)	
T6005	⚠1-435-445-11	TRANSFORMER, CONVERTER (PIT)	
T6100	⚠1-435-444-11	TRANSFORMER, STAND-BY (ES43ME1/MN1, ES48ME1/MN1, ES53ME1/MN1, ES61ME1/MN1)	
T6100	⚠1-433-844-11	TRANSFORMER, CONVERTER (ES43HK1/SN1, ES48HK1/SN1, ES53HK1/SN1, ES61HK1/SN1)	

<THERMISTOR>

REF.NO.	PART NO.	DESCRIPTION	REMARK
TH6100	1-803-586-11	THERMISTOR, NTC	

<VARISTOR>

REF.NO.	PART NO.	DESCRIPTION	REMARK
VD6000	1-803-614-11	VARISTOR (ES43ME1/MN1, ES48ME1/MN1, ES53ME1/MN1, ES61ME1/MN1)	
VD6001	⚠1-803-830-51	VARISTOR (ERZV14D621)	
VD6002	⚠1-803-830-51	VARISTOR (ERZV14D621)	

****

MISCELLANEOUS
****

PART NO.	DESCRIPTION	REMARK
⚠1-223-925-11	RESISTOR ASSY (HIGH-VOLTAGE) (FOCUS PACK)	
⚠1-452-790-41	NECK ASSY (NA-295)	
1-528-864-11	BATTERY, SOLAR	
1-529-403-11	SPEAKER (6.6 CM) (ES48, ES53)	
1-529-405-11	SPEAKER (13 CM) (ES53)	
1-529-643-11	SPEAKER (13 CM) (ES48)	
1-529-757-11	SPEAKER (2.7 CM) (ES61)	
1-529-758-11	SPEAKER (8 CM) (ES61)	
1-529-759-11	SPEAKER (16 CM) (ES61)	
1-529-791-11	SPEAKER (10 CM) (ES43)	
1-529-792-11	SPEAKER (12 CM) (ES43)	
1-543-982-11	CORE, FERRITE	
⚠1-574-062-52	CORD, POWER (WITH CONNECTOR) (ES43ME1/MN1, ES48ME1/MN1, ES53ME1/MN1, ES61ME1/MN1)	
* 1-761-348-11	PWB, MOUNTED (NET WORK) (ES43)	
1-790-082-11	CABLE, RF	
⚠1-792-002-11	CORD, POWER (WITH FILTER) (ES43HK1, ES48HK1, ES53HK1, ES61HK1)	
⚠1-792-035-11	CORD, POWER (WITH FILTER) (ES43SN1, ES48SN1, ES53SN1, ES61SN1)	
⚠8-598-955-12	BLOCK ASSY, HIGH-VOLTAGE	
⚠8-733-570-15	PICTURE TUBE 07MXC2 (G) (HEATER)	
⚠8-733-571-15	PICTURE TUBE 07MXC2 (R) (HEATER) (ES43)	
⚠8-733-572-15	PICTURE TUBE 07MXC3 (R) (HEATER) (ES48, ES53)	
⚠8-733-573-15	PICTURE TUBE 07MXC4 (R) (HEATER) (ES61)	
⚠8-733-574-15	PICTURE TUBE 07MAC2 (B) (HEATER) (ES43)	
⚠8-733-575-15	PICTURE TUBE 07MAC3 (B) (HEATER) (ES48, ES53)	
⚠8-733-576-15	PICTURE TUBE 07MAC4 (B) (HEATER) (ES61)	

****

The components identified by shading
and mark ⚠ are critical for safety.
Replace only with part number specified.

REF.NO.	PART NO.	DESCRIPTION	REMARK

ACCESSORIES AND PACKING MATERIALS
****

⚠1-569-008-11 ADAPTOR, CONVERSION 2P
                      (ES43ME1/MN1, ES48ME1/MN1,
                      ES53ME1/MN1, ES61ME1/MN1)
* 4-029-168-01 BAG, PROTECTION (ES43)
* 4-030-895-01 JOINT
* 4-041-423-11 SHEET, PROTECTION (ES43, ES48)
* 4-055-672-01 BAG, PROTECTION (ES53)

* 4-055-673-01 SHEET, PROTECTION (ES53,ES61)
* 4-059-461-01 BAG, PROTECTION (ES61)
* 4-060-976-01 BAG, PROTECTION (ES48)
* 4-069-899-01 TRAY(ES48)
* 4-069-900-02 BOARD, TOP (ES48)

* 4-069-901-01 BOARD, BOTTOM (ES48)
* 4-069-994-01 TRAY(ES53)
* 4-069-995-01 BOARD, TOP (ES53)
* 4-069-996-01 BOARD, BOTTOM (ES53)
* 4-071-930-01 TRAY(ES61)

* 4-071-931-01 BOARD, TOP (ES61)
* 4-071-932-01 BOARD, BOTTOM (ES61)
* 4-071-933-01 CUSHION (UPPER) (ASSY) (ES61)
* 4-071-934-01 CUSHION (LOWER) (ASSY) (ES61)
* 4-076-536-01 TRAY(ES43)

* 4-076-537-01 INDIVIDUAL CARTON (ES43)
* 4-076-538-01 CUSHION (UPPER) (ASSY) (ES43)
* 4-076-539-01 CUSHION (LOWER) (ASSY) (ES43)
  4-076-694-11 MANUAL, INSTRUCTION
                      (ENGLISH, FRENCH, CHINESE,
                              PERUSSIAN, ARABIC)
* 4-076-803-01 INDIVIDUAL CARTON (ES48)

* 4-076-804-01 CUSHION (UPPER) (ASSY) (ES48)
* 4-076-805-01 CUSHION (LOWER) (ASSY) (ES48)
* 4-077-770-01 INDIVIDUAL CARTON (ES53)
* 4-077-771-01 CUSHION (UPPER) (ASSY) (ES53)
* 4-077-772-01 CUSHION (LOWER) (ASSY) (ES53)

* 4-077-862-01 INDIVIDUAL CARTON (ES61)
****

REMOTE COMMANDER
****

1-476-170-11 REMOTE COMMANDER (RM-961)
4-978-977-01 COVER, BATTERY (for RM-961)